



TFT-LCD TV

Chassis	Model
GML26KE	LE26M51B
GML32KE	LE32M51B
	LE32M61B
GML40KE	LE40M51B
	LE40M61B
GML46KE	LE46M51B

SERVICE Manual

TFT-LCD TV



Fashion Feature

- Luxurious Slim Design
- Supreme Picture Quality
- Supreme Sound Quality
- Supreme Convenience Quality
- Convenience for Users

1 Precautions

Follow these safety, servicing and ESD precautions to prevent damage and to protect against potential hazards such as electrical shock.

1-1 Safety Precautions

1-1-1 Warnings

1. For continued safety, do not attempt to modify the circuit board.
2. Disconnect the AC power and DC Power Jack before servicing.

1-1-2 Servicing the LCD Monitor

1. When servicing the LCD Monitor Disconnect the AC line cord from the AC outlet.
2. It is essential that service technicians have an accurate voltage meter available at all times. Check the calibration of this meter periodically.

1-1-3 Fire and Shock Hazard

Before returning the monitor to the user, perform the following safety checks:

1. Inspect each lead dress to make certain that the leads are not pinched or that hardware is not lodged between the chassis and other metal parts in the monitor.
2. Inspect all protective devices such as nonmetallic control knobs, insulating materials, cabinet backs, adjustment and compartment covers or shields, isolation resistor-capacitor networks, mechanical insulators, etc.
3. Leakage Current Hot Check (Figure 1-1):
WARNING: Do not use an isolation transformer during this test.

Use a leakage current tester or a metering system that complies with American National Standards Institute (*ANSI C101.1, Leakage Current for Appliances*), and Underwriters Laboratories (*UL Publication UL1410, 59.7*).




Figure 1-1. Leakage Current Test Circuit

4. With the unit completely reassembled, plug the AC line cord directly into a 120V AC outlet. With the unit's AC switch first in the ON position and then OFF, measure the current between a known earth ground (metal water pipe, conduit, etc.) and all exposed metal parts, including: metal cabinets, screwheads and control shafts. The current measured should not exceed 0.5 milliamp. Reverse the power-plug prongs in the AC outlet and repeat the test.

1-1-4 Product Safety Notices

Some electrical and mechanical parts have special safety-related characteristics which are often not evident from visual inspection. The protection they give may not be obtained by replacing them with components rated for higher voltage, wattage, etc. Parts that have special safety characteristics are identified by \triangle on schematics and parts lists. A substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire and/or other hazards. Product safety is under review continuously and new instructions are issued whenever appropriate.

1-2 Servicing Precautions

WARNING: An electrolytic capacitor installed with the wrong polarity might explode.

Caution: Before servicing units covered by this service manual, read and follow the Safety Precautions section of this manual.

Note: If unforeseen circumstances create conflict between the following servicing precautions and any of the safety precautions, always follow the safety precautions.

1-2-1 General Servicing

Precautions

1. Always unplug the unit's AC power cord from the AC power source and disconnect the DC Power Jack before attempting to:
(a) remove or reinstall any component or assembly, (b) disconnect PCB plugs or connectors, (c) connect a test component in parallel with an electrolytic capacitor.
2. Some components are raised above the printed circuit board for safety. An insulation tube or tape is sometimes used. The internal wiring is sometimes clamped to prevent contact with thermally hot components. Reinstall all such elements to their original position.
3. After servicing, always check that the screws, components and wiring have been correctly reinstalled. Make sure that the area around the serviced part has not been damaged.

4. Check the insulation between the blades of the AC plug and accessible conductive parts (examples: metal panels, input terminals and earphone jacks).
5. Insulation Checking Procedure: Disconnect the power cord from the AC source and turn the power switch ON. Connect an insulation resistance meter (500 V) to the blades of the AC plug.
The insulation resistance between each blade of the AC plug and accessible conductive parts (see above) should be greater than 1 megohm.
6. Always connect a test instrument's ground lead to the instrument chassis ground before connecting the positive lead; always remove the instrument's ground lead last.

1-3 Static Electricity Precautions

Some semiconductor (solid state) devices can be easily damaged by static electricity. Such components are commonly called Electrostatically Sensitive Devices (ESD). Examples of typical ESD are integrated circuits and some field-effect transistors. The following techniques will reduce the incidence of component damage caused by static electricity.

1. Immediately before handling any semiconductor components or assemblies, drain the electrostatic charge from your body by touching a known earth ground. Alternatively, wear a discharging wrist-strap device. To avoid a shock hazard, be sure to remove the wrist strap before applying power to the monitor.
2. After removing an ESD-equipped assembly, place it on a conductive surface such as aluminum foil to prevent accumulation of an electrostatic charge.
3. Do not use freon-propelled chemicals. These can generate electrical charges sufficient to damage ESDs.
4. Use only a grounded-tip soldering iron to solder or desolder ESDs.
5. Use only an anti-static solder removal device. Some solder removal devices not classified as "anti-static" can generate electrical charges sufficient to damage ESDs.

6. Do not remove a replacement ESD from its protective package until you are ready to install it. Most replacement ESDs are packaged with leads that are electrically shorted together by conductive foam, aluminum foil or other conductive materials.
7. Immediately before removing the protective material from the leads of a replacement ESD, touch the protective material to the chassis or circuit assembly into which the device will be installed.

Caution: Be sure no power is applied to the chassis or circuit and observe all other safety precautions.

8. Minimize body motions when handling unpackaged replacement ESDs. Motions such as brushing clothes together, or lifting your foot from a carpeted floor can generate enough static electricity to damage an ESD.

1-4 Installation Precautions

1. For safety reasons, more than two people are required for carrying the product.
2. Keep the power cord away from any heat emitting devices, as a melted covering may cause fire or electric shock.
3. Do not place the product in areas with poor ventilation such as a bookshelf or closet. The increased internal temperature may cause fire.
4. Bend the external antenna cable when connecting it to the product. This is a measure to protect it from being exposed to moisture. Otherwise, it may cause a fire or electric shock.
5. Make sure to turn the power off and unplug the power cord from the outlet before repositioning the product. Also check the antenna cable or the external connectors if they are fully unplugged. Damage to the cord may cause fire or electric shock.
6. Keep the antenna far away from any high-voltage cables and install it firmly. Contact with the high-voltage cable or the antenna falling over may cause fire or electric shock.
7. When installing the product, leave enough space (10cm) between the product and the wall for ventilation purposes. A rise in temperature within the product may cause fire.

1 Precautions

Memo

2 Product specifications

2-1 Fashion Feature

Supreme Digital Interface & Networking

-With a built-in HD digital tuner, it supports HD broadcasting with no particular set-top box and provides simple access with a single remote control.

Excellent Picture Quality

-DNIe technology provides life-like clear images.

My Color Control

-Colors can be set to your preference by adjusting Red, Green, Blue, Yellow, Pink and White.

Dynamic Contrast

-Automatically detects the input visual signal and adjusts to create optimum contrast.

Brightness Sensor

-Adjusts the screen brightness automatically depending on the brightness of the surrounding environment.

SRS TruSurround XT

-SRS TruSurround XT provides a virtual Dolby surround system.

Convenience

-The TV utilizes the HDMI system to implement perfect digital sound and picture quality.

The Anynet system enables you to easily control Samsung audio-video (AV) devices from this TV.

2-2 LE26M5 Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 26-Inch viewable, 0.4215(H) x 0.4215(V) mm pixel pitchh	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16,777,216 colours	
Maximum Resolution	Horizontal : 1360 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75Ω , internally terminated	
Input Sync Signal	Type : Separate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	556.4 mm / 339.8 mm	
AC power voltage & Frequency	AC 220 ~ 240 V, 60/50 Hz	
Power Consumption	140 W	
Dimensions(W x D x H) Set	678 x 226 x 532 mm(26.69 x 8.90 x 20.94 inches) After installation Stand 678 x 111 x 476 mm(26.69 x 4.37 x 18.74 inches) Without stand	
Weight Set(After installation Stand)	13.3 kg (29.32 lbs)	
TV System	Tuning	Frequency Synthesize
	System	PAL, SECAM
	Sound	MONO, STEREO, NICAM
Environmental Considerations	Operating Temperature : 50°F ~ 104°F (10°C ~ 40°C) Operating Humidity : 10 % ~ 80 % Storage Temperature : -4°F ~ 113°F (-20°C ~ 45°C) Storage Humidity : 5 % ~ 95 %	
Antenna Input	75Ω	
Sound Characteristic	-MAX Internal speaker Out : Right : 5W / Left : 5W -BASS Control Range : -8 dB ~ +8 dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-3 LE32M5 Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 32-Inch viewable, 0.511 (H) x 0.511 (V) mm pixel pitchh	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16,777,216 colours	
Maximum Resolution	Horizontal : 1360 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75 Ω, internally terminated	
Input Sync Signal	Type : Separate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	556.4 mm / 339.8 mm	
AC power voltage & Frequency	AC 220 ~ 240V, 50 ~ 60 Hz	
Power Consumption	170 W	
Dimensions(W x D x H) Set	804 x 250 x 622.5 mm(31.65 x 9.84 x 24.50 inches)After installation Stand 804 x 113 x 564 mm(31.65 x 4.45 x 22.20 inches) Without stand	
Weight Set(After installation Stand)	19.2 kg (42.33 lbs)	
TV System	Tuning	Frequency Synthesize
	System	PAL, SECAM
	Sound	MONO, STEREO, NICAM
Environmental Considerations	Operating Temperature : 50°F ~ 104°F (10°C ~ 40°C) Operating Humidity : 10 % ~ 80 % Storage Temperature : -4°F ~ 113°F (-20°C ~ 45°C) Storage Humidity : 5 % ~ 95 %	
Antenna Input	75Ω	
Sound Characteristic	-MAX Internal speaker Out : Right : 5W / Left : 5W -BASS Control Range : -8 dB ~ +8 dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-4 LE40M5 Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 40-Inch viewable, 0.648(H) x 0.216(V) mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16,777,216 colours	
Maximum Resolution	Horizontal : 1360 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75 Ω, internally terminated	
Input Sync Signal	Type : Separate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	556.4 mm / 339.8 mm	
AC power voltage & Frequency	AC 220 ~ 240V, 50 ~ 60 Hz	
Power Consumption	275 W	
Dimensions(W x D x H) Set	1004 x 330 x 749 mm(39.52 x 12.99 x 29.49 inches) After installation Stand 31004 x 115 x 680 mm(39.52 x 4.52 x 26.77 inches) Without stand	
Weight Set(After installation Stand)	27.5 kg (60.63 lbs)	
TV System	Tuning	Frequency Synthesize
	System	PAL, SECAM
	Sound	MONO, STEREO, NICAM
Environmental Considerations	Operating Temperature : 50°F ~ 104°F (10°C ~ 40°C) Operating Humidity : 10 % ~ 80 % Storage Temperature : -4°F ~ 113°F (-20°C ~ 45°C) Storage Humidity : 5 % ~ 95 %	
Antenna Input	75Ω	
Sound Characteristic	-MAX Internal speaker Out : Right : 5W / Left : 5W -BASS Control Range : -8 dB ~ +8 dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	





2-5 LE46M51B Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 46-Inch viewable, 0.2485(H) x 0.7455(V) mm pixel pitchh	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.2 Million colors	
Maximum Resolution	Horizontal : 1366 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75Ω, internally terminated	
Input Sync Signal	Type : Separate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	556.4 mm / 339.8 mm	
AC power voltage & Frequency	AC 220 ~ 240V, 50 ~ 60 Hz	
Power Consumption	150 W	
Dimensions(W x D x H) Set	1126 x 360 x 820 mm(44.33 x 14.17 x 32.28 inches) After installation Stand 1126 x 140 x 752 mm(44.33 x 5.51 x 29.60 inches) Without stand	
Weight Set(After installation Stand)	37 kg (81.57 lbs)	
TV System	Tuning	Frequency Synthesize
	System	PAL, SECAM
	Sound	MONO, STEREO, NICAM
Environmental Considerations	Operating Temperature : 50°F ~ 104°F (10°C ~ 40°C) Operating Humidity : 10 % ~ 80 % Storage Temperature : -4°F ~ 113°F (-20°C ~ 45°C) Storage Humidity : 5 % ~ 95 %	
Antenna Input	75Ω	
Sound Characteristic	-MAX Internal speaker Out : Right : 5W / Left : 5W -BASS Control Range : -8 dB ~ +8 dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-6 Spec Comparison

Model	LE26R51B/LE32R51B/LE40R51B/LE46R51B	LE26M5/LE32M5/LE40M5/LE46M5
Design		
Frequency		
Horizontal	30 ~ 60 kHz	30 ~ 60 kHz
Vertical	60 ~ 75 Hz	60 ~ 75 Hz
Display Color	16,777,216 colors	16,777,216 colors
PC Resolution		
Maximum mode	1366 x 768 @ 60 Hz	1360 x 768 @ 60 Hz
Input Signal		
Sync Signal	Separate H/V sync	H/V Separate, TTL, P. or N.
Video Signal	RGB, Analog	0.7 Vp-p @ 75ohm
Power Consumption		
Normal	285W	285 W
Power Saving	<20W	< 20 W

2-7 Option Specification

Item	Item Name	Code.No	Remark
	Remote Control & Batteries (AAA x 2)	BN59-00460A	
	RF Cable	AA39-00039A	
	Power Cord	3903-000085	
	Cleaning Cloth	BN63-001798A	
	Owner' s Instructions	BH68-00376M	
	Stand	LE26M5: BN96-02203A LE32M5: BN96-02202A	
	Cover-Bottom	LE26M5/LE32M5: BN63-01947A LE40M5: BN63-01938A LE46M5: BN63-01810A	

Memo

3 Alignments and Adjustments

3-1 Service Instruction

1. Usually, a color TV-VCR needs only slight touch-up adjustment upon installation.
Check the basic characteristics such as height, horizontal and vertical sync.
2. Use the specified test equipment or its equivalent.
3. Correct impedance matching is essential.
4. Avoid overload. Excessive signal from a sweep generator might overload the front-end of the TV. When inserting signal markers, do not allow the marker generator to distort test result.
5. Connect the TV only to an AC power source with voltage and frequency as specified on the backcover nameplate.
6. Do not attempt to connect or disconnect any wire while the TV is turned on. Make sure that the power cord is disconnected before replacing any parts.
7. To protect against shock hazard, use an isolation transform.

3-2 How to Access Service Mode

3-2-1 Entering Factory Mode

1. To enter "Service Mode" Press the remote -control keys in this sequence :
- If you do not have Factory remote - control



- If you have Factory remote - control



- The buttons are active in the service mode.

1. Remote - Control Key : Power, Arrow Up, Arrow Down, Arrow Left
Arrow Right, Menu, Enter, Number Key(0~9)
2. Function - Control Key : Power, CH +, CH -, VOL +, VOL -,
Menu, TV/VIDEO(Enter)

3-2-2 Panel Check

Specially for LE32R51BX, You have to check Panel Maker Because of different adjustments as follows.
First of all, Check the label rating!

1) Label Rating File



- LCD PANEL MARK -

A:ACER(AUO) S:SEC

* If not printed you could consider S(sec) panel mark.

2) If Panel Mark is "A", Set the factory mode indicating as follows.

- * Option Byte
- 1. Inch Option 32"
- 2. Gamma 32"AUO
- 3. Panel Option AUO

Others are same shown below.

3-3 Factory Data

1. Calibration

2. Option Table XXXX XXXX

3. White Balance

4. SVP-EX

5. MST9883

6. MSP34XX/44XX

7. YC Delay

8. Adjust

9. I2C Check

10. Chip Debugger : OFF

11. Checksum

12. Reset

13. Spread Spectrum

T-MILMPEU-1006 (*Main Micom Ver*)

T-MILMPEUS-1002 (*Sub Micom Ver*)

Month/ Day / Year / Hour/ Min./Sec.

1. Calibration

1. AV Calibration

2. DTV Calibration

3. PC Calibration

2. Option Byte XXXX XXXX

NO	Name	Range	Remark
1	Inch Option	32"	23"/26"/32"/40"
2	Gamma	32/AUO/CMO	OFF, 26AUO, 32AUO/CMO, AMLCD
3	Panel Option	AMLCD	AUO, CMO, AMLCD
4	Auto Power	On	ON/OFF
5	V-Chip	Off	ON/OFF
6	Anynet	Off	ON/OFF
7	LNA	Off	ON/OFF
8	Ant. Gain Display	Off	ON/OFF
9	Language	English	Osd언어
10	Auto FM	Off	ON/OFF
11	High Deviation	Off	ON/OFF
12	TTX	On	ON/OFF
13	TTX List	Flop	Flop/List
14	TTX TOP	Off	ON/OFF
15	TTX Group	Auto	TTX Language
16	TTX Level	Level 1.5	LEVEL 1.5 / 2.5
17	DNIE	On	ON/OFF
18	MSP Ver.	K	K/G
19	DVI	On	ON/OFF
20	Debug	Off	ON/OFF

Panel Life Time : X Day XX h XX m

3 Alignments and Adjustments

3. White Balance

No	Item		TV/AV	Component	PC	DVI(HDMI)
1	Sub-Brightness	0~255	80	115	128	140
2	R-offset	0~255	120	130	128	129
3	G-offset	0~255	128	128	128	128
4	B-offset	0~255	113	128	128	128
5	Sub-Contrast	0~63	36	32	32	28
6	R-Gain	0~255	140	129	128	130
7	G-Gain	0~255	128	128	128	128
8	B-Gain	0~255	150	128	128	120

4. SVP-EX

1. ComB Filter

No	Item	Range	EEPROM	NTSC	PAL	SECAM	Control IC	Remark
1	Y-Filter	0~255			80h			x

2. Peaking

No	Item	Range	EEPROM	TV	AV	Component	Control IC	Remark
1	V-Peaking	0~255			80h			x
2	Peaking Delay	0~255			80h			x
3	Peaking Gain	0~255			80h			x
4	Peaking Width	0~255			80h			x
5	Praking f0	0~255			80h			x

3. NR

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI	Control IC	Remark
1	Y-NR-Off	0~255			80h				x
2	C-NR-Off	0~255			80h				x
3	Y-NR-ON	0~255			80h				x
4	C-NR-ON	0~255			80h				x

4. Deinterlace

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI	Control IC	Remark
1	Motion	0~255			80h				x

5. Picture Gain Adjust

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI
1	TCD3 Contrast	0~255		AV Calibration(78h)	78h	78h	78h
2	TCD3 Brightness	0~255		AV Calibration(20h)	20h	20h	20h
3	TCD3 CR Saturation	0~255		78h	78h	78h	78h
4	TCD3 CB Saturation	0~255		78h	78h	78h	78h
5	TCD3 YC Delay	0~15		00h	00h	00h	00h
6	Analog Y offset	00~255		40h	3	40h	40h
7	Analog PB offset	00~255		80h	DTV Calibration(80h)	80h	80h
8	Analog PR offset	00~255		80h	DTV Calibration(80h)	80h	80h
9	Analog Y Gain	00~255		D6h	DTV Calibration(D6h)	D6h	D6h
10	Analog PB Gain	00~255		FEh	FEh	FEh	FEh
11	Analog PR Gain	00~255		FEh	FEh	FEh	FEh
12	Black Level Setting	00~255		00h			
13	Brightness(SVP)	0~255		00h			

5. MST9883

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI
1	R-Offset	00~255		151(SC1 RGB)		PC Calibration(128)	
2	G-Offset	00~255		151(SC1 RGB)		PC Calibration(128)	
3	B-Offset	00~255		151(SC1 RGB)		PC Calibration(128)	
4	R-Gain	00~255		123(SC1 RGB)		PC Calibration(192)	
5	G-Gain	00~255		123(SC1 RGB)		PC Calibration(192)	
6	B-Gain	00~255		123(SC1 RGB)		PC Calibration(192)	

6. MSP34XX/44XX

No	Item	Range	EEPROM	PAL
1	FM-Prescale	00~255		20h
2	NT-M-Prescale	00~255		20h
3	SECAM-L-Prescale	00~255		22h
4	NICAM-Prescale	00~255		42h
5	AV-Prescale	00~255		1Ah
6	I2S_1 Prescale	00~255		10h
7	I2S_2 Prescale	00~255		10h
8	Carrier Mute	00~255		42h
9	Pilot High	00~255		14
10	Pilot Low	00~255		7

7. YC Delay

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI
1	RF PAL-B/G	00~255		77h			
2	RF PAL-D/K	00~255		88h			
3	RF PAL-I	00~255		66h			
4	RF SECAM-B/G	00~255		88h			
5	RF SECAM-D/K	00~255		77h			
6	RF SECAM-J/L'	00~255		88h			
7	RF NTSC3.58	00~255		66h			
8	RF NTSC4.43	00~255		CCh			
9	AV PAL	00~255		77h			
10	AV SECAM	00~255		BBh			
11	AV NTSC 3.58	00~255		66h			
12	AV NTSC4.43	00~255		CCh			
13	AV PAL60	00~255		77h			

3 Alignments and Adjustments

8. Adjust

No	Item	Range	EEPROM	TV/AV/S_Video	Component	PC	DVI/HDMI	Control IC	Remark
1	Video Mute Time			10					
2	Melody Volume	0 ~ 20		5					
	Ana_Dimm_Max			FEH					
3	TTX Contrast	0 ~ 100		50					
4	TTX Brightness	0 ~ 100		50					
5	TTX Color	0 ~ 100		50					
6	Dynamic Contrast	0 ~ 100		100					
7	Dynamic Brightness	0 ~ 100		50					
8	Dynamic Color	0 ~ 100		55					
9	Dynamic Sharpness	0 ~ 100		75					
10	Standard Contrast	0 ~ 100		80					
11	Standard Brightness	0 ~ 100		50					
12	Standard Color	0 ~ 100		50					
13	Standard Sharpness	0 ~ 100		50					
14	Movie Contrast	0 ~ 100		70					
15	Movie Brightness	0 ~ 100		50					
16	Movie Color	0 ~ 100		25					
17	Movie Sharpness	0 ~ 100		45					
No	Item	Range	EEPROM	TV/AV/S-Video	Component/PC/HDMI				
1	LNA PLUS								
2	RFDB_1 Level			1					
3	RFDB_2 Level			5					
4	RFDB_3 Level			10					
5	RFDB_4 Level			16					

9. I2C Check

10. Chip Debugger : OFF

11. Checksum XXXX XXXX

12. Reset

13. Spread Spectrum

1	Spectrum	ON
2	Delta	-3
3	Positive	8
4	Negative	2

3 Alignments and Adjustments

3-4 Service Adjustment

3-4-1 White Balance - Calibration


If picture color is wrong, do calibration first.

Equipment : CA210, Patten : 16 gray

Execute calibration in Factory Mode

Source AV : PAL composite, Component : 1280*720/60Hz

PC : 1024*768/60Hz



3-4-2 White Balance - Adjustment

If picture color is wrong, check White Balance condition.

Equipment : CA210, Patten : Toshiba


Adjust W/B in Factory Mode

Sub brightness and R/G/B Offset controls low light region

Sub contrast and R/G/B Gain controls high light region

Source AV : PAL composite, Component : 1280*720/60Hz

HDMI[DVI] : 1280*720/60Hz



[Test Pattern : MSPG-945 Series Pattern #16]

*Color temperature

1500K +/-500, -6 ~-20 MPCD

*Color coordinate

H/L : 267/263 +/- 2 35.0 Ft +/- 2.0Ft

L/L : 270/260 +/- 3 1.5 Ft +/- 0.2Ft

3-4-3 Conditions for Measurement


1. On the basis of toshiba ABL pattern : High Light level (57 IRE)
 - INPUT SIGNAL GENERATOR : MSPG-925LTH
 - * Mode NO 1 : 744X484@60 Hz
 - NO 6 : 1280X720@60 Hz
 - NO 21 : 1024X768@60 Hz
 - * Pattern NO 36 : 16 Color Pattern
 - NO 16 : Toshiba ABL Pattern
2. Optical measuring device : CA210 (FL)

Please use the MSPG-925 LTH generator for model LE26M51B/LE32M51B/LE40M51B/LE46M51B.

3-4-4 Method of Adjustment

1. Adjust the basic level of DTV and PC input signals.
 - a) Set the input to the mode in which the adjustment will be made (DTV → PC).
 - * Input signal - DTV Mode : Model #6 (1280*720 Mode), Pattern #36
 - PC Mode : Model #21 (1024*768 Mode), Pattern #16 (Picture 4-1)
 - b) Enter factory Calibration, confirm the ADC data (DTV, PC Mode Only).
 - * ADC default value : Table 4-3.

Picture 4-1 Toshiba ABL Pattern




2. Adjust the white balance of RF, DTV, PC and DVI Modes.
 - a) Set the input to the mode in which the adjustment will be made
(RF → DTV → PC → DVI).
 - * Input signal - VIDEO Mode : Model #1 (744*484 Mode), Pattern #16
 - DTV,DVI Mode : Model #6 (1280*720 Mode), Pattern #16
 - PC Mode : Model #21 (1024*768 Mode), Pattern #16
 - b) Enter factory color control, confirm the data.

3 Alignments and Adjustments

c) Adjust the low light. (Refer to table 1, 2 in adjustment position by mode)

- Adjust sub - Brightness to set the 'Y' value.
- Adjust red offset ('x') and blue offset ('y') to the color coordinates.
- * Do not adjust green offset data.


Picture 4-2 Toshiba ABL Pattern



d) Adjust the high light. (Refer to table 1, 2 in adjustment position by mode)

- Adjust red gain ('x') and blue gain ('y') to the color coordinates.
- * Do not adjust the green gain and sub-contrast (Y) data.

Picture 4-3 Toshiba ABL Pattern



3-5 Software Upgrade

3-5-1 How to Update Flash ROM

1. Install the Flash Downloader


Connect Set (Service Jack) and Jig Cable to execute Program Update.



2. Flash Downloader program update

- Before Turning on the set, Click "connect" which is under of OSD Screen!

- Turn on the Set.



Memo


4 Troubleshooting

4-1 First Checklist for Troubleshooting


1. Check the various cable connections first.
 - Check to see if there is a burnt or damaged cable.
 - Check to see if there is a disconnected cable connection or a connection is too loose.
 - Check to see if the cables are connected according to the connection diagram.
2. Check the power input to the Video Board.
3. Check the voltage in and out between the SMPS ↔ Video Board, between the SMPS ↔ X, Y Drive Board, and between the Logic Boards.

4-2 Checkpoints by Error Mode

4-2-1 No Power




4-2-2 No Video (Analog PC Signal)




4 Troubleshooting

WAVEFORMS


1 R,G,B Output Signal of IC906




2 R,G,B Output Signal of IC312




3 Digital Output Data of IC201




4-2-3 No Video (HDMI-Digital Signal)



4 Troubleshooting




4-2-4 No Picture (Tuner_CVBS)




4 Troubleshooting

WAVEFORMS


3 Digital Output Data of IC201



5 Tuner_CVBS Output Signal




4-2-5 No Picture (Video_CVBS)




4 Troubleshooting

WAVEFORMS


3 Digital Output Data of IC515



5 Tuner_CVBS Output Signal




4-2-6 No Picture (S-VIDEO_Y,C)




4 Troubleshooting

WAVEFORMS


3 Digital Output Data of IC201



6 Analog Signal(Y,C) to IC201




4-2-7 No Sound




4 Troubleshooting

WAVEFORMS


7 The Signal are Inputed to IC610



8 DC +8V




9 Output WaveForm



5 Exploded View and Parts List

- You can search for updated part codes through ITSELF web site.
URL : <http://itself.sec.samsung.co.kr/>


5-1 LE26M51B



5 Exploded View & Parts List

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-02209B	ASSY COVER P-FRONT;MILANO,26EO,ABS,HB,BK	1		
M0112	BN63-01927B	COVER-FRONT;MILANO,26EO,ABS,HB,BK23,STEA	1	S.N.A	
T0069	BN63-01928A	COVER-MIDDLE;MILANO,26,ABS,V0,GR70,SV012	1	S.N.A	
T0603	BN64-00343A	WINDOW-RMC;ROME,40,PC,CLEAR	1	S.N.A	
T0022	BN64-00375A	KNOB CONTROL;MILANO,26,ABS+PC,GR70,SVM-3	1	S.N.A	
T0023	BN96-02244A	ASSY COVER P-KNOB POWER;MILANO,26,ABS,V0	1	S.N.A	
T0023	BN64-00376A	KNOB POWER;MILANO,26,ABS,V0,GR70,AL,H/ST	1	S.N.A	
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1		
T0023	BN64-00376A	KNOB POWER;MILANO,26,ABS,V0,GR70,AL,H/ST	1	S.N.A	
T0081	BN61-01821A	GUIDE-POWER;MILANO,26,ACRYL,SMOG	1	S.N.A	
T0175	BN96-02189B	ASSY SPEAKER P;16ohm,Right,5W,DTV Ready,	1		
M0215	BN07-00239A	LCD-PANEL;LTA260W2-L11,8bit,626.0*373.0*	1		
T0120	BN94-00699D	ASSY PCB POWER;ROME,32",Free Volt,CIS,##	1		
T0175	BN96-02188B	ASSY SPEAKER P;16ohm,Left,5W,DTV Ready,M	1		
M0131	AA63-01216A	GASKET;GSJ26KU,Conductive Fabric,1mm,30m	1	S.N.A	
M0131	AA63-01217A	GASKET;GSJ26KU,Conductive Fabric,27mm,15	1	S.N.A	
M0014	BN94-00736A	ASSY PCB MAIN-AMLCD;LE26M51BX/*	1		
M0013	BN96-02206B	ASSY COVER P-REAR;MILANO,26,HIPS,HB,GR50	1		
M0114	BN61-01605A	HOLDER-WIRE;FIRENZE 46,HIPS HB,GR503	1	S.N.A	
M0006	BN63-01929B	COVER-REAR;MILANO,26,HIPS,HB,GR503	1	S.N.A	
M0113	BN61-01302A	BRACKET-VESA;32,DUOMO,SECC,T1.6	1	S.N.A	
M0013	BN96-02203A	ASSY STAND P-BASE;26 MILANO,ABS HB,BK07,	1		
M0111	BN63-01946A	COVER-STAND;26 MILANO,ABS,HB,BK07,BKM150	1	S.N.A	
T0132	BN73-00052A	RUBBER FOOT;ARES 17,SILICON,DIA 17 * T1.	6	S.N.A	


5-2 LE32M51B, LE32M61B



5 Exploded View & Parts List

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-02208C	ASSY COVER P-FRONT;MILANO,32EO,ABS,HB,BK	1		
T0023	BN96-02244A	ASSY COVER P-KNOB POWER;MILANO,26,ABS,V0	1	S.N.A	
T0175	BN96-02191C	ASSY SPEAKER P;8ohm,Right,10W,DTV Ready,	1		
M0215	BN07-00243A	LCD-PANEL;LTA320W2-L03,8bit,760*450*50.0	1		
T0447	BN96-02551A	ASSY BRACKET P-PANEL;32 MILANO,SECC,READ	1	S.N.A	
T0120	BN94-00699D	ASSY PCB POWER;ROME,32",Free Volt,CIS,##	1		
M0013	BN96-02205B	ASSY COVER P-REAR;MILANO,32,HIPS,HB,GR50	1		
T0175	BN96-02190C	ASSY SPEAKER P;8ohm,Left,10W,DTV Ready,M	1		
M0013	BN96-02202A	ASSY STAND P-BASE;32 MILANO,ABS HB,BK07,	1		
M0014	BN94-00736B	ASSY PCB MAIN-AMLCD;LE32M51BX/*	1		
M0452	BN96-02438C	ASSY COVER P-HOLDER AV;MILANO,32,57EO,AB	1	S.N.A	
M0013	BN96-02202A	ASSY STAND P-BASE;32 MILANO,ABS HB,BK07,	1		


5-3 LE40M51B, LE40M61B



5 Exploded View & Parts List

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-02349C	ASSY COVER P-FRONT;MILANO,40EO,ABS,HB,BK	1		
T0023	BN96-02244A	ASSY COVER P-KNOB POWER;MILANO,26,ABS,V0	1	S.N.A	
T0175	BN96-02191D	ASSY SPEAKER P;8ohm,Right,10W,DTV Ready,	1		
T0852	BN91-00833E	ASSY LCD-SPZ;RE40EO*AM LCD	1	S.N.A	
T0447	BN96-02511B	ASSY BRACKET P-PANEL;MILANO,40,SECC,READ	1	S.N.A	
T0120	BN94-00622J	ASSY PCB POWER;ROME,40",FREE VOLT,CIS,CH	1		
M0112	BN96-01797A	ASSY SHIELD P-PCB;40" ROME,SECC,T0.5,REA	1	S.N.A	
M0013	BN96-02348B	ASSY COVER P-REAR;MILANO,40,HIPS,HB,GR50	1		
T0175	BN96-02190D	ASSY SPEAKER P;8ohm,Left,10W,DTV Ready,M	1		
M0014	BN94-00736C	ASSY PCB MAIN-AMLCD;LE40M51BX/*	1		
M0452	BN96-02447C	ASSY COVER P-HOLDER AV;MILANO,40,46EO,AB	1	S.N.A	
M0013	BN96-02350A	ASSY STAND P-BASE;MILANO,40,ABS HB,BK07,	1		

5-4 LE46M5



5 Exploded View & Parts List

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-02052C	ASSY COVER P-FRONT;MILANO,46EO,ABS,HB,BK	1		
T0023	BN96-02244A	ASSY COVER P-KNOB POWER;MILANO,26,ABS,V0	1	S.N.A	
M0146	BN96-02401A	ASSY BOARD P-POWER & IR;LNR329DX/XAA,CT5	1		
T0175	BN96-02077D	ASSY SPEAKER P;8ohm,Left,15W,400mm,Milan	1		
T0175	BN96-02078D	ASSY SPEAKER P;8ohm,Right,15W,400mm,Mila	1		
M0019	BN07-00187A	LCD;LTA460W2-L03,8BIT,1082.0*627.0*56.5,	1		
M0412	BN96-02412C	ASSY BRACKET P-PCB;MILANO,46,SECC T2.0,R	1	S.N.A	
M0452	BN96-02447C	ASSY COVER P-HOLDER AV;MILANO,40,46EO,AB	1	S.N.A	
M0014	BN94-00736D	ASSY PCB MAIN-AMLCD;LE46M51BX/*	1		
M0112	BN96-02411C	ASSY SHIELD P-PCB;46MILANO,SECC,T0.5,REA	1	S.N.A	
M0013	BN96-02053B	ASSY STAND P-BASE;46 MILANO,ABS HB,BK07,	1		
M0013	BN96-02200B	ASSY COVER P-REAR;46 MILANO,HIPS,HB,GR50	1		

6 Electrical Parts List

-You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
0		LE40M61BX/XEC	LE40M61B,Q72A/40M50-GMN,40,LCD-TV,SPAIN	0	
0.1	M0001	BN90-00763F	ASSY COVER FRONT;40M50,EO,MILANO-2	1	S.N.A
.2	M0081	6003-001003	SCREW-TAPITTE;BH,+,B,M4,L12,ZPC(BLK),SWR	1	S.N.A
.2	M0081	6006-001096	SCREW-TAPITTE;WP,BH,+,M4.0,L12,BLK,SWRCH	6	S.N.A
.2	T0175	BN96-02190D	ASSY SPEAKER P;8ohm,Left,10W,DTV Ready,M	1	
.2	T0175	BN96-02191D	ASSY SPEAKER P;8ohm,Right,10W,DTV Ready,	1	
.2	T0023	BN96-02244C	ASSY COVER P-KNOB POWER;MILANO-2,26,ABS,	1	
...3	T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	
...3	T0081	BN61-01821A	GUIDE-POWER;MILANO,26,ACRYL,SMOG	1	S.N.A
...3	T0023	BN64-00376C	KNOB POWER;MILANO-2,26,ABS,V0,BK07,H/STA	1	S.N.A
...3		BN64-00406B	KNOB-DECORATION;MILANO-2,ABS,HB,BK07,DGM	1	S.N.A
.2	T0003	BN96-02349F	ASSY COVER P-FRONT;MILANO-2,40EO,ABS,HB,	1	
...3	M0081	6003-001003	SCREW-TAPITTE;BH,+,B,M4,L12,ZPC(BLK),SWR	4	S.N.A
...3	M0081	6003-001003	SCREW-TAPITTE;BH,+,B,M4,L12,ZPC(BLK),SWR	2	S.N.A
...3	T0069	AA60-00091G	SPACER-FELT;-,FELT,200X10,-,BLK,T0.5,-	4	S.N.A
...3		BN63-01940E	COVER-DECORATION;MILANO-2,40EO,ABS,V0,BK	1	S.N.A
...3	T0069	BN63-01941A	COVER-MIDDLE;MILANO,40,ABS,V0,GR70,SV012	1	S.N.A
...3	M0112	BN63-01942C	COVER-FRONT;MILANO,40EO,ABS,HB,BK23,STEA	1	S.N.A
...3	C/F	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	1.983	S.N.A
...3	T0603	BN64-00343A	WINDOW-RMC;ROME,40,PC,CLEAR	1	S.N.A
...3	T0022	BN64-00375B	KNOB CONTROL;MILANO-2,26,ABS+PC,V0,BK07	1	S.N.A
...3	M0145	BN96-02400A	ASSY BOARD P-FUNCTION;LNR269DX/XAA,CT500	1	
...3	T0382	BP61-00509C	HOLDER-CARE;PJT,ACRYL-FOAM,T0.25,W20.0mm	0.28	S.N.A
.2	T0382	BP61-00495C	HOLDER-CARE;PJT,ACRYL-FOAM,T0.25,W30.0mm	0.2	S.N.A
0.1	M0002	BN90-00764C	ASSY COVER REAR;40M50,EO,HIPS,HB,GR503	1	S.N.A
.2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	10	
.2	M0013	BN96-02348B	ASSY COVER P-REAR;MILANO,40,HIPS,HB,GR50	1	
...3	M0081	6003-001003	SCREW-TAPITTE;BH,+,B,M4,L12,ZPC(BLK),SWR	2	S.N.A
...3	M0081	6003-001321	SCREW-TAPITTE;BH,+,B,M4,L8,ZPC(BLK),SWRC	4	
...3	M0113	BN61-01505A	BRACKET-VESA;40,ROME,SECC,T1.6	1	S.N.A
...3	M0114	BN61-01605A	HOLDER-WIRE;FIRENZE 46,HIPS HB,GR503	1	S.N.A
...3	M0006	BN63-01943B	COVER-REAR;MILANO,40,HIPS,HB,GR503	1	S.N.A
.2	M0081	6003-000115	SCREW-TAPITTE;BH,+,B,M3,L6,ZPC(BLK),SWRC	3	S.N.A
.2	T0130	BN96-02572A	ASSY COVER P-TERMINAL;MILANO,40EO,SCART	1	S.N.A
...3	M0081	6003-000282	SCREW-TAPITTE;BH,+,B,M3,L8,ZPC(BLK),SWCH	2	S.N.A
...3		BN61-01754A	HOLDER-BOSS;ROME 40,ABS,V0,T3.0,14,63,GR	1	S.N.A
...3		BN63-02113A	COVER-JACK;26,32,40,46 MILANO,HIPS,T3.0,	1	S.N.A
.2	CCM1	6001-001947	SCREW-MACHINE;BH,+,WSP,M6,L16,ZPC(WHT),S	2	
0.1	M0216	BN90-00765B	ASSY STAND;40M50,MILANO-2	1	S.N.A
.2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	4	
.2	M0013	BN96-02350B	ASSY STAND P-BASE;MILANO-2,40,ABS HB,BK0	1	
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	7	
...3	M0081	6003-001239	SCREW-TAPITTE;FH,+,B,M4,L10,ZPC(YEL),SWR	11	
...3		BN61-01811A	BRACKET-STAND BOTTOM;40 MILANO,SECC,T3.0	1	S.N.A
...3		BN61-01818A	GUIDE-STAND;40 MILANO,ABS HB,GR70	1	S.N.A
...3	M0111	BN63-01939B	COVER-STAND;40 MILANO-2,ABS,HB,BK07,BKN-	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,SILICON,DIA 17 * T1.	9	S.N.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
0.1	M0112	BN91-00903C	ASSY SHIELD;LE40M51BX/*	1	S.N.A
.2	M0081	6003-000133	SCREW-TAPTTIE;BH,+,;S,M4,L8,ZPC(BLK),SW	2	S.N.A
.2	M0081	6003-000133	SCREW-TAPTTIE;BH,+,;S,M4,L8,ZPC(BLK),SW	2	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	5	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	4	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	11	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	4	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	3	S.N.A
.2	M0081	6003-001003	SCREW-TAPTTIE;BH,+,B,M4,L12,ZPC(BLK),SWR	2	S.N.A
.2	CCM1	6006-000245	SCREW-MACHINE;WSP,PH,+,M4,L8,ZPC(YEL),SW	1	S.N.A
.2	T0562	6046-001013	STAND OFF;M3,L5,Ni PLT,SUM24L,#4-40	2	S.N.A
.2	T0245	AA39-20497B	LEAD CONNECTOR-ASSY;,1P,200,YFH800-01,RI	1	
.2	M2893	BN39-00028G	LEAD CONNECTOR;RE40**,UL1007#26,14P,200m	1	
.2	M0125	BN39-00046A	CBF-HARNESS;UL1007#26,3P,70MM,BLACK,AWG2	1	
.2	M2893	BN39-00603A	LEAD CONNECTOR;RE40**,UL1007#26,UL,14P,2	1	
.2	M2893	BN39-00604A	LEAD CONNECTOR;RE40**,UL1007#26,14P,600m	1	
.2	M2893	BN39-00605A	LEAD CONNECTOR;RE40**,UL2835#28,12/15P,4	1	
.2	M2893	BN39-00614A	LEAD CONNECTOR;RE40**,UL20276#30,30P,300	1	
.2	T0076	BN39-00615B	CBF HARNESS-INLET;RE40EO,UL1617#22/1015#	1	
.2		BN61-01501A	BRACKET-PANEL SIDE;40" ROME,SECC,T1.2,LE	1	S.N.A
.2		BN61-01502A	BRACKET-PANEL SIDE;40" ROME,SECC,T1.2,RI	1	S.N.A
.2		BN61-01820A	BRACKET-GUIDE STAND;40 MILANO,SECC,T1.0	1	S.N.A
.2		BN61-01824A	BRACKET-STAND LINK;40 MILANO,SECC,T2.0	1	S.N.A
.2	M0146	BN96-02401A	ASSY BOARD P-POWER & IR;LNR329DX/XAA,CT5	1	
.2	M0452	BN96-02447C	ASSY COVER P-HOLDER AV;MILANO,40,46EO,AB	1	S.N.A
...3		BN61-01975A	HOLDER-SIDE AV;40MILANO,HIPS V0,T3.0,GR5	1	S.N.A
...3	T0578	BN64-00403C	INLAY AV;MILANO,32,40,46,57,PS,T0.5,BLK,	1	S.N.A
...3		BN96-02439A	ASSY BOARD P-SUB AV SIDE;MILANO,CT5000-3	1	S.N.A
...3	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	2	S.N.A
.2	M2893	BP39-00177B	LEAD CONNECTOR;RE40**,UL1007#26,5P,150mm	1	
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	2	S.N.A
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	2	S.N.A
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	1	S.N.A
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.N.A
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.N.A
.2	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	9	S.N.A
.2		BN63-01949A	SHIELD CASE;26 MILANO,SPTE,T0.5,POWER	1	S.N.A
.2	M0112	BN96-01797A	ASSY SHIELD P-PCB;40" ROME,SECC,T0.5,REA	1	S.N.A
...3		BN63-01647A	SHIELD-PCB MAIN;40" ROME,SECC,T0.5,READY	1	S.N.A
...3		BN63-01649A	SHIELD-PCB SMPS;40" ROME,SECC,T0.5	1	S.N.A
.2	T0447	BN96-02511B	ASSY BRACKET P-PANEL;MILANO,40,SECC,READ	1	S.N.A
...3	M0081	6003-000115	SCREW-TAPTTIE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.N.A
...3		BN61-01503A	BRACKET-PANEL TOP;40" ROME,SECC,T1.2	1	S.N.A
...3		BN61-01822A	BRACKET-PANEL BOTTOM;40 MILANO,SECC,T1.6	1	S.N.A
...3	T0852	BN96-01871A	ASSY BRACKET P-GUIDE MAIN;40" ROME,SECC,	1	S.N.A
...4	M0131	AA63-01046A	GASKET;ROMR 40",Conductive Fabric,11mm,1	1	S.N.A
...4		BN61-01497B	BRACKET-GUIDE MAIN;40" ROEM,SECC,T1.2,BU	1	S.N.A
...4	M0131	AA63-01046B	GASKET;ROMR 40,Conductive Fabric,11mm,10	1	S.N.A
...3	MP1.0	BN96-01902A	ASSY BRACKET P-GUIDE POWER;ROME 40",SECC	1	S.N.A
...4	M0131	AA63-01047A	GASKET;ROMR 40,Conductive Fabric,5.5mm,1	1	S.N.A
...4		BN61-01499B	BRACKET-GUIDE POWER;40" ROME,SECC,T1.2,R	1	S.N.A
...3	MP1.0	BN96-02477A	ASSY BRACKET P-GUIDE POWER;ROME 40",SECC	1	S.N.A
...4	M0131	AA63-01048A	GASKET;ROMR 40,Conductive Fabric,1mm,10m	1	S.N.A
...4		BN61-01959A	BRACKET-GUIDE POWER;40 ROME,SECC,T1.2,LE	1	S.N.A
.2	M2893	BN39-00672B	LEAD CONNECTOR;LNR469DX/XAA,UL2835#28,14	1	
.2	M0162	6502-001027	CABLE CLAMP;DAWH-5NA,1D11.5,T3,NYLON66,N	1	S.N.A
.2	M0114	BN61-01710A	HOLDER-WIRE;NYLON 6/6,NATURAL,DAWH-2NC	1	S.N.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
.2	M0114	BN61-01778A	HOLDER-WIRE;NYLON-66,NATURAL or GRAY,DAF	2	S.N.A
0.1	T0852	BN91-00953B	ASSY LCD-SPZ;LE40M51BX/XEC	1	S.N.A
.2	M0215	BN07-00245A	LCD-PANEL;LTA400WS-LH1,8bit,952*551*51.0	1	
0.1	M0017	BN91-00962A	ASSY CHASSIS;LE40M61BX/*	1	S.N.A
.2	T0120	BN94-00622J	ASSY PCB POWER;ROME,40",FREE VOLT,CIS,CH	1	
...3	T0245	0202-001366	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb,	0.02	S.N.A
...3	D811S	0402-000102	DIODE-BRIDGE;D2SB60,600V,1.5A,SIP-4,ST	1	
...3	DP803	0402-000562	DIODE-RECTIFIER;UF5406,600V,3A,DO-201AD,	1	
...3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	1	
...3	PC802S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	1	
...3	PC803S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	1	
...3	PC811S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	1	
...3	T0086	1203-002177	IC-PWM CONTROLLER;VIPER12ADIP,DIP,8P,300	1	
...3	T0086	1203-003398	IC-PWM CONTROLLER;ICE1PCSO2,DIP,8P,9.52x	1	
...3	T0900	1404-001195	THERMISTOR-NTC;5.1ohm,15%,2900,27mW/C,BK	1	
...3	T0900	1404-001195	THERMISTOR-NTC;5.1ohm,15%,2900,27mW/C,BK	1	
...3	CY814S	2201-000963	C-CERAMIC,DISC;1NF,20%,400V,Y5U,TP,9.5X6	1	
...3	CX813S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	1	
...3	CX811S	2306-000321	C-FILM,LEAD-PPF;470NF,20%,275V,BK,31X11X	1	
...3	CX812S	2306-000321	C-FILM,LEAD-PPF;470NF,20%,275V,BK,31X11X	1	
...3	CP823	2401-003671	C-AL;120UF,##20%,450V,-,BK,25.4X30MM,10	1	
...3	CP824	2401-003671	C-AL;120UF,##20%,450V,-,BK,25.4X30MM,10	1	
...3	RL811S	3501-001053	RELAY-POWER;5VDC,530MW,10000MA,1FORMA,15	1	
...3	FD802	3601-001007	FUSE-CARTRIDGE;250V,6.3A,TIME-LAG,GLASS,	1	
...3	CN906	3711-000024	CONNECTOR-HEADER;BOX,3P,1R,2.5MM,STRAIGH	1	
...3	CN906	3711-002855	CONNECTOR-HEADER;BOX,2P,1R,7.92mm,STRAIG	1	
...3	CN906	3711-004122	CONNECTOR-HEADER;BOX,14P,1R,2mm,STRAIGHT	1	
...3	CN906	3711-004122	CONNECTOR-HEADER;BOX,14P,1R,2mm,STRAIGHT	1	
...3	CN906	3711-004122	CONNECTOR-HEADER;BOX,14P,1R,2mm,STRAIGHT	1	
...3	CN906	3711-004484	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	1	
...3	T0010	AA27-00119A	COIL CHOKE;10uH,-,10uH,10%,0.07,0.1ohm M	1	
...3	T0010	AA27-00119A	COIL CHOKE;10uH,-,10uH,10%,0.07,0.1ohm M	1	
...3	GT811	AA60-40012A	PIN-GT,ASSY;T1.6,1P	1	S.N.A
...3	GT811	AA60-40012B	PIN-GT,ASSY;T1.6,10MM,NYLON66	1	S.N.A
...3	GT811	AA60-40012B	PIN-GT,ASSY;T1.6,10MM,NYLON66	1	S.N.A
...3	DM807	AA96-50162N	ASSY HEAT SINK P;KA378R12,SCREW,AA62-300	1	S.N.A
...4	M0081	6003-000333	SCREW-TAPITTE;RH,+,2S,M3,L10,ZPC(YEL),SW	1	S.N.A
...4	T0066	AA62-30013E	HEAT SINK-ES;-A6063 EXTR,-,-,30(21) T02	1	S.N.A
...4	T0087	1203-002139	IC-POSI.FIXED REG.;378R12,TO-220F,4P,393	1	
...3	T811S	BN26-00004A	TRANS SWITCHING-DPMSS;EE 2020,LCD-TV,400V	1	
...3	T802S	BN26-00025A	TRANS SWITCHING,EER3541,DUOMO,DC200-380V	1	
...3	T801S	BN26-00026A	TRANS-INVERTER POWER;EER 4445,LCD TV,16P	1	
...3	LP801	BN27-00026A	COIL CHOKE-PFC;600uH,10%,ER4042,90T,PF 2	1	
...3	M0020	BN96-00324A	ASSY BOARD P;PDB20049A M,CONTROLLER ASS'	1	
...3	T0852	BN97-00457J	ASSY AUTO-POWER;ROME,40",FREE VOLT,CIS,C	1	S.N.A
...4	DI808	0401-000005	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	1	
...4	DI809	0401-000005	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	1	
...4	DM804	0401-000005	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	1	
...4	DP801	0401-000005	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T	1	
...4	DB812	0401-000006	DIODE-SWITCHING;BAV21,250V,200MA,DO-35,T	1	
...4	DM801	0401-000006	DIODE-SWITCHING;BAV21,250V,200MA,DO-35,T	1	
...4	DM803	0401-000006	DIODE-SWITCHING;BAV21,250V,200MA,DO-35,T	1	
...4	DB815	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	1	
...4	DB817	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	1	
...4	DB813	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	1	

6 Electrical Parts List

7-2 Others

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	DM802	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	1	
....4	DM806	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	1	
....4	DM809	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	1	
....4	DP804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	1	
....4	DM805	0402-001470	DIODE-RECTIFIER;RU2BV1,800V,1A,DO-204AC,	1	
....4	ZDI810	0403-000355	DIODE-ZENER;UZ5.1BSB,5-5.2V,500MW,DO-35,	1	
....4	ZDI808	0403-000510	DIODE-ZENER;MTZJ6.2B,5.96-6.27V,500MW,DO	1	
....4	ZDM803	0403-000510	DIODE-ZENER;MTZJ6.2B,5.96-6.27V,500MW,DO	1	
....4	ZDM802	0403-000720	DIODE-ZENER;MTZJ9.1B,8.57-9.01V,500MW,DO	1	
....4	ZDI809	0403-000753	DIODE-ZENER;MTZJ27D,26.2-27.6V,500MW,DO-	1	
....4	ZDB812	0403-001167	DIODE-ZENER;MTZJ30D,29.02-30.51V,500MW,D	1	
....4	ZDM804	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500MW,DO	1	
....4	ZDM806	0403-001320	DIODE-ZENER;MTZJ6.2C,6.16-6.4V,500MW,DO-	1	
....4	ZDB813	0403-001325	DIODE-ZENER;MTZJ15C,14.42-15.02V,500MW,D	1	
....4	ZDP803	0403-001325	DIODE-ZENER;MTZJ15C,14.42-15.02V,500MW,D	1	
....4	ZDP804	0403-001325	DIODE-ZENER;MTZJ15C,14.42-15.02V,500MW,D	1	
....4	ZDM801	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500MW,D	1	
....4	ZDI801	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.2V,500MW,DO	1	
....4	ZDM805	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.2V,500MW,DO	1	
....4	DB814	0404-001056	DIODE-SCHOTTKY;RK16.60V,1500mA,DO-204AC,	1	
....4	ZDB814	0406-001007	DIODE-TVS;P6KE180A,171/180V/189V,600W,CAS	1	
....4	ZDB816	0406-001062	DIODE-TVS;P6KE200A,190/200/210V,600W,CAS	1	
....4	ZDB815	0406-001106	DIODE-TVS;P6KE300A,285/-315V,600W,DO-20	1	
....4	Q813	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	1	
....4	QB811	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	1	
....4	QI807	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	1	
....4	QP802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	1	
....4	QB812	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	1	
....4	QI810	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	1	
....4	QM801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	1	
....4	IC012	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	1	
....4	IC012	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	1	
....4	VX811S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	1	
....4	RI809	2001-000019	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RM824	2001-000037	R-CARBON(S);3300OHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RI832	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RM822	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RP825	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RM815	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RB820	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI808	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI810	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RP803	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI807	2001-000302	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RP822	2001-000302	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RP823	2001-000302	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RB816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI818	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI830	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RM812	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RB815	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RB817	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI827	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RM817	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI831	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI835	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI802	2001-000745	R-CARBON;4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	RI820	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RI801	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	1	
....4	RM819	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	1	
....4	RB814	2001-001072	R-CARBON(S);120HM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RI834	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RI811	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RI837	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RM813	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RM816	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	1	
....4	RM818	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	1	
....4	RP809	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	1	
....4	RI805	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RM811	2001-001097	R-CARBON(S);2.4KOHM,5%,1/2W,AA,TP,2.4X6.	1	
....4	RP824	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	1	
....4	RM806	2001-001112	R-CARBON(S);24KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RM827	2001-001152	R-CARBON(S);47KOHM,5%,1/2W,AA,TP,2.4X6.4	1	
....4	RI833	2001-001168	R-CARBON(S);6.8KOHM,5%,1/2W,AA,TP,2.4X6.	1	
....4	RM801	2001-001174	R-CARBON;62KOHM,5%,1/2W,AA,TP,2.4X6.4MM	1	
....4	RM802	2001-001174	R-CARBON;62KOHM,5%,1/2W,AA,TP,2.4X6.4MM	1	
....4	RM803	2001-001174	R-CARBON;62KOHM,5%,1/2W,AA,TP,2.4X6.4MM	1	
....4	RM804	2001-001174	R-CARBON;62KOHM,5%,1/2W,AA,TP,2.4X6.4MM	1	
....4	RM805	2001-001174	R-CARBON;62KOHM,5%,1/2W,AA,TP,2.4X6.4MM	1	
....4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	1	
....4	RP810	2002-001016	R-COMPOSITION;330Kohm,5%,1/2W,AA,TP,3.7x	1	
....4	RP811	2002-001016	R-COMPOSITION;330Kohm,5%,1/2W,AA,TP,3.7x	1	
....4	RP804	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	1	
....4	RM807	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	1	
....4	RM808	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	1	
....4	RM809	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	1	
....4	RM810	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	1	
....4	RM820	2003-001023	R-METAL OXIDE(S);120ohm,5%,2W,AF,TP,3.9x	1	
....4	RM821	2003-002071	R-METAL OXIDE;560ohm,5%,2W,AF,TP,3.9x10m	1	
....4	RM823	2003-002071	R-METAL OXIDE;560ohm,5%,2W,AF,TP,3.9x10m	1	
....4	RB811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	1	
....4	RP843	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	1	
....4	RP844	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	1	
....4	RP845	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	1	
....4	RP839	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	1	
....4	RI819	2004-001379	R-METAL(S);12Kohm,1%,1/2W,AA,TP,2.4x6.4m	1	
....4	RP837	2004-001395	R-METAL(S);330Kohm,2%,1/2W,AA,TP,2.4x6.4	1	
....4	RP838	2004-001395	R-METAL(S);330Kohm,2%,1/2W,AA,TP,2.4x6.4	1	
....4	RI828	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	1	
....4	RP826	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	1	
....4	RI826	2004-004029	R-METAL(S);10Kohm,1%,1/2W,AA,TP,2.5x6.5m	1	
....4	RP841	2004-004029	R-METAL(S);10Kohm,1%,1/2W,AA,TP,2.5x6.5m	1	
....4	RM814	2008-000205	R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	1	
....4	RB813	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	1	
....4	RM826	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	1	
....4	FD801S	2008-001163	R-PICO FUSIBLE;10mohm,20%,1W,AA,TP,2.3x6	1	
....4	FD802S	2008-001163	R-PICO FUSIBLE;10mohm,20%,1W,AA,TP,2.3x6	1	
....4	VRM801	2103-000670	VR-SEMI;1Kohm,25%,1/5W,TOP	1	
....4	C1808	2201-000012	C-CERAMIC,DISC;0.22nF,10%,1000V,Y5P,-,6.	1	
....4	CB807	2201-000014	C-CERAMIC,DISC;0.33nF,10%,1KV,Y5P,TP,6.3	1	
....4	CM809	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	1	
....4	CI802	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1000V,Y5P,-,7x4	1	
....4	CI824	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1000V,Y5P,-,7x4	1	
....4	CP807	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1000V,Y5P,-,7x4	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	CM802	2201-000131	C-CERAMIC,DISC;0.1NF,10%,2KV,Y5P,TP,6.3X	1	
....4	CM803	2201-000131	C-CERAMIC,DISC;0.1NF,10%,2KV,Y5P,TP,6.3X	1	
....4	CM805	2201-000146	C-CERAMIC,DISC;0.1NF,5%,50V,SL,TP,5X3.5M	1	
....4	CM808	2201-000146	C-CERAMIC,DISC;0.1NF,5%,50V,SL,TP,5X3.5M	1	
....4	CP815	2201-000281	C-CERAMIC,DISC;1NF,+80-20%,50V,Y5V,TP,5X	1	
....4	CP801	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	1	
....4	CP802	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	1	
....4	CI820	2201-000376	C-CERAMIC,DISC;0.22NF,5%,50V,SL,TP,6.3X3	1	
....4	CM825	2201-000376	C-CERAMIC,DISC;0.22NF,5%,50V,SL,TP,6.3X3	1	
....4	CP819	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	1	
....4	CB809	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	1	
....4	CB810	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	1	
....4	CM814	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	1	
....4	CM815	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	1	
....4	CM816	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	1	
....4	CY803S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CY804S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CY805S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CY811S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CY812S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CY813S	2201-002026	C-CERAMIC,DISC;1NF,20%,400V,Y5P,TP,11X6M	1	
....4	CB814	2301-000356	C-FILM,LEAD-PEF;47nF,5%,50V,TP,7.5x4.0x6	1	
....4	CI801	2301-001396	C-FILM,LEAD-PEF;100nF,10%,630V,TP,18x6.5	1	
....4	CM821	2301-001396	C-FILM,LEAD-PEF;100nF,10%,630V,TP,18x6.5	1	
....4	CI811	2301-001741	C-FILM,LEAD;10nF,+5%,1600V,TP,18x15x8.5	1	
....4	CM801	2303-000122	C-FILM,LEAD-PEF;10nF,5%,630V,TP,19x12.5m	1	
....4	CI804	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	1	
....4	CI819	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	1	
....4	CM824	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	1	
....4	CI815	2305-000411	C-FILM,LEAD-PEF;470nF,5%,50V,TP,7.3x4.8x	1	
....4	CM806	2305-000411	C-FILM,LEAD-PEF;470nF,5%,50V,TP,7.3x4.8x	1	
....4	CB808	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	1	
....4	CI813	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	1	
....4	CM817	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	1	
....4	CM829	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	1	
....4	CB819	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CI821	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CI823	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CM812	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CM826	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CM827	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CP812	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CP816	2306-000122	C-FILM,LEAD-PPF;100nF,5%,50V,TP,7.3x4.0x	1	
....4	CB817	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	1	
....4	CM804	2401-000481	C-AL;10uF,20%,50V,WT,TP,5x11,5	1	
....4	CP811	2401-000603	C-AL;1uF,20%,50V,GP,TP,5X11,2	1	
....4	CM818	2401-000698	C-AL;2200uF,20%,16V,WT,TP,12.5x25,5	1	
....4	CM819	2401-000698	C-AL;2200uF,20%,16V,WT,TP,12.5x25,5	1	
....4	CM820	2401-000698	C-AL;2200uF,20%,16V,WT,TP,12.5x25,5	1	
....4	CI817	2401-000733	C-AL;2200uF,20%,35V,WT,TP,16x25,7.5	1	
....4	CI818	2401-000733	C-AL;2200uF,20%,35V,WT,TP,16x25,7.5	1	
....4	CP805	2401-000758	C-AL;0.22uF,20%,50V,GP,TP,5X11,5	1	
....4	CB813	2401-000957	C-AL;22uF,20%,450V,GP,BK,16X25MM,7.5	1	
....4	CM811	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	1	
....4	CM813	2401-001580	C-AL;47uF,20%,50V,LZ,TP,8x11.5mm,5m	1	
....4	CB816	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	1	
....4	CP809	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
...4	CP814	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	1	
...4	C1812	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	1	
...4	CM822	2401-003139	C-AL;1000uF,20%,25V,WT,TP,10*20,5mm	1	
...4	CM823	2401-003139	C-AL;1000uF,20%,25V,WT,TP,10*20,5mm	1	
...4	CM828	2401-003141	C-AL;2200uF,20%,25V,WT,TP,13x25,5mm	1	
...4	CM830	2401-003141	C-AL;2200uF,20%,25V,WT,TP,13x25,5mm	1	
...4	CM807	2401-003704	C-AL;1UF,##20%,100V,WT,TP,5X11MM,5	1	
...4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,3.5x5,TP,-	1	
...4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,3.5x5,TP,-	1	
...4	FD811S	3601-001064	FUSE-AXIAL LEAD;125V,4A,FAST-ACTING,GLAS	1	
...4	FS811A	3602-000114	FUSE-HOLDER;-,;30mohm	1	
...4	FS811B	3602-000114	FUSE-HOLDER;-,;30mohm	1	
...4	DB816	0403-000716	DIODE-ZENER;MTZJ4.7B,4.59-4.77V,500MW,DO	1	
...4	ZD1802	0403-001211	DIODE-ZENER;MTZJ12B,11.8-12.3V,500MW,DO	1	
...4	R1817	2001-001124	R-CARBON(S);3.9OHM,5%,1/2W,AA,TP,2.4X6.4	1	
...4	RB812	2008-000299	R-FUSIBLE(S);47ohm,5%,2W,AF,TP,3.9x10mm	1	
...4	RB819	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	1	
...4	RP812	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	1	
...4	RP813	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	1	
...4		2009-000017	R-METAL PLATE;0.1ohm,10%,5W,CL,TP,5x14x1	1	
...4	CB815	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	1	
...4	RX811S	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X	1	
...4	MP2.0	BN41-00521B	PCB-POWER;RE40EO,FR4,2,B,1.6T,330*197,1	1	S.N.A
...3	D801S	BP96-00631A	ASSY HEAT SINK P;BN62-00012B,SCREW,D5SB6	1	S.N.A
...4	CIS1	0205-001154	OIL-SILICON;G746,-,-	0.3	S.N.A
...4	M0081	6003-000333	SCREW-TAPITTE;RH,+,2S,M3,L10,ZPC(YEL),SW	1	S.N.A
...4	T0063	AA60-30003A	WASHER;T1.5,SBHG-1	1	S.N.A
...4	T0066	BN62-00012B	HEAT SINK-ES;DUOMO,A6063,2.0,20,50	1	S.N.A
...4	H/S	0402-001160	DIODE-BRIDGE;D5SB60,600V,6A,SIP-4,ST	1	
...3	IC804S	BP96-00632A	ASSY HEAT SINK P;BN62-00012C,SPRING,STR-	1	S.N.A
...4	CIS1	0205-001154	OIL-SILICON;G746,-,-	0.1	S.N.A
...4	M0144	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,T	1	S.N.A
...4	T0066	BN62-00012C	HEAT SINK-ES;DUOMO,A6063,2.0,20,50	1	S.N.A
...4	IC063	BN13-00006A	IC HYBRID;STR-W6765,DU32EO,6,-20 to +115	1	
...3	DM808	BP96-00633A	ASSY HEAT SINK P;BN62-00012D,SCREW,FML-G	1	S.N.A
...4	CIS1	0205-001154	OIL-SILICON;G746,-,-	0.3	S.N.A
...4	M0081	6003-000333	SCREW-TAPITTE;RH,+,2S,M3,L10,ZPC(YEL),SW	3	S.N.A
...4	T0066	BN62-00012D	HEAT SINK-ES;DUOMO,A6063,2.0,20,60	1	S.N.A
...4	H/S	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	2	
...4	H/S	0404-001253	DIODE-SCHOTTKY;GMR40H100CTBF3,100V,40000	1	
...3	IC801S	BP96-00714A	ASSY HEAT SINK P;BN62-00012F,SCREW,SPW-2	1	S.N.A
...4	CIS1	0205-001154	OIL-SILICON;G746,-,-	0.1	S.N.A
...4	M0081	6003-000333	SCREW-TAPITTE;RH,+,2S,M3,L10,ZPC(YEL),SW	5	S.N.A
...4	T0607	BN61-01056A	BRACKET-IC;SPD-50P4,SECC,T1.0	2	S.N.A
...4	T0066	BN62-00012F	HEAT SINK-ES;DUOMO,A6063,2.0,20,130,WHIT	1	S.N.A
...4	CCMM1	BN73-00047A	SILICON/RUBBER;VENUS,TC1370,17*19*T0.4,	2	S.N.A
...4	H/S	0402-001573	DIODE-RECTIFIER;UGF15JT,600V,15A,TO-220,	1	
...4	Q409	0505-001509	FET-SILICON;SPW20N60S5,N,600V,20A,0.16oh	2	
...4	Q409	0505-001762	FET-SILICON;IRFB20N50K,N,500V,20A,0.21OH	2	
...4	CCMM1	BN73-00047C	SILICON/RUBBER;Chagall 2,RUBBER,W27,L18,	2	S.N.A
...3	DI810	BP96-00818A	ASSY HEAT SINK P;BN62-00012G,SCREW,GMR40	1	S.N.A
...4	CIS1	0205-001154	OIL-SILICON;G746,-,-	0.4	S.N.A
...4	M0081	6003-000333	SCREW-TAPITTE;RH,+,2S,M3,L10,ZPC(YEL),SW	4	S.N.A
...4	T0066	BN62-00012G	HEAT SINK-ES;DUOMO,A6063,2.0,20,80	1	S.N.A
...4	H/S	0404-001253	DIODE-SCHOTTKY;GMR40H100CTBF3,100V,40000	4	
...3	RP805	2009-000017	R-METAL PLATE;0.1ohm,10%,5W,CL,TP,5x14x1	1	
...3	LX813S	BN29-00009A	FILTER LINE NOISE;ROME,SQE 3535H,20HM,30	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
...3	LX816S	BN29-00009A	FILTER LINE NOISE;ROME,SQE 3535H,20HM,30	1	
...3	RM825	2009-000026	R-METAL PLATE;0.150HM,10%.5W,CL,TP,5X14X	1	
...3	F101	2901-000297	FILTER-EMI ON BOARD;.3A,-,3.5x5,TP,-	1	
.2	M0014	BN94-00769A	ASSY PCB MAIN-AMLCD;LE40M61BX/*	1	
...3	T0245	0202-001366	SOLDER-WIRE FLUX-.RS60S,D1.2,63Sn/37Pb,	0.01	S.N.A
...3	JA751	3701-001294	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,AU	1	
...3	CN906	3705-001331	CONNECTOR-COAXIAL;PAL,ADAPTOR(J/J),-,750	1	
...3	CN906	3711-000057	CONNECTOR-HEADER;BOX,3P,1R,2.5MM,ANGLE,S	1	
...3	CN906	3711-004068	CONNECTOR-HEADER;BOX,5P,1R,2MM,ANGLE,SN,	1	
...3	CN906	3711-004122	CONNECTOR-HEADER;BOX,14P,1R,2mm,STRAIGHT	1	
...3	CN906	3711-004484	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	1	
...3	CN906	3711-004909	CONNECTOR-HEADER;BOX,14P,2R,2MM,ANGLE,SN	1	
...3	JA721_EU	3722-000498	JACK-SCART;21P,-,SN,BLK,NO	1	
...3	JA722_EU	3722-000498	JACK-SCART;21P,-,SN,BLK,NO	1	
...3	JA752	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	
...3	JA785	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	
...3	JA712	3722-001903	JACK-PIN;2P,-,AU,WHT/RED,-	1	
...3	JA714_EU	3722-001903	JACK-PIN;2P,-,AU,WHT/RED,-	1	
...3	JA784	3722-001903	JACK-PIN;2P,-,AU,WHT/RED,-	1	
...3	JA715_EU	3722-001938	JACK-PIN;3P,-,AU,GRN/BLU/RED,-	1	
...3	CIS3	BN40-00051A	TUNER;TMQZ6-404C,PDP-NELSON,PAL B/G,PAL	1	
...3	T0530	BN61-01521A	SUPPORT-PCB;ROME,SPTE,T0.5,L11.0	1	S.N.A
...3	T0530	BN61-01521A	SUPPORT-PCB;ROME,SPTE,T0.5,L11.0	1	S.N.A
...3	T0530	BN61-01521A	SUPPORT-PCB;ROME,SPTE,T0.5,L11.0	1	S.N.A
...3	M0107	BN63-01847A	SHIELD-COVER;ROME,SECC,T0.3,49.5,79.5,HE	1	S.N.A
...3	CIS6	BN73-00024C	SILICON/RUBBER-BERGQUIST;VENUS 32,40",SI	1	S.N.A
...3		BN97-00684A	ASSY SMD-AM LCD;LE40M51BX/*	1	S.N.A
...4	CIS5	0202-001375	SOLDER-CREAM;RMA-20-21L,S63,-,Sn63/Pb36.	7.46	S.N.A
...4	D101	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D709_EU	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7102	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7103	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7104	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7105	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D710_EU	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7113	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D7114	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D711_EU	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D712_EU	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D719	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D722	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D741	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D742	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D950	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D951	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D952	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D953	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D954	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D955	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D956	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D957	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200MA,SO	1	
...4	D812	0402-000553	DIODE-RECTIFIER;SS24,40V,2.0A,DO-214AA	1	
...4	D617	0403-000258	DIODE-ZENER;BZX84C5V6,5.2-6V,225MW,SOT-2	1	
...4	D620	0403-000258	DIODE-ZENER;BZX84C5V6,5.2-6V,225MW,SOT-2	1	
...4	D621	0403-000258	DIODE-ZENER;BZX84C5V6,5.2-6V,225MW,SOT-2	1	
...4	D901	0403-000258	DIODE-ZENER;BZX84C5V6,5.2-6V,225MW,SOT-2	1	
...4	D726_EU	0403-000579	DIODE-ZENER;BZX84C5V1,4.8-5.4V,200MW,SOT	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	D727_EU	0403-000579	DIODE-ZENER;BZX84C5V1,4.8-5.4V,200MW,SOT	1	
....4	D210	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D211	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D212	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D213	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D214	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D215	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D216	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D217	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D300_DE	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D769	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D770	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D771	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D930	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D961	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D962	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D970	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D971	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D972	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D973	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D974	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D975	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D980_DE	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D981_DE	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D990	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500MW,LL-	1	
....4	D725	0403-001016	DIODE-ZENER;RD8.2MB,5.96-6.27V,500mW,LL-	1	
....4	D701_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D702	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D703_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D704	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D705_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D706	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D707_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D708	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7108	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7109	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7110	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7111	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7112	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D713_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D714_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D715_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D716_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D717	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D718	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D720	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D721	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D723	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D724	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7301	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D743	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D744	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D745	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D746	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D748	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D750	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D751	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	D752	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D753_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D754_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7551	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7552	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D7553	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D755_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D756	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D757_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D758	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D759	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D760_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D761	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D762_EU	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D763	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D764	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D765	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D766	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D767	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D772	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D773	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D774	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D775	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D776	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D777	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D778	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D779	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D780	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D781	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D782	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D958	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D959	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D960	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D982_DE	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D983_DE	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200MW,SOT-2	1	
....4	D102	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350MW,SOT-23	1	
....4	D7302	0406-001172	DIODE-TVS;CDS3C30GTH,48V,0W,SMD	1	
....4	D7303	0406-001172	DIODE-TVS;CDS3C30GTH,48V,0W,SMD	1	
....4	D7304	0406-001172	DIODE-TVS;CDS3C30GTH,48V,0W,SMD	1	
....4	D7305	0406-001172	DIODE-TVS;CDS3C30GTH,48V,0W,SMD	1	
....4	D622	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	D911	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	D912	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	D963	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	D964	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	D976	0407-000123	DIODE-ARRAY;DAN202K,80V,100MA,CA2-3,SOT-	1	
....4	Q1211_EU	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	1	
....4	Q214_EU	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	1	
....4	Q100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q211	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q221	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q3004_EU	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q608	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q611	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q612	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q615	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q630	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	Q631	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q632	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q633	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q634	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q635	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q912_EU	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q918	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q930	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q931	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q952	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q970	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q971	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	
....4	Q1210_EU	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q1212_EU	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q212_EU	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q213_EU	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q215	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q216	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q610	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q620	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q801	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q802	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q803	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q910	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q911	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	
....4	Q409	0505-001170	FET-SILICON;Si19933ADY-T1,P,-20V,3.4A,0.0	1	
....4	IC104	0801-002095	IC-CMOS LOGIC;74LCX245,TRANSCEIVER,TSSOP	1	
....4	IC104	0801-002267	IC-CMOS LOGIC;74LCX14,-,SOIC,14P,150MIL,	1	
....4	IC104	0801-002267	IC-CMOS LOGIC;74LCX14,-,SOIC,14P,150MIL,	1	
....4	IC104	0801-002633	IC-CMOS LOGIC;NC7WBD3125,2BIT BUS SWITCH	1	
....4	IC901	0903-001362	IC-MICROCOMPUTER;M30620SPGP,16BIT,LQFP,1	1	
....4	IC605	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	
....4	IC106	1001-001082	IC-VIDEO SWITCH;BA7657F,-,SOP,24P,300MIL	1	
....4	IC909_EU	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	
....4	IC913	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	
....4	IC203	1001-001211	IC-ANALOG MULTIPLEX;MM74HC4052MTC,DUALMU	1	
....4	IC108	1002-001398	IC-A/D CONVERTER;MST9883CR-110,24Bit(8x3	1	
....4	IC110	1006-001076	IC-DRIVER/RECEIVER;MAX232ECWE+T,SOP,16P,	1	
....4	IC112	1103-000129	IC-EEPROM;24C02,256x8,SOP,8P,5x4mm,4.5/5	1	
....4	IC112	1103-000129	IC-EEPROM;24C02,256x8,SOP,8P,5x4mm,4.5/5	1	
....4	IC112	1103-001279	IC-EEPROM;24C32,4Kx8,SOP,8P,5x4mm,2.5/5.	1	
....4	IC113	1105-001674	IC-DRAM;EM6A9320BI,4Mx32Bit,FBGA,144P,12	1	
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	
....4	T0085	1201-001495	IC-AUDIO AMP;7050,SOP,8P,150MIL,DUAL,26D	1	
....4	T0085	1201-002119	IC-AUDIO AMP;TPA3004D2,HTQFP,48P,7x7mm,-	1	
....4	IC616	1203-001109	IC-VOL. DETECTOR;7045,SOT-89,3P,-,PLASTI	1	
....4	IC905	1203-001559	IC-RESET;DS1834A,SOIC,8P,150MIL,PLASTIC,	1	
....4	T0087	1203-001815	IC-POSI.FIXED REG.;78M09,TO-252,3P,-,PLA	1	
....4	T0087	1203-001816	IC-POSI.FIXED REG.;78M08,TO-252,3P,-,PLA	1	
....4	IC920	1203-001824	IC-VOL. DETECTOR;7042,SOT-89,3P,-,PLASTI	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	T0087	1203-002708	IC-POSI.FIXED REG.;1085,TO-263,3P,340MIL	1	
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	
....4	T0087	1203-002844	IC-POSI.FIXED REG.;AP1117D-18A,TO-252-3L	1	
....4	T0087	1203-002855	IC-POSI.FIXED REG.;MC33269DTRK-5.0,DPRK,	1	
....4	T0087	1203-002855	IC-POSI.FIXED REG.;MC33269DTRK-5.0,DPRK,	1	
....4	T0087	1203-002974	IC-POSI.FIXED REG.;AP1117D-25A,TO-252,3P	1	
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	
....4	IC118	1204-002352	IC-VIDEO PROCESS;SVP-EX52-7052,PQFP,256P	1	
....4	IC610	1204-002411	IC-AUDIO PROCESSOR;MSP4410K-QA-B3-500,PQ	1	
....4	IC311	1205-002383	IC-RECEIVER;SII9993CT100,TQFP,100P,14x14	1	
....4	R229	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	
....4	R230	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	
....4	R2357	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R919	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R9401	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R9405	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R9407_EU	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R963	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R964	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R965	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R966	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R9661	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R9662	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	
....4	R121	2007-000060	R-CHIP;100Kohm,1%,1/10W,TP,1608	1	
....4	40_	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	EO_	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R2008_OP	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R207	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R214	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R216	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R221	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R222	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R223	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R236	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R237	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R239	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R240	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R241	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R245	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R247	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R248	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R280	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R281	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R282	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R283	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R3261_EU	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R331	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R332	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R333	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R375	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R378	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R380_EU	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R381_EU	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R640	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	
....4	R645	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R646	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R650	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R651	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R652	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R655	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R681	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R686	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R688	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R717_EU	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R718_EU	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R7602_EU	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R7618_EU	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R7716_EU	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R772	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R788_OP	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9124	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9125	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9129	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R918	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9207	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9209	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9215	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9330	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R934	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R935	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9403	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R960	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9664	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R9665	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R994	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R995	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R996	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R997	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	1	
....4	R201	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R2013	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R2015	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R202	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R203	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R206	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R208	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R209	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R210	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R212	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R337	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R340	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R345	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R754	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R758	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R9673	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	1	
....4	R100	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R101	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R347	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R349	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R350	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R351	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R616	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	
....4	R617	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R761	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R7610	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R7611	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R762	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R782	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R783	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R982	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R983	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R984	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R985	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R986	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	
....4	R102	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R104	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R1245_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R2344	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R2345	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R252_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R260	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R261	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R270	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R271	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R272	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R273	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R3159_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R334	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R613	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R614	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R618	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R628	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R629	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R630	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R631	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7111_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7120	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R719_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R738	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R745	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R757	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7590	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7613	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7614	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7619	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R7630	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R781	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R799_OP	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9110_EU	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9119	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9120	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9122	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9123	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R932	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R936	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R937	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R940	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R941	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R953	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R954	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R955	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R962	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9668	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R9669	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R967	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R968	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R969	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R974	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R975	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R976	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R990	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R991	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R992	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R993	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	
....4	R291	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	
....4	R190	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R711_EU	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R713_EU	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R747_EU	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R748	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R7490	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R749_EU	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	
....4	R1246	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R1267_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R1268_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R2358	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R251_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R253_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R254_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R355	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R356	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R357	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R712_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R748_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R750_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R7582	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R7585_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R7588	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R7616_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R7617_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R765	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R766	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R793	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R794	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R9108_EU	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R9663	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	
....4	R131_OP	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R211	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R258	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R259	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R323	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R3260_EU	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R615	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R6402	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R6404	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R692	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R696	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R767	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R768	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R9104_EU	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R924	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R931	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R9666	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R9667	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	
....4	R204	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	1	
....4	R205	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,1608	1	
....4	R693	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,1608	1	
....4	R224	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R242	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R244	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R338	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R925	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R926	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R927	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R928	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R938	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R939	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R945	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R946	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R9671	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R9672	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	
....4	R225	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R2356	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R238	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R256	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R257	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R321	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R336	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R339	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R342	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R343	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R619	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R632	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R657	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R810	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9109_EU	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9118	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9132	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R917	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9187	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9213	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9222	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9224	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9231	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9232	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9234	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9235	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9238	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R929	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9332	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9334_EU	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9335	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9336	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9402	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R942	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R943	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R944	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R9670	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R988	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R989	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	
....4	R626_OP	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	1	
....4	R627_OP	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	1	
....4	R714_EU	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	1	
....4	R743_EU	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	1	
....4	R233	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R623	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R639	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R641	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R642	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R649	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R690	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R691	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R759	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R760	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R7609	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R7612	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R763	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R802	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R803	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R804	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R805	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R812	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R8877	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R901	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R907_EU	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R913	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R9131	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R9133	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R9135	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R9211	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R957	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	
....4	R679	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	
....4	R860	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	1	
....4	R861	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	
....4	R621	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	
....4	R622	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	
....4	R191	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	
....4	R9337	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	
....4	R1270_EU	2007-000096	R-CHIP;30Kohm,5%,1/10W,TP,1608	1	
....4	R249_EU	2007-000096	R-CHIP;30Kohm,5%,1/10W,TP,1608	1	
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R111	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R633	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R634	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R635	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R638	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R7608	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R795	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R796	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R797	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R798	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R9114	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	
....4	R601	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R602	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R603	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R604	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R605	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R606	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R607	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R608	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R609	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R610	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R611	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R612	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R670	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R671	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R672	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R673	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608	1	
....4	R175	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R310_EU	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R636	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R637	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R801	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R806	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R9675	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	
....4	R653	2007-000103	R-CHIP;120Kohm,5%,1/10W,TP,1608	1	
....4	R105	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	
....4	R120	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	
....4	R1260_EU	2007-000120	R-CHIP;680ohm,5%,1/10W,TP,1608	1	
....4	R255_EU	2007-000120	R-CHIP;680ohm,5%,1/10W,TP,1608	1	
....4	R811	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9111	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9112	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9113	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9115	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9116	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R9117	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	
....4	R335	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	1	
....4	R647	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	
....4	R1271_EU	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R250_EU	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R262	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R263	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R264	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R265	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R266	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R267	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R268	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R269	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R643_OP	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R644_OP	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	1	
....4	R7132	2007-000293	R-CHIP;100ohm,5%,1/4W,TP,3216	1	
....4	R7133	2007-000293	R-CHIP;100ohm,5%,1/4W,TP,3216	1	
....4	R7134	2007-000293	R-CHIP;100ohm,5%,1/4W,TP,3216	1	
....4	R721	2007-000293	R-CHIP;100ohm,5%,1/4W,TP,3216	1	
....4	R722	2007-000293	R-CHIP;100ohm,5%,1/4W,TP,3216	1	
....4	R3111	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	R7309	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7310	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7311	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7312	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7313	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7314	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7315	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R7316	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R900_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R902_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R903_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R904_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R905_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R906_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R908_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R909_EU	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9100	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9101	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9102	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9103	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9105	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9106	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9128	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9331	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9501_OP	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R9502_OP	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R951_OP	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R952	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R956_OP	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R970	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R971	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R972	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R973	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R977	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R978	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R979	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R981	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R998	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R999	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	RA920	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	
....4	R694	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	1	
....4	R715_EU	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	1	
....4	R746_EU	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	1	
....4	R328	2007-000779	R-CHIP;33ohm,1%,1/10W,TP,1608	1	
....4	R330	2007-000779	R-CHIP;33ohm,1%,1/10W,TP,1608	1	
....4	R327	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	
....4	R624	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	
....4	R625	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	
....4	R292	2007-000903	R-CHIP;430ohm,1%,1/10W,TP,1608	1	
....4	R231	2007-001014	R-CHIP;51OHM,5%,1/10W,TP,1608	1	
....4	R232	2007-001014	R-CHIP;51OHM,5%,1/10W,TP,1608	1	
....4	R858	2007-001068	R-CHIP;6.8Kohm,1%,1/10W,TP,1608	1	
....4	C7790	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
....4	R103	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
....4	R710_EU	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
....4	R7112_EU	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
....4	R7140_EU	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	

6 Electrical Parts List

7-2 Others

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
...4	R744	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7581	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7583	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7584	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7587_EU	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R770	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R771	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7788	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R7789	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	
...4	R352	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R353	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R354	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R751	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R752	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R753	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R755	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	R756	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	
...4	RA2015	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2016	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2017	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2018	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2019	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2020	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2021	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA2022	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA933	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	
...4	RA934	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	
...4	RA323	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA324	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA325	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA326	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA327	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA328	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA329	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA330	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	
...4	RA316	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA317	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA318	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA319	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA320	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA321	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA322	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA913	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA914	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA915	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA916	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA917	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA919	2011-000651	R-NET;10ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA910	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA911	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA912	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA922	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA923	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA924	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA925	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA926	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
...4	RA927	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	RA928	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
....4	RA929	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
....4	RA930	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
....4	RA931	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
....4	RA932	2011-001093	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP,3216	1	
....4	C3069_EU	2203-000041	C-CER,CHIP;0.01nF,0.25pF,50V,C0G,1608	1	
....4	C622	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	
....4	C646	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C2061	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C2065	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C2102	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C2104	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C2106	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C224	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C225	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C236	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C240	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C241	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C242	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C243	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C244	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C245	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C246	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C247	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C248	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C249	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C25026	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C252	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C253	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C254	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C255	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C256	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C258	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C259	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C260	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C261	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C262	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C263	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C264	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C265	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C266	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C267	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C268	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C269	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C277	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C279	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C281	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C285	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C286	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C287	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C288	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C289	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C290	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C291	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C292	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C293	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C294	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C295	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C296	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C298	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C299	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C310_EU	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C317	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C331	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C349	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C353	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C356	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C357	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C359	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C380	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C383	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C385	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C389	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C630	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C649	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C654	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C669	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C671	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C676	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C686	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C687	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C736	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C737	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C802	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C805	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C808	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C811	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C814	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C818	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C820	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C868	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C877	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C907	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C939	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C953	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C955	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C9846	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	
....4	C118	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C119	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C25020	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C25021	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C25022	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C25023	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C283	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C323	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C344	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C387	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C5132	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C695_OP	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C696_OP	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C697_OP	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C698_OP	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	
....4	C701_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,COG,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C702	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C703_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C704	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C729_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C730_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C731	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C732_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C733	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C734	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C735	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C9233_EU	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C988	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C989	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	
....4	C102	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C105	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C106	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C213	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C214	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C215	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C216	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C217	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C223	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C226	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C2301	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C388	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C803	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C806	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C809	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C812	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C819	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C838	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C854	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C869	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C932	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C934	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C936	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C937	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C940	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	
....4	C707_EU	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	
....4	C850	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	
....4	C25016	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C25017	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C25018	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C25019	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C341	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C350	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C351	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C354	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C355	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C381	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C386	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C635	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C636	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C901	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C903	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C906	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
....4	C9548	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
...4	C9549	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
...4	C990	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	
...4	C109	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	1	
...4	C238	2203-000552	C-CER,CHIP;0.02nF,5%,50V,C0G,TP,1608	1	
...4	C239	2203-000552	C-CER,CHIP;0.02nF,5%,50V,C0G,TP,1608	1	
...4	C919	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	
...4	C920	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	
...4	C929	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	
...4	C930	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	
...4	C8822	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	
...4	C739	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C742	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C7420	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C7422	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C749	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C750	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C7579	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C760	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	D747	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	
...4	C271_EU	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C7763_EU	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C7764_EU	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C7765_EU	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C921	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C922	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	
...4	C333	2203-000838	C-CER,CHIP;0.39nF,5%,50V,C0G,TP,1608	1	
...4	C332	2203-000843	C-CER,CHIP;0.39nF,10%,25V,X7R,1608	1	
...4	C627	2203-000872	C-CER,CHIP;0.003nF,0.25PF,50V,C0G,TP,160	1	
...4	C628	2203-000872	C-CER,CHIP;0.003nF,0.25PF,50V,C0G,TP,160	1	
...4	C110	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C218	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C219	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C324	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C335	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C633	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C634	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	
...4	C107	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,TP,1608	1	
...4	C620	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,TP,1608	1	
...4	C370	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	
...4	C667	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	
...4	C668	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	
...4	C681	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	
...4	C685	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	
...4	C705_EU	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	
...4	C728_EU	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	
...4	C935	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	
...4	C624	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	
...4	C625	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	
...4	C626	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	
...4	C664	2203-001391	C-CER,CHIP;150nF,10%,25V,X7R,TP,2012,-	1	
...4	C665	2203-001391	C-CER,CHIP;150nF,10%,25V,X7R,TP,2012,-	1	
...4	C682	2203-001391	C-CER,CHIP;150nF,10%,25V,X7R,TP,2012,-	1	
...4	C684	2203-001391	C-CER,CHIP;150nF,10%,25V,X7R,TP,2012,-	1	
...4	C108	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	
...4	C675	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	
...4	C657	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,1608	1	
...4	C658	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C623	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	
....4	C644	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	
....4	C956_EU	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	
....4	C100	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C113	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C2107	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C211	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C212	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C222	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C228	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C230	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C231	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C232	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C25025	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C3068_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C321	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C322	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C325	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C327	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C328	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C329	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C330	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C334	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C336	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C337	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C338	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C339	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C340	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C342	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C343	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C346	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C347	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C348	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C361	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C392	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C394	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C609	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C632	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C647	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C679	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C816	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C823	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C825	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C837	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C840	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C842	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C848	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C860	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C862	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C864	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C866	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C871	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C873	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C874	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C881	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C883	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C918	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C941	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C942	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C944_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C946_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C948_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C950_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C952_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C955_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C957_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C960	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C962	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C963	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C964	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C967	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C970_EU	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C991	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C992	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C993	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C994	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C995	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C997	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C998	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	
....4	C666	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	
....4	C683	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	
....4	C1301_EU	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C2049	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C235	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C237	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C3070_EU	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C638	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C639	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C680	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C689	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C690	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C691	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C692	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C693	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C826	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C827	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C876	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C928	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	
....4	C371	2203-005437	C-CER,CHIP;10000nF,+80-20%,10V,Y5V,TP,32	1	
....4	C674	2203-006036	C-CER,CHIP;680nF,+80-20%,16V,Y5V,TP,1608	1	
....4	C678	2203-006036	C-CER,CHIP;680nF,+80-20%,16V,Y5V,TP,1608	1	
....4	C738	2402-00108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.4	1	
....4	C670	2402-001081	C-AL,SMD;100uF,20%,25V,WT,TP,8.3x8.3x10	1	
....4	C688	2402-001081	C-AL,SMD;100uF,20%,25V,WT,TP,8.3x8.3x10	1	
....4	C801	2402-001081	C-AL,SMD;100uF,20%,25V,WT,TP,8.3x8.3x10	1	
....4	C817	2402-001081	C-AL,SMD;100uF,20%,25V,WT,TP,8.3x8.3x10	1	
....4	C836	2402-001081	C-AL,SMD;100uF,20%,25V,WT,TP,8.3x8.3x10	1	
....4	C101	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C210	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C220	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C25027	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C345	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C391	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C648	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C660	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C677	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C804	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C807	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C865	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C867	2402-001128	C-AL,SMD:100UF,20%,16V,WT,TP,6.3X5.7MM	1	
....4	C115_OP	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C619	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C655	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C938	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C958_EU	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C959_EU	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM	1	
....4	C2109	2402-001158	C-AL,SMD:1UF,20%,50V,WT,TP,4X5.2MM	1	
....4	C250	2402-001158	C-AL,SMD:1UF,20%,50V,WT,TP,4X5.2MM	1	
....4	C2060	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C2064	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C2100	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C2101	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C2103	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C2105	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C229	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C233	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C234	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C25015	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C25024	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C270_EU	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C272_EU	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C273	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C274	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C275	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C276	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C278	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C280	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C282	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C297	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C390	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C601	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C602	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C603	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C604	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C605	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C606	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C607	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C608	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C6105	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C611	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C612	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C6120	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C629	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C631	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C645	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C650	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C651	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C652	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C653	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C7766	2402-001178	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	C839	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C910	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C923	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C933	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C943_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C945_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C947_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C949_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C951_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C953_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C9540	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C9543	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C961	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C965	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C966	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C971_EU	2402-001178	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.8m	1	
....4	C103	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C112	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C2108	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C227	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C284	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C320	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C326	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C352	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C358	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C382	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C384	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C610	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C621	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C656	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C659	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C813	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C815	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C821	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C822	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C824	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C853	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C855	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C861	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C863	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C870	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C872	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C875	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C880	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C882	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C931	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C996	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	
....4	C1671_EU	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C393	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C6104	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C613	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C614	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C615	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C616	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C617	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C618	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	
....4	C104	2402-001238	C-AL,SMD;1uF,20%,50V,HR,TP,4.3x4.3x5.2mm	1	

6 Electrical Parts List

6 Electrical Parts List


Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
...4	X610	2801-004300	CRYSTAL-SMD;18.432MHz,30ppm,28-ABX,13pF,	1	
...4	F103	2901-001264	FILTER-EMI SMD;25V,1A,-,297PF,3.2X1.6X10	1	
...4	F103	2901-001302	FILTER-EMI SMD;20V,0.3A,-,2.0x1.2x1.3m	1	
...4	F103	2901-001302	FILTER-EMI SMD;20V,0.3A,-,2.0x1.2x1.3m	1	
...4	F103	2901-001302	FILTER-EMI SMD;20V,0.3A,-,2.0x1.2x1.3m	1	
...4	F103	2901-001302	FILTER-EMI SMD;20V,0.3A,-,2.0x1.2x1.3m	1	
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	T0568	3301-001145	BEAD-SMD;60OHM,4516,6000,TP,70OHM/45MHZ,	1	S.N.A
...4	J4711	3701-001311	CONNECTOR-HDMI:21P,2R,FEMALE,SMD-S,AU30U	1	
...4	CN906	3711-005291	CONNECTOR-HEADER;BOX,2P,1R,2MM,SMD-A,SN,	1	
...4	CN906	3711-005292	CONNECTOR-HEADER;BOX,3P,1R,2MM,SMD-A,SN,	1	
...4	CN906	3711-005470	CONNECTOR-HEADER;BOX,30P,1R,1.25mm,SMD-A	1	

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	EA	SA/SNA
....4	CN906	3711-005497	CONNECTOR-HEADER;BOX,15P,1R,1.25MM,SMD-A	1	
....4	L811	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5.GH15/17PS,22	1	
....4	T0010	BN27-00009A	COIL CHOKE;SMD 12X12X6,EO5,33UH,15%,-,0.	1	
....4	T0010	BN27-00009A	COIL CHOKE;SMD 12X12X6,EO5,33UH,15%,-,0.	1	
....4	T0010	BN27-00009A	COIL CHOKE;SMD 12X12X6,EO5,33UH,15%,-,0.	1	
....4	T0010	BN27-00009A	COIL CHOKE;SMD 12X12X6,EO5,33UH,15%,-,0.	1	
....4	T0077	BN41-00630A	PCB MAIN;MILANO,FR-4,4,MP1.0,1.6,195*200	1	S.N.A
....4	M0018	BN97-00484B	ASSY MICOM:NEW	1	
....5	IC520	0903-001389	IC-MICROCONTROLLER;S3F866B,8Bit,QFP,44P,	1	S.N.A
....4	M0018	BN97-00683A	ASSY MICOM:20050628,1107-001555,GMN40KE-	1	
....5	IC115	1107-001555	IC-FLASH MEMORY;49BV802A,8MBIT,1MX8/512K	1	
0.1	M0019	BN92-01044V	ASSY LABEL;LM	1	S.N.A
0.1	M0003	BN92-01515C	ASSY BOX;40M50,EO	1	S.N.A
.2		BN69-01101C	BOX-00,SET;ML40KE,DY-01,AB,YEL,A1,EUROPE	1.02	S.N.A
0.1	M0113	BN92-01516A	ASSY P/MATERIAL;40M50	1	S.N.A
.2	T0376	6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	0.05	S.N.A
.2	T0376	6902-000379	BAG AIR;LDPE,T0.2,W1000,L1800,TRP,,-	0.015	S.N.A
.2		6902-000604	BAG WRAPPING;LDPE,T0.02,W500,L10000,TRP,	13.96	S.N.A
.2	T0527	6902-000703	BAG SHEET;HDPE/PE FOAM,T0.015/T1.0,W1300	1	S.N.A
0.1	M0045	BN92-01573P	ASSY ACCESSORY;LE40M61BX/XEC	1	S.N.A
.2	M0045	BN96-02756Q	ASSY ACCESSORY;LE40M61BX/XEC	1	
...3	T0268	3903-000042	CBF-POWER CORD;DT,EU,FP3/YES,IEC320 C13/	1	
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,L356,W240,TRP,28,2,P	1	S.N.A
...3	ACCESSORY	AA68-00291A	MANUAL-S/NETWORK;-,SPANISH,-,B5,W/P100G,	1	S.N.A
...3	ACCESSORY	AA68-01092B	MANUAL-S/NETWORK;ITA,B5,W/P100(G),1,1P,	1	S.N.A
...3	T0610	AA68-03242E	MANUAL-SAFETY GUIDE;All Model,SAMSUNG,8L	1	S.N.A
...3	ACCESSORY	AA68-03575A	MANUAL-01,REGISTRATION CARD;XEU,ENG,UK,W	1	S.N.A
...3	ACCESSORY	AA68-03575B	MANUAL-010,REGISTRATION CARD;XEG,GERMAN,	1	S.N.A
...3	ACCESSORY	AA68-03575C	MANUAL-01,REGISTRATION CARD;XEF,FRENCH,W	1	S.N.A
...3	ACCESSORY	AA68-03575D	MANUAL-02,REGISTRATION CARD;XEC,SPANISH,	1	S.N.A
...3	ACCESSORY	AA68-03575E	MANUAL-02,REGISTRATION CARD;XET,ITALY,W/	1	S.N.A
...3	ACCESSORY	AA68-03575F	MANUAL-01,REGISTRATION CARD;XEN,DUTCH,W/	1	S.N.A
...3	ACCESSORY	AA68-03575G	MANUAL-01,REGISTRATION CARD;XEP,PORTUGAL	1	S.N.A
...3	T0074	BN59-00493A	REMOCON;Milano2,TM77,Single Micom,47,EX,	1	
...3	ACCESSORY	BN63-01798A	CLOTH-CLEAN;RE40**,CLOTH,310,320,RHCM	1	S.N.A
...3	T0531	BN63-01938A	COVER-BOTTOM;40 MILANO,ABS,V0,GR503	1	S.N.A
...3	ACCESSORY	BN68-00514A	MANUAL-03,WARRANTY CARD;PDP/LCD TV,EN,FR	1	S.N.A
...3	T0511	BN68-00895A	MANUAL USERS;ROME,SAMSUNG,W/P 5G,PRECAUT	1	S.N.A
...3	T0059	BN68-00907A	MANUAL-CARD;WEEE,SAMSUNG,18 Lang,Europe,	1	S.N.A
...3	ACCESSORY	BN69-01052A	BOX-ACCESSORY;ALL,CB-SW1,YEL,W603,D672	1	S.N.A
...3	T0685	4301-000103	BATTERY-ALKALINE;1.5V,750mAH,AAA,10.5x44	2	
...3	M0596	BN68-00956A	MANUAL USERS-00;LE32/40M6,SAMSUNG,7LANG,	1	S.N.A

7 Block Diagram


-This Document can not be used without Samsung's authorization.



Memo

8 Wiring Diagram

8-1 Wiring Diagram




Memo


9 Schematic Diagrams

-This Document can not be used without Samsung's authorization.

9-1 Power_Sound Schematic Diagram




9 Schematic Diagrams




-This Document can not be used without Samsung's authorization.


9-2 AV In_Out_Tuner Schematic Diagram



-This Document can not be used without Samsung's authorization.


9-3 Micom Schematic Diagram








-This Document can not be used without Samsung's authorization.

9-4 SVP EX Schematic Diagram






-This Document can not be used without Samsung's authorization.


9-5 INVERTER Schematic Diagram(26", 32")

ROME PJT 26" **32"**
INVERTER SMPS 24V




-This Document can not be used without Samsung's authorization.

9-6 MULTI_SMPs Schematic Diagram(26", 32")



-This Document can not be used without Samsung's authorization.


9-7 PFC_CONTROL SMPS Schematic Diagram(26", 32")



-This Document can not be used without Samsung's authorization.

9-8 STAND BY SMPS Schematic Diagram(26", 32")

ROME PJT 26^{pp} 32^{pp}
STAND-BY SMPS




-This Document can not be used without Samsung's authorization.

9-9 INVERTER Schematic Diagram(40'')

Last Modified Date : 2004.09.21

FREE VOLT 40^{pp}

INVERTER SMPS




-This Document can not be used without Samsung's authorization.

9-10 MULTI_SMPS Schematic Diagram(40")

Last Modified Date : 2004.09.21

FREE VOLT 40^{pp}

INVERTER SMPS




-This Document can not be used without Samsung's authorization.

9-11 PFC_CONTROL SMPS Schematic Diagram(40")

Last Modified Date : 2004.09.21

FREE VOLT 40^{pp}

PFC-CONTROL SMPS




-This Document can not be used without Samsung's authorization.

9-12 STAND BY SMPS Schematic Diagram(40")

Last Modified Date : 2004.09.21

FREE VOLT 40^W STAND-BY SMPS




Memo

10 Operating Installations and Installation

10-1 Product Features

10-1-1 Front



1. SOURCE

Displays a menu of all of the available input sources (TV, Ext. 1, Ext. 2, AV, S-Video, Component, PC, HDMI).

Also used to confirm your choice on the on-screen menu.

2. MENU

Press to see an on-screen menu of your TV's features.

3. - VOL +

Press to decrease or increase the volume.
Also used to select items on the on-screen menu.

4. CH ^ \ CH ^

Press to change channels.
Also press to highlight various items on the on-screen menu.

5. POWER

Press to turn the TV on and off.

6. POWER INDICATOR

Blinks and turns off when the power is on and lights up in stand-by mode.

7. REMOTE CONTROL SENSOR


Aim the remote control towards this spot on the TV.

8. LIGHT DETECTING SENSOR


Adjusts the brightness of the screen automatically by detecting brightness of the surrounding environment. This sensor works when the Brightness Sensor is on.

9. SPEAKERS

10-1-2 Back(LE26M51B)



10-1-3 Back(LE32M51B / LE32M61B / LE40M51B / LE40M61B/ LE46M51B)



1. Connecting an Aerial or Cable Television Network

To view television channels correctly, a signal must be received by the set from one of the following sources:

- An outdoor aerial
- A cable television network
- A satellite network

2. Connecting Component Devices (DTV/DVD)

- Connect component video cables to component connector ("PR", "PB", "Y") on the rear of your set and the other ends to corresponding component video out connectors on the DTV or DVD.
- If you wish to connect both the Set-Top Box and DTV (or DVD), you should connect the Set-Top Box to the DTV (or DVD) and connect the DTV (or DVD) to component connector ("PR", "PB", "Y") on your set.
- The Y, Pb and Pr connectors on your component devices (DTV or DVD) are sometimes labeled Y, B-Y and R-Y or Y, Cb and Cr.
- Connect RCA audio cables to \textcircled{R} - AUDIO - L \pm on the rear of your set and the other ends to corresponding audio out connectors on the DTV or DVD.

3. Connecting External A/V Devices

- Connect RCA or S-VIDEO cable to an appropriate external A/V device such as VCR, DVD or Camcorder.
- Connect RCA audio cables to \textcircled{R} - AUDIO - L \pm on the rear of your set and the other ends to corresponding audio out connectors on the A/V device.
- Headphone may be connected to the headphone output () on the rear of your set. While the headphone is connected, the sound from the built-in speakers will be disabled.

4. SERVICE

- Connector for engineer.

5. Connecting Set-Top Box, VCR or DVD

- Connect the VCR or DVD SCART cable to the SCART connector of the VCR or DVD.
- If you wish to connect both the Set-Top Box and VCR (or DVD), you should connect the Set-Top Box to the VCR (or DVD) and connect the VCR (or DVD) to your set.

6. Connecting HDMI/DVI

- Supports connections between HDMI-connection-enabled AV devices (Set-Top Boxes, DVD players, AV receivers and digital TVs).
- No sound connection is needed for an HDMI to HDMI connection.

- What is HDMI?

- HDMI, or high-definition multimedia interface, is a next-generation interface that enables the transmission of digital audio and video signals using a single cable without compression.
- "Multimedia interface" is a more accurate name for it especially because it allows multiple channels of digital audio (5.1 channels).The difference between HDMI and DVI is that the HDMI device is smaller in size, has the HDCP (High Bandwidth Digital Copy Protection) coding feature installed, and supports multi - channel digital audio.
- Use the HDMI/DVI terminal for DVI connection to an extended device.

- * You should use the DVI-to-HDMI cable or DVI-HDMI Adapter for the connection, and the "R - AUDIO - L" terminal on DVI for sound output.

7. Connecting Computer

- Connect the D- Sub cable to "PC (PC IN)" on the rear of your set and the other end to the Video Card of your computer.
- Connect the stereo audio cable to "AUDIO (PC IN)" on the rear of your set and the other end to "Audio Out" of the sound card on your computer.

8. Connecting AUDIO


- Connect RCA audio cables to "R - AUDIO - L" on the rear of your set and the other ends to corresponding audio in connectors on the Amplifier or DVD Home Theater.

10. Kensington Lock

- Refer to "Using the Anti-Theft Kensington Lock"
- The place of the Kensington Lock may be different depending on its model.


10-2 Installation Notes and Precautions

10-2-1 Installing the stand (LE26M51B, LE32M51B, LE32M61B)



1. Lower the TV set in the direction of the arrow and fix the stand.
2. Use the four screws to tightly fix the stand.

10-2-2 Disconnecting the stand



1. Remove four screws from the back of the TV.
2. Separate the stand from the TV.
3. Cover the bottom hole with a cap.

10-2-2 Installing the Wall Mount Kit (LE26M5)


Components (Sold separately)




How to assemble the Wall Mount Bracket

- 1**
 - ① Mark the location on the wall where the hole will be drilled.
 - ② Make over 35mm-depth-hole on the marked location using drill.
 - ③ Fix anchors ⓔ on each hole on the wall.
 - ④ Connect wall-bracket Ⓛ to the wall with wood screws Ⓝ after fitting anchors ⓔ into the wall-bracket Ⓛ.

Note: If the bracket is not firmly fixed to the wall, LCD TV can fall off.




- 2**
 - ① Turn the power off and unplug the power cord from the outlet.
 - ② Place the TV faced down on a soft cloth or cushion on a table.
 - ③ Attach the set-bracket Ⓛ on to the rear side of the TV set and secure the screws Ⓜ.



- 3**
 - ① Insert three Hangers of the set-bracket Ⓛ into the grooves of the wall-bracket Ⓛ.
 - ② Fix set-bracket Ⓛ and wall-bracket Ⓛ with screws Ⓜ.

Note: Before installing the set on the wall, connect the cables to the set first.



10-2-4 Installing the Wall Mount Kit(LE32M51B / LE32M61B / LE40M51B / LE40M61B/ LE46M51B)


Components (Sold separately)




How to assemble the Wall Mount Bracket

- 1** ① Mark the location on the wall where the hole will be drilled.
② Make over 35mm-depth-hole on the marked location using drill.
③ Fix anchors on each hole on the wall.
④ Connect wall-bracket to the wall with wood screws after fitting anchors into the wall-bracket .

Note: If the bracket is not firmly fixed to the wall, LCD TV can fall off.




- 2** ① Turn the power off and unplug the power cord from the outlet.
② Place the TV faced down on a soft cloth or cushion on a table.
③ Attach the set-bracket onto the rear side of the TV set and secure the screws .



- 3** ① Insert three Hangers of the set-bracket ⑤ into the grooves of the wall-bracket ②.
② Fix set-bracket ⑤ and wall-bracket ② with screws ①.


Note: Before installing the set on the wall, connect the cables to the set first.



10 Operating Installations and Installation

10-1 Product Features

10-1-1 Front



1. SOURCE

Displays a menu of all of the available input sources (TV, Ext. 1, Ext. 2, AV, S-Video, Component, PC, HDMI).

Also used to confirm your choice on the on-screen menu.

2. MENU

Press to see an on-screen menu of your TV's features.

3. - VOL +

Press to decrease or increase the volume.
Also used to select items on the on-screen menu.

4. CH ^ \ CH ^

Press to change channels.
Also press to highlight various items on the on-screen menu.

5. POWER

Press to turn the TV on and off.

6. POWER INDICATOR

Blinks and turns off when the power is on and lights up in stand-by mode.

7. REMOTE CONTROL SENSOR


Aim the remote control towards this spot on the TV.

8. LIGHT DETECTING SENSOR


Adjusts the brightness of the screen automatically by detecting brightness of the surrounding environment. This sensor works when the Brightness Sensor is on.

9. SPEAKERS

10-1-2 Back(LE26M51B)



10-1-3 Back(LE32M51B / LE32M61B / LE40M51B / LE40M61B/ LE46M51B)



1. Connecting an Aerial or Cable Television Network

To view television channels correctly, a signal must be received by the set from one of the following sources:

- An outdoor aerial
- A cable television network
- A satellite network

2. Connecting Component Devices (DTV/DVD)

- Connect component video cables to component connector ("PR", "PB", "Y") on the rear of your set and the other ends to corresponding component video out connectors on the DTV or DVD.
- If you wish to connect both the Set-Top Box and DTV (or DVD), you should connect the Set-Top Box to the DTV (or DVD) and connect the DTV (or DVD) to component connector ("PR", "PB", "Y") on your set.
- The Y, Pb and Pr connectors on your component devices (DTV or DVD) are sometimes labeled Y, B-Y and R-Y or Y, Cb and Cr.
- Connect RCA audio cables to \textcircled{R} - AUDIO - L \pm on the rear of your set and the other ends to corresponding audio out connectors on the DTV or DVD.

3. Connecting External A/V Devices

- Connect RCA or S-VIDEO cable to an appropriate external A/V device such as VCR, DVD or Camcorder.
- Connect RCA audio cables to \textcircled{R} - AUDIO - L \pm on the rear of your set and the other ends to corresponding audio out connectors on the A/V device.
- Headphone may be connected to the headphone output () on the rear of your set. While the headphone is connected, the sound from the built-in speakers will be disabled.

4. SERVICE

- Connector for engineer.

5. Connecting Set-Top Box, VCR or DVD

- Connect the VCR or DVD SCART cable to the SCART connector of the VCR or DVD.
- If you wish to connect both the Set-Top Box and VCR (or DVD), you should connect the Set-Top Box to the VCR (or DVD) and connect the VCR (or DVD) to your set.

6. Connecting HDMI/DVI

- Supports connections between HDMI-connection-enabled AV devices (Set-Top Boxes, DVD players, AV receivers and digital TVs).
- No sound connection is needed for an HDMI to HDMI connection.

- What is HDMI?

- HDMI, or high-definition multimedia interface, is a next-generation interface that enables the transmission of digital audio and video signals using a single cable without compression.
- "Multimedia interface" is a more accurate name for it especially because it allows multiple channels of digital audio (5.1 channels).The difference between HDMI and DVI is that the HDMI device is smaller in size, has the HDCP (High Bandwidth Digital Copy Protection) coding feature installed, and supports multi - channel digital audio.
- Use the HDMI/DVI terminal for DVI connection to an extended device.

* You should use the DVI-to-HDMI cable or DVI-HDMI Adapter for the connection, and the "R - AUDIO - L" terminal on DVI for sound output.

7. Connecting Computer

- Connect the D-Sub cable to "PC (PC IN)" on the rear of your set and the other end to the Video Card of your computer.
- Connect the stereo audio cable to "AUDIO (PC IN)" on the rear of your set and the other end to "Audio Out" of the sound card on your computer.

8. Connecting AUDIO

- Connect RCA audio cables to "R - AUDIO - L" on the rear of your set and the other ends to corresponding audio in connectors on the Amplifier or DVD Home Theater.

10. Kensington Lock

- Refer to "Using the Anti-Theft Kensington Lock"
- The place of the Kensington Lock may be different depending on its model.


10-2 Installation Notes and Precautions

10-2-1 Installing the stand (LE26M51B, LE32M51B, LE32M61B)



1. Lower the TV set in the direction of the arrow and fix the stand.
2. Use the four screws to tightly fix the stand.

10-2-2 Disconnecting the stand



1. Remove four screws from the back of the TV.
2. Separate the stand from the TV.
3. Cover the bottom hole with a cap.

10-2-2 Installing the Wall Mount Kit (LE26M5)


Components (Sold separately)




How to assemble the Wall Mount Bracket

- 1**
 - ① Mark the location on the wall where the hole will be drilled.
 - ② Make over 35mm-depth-hole on the marked location using drill.
 - ③ Fix anchors ⓔ on each hole on the wall.
 - ④ Connect wall-bracket Ⓛ to the wall with wood screws Ⓝ after fitting anchors ⓔ into the wall-bracket Ⓛ.

Note: If the bracket is not firmly fixed to the wall, LCD TV can fall off.




- 2**
 - ① Turn the power off and unplug the power cord from the outlet.
 - ② Place the TV faced down on a soft cloth or cushion on a table.
 - ③ Attach the set-bracket Ⓛ on to the rear side of the TV set and secure the screws Ⓜ.



- 3**
 - ① Insert three Hangers of the set-bracket Ⓛ into the grooves of the wall-bracket Ⓛ.
 - ② Fix set-bracket Ⓛ and wall-bracket Ⓛ with screws Ⓜ.

Note: Before installing the set on the wall, connect the cables to the set first.



10-2-4 Installing the Wall Mount Kit(LE32M51B / LE32M61B / LE40M51B / LE40M61B/ LE46M51B)


Components (Sold separately)




How to assemble the Wall Mount Bracket

- 1** ① Mark the location on the wall where the hole will be drilled.
② Make over 35mm-depth-hole on the marked location using drill.
③ Fix anchors on each hole on the wall.
④ Connect wall-bracket to the wall with wood screws after fitting anchors into the wall-bracket .

Note: If the bracket is not firmly fixed to the wall, LCD TV can fall off.




- 2** ① Turn the power off and unplug the power cord from the outlet.
② Place the TV faced down on a soft cloth or cushion on a table.
③ Attach the set-bracket onto the rear side of the TV set and secure the screws .



- 3** ① Insert three Hangers of the set-bracket ⑤ into the grooves of the wall-bracket ②.
② Fix set-bracket ⑤ and wall-bracket ② with screws ①.

Note: Before installing the set on the wall, connect the cables to the set first.




11 Disassembly and Reassembly

This section of the service manual describes the disassembly and reassembly procedures for the LE26M51B /LE32M51B / LE32M61B / LE40M51B / LE40M61B / LE46M51B LCD TV.

⚠ WARNING: This monitor contains electrostatically sensitive devices. Use caution when handling these components.

11-1 Disassembly

- ⚠ Cautions:
- 1. Disconnect the monitor from the power source before disassembly.**
 - 2. Follow these directions carefully; never use metal instruments to pry apart the cabinet.**
 - 3. R/Cover opening jig : BH81-00001A**




1. Place LCD TV face down on cushioned table. Remove 10 screws from the rear cover.
Remove 4 screws from grip on the stand. and remove the stand.



2. Remove 3 screws from the Jack-cover.


11 Disassembly and Reassembly




3. Remove screws from the Shield-cover and disconnect cables.



4. Remove screws from the boards and lift up the boards.



5. Remove 2 screws from the side-jack and remove screws from the BRKT.



6. Remove 4 screws from the side-BRKT.


11-2 Reassembly

Reassembly procedures are in the reverse order of disassembly procedures, place the lamp wire correctly in the locator groove so that the wire will not bind or interfere with rear cover.


Memo

12 PCB Layout


12-1 Main PCB Layout



12-2 Power board (LE26M5 / LE32M5 / LE40M5)




12-2 Power board (LE46M5)




13 Circuit Descriptions

13-1 Overall Block Structure



13-2 Partial Block Description

13-2-1 Main Board Layout



13-2-2 PIN characteristic

CN801- Main Board power supply

PIN	1	2	3	4	5	6	7	8	9	10	11	12	13	14
NAME	12V	GND	5V	5V	5V	GND	GND	GND	12VS	12VS	12VS	GND	GND	GND

FUNCTION DEFINE:

- 12V B5V_VCCA B5V_VCCB IC611 POWER SUPPLY
- 5V B5V B3.3V B2.5V_VDD B3.3VD VCC50
- 12VS B12VS

CN802-stand by supply

PIN	1	2	3
NAME	POWER	GND	SW_POWER
VOLTAGE	6V	0V	ON/OFF

FUNCTION DEFINE:

- POWER 6V STAND BY 5V , Sub-MICOM power supply
- SW_POWER L: Power OFF , H: Power ON

CN621/CN622-SPEAKER CONNECTOR

PIN	1	2	3
NAME	R-OUT	NOP	R-REFERENCE

PIN	1	2
NAME	L-OUT	L-REFERENCE

CN812-Front control

PIN	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
NAME	GND	GND	A5V	-	KEY INPUT1	KEY INPUT2	GND	-	IR	-	LED_GREEN	LED_RED	GND	SDA	SCL

FUNCTION DEFINE:

- A5V Front control board power supply
- KEY INPUT1,2/SDA/SCL key control, form the Menu , channel up/down Etc.
- IR remote control signal
- LED_GREEN/LED_RED control the timing and standby LED color

CN815-panel control

PIN	1	2	3	4	5
NAME	SW_inverter	Ana_dimming	PWM_dimming	GND	SENSOR POWER


FUNCTION DEFINE:

- SW_inverter panel inverter control, about 5V
- Ana_dimming panel dimming control
- PWM_dimming panel PWM control, duty 40%~90%
- SENSOR POWER brightness sensor power supply

CN702-LVDS Signal

PIN	NAME	PIN	NAME
1	VCC	16	TXOUTCLK+
2	VCC5P	17	TXOUTCLK-
3	VCC5P	18	GND
4	VCC5P	19	TXOUT2+
5	VCC5P	20	TXOUT2-
6	GND	21	GND
7	GND	22	TXOUT1+
8	NOP (NOT USE)	23	TXOUT1-
9	SDA1	24	GND
10	SCL1	25	TXOUT0+
11	PANEL_SYNC_EN	26	TXOUT0-
12	GND	27	GND
13	TXOUT3+	28	SW_INVERTER
14	TXOUT3-	29	ANA_DIMMING
15	GND	30	PWM_DIMMING

13-2-3 Power Board Layout



13 Circuit Descriptions

CNB811-stand by supply

PIN	1	2	3
NAME	POWER	GND	SW_POWER
VOLTAGE	6V	0V	ON/OFF

FUNCTING DEFINE:

Refer to: CN802 function define

CNM801- Main Board power supply

PIN	1	2	3	4	5	6	7	8	9	10	11	12	13	14
NAME	12V	GND	5V	5V	5V	GND	GND	GND	12V	12V	12V	GND	GND	GND

FUNCTING DEFINE:

Refer to: CN801 function define

CNI804-panel control

PIN	1	2	3	4	5
NAME	SW_inverter	Ana_dimming	PWM_dimming	GND	SENSOR POWER

FUNCTING DEFINE:

Refer to: CN815 function define

14 Reference Infomation

14-1 Technical Terms

-Dot Pitch

The image on a monitor is composed of red, green and blue dots. The closer the dots, the higher the resolution. The distance between two dots of the same color is called the 'Dot Pitch'. Unit: mm

-Vertical Frequency

The screen must be redrawn several times per second in order to create and display an image for the user. The frequency of this repetition per second is called Vertical Frequency or Refresh Rate. Unit: Hz
Example: If the same light repeats itself 60 times per second, this is regarded as 60 Hz.

-Horizontal Frequency

The time to scan one line connecting the right edge to the left edge of the screen horizontally is called Horizontal Cycle. The inverse number of the Horizontal Cycle is called Horizontal Frequency. Unit: kHz

-Interlace and Non-Interlace Methods

Showing the horizontal lines of the screen from the top to the bottom in order is called the Non-Interlace method while showing odd lines and then even lines in turn is called the Interlace method. The Non-Interlace method is used for the majority of monitors to ensure a clear image. The Interlace method is the same as that used in TVs.

-Plug & Play

This is a function that provides the best quality screen for the user by allowing the computer and the monitor to exchange information automatically. This monitor follows the international standard VESA DDC for the Plug & Play function.

-Resolution

The number of horizontal and vertical dots used to compose the screen image is called 'resolution'. This number shows the accuracy of the display. High resolution is good for performing multiple tasks as more image information can be shown on the screen.

Example: If the resolution is 1920 x 1200 , this means the screen is composed of 1920 horizontal dots (horizontal resolution) and 1200 vertical lines (vertical resolution).

-A2

This system uses two carriers to transmit voice data. Countries such as South Korea and Germany use this system.

-BTSC

Broadcast Television System Committee

The stereo broadcasting system that is used in most of the countries that have adopted the NTSC system, including the United States, Canada, Chile, Venezuela and Taiwan. It also refers to the organization that has been organized to promote its development and management.

-EIAJ

Electronic Industries Association of Japan.

-RF Cable

A round signal cable generally used for TV antennas.

-Satellite Broadcasting

Broadcasting service provided via satellite. Enables high picture quality and clear sound throughout the country regardless of the location of the viewer.

-Sound Balance

Balances the levels of the sound coming from each speaker in televisions with two speakers.

-Cable TV

Whereas the terrestrial broadcasting is delivered via frequency signals through the air, cable broadcasting is transmitted via a cable network. In order to view cable TV, one must purchase a cable receiver and hook it up to the cable network.

-CATV

"CATV" refers to the broadcasting service offered at hotels, schools and other buildings through their own broadcasting system, apart from VHF or UHF broadcasting by terrestrial broadcasters. The CATV programs may include movies, entertainment and educational programs. (Different from cable TV.)

CATV can be viewed only within the area in which the CATV service is offered.

S-Video

Short for "Super Video." S-Video allows up to 800 lines of horizontal resolution, enabling high-quality video.

-VHF/UHF

VHF indicates TV channels 2 to 13, and UHF indicates channels 14 through 69.

-Channel Fine Tuning

This feature allows the viewer to fine-tune the TV channel to obtain the best viewing conditions. The Samsung LCD TV has both automatic and manual channel fine-tuning features to enable the viewer to adjust their desired settings.

-External Device Input

External device input refers to video input from such external video devices as VCRs, camcorders and DVD players, separate from a TV broadcast.

14-2 Pin Assignments

14-2-1 HDMI

Type A pin	Singnal Name	Wire
1	TMDS Data2+	TMDS Signal wire
2	TMDS Data2 Shield	TMDS Shield
3	TMDS Data2-	TMDS Signal wire
4	TMDS Data1+	TMDS Signal wire
5	TMDS Data2 Shield	TMDS Shield
6	TMDS Data1-	TMDS Signal wire
7	TMDS Data0+	TMDS Signal wire
8	TMDS Data0 Shield	TMDS Shield
9	TMDS Data0-	TMDS Signal wire
10	TMDS Clock+	TMDS Signal wire
11	TMDS Clock Shield	TMDS Clock Shield
12	TMDS Clock-	TMDS Shield
13	CEC	Control
14	Reserved (in cable but N.C on device)	Control
15	SCL	Control
16	SDA	Control
17	DDC/CEC Ground	Control
18	+5V Power	5 Volts Power wire
19	Hot Plug Delect	Control

14 Reference Infomation

14-2-2 Component 1

RCA Green	Y
	GND
RCA Blue	Pb (Cb)
	GND
RCA Red	Pr (Cr)
	GND
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-2-4 S-Video

Pin	Separate
1	GND
2	Y
3	C
4	GND
5	GND

14-2-3 A/V


RCA Yellow	CVBS
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-3 Timing Chart

This section of the service manual describes the timing that the computer industry recognizes as standard for computer-generated video signals.

14-3-1 LCD Panel Mode1

Timing No. Originator Mode Name Resolution (HxV)	VESA 1280/60Hz 1280x768	VESA 1366/60Hz 1366x768
HORIZONTAL		
Frequency	47.700kHz	47.712kHz
Total time	20.964 μ s	20.959 μ s
Active time	15.973 μ s	15.906 μ s
Blank time	4.992 μ s	5.053 μ s
Border(L / R)	0.000 μ s	0.000 μ s
Data time	15.964 μ s	15.906 μ s
Front porch	0.799 μ s	0.749 μ s
Sync. width	1.697 μ s	1.702 μ s
Back porch	2.496 μ s	2.994 μ s
Sync. polarity	Negative	Positive
VERTICAL		
Frequency	60.000Hz	60.015Hz
Total time	16.667ms	16.662 ms
Active time	16.101ms	16.097ms
Blank time	0.566ms	0.566 ms
Border(T / B)	0.000ms	0.000 ms
Data time	16.101ms	16.097ms
Front porch	20.964ms	0.063 ms
Sync. width	62.893ms	0.105 ms
Back porch	482.180	0.377ms
Sync polarity	Positive	Positive
Dot Clock	80.136MHz	85.500MHz
Sync. Type	Separate	Separate
Scan Type	N/I	N/I



14-3-1 Supported Modes (2)

Timing No.	2	3	11	17
Originator	IBM	IBM	VESA	VESA
Mode Name	VGA2	VGA3	640/72Hz	640/75Hz
Resolution (HxV)	720x400	640x480	640x480	640x480
HORIZONTAL				
Frequency	31.469kHz	31.469kHz	37.861kHz	37.500kHz
Total time	31.777μs	31.778μs	26.413μs	26.667μs
Active time	26.058μs	26.058μs	20.825μs	20.317μs
Blank time	5.720μs	5.720μs	5.588μs	6.350μs
Border(L / R)	0.318μs	0.318μs	0.254μs	0.000μs
Data time	25.422μs	25.422μs	20.317μs	20.317μs
Front porch	0.318μs	0.318μs	0.508μs	0.508μs
Sync. width	3.813μs	3.813μs	1.270μs	2.032μs
Back porch	1.589μs	1.589μs	3.810μs	3.810μs
Sync. polarity	Negative	Negative	Negative	Negative
VERTICAL				
Frequency	70.087Hz	59.940Hz	72.809Hz	75.000Hz
Total time	14.268ms	16.683ms	13.735ms	13.333ms
Active time	13.155ms	15.761ms	13.100ms	12.800ms
Blank time	1.113ms	0.922ms	0.635ms	0.533ms
Border(T / B)	0.222ms	0.254ms	0.211ms	0.000ms
Data time	12.711ms	15.253ms	12.678ms	12.800ms
Front porch	0.191ms	0.064ms	0.026ms	0.027ms
Sync. width	0.064ms	0.064ms	0.079ms	0.080ms
Back porch	0.858ms	0.794ms	0.528ms	0.427ms
Sync polarity	Positive	Negative	Negative	Negative
Dot Clock	28.322MHz	25.175MHz	31.500MHz	31.500MHz
Sync. Type	Separate	Separate	Separate	Separate
Scan Type	N/I	N/I	N/I	N/I

14-3-1 Supported Modes (3)

Timing No.	13 VESA 800/60Hz 800x600	14 VESA 800/72Hz 800x600	18 VESA 800/75Hz 800x600
HORIZONTAL			
Frequency	37.879kHz	48.077kHz	46.875kHz
Total time	26.400μs	20.800μs	21.333 μs
Active time	20.000μs	16.000μs	16.162 μs
Blank time	6.400 μs	4.800 μs	5.171 μs
Border(L / R)	0.000 μs	0.000 μs	0.000 μs
Data time	20.000μs	16.000μs	16.162 μs
Front porch	1.000 μs	1.120 μs	0.323 μs
Sync. width	3.200 μs	2.400 μs	1.616 μs
Back porch	2.200 μs	1.280 μs	3.232 μs
Sync. polarity	Positive	Positive	Positive
VERTICAL			
Frequency	60.317Hz	72.188Hz	75.000Hz
Total time	16.579ms	13.853ms	13.333ms
Active time	15.840ms	12.480ms	12.800ms
Blank time	0.739ms	1.373ms	0.533ms
Border(T / B)	0.000ms	0.000ms	0.000ms
Data time	15.840ms	12.480ms	12.800ms
Front porch	0.026ms	0.770ms	0.021ms
Sync. width	0.106ms	0.125ms	0.064ms
Back porch	0.607ms	0.478ms	0.448ms
Sync polarity	Positive	Positive	Positive
Dot Clock	40.000MHz	50.000MHz	49.500MHz
Sync. Type	Separate	Separate	Separate
Scan Type	N/I	N/I	N/I

14-3-1 Supported Modes (4)

Timing No.	15	16	19	
Originator	VESA	VESA	VESA	VESA
Mode Name	1024/60Hz	1024/70Hz	1024/75Hz	1360/60Hz
Resolution (HxV)	1024x768	1024x768	1024x768	1360x768
HORIZONTAL Frequency	48.363kHz	56.476kHz	60.023kHz	47.712kHz
Total time	20.677μs	17.707μs	16.660μs	20.959μs
Active time	15.754μs	13.653μs	13.003μs	15.906μs
Blank time	4.923μs	4.053 μs	3.777 μs	5.053μs
Border(L / R)	0.000 μs	0.000 μs	0.000 μs	0.000μs
Data time	15.754μs	13.653μs	13.003μs	15.906μs
Front porch	0.369 μs	0.320 μs	0.323 μs	0.749μs
Sync. width	2.092 μs	1.813 μs	1.219 μs	1.702μs
Back porch	2.462 μs	1.920 μs	2.235 μs	2.994 μs
Sync. polarity	Negative	Negative	Positive	Positive
VERTICAL Frequency	60.004Hz	70.069Hz	75.029Hz	60.015Hz
Total time	16.666ms	14.272ms	13.328ms	16.662 ms
Active time	15.880ms	13.599ms	12.795ms	16.097ms
Blank time	0.786ms	0.672ms	0.533ms	0.566 ms
Border(T / B)	0.000ms	0.000ms	0.000ms	0.000 ms
Data time	15.880ms	13.599ms	12.795ms	16.097ms
Front porch	0.062ms	0.053ms	0.017ms	0.063 ms
Sync. width	0.124ms	0.106ms	0.050ms	0.105 ms
Back porch	0.600ms	0.513ms	0.466ms	0.377ms
Sync polarity	Negative	Negative	Positive	Positive
Dot Clock	65.000MHz	75.000MHz	78.750MHz	85.500MHz
Sync. Type	Separate	Separate	Separate	Separate
Scan Type*	N/I	N/I	N/I	N/I

14-4 Display Mode

Both screen position and size will vary depending on the type of PC monitor and its resolution.
The table below shows all of the display modes that are supported:

Mode	Resolution	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Pixel Clock Frequency (MHz)	Sync Polarity (H/V)
IBM	640 x 480	31.469	59.940	25.175	- / -
	720 x 400	31.469	70.087	28.322	- / +
VESA	640 x 480	37.861	72.809	31.500	- / -
	640 x 480	37.500	75.000	31.500	- / -
	800 x 600	37.879	60.317	40.000	+ / +
	800 x 600	48.077	72.188	50.000	+ / +
	800 x 600	46.875	75.000	49.500	+ / +
	1024 x 768	48.364	60.000	65.000	- / -
	1024 x 768	56.476	70.069	75.000	- / -
	1024 x 768	60.023	75.029	78.750	+ / +
	1360 x 768	47.712	60.015	85.800	+ / +

- The interlace mode is not supported.
- The set might operate abnormally if a non-standard video format is selected.
- DVI does not support PC function.

14-5 Panel Description

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LT140X1-002	BN07-00004A	SA	BN68-00239H	-
SEC	LT150XS-L01	BN07-00009A	SB		-
SEC	LT150XS-L01-B	BN07-00022A	SC		-
SEC	LTM150XS-L02	BN07-00005A	SD		-
SEC	LT181E2-132	BN07-00001A	SE		-
SEC	LT150XS-T01	BN07-00010A	SF		-
SEC	LTM181E3-132	BN07-00019A	SG		-
SEC	LT170E2-131	BN07-10001D	SH		-
SEC	LT181E2-131	BN07-10001E	SJ		-
SEC	LTM170E4-L01	BN07-00018A	SK		-
SEC	LTM240W1-L01	BN07-00015A	SL		-
SEC	LTM213U3-L01	BN07-00016A	SM		-
SEC	LTM150XH-L01	BN07-00026A	SN		-
SEC	LTM150XH-L03	BN07-00027A	SP		-
SEC	LTM150XS-L01	BN07-00032A	SQ	DELL(ZPD)	
SEC	LTM181E4-L01	BN07-00034A	SR	PVA	
SEC	LTM170EH-L01	BN07-00036A	SS	TN	
SEC	LTM170E5-L01	BN07-00037A	SU	PVA	
SEC	LTM150XH-L11	BN07-00041A	SV	-	
SEC	LTM213U4-L01	BN07-00039A	SW	PVA	
SEC	LTM150XH-L01(ZPD)	BN07-00045A	SX	ZPD	
SEC	LTM150XH-L04	BN07-00046A	SY	New panel with high brightness	
SEC	LTM170W1-L01	BN07-00047A	SZ	Panel for TV	
SEC	LTM150XH-L06	BN07-00053A	EA	Panel for TV/ High luminance for 450cd _ SONY&EOS Team Panel for TV	
SEC	LTM153W1-L01	BN07-00054A	EB	Use NIKE MODEL	
SEC	LTM170EH-L05	BN07-00055A	EC	Panel EOS proj. for high brightness of 17" EH-L05	
SEC	LTM170E5-L03	BN07-00056A	ED	Dell 1702FP pro. E4. EH mechanical Compatible	
SEC	LTM190E1-L01	BN07-00057A	EE	DELL 1900 FP	
SEC	LTM181E5-L01	BN07-00061A	EF	18" narrow bezel GH18PS	
SEC	LTM150XP-L01	BN07-00065A	EG	AMLCD PVA PANEL	
SEC	LTM240W1-L02	BN07-00062A	EH	Panel for 15" Wide TV	
SEC	LTM170EU-L01	BN07-00071A	EJ	Slim design, TN	
SEC	LTM170E5-L04	BN07-00072A	EK	E5-L04 6 bits FRC... for IBM	
SEC	LTA220W1-L01	BN07-00074A	EL	Panel for 22" TV	
SEC	LTM170E6-L02	BN07-00075A	EM	AMLCD Narrow & slim design 17" PVA mode	
SEC	LTM170W1-L01	BN07-00082A	EN	LTM170W1-L01 ZPD panel	
SEC	LTM170EH-L01	BN07-00080A	EP	LTM170EH-L01 ZPD panel	
SEC	LTM170E5-L01	BN07-00081A	EQ	LTM170E5-L01 ZPD panel	
SEC	LTM170EH-L05	BN07-00083A	ER	LTM170EH-L05 ZPD panel	
SEC	LTM170E5-L03	BN07-00084A	ES	LTM170E5-L03 ZPD panel	
SEC	LTM170EU-L01	BN07-00085A	ET	LTM170EU-L01 ZPD panel	
SEC	LTM170E5-L04	BN07-00086A	EU	LTM170E5-L04 ZPD panel	
SEC	LTM170E6-L02	BN07-00087A	EV	LTM170E6-L02 ZPD panel	
SEC	LTM150XH-L06	BN07-00091A	EW	Color coordinates change for LCD TV	
SEC	LTM153W1-L01	BN07-00092A	EX	AMLCD WIDE 15",9/10	
SEC	LTM170W1-L01	BN07-00100A	EY	Color Coordinates change code management	
SEC	LTM170EH-L05	BN07-00097A	EZ	LTM170E5-L05 Color Coordinates Change Panel Code	
SEC	LTA400W1-L01	BN07-00109A	S1	PANEL of AMLCD 40" TV	
SEC	LTM153W1-L01	BN07-00110A	S2	Color coordinates change 0.280/0.290, 10000k & ZPD Panel	
SEC	LTM150XH-L06	BN07-00111A	S3	Color coordinates change 0.280/0.290, 10000k & ZPD Panel	
SEC	LTM170W1-L01	BN07-00112A	S4	Color coordinates change 0.280/0.290, 10000k & ZPD Panel	
SEC	LTM170EH-L05	BN07-00113A	S5	Color coordinates change 0.280/0.290, 10000k & ZPD Panel	
SEC	LTM220W1-L01	BN07-00114A	S6	ZPD Panel for AMLCD 22" TV	
SEC	LTM150XH-L06	BN07-00117A	S7	ZPD Panel code	

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LTM153W1-L01	BN07-00118A	S8		ZPD Panel code
SEC	LTM170WP-L01	BN07-00119A	S9		PVA Panel for NIKE
SEC	LTM213U4-L01	BN07-00039A	E1		21.3" NARROW
SEC	LTA260W1-L01	BN07-00121A	E2		VENUS
SEC	LTA220W1-L01	BN07-00074B	E3		"Panel B-level panel code for 22"" TV Panel "
SEC	LTA320W1-L01	BN07-00108A	E4		"Panel for AMLCD 32"" TV"
SEC	LTM213U4-L01	BN07-00124A	E5		NARROW BEZEL 21 " PANEL
SEC	LTM170E6-L04	BN07-00129A	E6		"HIGHLAND 17"" LOW PANEL (Panel only for TCO03)"
SEC	LTM190E1-L01	BN07-00088A	E7		LTM190E1-L01 ZPD panel
SEC	M150X4-L06	BN07-00137A	E8		15" Narrow & Slim panel
SEC	LTA170V1	BN07-00139A	E9		"17"" Panel for Muse 4:3 VGA TV"
SEC	LTM190E1-L02	BN07-00128A	E10		"New Panel from AMLCDI, Specification : 6bit Driver IC"
SEC	LTM170EX-L01	BN07-00143A	E11		"Development new Panel from AMLCD"
SEC	LTM170E8-L01	BN07-00144A	E12		"Development new Panel from AMLCD"
SEC	LTM170E6-L04	BN07-00129B	E13		"ZPD panel for AMLCD (Panel only for TCO03)"
SEC	LTA320W1-L02	BN07-00108B	E14		"Creat B-level Panel code for AMLCD 32"" TV"
SEC	LTM190E1-L03	BN07-00151A	E15		"Development new 19"" Panel form AMLCD (Panel only for TCO03)"
SEC	LTM240W1-L03	BN07-00134A	E16		"AMLCD 24"" panel development"
SEC	LTM190E1-L02	BN07-00128B	E17		"New Panel from AMLCD, Specification : 6bit Driver IC(ZPD)"
SEC	LTM190E4-L01	BN07-00145A	E18		"AMLCD 24"" new panel development"
SEC	LTM170E8-L01	BN07-00158A	E19		"ZPD code derivation"
SEC	LTM170EX-L01	BN07-00159A	E20		"ZPD code derivation"
SEC	LTM190E1-L03	BN07-00151B	E21		"Creat new panel code for AMLCD 19"" (Panel only for TCO03)"
SEC	LTA460H1-L01	BN07-00157A	E22		"creat panel code for AMLCD 46"" TV "
SEC	LTM170EU-L11	BN07-00160A	E23		"creat new panel code for AMLCD 17"" (Panel only for TCO03)"
SEC	LTM240W1-L03	BN07-00134B	E24		"24"" panel ZPD code derivation"
SEC	LTM190E4-L01	BN07-00145B	E25		"AMLCD 19"" ZPD Panel code derivation"
SEC	LTM240W1-L03	BN07-00134B	E26		"24"" panel ZPD code derivation"
SEC	LTM150XO-L01	BN07-00164A	E27		"AMLCD 15"" XO-L01 new panel development"
SEC	LTM150XO-L01	BN07-00164B	E28		"AMLCD 15"" XO-L01 ZPD code derivation"
SEC	LTM170EU-L11	BN07-00160B	E29		"AMLCD 17"" NEW panel code derivation"
SEC	LTA320W2-L01	BN07-00172A	SPZ		AMLCD 32" NEW panel
SEC	LTM213U4-L01	BN07-00124B	SPZ		21.3" Narrow PANEL ZPD Panel derivation
SEC	LTM170EU-L11	BN07-00189A	STH		AMLCD EU-L11 Pb free panel code derivation
SEC	LTM170EU-L11	BN07-00189B	STZ		AMLCD EU-L11 Pb free panel ZPD code derivation
SEC	LTM240W1-L04	BN07-00188A	SPH		24" A-DCC new panel development
SEC	LTM240W1-L04	BN07-00188B	SPZ		24" A-DCC panel ZPD code derivation
SEC	LTM190EX-L01	BN07-00191A	STH		AMLCD 19" TN new Panel
SEC	LTM190EX-L02	BN07-00191B	STZ		AMLCD 19" TN new Panel ZPD derivation
SEC	LTA230W1-L02	BN07-00184A	SPZ		AMLCD 23" 16:9 new Panel
SEC	LTA260W2-L01	BN07-00185A	SPZ		AMLCD 26" 16:9 new Panel
SEC	LTM240M1-L01	BN07-00195A	SPH		24" panel with high brightness deveiopment
SEC	LTA400W2-L01	BN07-00186A	SPZ		AMLCD 40" 16:9 new Panel
SEC	LTM150XO-L01	BN07-00197A	STH		AMLCD 15" XO-L01 Pb free panel code
SEC	LTM150XO-L01	BN07-00197B	STZ		AMLCD 15" XO-L01 Pb free panel ZPD code
SEC	LTM170EU-L21	BN07-00202A	STZ		AMLCD EU-L21 ZPD new code derivation
SEC	LTA460W2-L03	BN07-00187A	SPZ		BEETOVEN 46"ZPD new panel
SEC	LTM240M1-L01	BN07-00195B	SPZ		24" igh brightness panel ZPD code derivation
SEC	M170EX-L21	BN07-00206A	STZ		AMLCD LTM170EX-L21 ZPD new code derivation
SEC	LTA460H3-L01	BN07-00200A	SPZ		AMLCD 46" LED BLU panel
SEC	LTM170EU-L15	BN07-00214A	STZ		AMLCD EU-L15 TV high brightness ZPD new code derivtion
SEC	LTM170E8-L21	BN07-00218A	SPZ		AMLCD LTM170E8-L21 PVA ZPD new code derivation
SEC	LTM190EX-L21	BN07-00222A	STZ		DISPLAY LCD
SEC	LTM201U1-L01	BN07-00190B	SPZ		AMLCD 20.1" Normal panel ZPD code derivation

14 Reference Information

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LTM190E4-L21	BN07-00223A	SPZ		HAYDN 17" PZD code PANEL derivation
SEC	LTA570H1-L01	BN07-00196A	SPZ		AMLCD 57" new panel development
SEC	LTM150XO-L21	BN07-00229A	STZ		AMLCD 15" XO-L21 8ms panel code
SEC	LTA260W2-L11	BN07-00239A	SPZ		AMLCD 26" 16:9 7Line new Panel
SEC	LTA400WS-LH1	BN07-00245A	SPZ		AMLCD 40" 16:9 SPVA 90% new Panel
SEC	LTM213U6-L01	BN07-00231A	SPZ		AMLCD 21.3" PVA new Panel Code
SEC	LTA320WS-LH2	BN07-00244A	SPZ		AMLCD 32" 16:9 SPVA 90% new Panel
SEC	LTA400WS-LH1	BN07-00245A	SPZ		AMLCD 40" 16:9 SPVA 90% new Panel
CPT	CLAA150XG09	BN07-00141A	PA		"CPT 15"" Monitor new panel development"
CPT	CLAA170EA02	BN07-00148A	PB		"17"" CPT NEW development panel"
CPT	CLAA170EA02	BN07-00148B	PC		"17"" CPT ZPD panel code derivation"
CPT	CLAA150XG09	BN07-00141B	PTZ		"CPT 15"" panel ZPD code derivation (GOYA-PJT)"
CPT	CLAA150XP01	BN07-00173A	PTH		CPT 15" PSWG code derivation
CPT	CLAA150XP01	BN07-00173B	PTZ		CPT 15" PSWG panel ZPD code
CPT	CLAA170EA07	BN07-00174A	PTH		"CPT 17" PSWG panel code derivation
CPT	CLAA170EA07	BN07-00174B	PTZ		CPT 17"" PSWG type new Panel code""
CPT	CLAA170EA07	BN07-00174B	PTZ		CPT 17" PSWG type new Panel code
CPT	CLAA170EA07Q	BN07-00220A	PTZ		CPT 17" PSWG R/T 8msec code derivation
CPT	CLAA170EA07Q	BN07-00220B	PTH		CPT 17" PSWG R/T 8msec HPD code derivation
CPT	CLAA150XP01F	BN07-00236A	PTZ		CPT 15" PSWG panel ZPD & Lead free code derivation
TOSHIBA	LTM15C419(A)	BN07-00002A	TA		-
TOSHIBA	LTM15C423(B)	BN07-00006A	TB		-
TOSHIBA	LTM18C161	BN07-00008A	TC		-
TOSHIBA	LTM15C443	BN07-00031A	TD		-
TOSHIBA	LTM15C458	BN07-00043A	TE		-
TOSHIBA	LTM15C458S	BN07-00077A	TF		"TSB 15" high brightness Panel"
TOSHIBA	LTM15C458	BN07-00078A	TG		Toshiba ZPD panel
TOSHIBA	LTM15C458S	BN07-00099A	TH		TSB LTM15C458S (ZPD)
HANNSTAR	HSD150MX41A(A)	BN07-00020A	NA		"TTL type"
HANNSTAR	HSD150MX12	BN07-00030A	NB		"TTL type"
HANNSTAR	HSD170ME13	BN07-00180A	NTH		Hannstar 17" TN new panel development
HANNSTAR	HSD170ME13	BN07-00180B	NTZ		Hannstar 17" TN new panel development ZPD code derivation
HANNSTAR	HSD190ME12	BN07-00210A	NTZ		Hannstar 19" TN new panel development
HANNSTAR	HSD150MX17-A	BN07-00226A	NTZ		Hannstar 15" slim panel ZPD code derivation
TORISAN	TM150XG-22L03(A)	BN07-00021A	RA		-
TORISAN	TM150XG-26L06	BN07-00042A	RB		-
TORISAN	TM181SX-76N01	BN07-00048A	RC		-
TORISAN	TM150XG-26L06	BN07-00059A	RD		15" XGA TN MODE(ZPD)
TORISAN	TM290WX-71N31	BN07-00063A	RE		"RS24NS (TORISAN 29" NEW PANEL)"
TORISAN	TM396WX-71N31	BN07-00064A	RF		"RS24NS (TORISAN 40" NEW PANEL)"
TORISAN	TM150XG-26L09	BN07-00073A	RG		"Panel for 15" TV"
TORISAN	TM150XG-26L10	BN07-00089A	RH		"L10(change except D/IC) ZPD"
TORISAN	TM150XG-26L10	BN07-00090A	RJ		L10 NORMAL
TORISAN	TM190SX-70N01	BN07-00098A	RK		Torisan 19" Panel
TORISAN	TM181SX-76N01	BN07-00106A	RL		ZPD Panel code
TORISAN	TM190SX-70N01	BN07-00107A	RM		ZPD Panel code
TORISAN	TM290WX-71N31	BN07-00115A	RN		"Color Coordinates change panel for TORISAN 29" TV"
TORISAN	TM396WX-71N31	BN07-00116A	RP,Q		"Color Coordinates change panel for TORISAN 40" TV"
TORISAN	TM220WX-71N31	BN07-00125A	RR		"Development TORISAN 22" TV PANEL (ZPD)"
TORISAN	TM220WX-71N31	BN07-00127A	RS		"Development TORISAN 22" TV PANEL (HPD)"

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
TORISAN	TM396WX-71N32A	BN07-00150A	RT		120V inverter Exclusive panel
TORISAN	TM190SX-70N02	BN07-00154A	RMH		Torisan 6bit panel code Derivation
TORISAN	TM190SX-70N02	BN07-00154B	RMZ		Torisan 6bit panel code Derivation
TORISAN	TM150XG-A01	BN07-00162A	RTH		Torisan 15" Narrow & Slim panel development
TORISAN	TM150XG-A01	BN07-00162B	RTZ		Torisan 15" N&S panel ZPD code Derivation
SHARP	LQ181E1DG11(A)	BN07-10001C	PA		-
SHARP	LQ150X1LW71	BN07-00067A	PB		SHARP 15" PVA PANEL
SHARP	LQ370T3LZ41	BN07-00216A	FAZ		Rome2
HITACHI	TX38D12VC0CAA(A)	BN07-00003A	HA		-
HITACHI	TX43DVCO CAB	BN07-00060A	HB		17" SXGA PVA MODE
HITACHI	TX43D15VC0CAB	BN07-00101A	HC		ZPD Panel
HITACHI	TX51D11VC0CAB	BN07-00122A	HD		20.1" NARROW
HITACHI	TX54D11VC0CAB	BN07-00123A	HE		21.3" NARROW
HITACHI	TX80D12VC0CAB	BN07-00169A	HIZ		"Development new panel for Hitachi 32"" TV (ZPD)"
HITACHI	TX54D11VC0CAB	BN07-00123B	HIZ		Hitachi 21.3"ZPD panel
IBM	ITSX94S	BN07-00017A	IA		-
UNIPAC	UM170E0	BN07-00028A	UA		Loaded by cisdba
HYUNDAI	HT15X13	BN07-00035A	DA		-
HYUNDAI	HT17E11-200	BN07-00049A	DB		TN MODE
HYUNDAI	HT17E11-300	BN07-00093A	DC		HT17E11-300 ZPD panel
HYUNDAI	HT17E11-400	BN07-00094A	DD		HT17E11-400 normal panel
HYUNDAI	HT17E11-400	BN07-00095A	DE		HT17E11-400 ZPD panel code
HYUNDAI	HT17E12	BN07-00096A	DF		HT17E12 (Narow & slim Design)
HYUNDAI	HT17E12	BN07-00105A	DG		ZPD Panel code
HYUNDAI	HT15X15-D00	BN07-00146A	DH		"Development for Ares 15"" Hydis TV"
HYUNDAI	HT15X15-D01	BN07-00146B	DJ		"Derivation panel HPD for Ares 15"" Hydis TV "
HYUNDAI	HT17E13-100	BN07-00167A	DTH		"PINEHURST-2(IBM) PJT 17"" HYDIS PANEL Derivation"
HYUNDAI	HT17E13-100	BN07-00167B	DTZ		"PINEHURST-2(IBM) Hydis 17"" ZPD code Derivation"
ACER	L170E3	BN07-00044A	AA		TN(ADT)
ACER	M170EN05	BN07-00076A	AB		AU 17" Panel (Narrow & slim design)
ACER	M170EN05	BN07-00102A	AC		ZPD Panel code
ACER	M190EN02	BN07-00170A	AMH		"AU Monitor 19"" new panel development (P19-1S)"
ACER	M190EN02	BN07-00170B	AMZ		"AU 19"" ZPD code derivation (ZPD)"
ACER	M170EN06	BN07-00171A	ATH		"AU Monitor 17"" New panel development "
ACER	T260XW01	BN07-00163A	AMZ		"AU 26"" new panel development (NF26EO)"
ACER	A201SN01	BN07-00177A	ATZ		"AU TV panel 20.1"" TN SVGA new panel development"
ACER	M170EN06	BN07-00171B	ATZ		AU Monitor 17" ZPD code derivation
ACER	T315XW01	BN07-00194A	AMZ		AU 32" new
ACER	M170EG01	BN07-00192A	ATH		AU TN PSWG type new Panel code
ACER	M170EG01	BN07-00192B	ATZ		AU TN PSWG type NEW panel code derivation
ACER	M190EN04	BN07-00203A	ATH		AU Monitor 19" ZPD new Panel code
ACER	T260XW02	BN07-00208A	AMZ		AUO 26" ZPD panel
ACER	M170EG01 V8	BN07-00221A	ATZ		AU TN PSWG type new Panel (8msec) ZPD code derivation
ACER	T260XW02	BN07-00233A	AMZ		AUO 26" Panel new (Cosmetic spec down grade)
ACER	T315XW01	BN07-00234A	AMZ		AUO 32" Grade new (Cosmetic spec down grade)
ACER	M190EN03	BN07-00224A	AMZ		AU Monitor 19" MVA new code derivation
ACER	T315XW01	BN07-00237A	AMZ		LCD TV VE project new
ACER	T315XW01	BN07-00238A	AMZ		LCD TV VE project new

14 Reference Information

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
ACER	M201UN02 V3	BN07-00168A	AMZ		
CHIMEI	M170E3-L01	BN07-00050A	CA		TN PANEL
CHIMEI	M150X3-L01	BN07-00051A	CB		COMPATIBLE
CHIMEI	M170E4-L01	BN07-00052A	CC		MVA PANEL
CHIMEI	M150X2-L01	BN07-00066A	CD		CHIMEI 15" I PVA PANEL
CHIMEI	M150X3-L01	BN07-00079A	CE		Chimei ZPD panel
CHIMEI	M170E3-L01	BN07-00103A	CF		ZPD Panel code
CHIMEI	M170E4-L01	BN07-00104A	CG		ZPD Panel code
CHIMEI	V296W1-L01	BN07-00120A	CH		MVA
CHIMEI	M170E6-L02	BN07-00126A	CJ		HIGHLAND 17" LOW PANEL
CHIMEI	M190E2-L01	BN07-00131A	CK		GH19AS, BS CHIMEI PANEL
CHIMEI	M150X4-L06	BN07-00137A	CL		15" Narrow & Slim panel
CHIMEI	M170E6-L01	BN07-00133A	CM		"2003-03-11 vendor change"
CHIMEI	M170E6-L01	BN07-00133B	CN		ZPD derivation panel
CHIMEI	V201V1-T01	BN07-00135A	CP		CHIMEI 20.1" panel development
CHIMEI	M170E6-L02	BN07-00126B	CQ		"HIGHLAND 17" LOW PANEL ZPD derivation panel"
CHIMEI	M170E6-L05	BN07-00152A	CR		"CMO 17" new panel development code"
CHIMEI	M170E6-L05	BN07-00152B	CS		"CMO 17" ZPD panel code derivation"
CHIMEI	M150X4-L06	BN07-00137B	CT		Chimei 15" Narrow & Slim panel ZPD derivation
CHIMEI	M170E5-L05	BN07-00165A	CTH		CMO 17" new panel development code (GOYA2-PJT)
CHIMEI	M170E5-L05	BN07-00165B	CTZ		CMO 17" ZPD panel(GOYA2-PJT)
CHIMEI	V230W1-L02	BN07-00209A	CMZ		CMO 23" development
CHIMEI	V320B1-L01	BN07-00207A	CMZ		CMO 32" development
CHIMEI	V270W1-L01	BN07-00136A	CMZ		CHIMEI 27" panel development
NEC	SVA150XG04TB	BN07-00225A	BTZ		SVA NEC 15" panel ZPD code



- This Service Manual is a property of
Samsung Electronics Co., Ltd.
Any unauthorized use of Manual can be
punished under applicable International
and/or domestic law.

Samsung Electronics Co.,Ltd.
416, Maetan-3Dong, Yeongtong-Gu, Suwon City,
Gyeonggi-Do, Korea, 443-742
Printed in Korea
P/N : BN82-00128M-00
URL : <http://itself.sec.samsung.co.kr/>