



LCD-TV

Chassis	Model
GBR32MUS	LN-T325H
GBR37MUS	LN-T375H
GBR40MUS	LN-T405H

SERVICE Manual

LCD TV



Fashion Feature

- RF, DVI-D, PC(Analog), Component, Video, S-Video
- Brightness : 500cd/m²
- Contrast Ratio : 32"/37"/40" => 8000:1
- Response time : 8ms
- Dynamic contrast
- PIP (on PC only)

Copyright

©2007 by Samsung Electronics Co., Ltd.

All rights reserved.

This manual may not, in whole or in part, be copied, photocopied, reproduced, translated, or converted to any electronic or machine readable form without prior written permission of Samsung Electronics Co., Ltd.

LN-T325HX/LN-T375HX/LN-T405HX
Service Manual

First edition March 2007.

Printed in Korea.

Trademarks

Samsung is the registered trademark of Samsung Electronics Co., Ltd.

LN-T325HX/LN-T375HX/LN-T405HX and MacMaster Cable Adapter are trademarks of Samsung Electronics Co., Ltd.

Macintosh, Power Macintosh are trademarks of Apple Computer, Inc.

All other trademarks are the property of their respective owners.

Contents

1	Precautions	1-1
1-1	Safety Precautions	1-1
1-2	Servicing Precautions	1-2
1-3	Electrostatically Sensitive Devices (ESD) Precautions	1-2
1-4	Installation Precautions	1-3
2	Product specifications	2-1
2-1	Features	2-1
2-2	LNT325H Specifications	2-2
2-3	LNT375H Specifications	2-3
2-4	LNT405H Specifications	2-4
2-5	Spec Comparison	2-5
2-6	Option Specification	2-6
3	Alignments and Adjustments	3-1
3-1	General Alignment Instruction	3-1
3-2	Factory Mode Adjustments	3-2
3-3	White Balance - Calibration	3-9
3-4	White Ratio (Balance) Adjustment	3-10
3-5	Servicing Information	3-11
4	Troubleshooting	4-1
4-1	No Power	4-1
4-2	No Video (Analog PC Signal)	4-2
4-3	No Video (HDMI - Digital Signal)	4-4
4-4	No Picture (Tuner_CVBS)	4-6
4-5	No Picture (Tuner DTV TS)	4-8
4-6	No Picture (Video CVBS)	4-10
4-7	No Picture (S-Video Y/C)	4-11
4-8	No Picture (Component1, 2 : 480i, 480p, 720p, 1080i[Y, Pb, Pr])	4-13
4-9	No Sound	4-15
5	Exploded View and Parts List	5-1
5-1	LNT325H Exploded View	5-1
5-2	LNT325H Parts list	5-2
5-3	LNT375H Exploded View	5-3
5-4	LNT375H Parts list	5-4
5-5	LNT405H Exploded View	5-5
5-6	LNT405H Parts list	5-6

Contents

6	Electrical Parts List	6-1
6-1	LNT325HAX Parts List	6-1
6-2	LNT375HAX Parts List	6-23
6-3	LNT405HAX Parts List	6-46
7	Block Diagram	7-1
8	Wiring Diagram	8-1
8-1	Wiring Diagram	8-1
9	Schematic Diagrams	9-1
10	Operating Instructions and Installation	10-1
10-1	Front	10-1
10-2	Connection Panel	10-2
10-3	Remote Control	10-3
11	Disassembly and Reassembly	11-1
11-1	Disassembly	11-1
11-2	Reassembly	11-6
12	Schematic Diagram	12-1
12-1	Main PCB Diagram	12-1
12-2	Power PCB Layout 32"	12-4
12-3	Power PCB Layout 37"	12-5
12-4	Power PCB Layout 40"	12-6
13	Circuit Descriptions	13-1
13-1	Block description	13-1
14	Reference Information	14-1
14-1	Technical Terms	14-1
14-2	Pin Assignments	14-4
14-3	Timing Chart	14-6



-This Service Manual is a property of Samsung Electronics Co., Ltd.
Any unauthorized use of Manual can be punished under applicable International and/or domestic law.

Samsung Electronics Co., Ltd.
416, Maetan-3Dong, Yeongtong-Gu, Suwon City,
Gyeonggi-Do, Korea, 443-742
Printed in Korea
P/N : BN82-
URL : <http://itself.sec.samsung.co.kr/>

3 Alignments and Adjustments

3-1 General Alignment Instruction

1. Usually, a color LCD-TV needs only slight touch-up adjustment upon installation.
Check the basic characteristics such as height, horizontal and vertical sync.
2. Use the specified test equipment or its equivalent.
3. Correct impedance matching is essential.
4. Avoid overload. Excessive signal from a sweep generator might overload the front-end of the TV. When inserting signal markers, do not allow the marker generator to distort test result.
5. Connect the TV only to an AC power source with voltage and frequency as specified on the backcover nameplate.
6. Do not attempt to connect or disconnect any wire while the TV is turned on. Make sure that the power cord is disconnected before replacing any parts.
7. To protect against shock hazard, use an isolation transformer.

3-2 Factory Mode Adjustments

3-2-1 Entering Factory Mode

To enter 'Service Mode' Press the remote -control keys in this sequence :

- If you do not have Factory remote - control



3-2-2 How to Access Service Mode

Using the Customer Remote

1. Turn the power off and set to stand-by mode
2. Press the remote buttons in this order; POWER OFF-MUTE-1-8-2-POWER ON to turn the set on.
3. The set turns on and enters service mode.
4. Press the Power button to exit and store data in memory.
 - If you fail to enter service mode, repeat steps 1 and 2 above.
5. Initial SERVICE MODE DISPLAY State

1. Calibration	
2. Option Byte	
3. White Balance	
4. W/B Movie	T-SC37AUSC-1004
5. Calibration Target	T-SC37AUSM-1002
6. Calibration Value	ACL 28.20.2.1
7. MST3388	RFS:T-SC37AUSC-20070228
8. X242	2007-03-05
9. X242 NTSC	DTP-LO-0022
10. FBE2	
11. Sound	
12. Dynamic Contrast	
13. Checksum 0x0000	
14. Reset	

6. Buttons operations withn Service Mode

KEY	FUNCTION
▲ / ▼	Item selection by moving the cursor
◀ / ▶	Data Increase/Decrease for the selected Item
MENU	Save set Data to EEPROM and go upper mode
DIGIT	Change channel
TV/VIDEO	Change AV mode

3-2-3 Factory Data

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

AV Calibration
Comp Calibration
PC Calibration
Hdmi Calibration

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Factory Name	RF	DTV	AV/ SVIDEO	COMP	PC	HDMI
Caption Level	On					
Watchdog enable	On					
Spread Spectrum	1	1	0	0	1	0
Panel Option	26AU					
Dimming	EXT_PWM					
RS-232C	Debug					
Gamma	0					
Panel Display Time	XX Hr					
Mute Time[RF]	600mS					
CH Memory	SAMEX					
Shop Mode	OFF					
SUB MICOM DOWN	OFF					
MAIN EEPROM WP	OFF					
DDC WP	OFF					
PC Mode Ident	Auto					
HDMI Mode Ident	Auto					
HPD Ctl Method	1					
HPD Low Duration	900ms					
Download RRT	OFF					
7.5 IRE On/Off	On					
7.5 IRE Offset	60					
HDMI Mute Time	1500					

3 Alignments and Adjustments

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-SC37AUSC-1004
6.Calibration Value	T-SC37AUSM-1002
7.MST3388	ACL 28.20.2.1
8.X242	RFS:T-SC37AUSC-20070228
9.X242 NTSC	2007-03-05
10.FBE2	DTP-LO-0022
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Sub Brightness	128
R-Offset	512
G-Offset	512
B-Offset	512
Sub Contrast	128
R-Gain	512
G-Gain	512
B-Gain	512

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-SC37AUSC-1004
6.Calibration Value	T-SC37AUSM-1002
7.MST3388	ACL 28.20.2.1
8.X242	RFS:T-SC37AUSC-20070228
9.X242 NTSC	2007-03-05
10.FBE2	DTP-LO-0022
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

W/B Movie On/Off	on	NOR_RGain	7
Mode	Dynamic	NOR_BGain	-11
Color Tone	Cool1	NOR_ROffset	-2
MSub Brightness	128	NOR_BOffset	2
MSub Contrast	128	C2_RGain	-32
W1_RGain	19	C2_BGain	22
W1_BGain	-26	C2_ROffset	5
W1_ROffset	-1	C2_BOffset	1
W1_BOffset	4	Movie Contrast	70
W2_RGain	49	Movie Bright	50
W2_BGain	-43	Movie Color	25
W2_ROffset	-4	Movie Sharpness	45
W2_BOffset	4		

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

1st_AV_Low	18	2nd_AV_High	235
1st_AV_High	220	2nd_AV_Delta	1
1st_AV_Delta	1	2nd_COMP_Low	1
1st_COMP_Low	16	2nd_COMP_High	235
1st_COMP_High	235	2nd_COMP_Delta	1
1st_COMP_Delta	1	2nd_PC_Low	1
1st_PC_Low	4	2nd_PC_High	235
1st_PC_High	235	2nd_PC_Delta	1
1st_PC_Delta	1	2nd_HDMI_Low	1
2nd_AV_Low	1	2nd_HDMI_High	235
		2nd_HDMI_Delta	1

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

LUMA_OFFSET	501
LUMA_GAIN	582
RED CUTOFF	-
GREEN CUTOFF	-
BLUE OFFSET	-
RED GAIN	-
GREEN GAIN	-
BLUE GAIN	-
2nd_X242_R_L	134
2nd_X242_G_L	134
2nd_X242_B_L	134
2nd_X242_R_H	1150
2nd_X242_G_H	1150
2nd_X242_B_H	1150

3 Alignments and Adjustments

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

RED CUTOFF	126	HSOPW	24
GREEN CUTOFF	93	SYNC_CTRL	64
BLUE CUTOFF	125	SOGMID_CTRL	189
PHASE_CC	0	SEP_THR	32
RED GAIN	200	PRECST	4
GREEN GAIN	200	POSTCST	14
BLUE GAIN	200	ADC_BW0	68
PLLDIV	858	ADC_BW1	4
PLL_GAIN	1	RDOFFSC	120
CLPDLY	8	GDOFFSC	0
CLPDUR	8	BDOFFSC	10

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

CH filter	ss_CH01
CV filter	Hardware
NR	ON
UVNR	OFF
LTI-YEE	ON
CTI-UVEE	ON
YH_MAX	128
YH_Edge	4096
YH_MIN	128
UVH_MAX	255
UVH_Edge	300
UVH_MIN	8
Color_Mid_Value	50

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

In Phase Line	24	CR_OFFSET	0
In Phase Frame	26	CB_GAIN	512
Out Phase Line	12	CB_OFFSET	0
Out Phase Frame	22	Y_DELAY_POS	0
CORING	2	Y_DELAY_NEG	12
LUMA_BW	0	CB_DELAY_POS	0
CHROMA_BW	4	CB_DELAY_NEG	13
CKILL_TH1	48	CR_DELAY_POS	0
CKILL_TH2	80	CR_DELAY_NEG	13
LUMA_GAIN	582	AGC_ON/OFF	OFF
LUNA_OFFSET	501	AGC_GAIN	538
CR_GAIN	512		

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Patt-Sel	0	ACR-Th2	100
B-Slope gain	64	Skin-Enable	1
B-Tilt min	70	Skin-Tu	128
B-Tilt max	140	Skin-Tv	128
Lfunc-Basis	75	Sub color	128
Hfunc-Basis	88	M-Skin-Tu	128
Mean-Offset1	75	M-Skin-Tv	128
Mean-Offset2	150	M-Au-Sub color	128
Mean-Slope	41	MW-Skin-Tu	128
Input-offset	128	MW-Skin-Tv	128
ACR-Offset	30	M-Wi-Sub color	128
ACR-Th1	30		

3 Alignments and Adjustments

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	


Carrier Mute	1
Stereo Pilot High	13
Stereo Pilot Low	7
Audio Delay	45
Spdif Delay	OFF
Melody Speak Vol.	5
Melody HP Vol.	5
NTP_Amp Vol.	30
NTP_PWM Mod.	243
NTP_DRC Thresh.	12
NTP_Speaker EQ	Off

1.Calibration	T-SC37AUSC-1004 T-SC37AUSM-1002 ACL 28.20.2.1 RFS:T-SC37AUSC-20070228 2007-03-05 DTP-LO-0022
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	
6.Calibration Value	
7.MST3388	
8.X242	
9.X242 NTSC	
10.FBE2	
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	


Dynamic CE	Off
Dynamic Dimming	Off
FBE2 Y_MEAN READ	Read Value

3-3 White Balance - Calibration

3-3-1 White Balance -Calibration



3-3-2 White Balance - Adjustment



3-3-3 Conditions for Measurement

1. On the basis of toshiba ABL pattern : High Light level (57 IRE)

- INPUT SIGNAL GENERATOR : MSPG-925LTH

* Mode NO 1 : 744X484@60 Hz

NO 6 : 1280X720@60 Hz (Component 720P)

NO 21 : 1024X768@60 Hz

* Pattern NO 15 : Color bar

NO 16 : Toshiba ABL Pattern

NO 17 : 16 gray

2. Optical measuring device : CA210 (FL)

Please use the MSPG-925 LTH generator for model LNR2355W,LNR2755W,LNR3255W.

3-4 White Ratio (Balance) Adjustment

1. You can adjust the white ratio in factory mode (1:Calibration, 3:White-Balance).
2. Since the adjustment value and the data value vary depending on the input source, you have to adjust these in CVBS, Component 1 and HDMI 1 modes.
3. The optimal values for each mode are configured by default. (Refer to Table 1, 2.)

It varies with Panel's size and Specification.

- Equipment : CA-210
- Pattern: Master MIK K7256 #92 "ABL Pattern" as standard
 - Use other equipment only after comparing the result with that of the Master equipment.
- Set Aging time : 60min ↑
- Calibration and Manual setting for WB adjustment.



HDMI: No Calibration Manual adjustment at #16 pattern (720p)

COMP: Calibration at #24 Chessboard Pattern → Manual adjustment at #16 pattern (720p)

CVBS: Calibration at #24 Chessboard Pattern → Manual adjustment at #16 pattern (NTSC)

PC : Calibration at #24 Chessboard Pattern → No Manual adjustment (1024x768@60Hz)

-White Balance Manual Adjustment (ABL Pattern)

	CA-210				
		x	y	Y (cd/m ²)	T(K) ± MPCD
CVBS (NTSC) #1, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0
COMP (720P) #6, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0
DVI (720P) #6, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0

-Adjustment Specification

White Balance : High light (± 3), Low light (± 5)

Luminance : High light (± 10%)

Low light (2.0fL ± 0.1fL, 2.1fL ± 0.2fL)

3-5 Servicing Information

3-5-1 USB Download Method

1.USB Download Method


- (1) Download the upgrade file in USB flash driver.
- (2) Extract the file. "T-SC37AUSC" folder will be appeared.
- (3) Turn on the LCD TV.
- (4) Insert the USB flash driver into the service jack of LCD TV and press the MENU button.
- (5) Place the cursor to SW Upgrade of Setup MENU.
- (6) Press the "ENTER" button.
- (7) "Scanning for USB..... It may take up to 30 seconds." will be appeared.
- (8) Press the "ENTER" button.
- (9) "Upgrading now... Please do not disconnect USB before upgrade is completed." will be appeared.
- (10) When upgrade is completed, the OSD says "Upgrade is completed. Power will be off 3 seconds from now and turned on automatically."

Memo

7 Block Diagram

- This Document can not be used without Samsung's authorization


X242 Block Diagram - Entry



Memo

13 Circuit Descriptions

13-1 Block description



NO.	BLOCK	DESCRIPTION	REMARK
1	X242(IC202)	DTV DECODER	215H4AALA11HG
2	FBEX(IC1301)	IMAGE BACKEND ENHANCER	NZ2YFKC
3	SUB_MICOM(IC602)	CONTROL POWER,PANEL, etc.	WT61P6S
4	SOUND AMP(IC1100)	SOUND AMP IC	NTP3000(H12363B)
5	SOUND PROCESSOR(IC1002)	SOUND MAIN PROCESSOR IC	MSP4450K E8
6	TUNER(TU500)	HALF-NIM-TUNER & SPLITTER	DTVS227CH281A
7	DDR MEMORY(IC201)	X242 DDR MEMORY	HYB18T512161BF-25
8	IC-RECEIVER(IC1201)	2ADC+1HDMI	MST3388MK-LF-110
9	HDMI SWITCH(IC1202)	3 TO 1 HDMI SWITCH	SIL9185CTU

Memo





11 Disassembly and Reassembly





This section of the service manual describes the disassembly and reassembly procedures for the TFT-LCD TV.







⚠ WARNING : This monitor contains electrostatically sensitive devices. Use caution when handling these components.




11-1 Disassembly

⚠ Cautions : 1. Disconnect the monitor from the power source before disassembly.
2. Follow these directions carefully; never use metal instruments to pry apart the cabinet.

Description	Description Picture
1. Place monitor face down on cushioned table. Remove screws from the rear cover and stand. Remove stand from the set. Remove the rear cover.	
	
	
	

Description	Description Picture
<p>2. Disconnect cables from the mainboards and SMPS.</p> <p>Remove screws from the main board and SMPS.</p>	
	
<p>3. Remove screws of stand bracket.</p> <p>Remove the bracket.</p>	
	

Description	Description Picture
<p>4. Remove the screws of Assy P_function. Remove Assy P_function. Remove speakers.</p>	
	
	
<p>5. Remove screws and lift up the bracket.</p>	
	
	

Description	Description Picture
<p>6. Lift up the bracket. Lift up the LCD panel.</p>	
	
	

11-2 Reassembly

Reassembly procedures are in the reverse order of disassembly procedures.

6 Electrical Parts List

-You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>

6-1 LNT325HAX Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
		LNT325HAX/XAA	LN-T325HA,N36A/32R83-GBR,32,LCD-TV,UNITE		
0.1	M0216	BN90-01149A	ASSY STAND;32R81,M81,SWIVEL,-,-,-	1	S.N.A
..2	T0524	6902-000241	BAG PE;NITRON/HDPE,T0.5/T0.012,W600,L600	1	S.N.A
..2	M0027	BN96-04662A	ASSY STAND P-BASE;32R81,M81,SWIVEL,-,ABS	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,-,M4,L16,ZPC(BLK)	4	S.A
...3	M0081	6003-001239	SCREW-TAPTITE;FH,+,-,B,M4,L10,ZPC(WHT),S	4	S.A
...3		BN61-02232A	HOLDER-SWIVEL RING;32R71,ACETAL NATUAL,T	1	S.N.A
...3		BN61-02233A	HOLDER-SWIVEL RING;32R71,ACETAL NATUAL,B	1	S.N.A
...3		BN61-02236A	BRACKET-HINGE SWIVEL;BORDEAUX 32,SECC,T1	1	S.N.A
...3		BN61-02942A	BRACKET-STAND BOTTOM;32,BORDEAUX PLUS,SE	1	S.N.A
...3	T0920	BN61-02943A	GUIDE-STAND;32R81,ABS,V0,-,-,-,BK500,-	1	S.N.A
...4		BN61-02967A	BRACKET-SUPPORT STAND;32 BORDEAUX PLUS,S	1	S.N.A
...4	T0514	BN61-03046A	BRACKET-SUPPORT;32 BORDEAUX PLUS,SECC,2.	1	S.N.A
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.4	S.N.A
...3	T0004	BN63-03102A	COVER-STAND BASE;32R81,ABS+PMMA,-,-,-,HB	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,SILICON,DIA 17 * T1.	4	S.N.A
0.1	M0002	BN90-01153X	ASSY COVER REAR;32R81,UO(CLUB),PC+ABS,V0	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,-,M4,L16,ZPC(BLK)	2	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,-,M4,L16,ZPC(BLK)	13	S.A
..2	M0013	BN96-04666N	ASSY COVER P-REAR;32R81,UO(CLUB),PC+ABS,	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	4	S.N.A
...3	T0101	BN61-03348A	BRACKET-WALL;LCD TV 32",SECC T1.6	4	S.N.A
...3	CCM1	BN63-02183F	COVER-SHEET;Rhcm,PE Vinyl,T0.05,900mm,20	0.7	S.N.A
...3	M0006	BN63-03101A	COVER-REAR;32R81,UO,PC+ABS,-,-,-,V0,-,BK	1	S.N.A
...3	T0071	BN64-00554A	INLAY-TERMINAL;07,COMMON,UO,PS SHEET,T0.	1	S.N.A
...3	T0064	BN65-00002A	CLAMPER CORE;BORDEAUX,PP,V0,BLK	1	S.N.A
...3	T0067	BP60-00099A	SPACER-SCREEN;Club-Bordeaux,EVA SPONGE,L	2	S.N.A
0.1	M0001	BN90-01317A	ASSY COVER FRONT;32R83,UO(CLUB),-PC+ABS	1	S.N.A
..2	T0175	BN96-04768B	ASSY SPEAKER P;8ohm,4pin,10W,150/650,Bor	1	S.A
..2	T0003	BN96-05625A	ASSY COVER P-FRONT;32R83,UO(CLUB),-PC+A	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A
...3	CCM1	BN63-02183F	COVER-SHEET;Rhcm,PE Vinyl,T0.05,900mm,20	1.48	S.N.A
...3	M0112	BN63-03650A	COVER-FRONT;32R83,UO,CLUB,PC+ABS,-,-,-,V	1	S.N.A
...3	T0059	BN64-00366A	INDICATOR LED;ROME-I,PC,CLEAR,ALL MODEL	1	S.N.A
...3	T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,V	1	S.N.A
...3	T0054	BN64-00640A	KNOB-DECORATION;37 BORDEAUX PLUS,ABS,-,-	1	S.N.A
...3	T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A
...3	M0146	BN96-04884C	ASSY BOARD P-POWER & IR;LNT4042HX/XAA,CT	1	S.A
...3		BN96-05667A	ASSY HOLDER P-BOSS;32R81,CLUB,PC+ABS,V0,	1	S.N.A
...4		BN61-03261A	BOSS-TAPE;Tulip,ACRYL,T1.1,W12mm,GRAY,TA	1.15	S.N.A
...4		BN61-03322A	HOLDER-BOSS BOTTOM;32 BORDEAUX PLUS,ABS+	1	S.N.A
...4	CCM1	BN63-02183F	COVER-SHEET;Rhcm,PE Vinyl,T0.05,900mm,20	0.3	S.N.A
...3		BN63-01151A	FELT-NON WOVEN;MM17NS,T0.5,393,10,BLACK	2	S.N.A
...3	T0069	BP60-00015D	SPACER-FELT;617W,FELT,L760,T0.5,W10	2	S.N.A
...3	M0279	BN63-00867A	FELT;AS17UO,FELT,0.5,10,68	1	S.N.A
...3	M0145	BN96-05677B	ASSY BOARD P-FUNCTION;LNT375HAX,CT5000-5	1	S.N.A
0.1	M0017	BN91-01550E	ASSY CHASSIS;LNT325HX/XAA.AMLCD	1	S.N.A
..2	M0014	BN94-01293F	ASSY PCB MAIN-AMLCD;LNT325HAX/VVE	1	S.N.A
...3	T0245	0202-001492	SOLDER-WIRE FLUX;HSE-02 LFM48 SR-34 S,-,	0.25	S.A
...3	JA900S	3701-001388	CONNECTOR-HDMI;20P,Phosphor Bronze,ANGLE	1	S.A
...3	JA700	3701-001400	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,Ni	1	S.A
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A
...3	CN330	3711-000058	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5MM,AN	1	S.A
...3	CN330	3711-004484	HEADER-BOARD TO CABLE;BOX,5P,1R,2mm,STRA	1	S.A
...3	CN330	3711-004531	HEADER-BOARD TO CABLE;BOX,10P,1R,2mm,ANG	1	S.A
...3	CN330	3711-005606	HEADER-BOARD TO CABLE;BOX,30P,2R,2mm,STR	1	S.A
...3	CN330	3711-005842	HEADER-BOARD TO CABLE;BOX,24P,2R,2MM,STR	1	S.A
...3	JA330	3722-000143	JACK-PHONE;1P(VER),AG,BLK,ANGLE	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA332	3722-001163	JACK-VHS;4P,AU,BLK,ANGLE	1	S.A
...3	JA332	3722-001734	JACK-VHS;4P,SN,BLK,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002363	JACK-PIN;3P,Sn,YEL/WHT/RED,STRAIGHT	1	S.A
...3	CN700	3722-002516	JACK-USB;4P/1C,AU30U,BLK,STRAIGHT,A TYPE	1	S.A
...3	JA333	3722-002543	JACK-PIN;3P,Sn,RED/WHT/YEL,ANGLE	1	S.A
...3	CIS3	BN40-00097A	TUNER;DTVS227CH281A,DTVS227CH281A,ATSC/N	1	S.A
...3	T0603	BN63-03210A	SHIELD-PCB MAIN;BORDEAUX PLUS,SPT-23,T0.3,	1	S.N.A
...3	CCMM1	BN73-00024D	SILICON/RUBBER;BORDEAUX,SILICON,28x28XT6	1	S.N.A
...3	T0174	BN97-01586F	ASSY SMD;LNT325HAX/*	1	S.N.A
...4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-,D20-45\$, .96.5Sn/	3.861	S.N.A
...4	D728	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D729	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D100	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1000	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D101	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1102	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1103	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1400	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D300	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1401	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1402	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1403	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1405	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1406	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D500	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D700	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D701	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D702	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D703	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D704	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D711	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D712	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D713	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D714	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D715	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D716	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D717	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D718	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D724	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D725	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D730	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D731	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D732	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D733	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D734	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D735	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D736	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D737	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D902S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D903S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D905S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D906S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D907S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D908S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D909S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D910S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D911S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D912S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1101	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1104	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1105	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1106	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1107	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D600D	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	D602D	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D603	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D746	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D747	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D930	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D102	0402-001098	DIODE-RECTIFIER;SK34,40V,3A,SMC,TP	1	S.A
....4	D601	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D609	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D719	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D739	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D913S	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D705	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D726	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D744	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D745	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D900S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D901S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D706	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D707	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D708	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D709	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D710	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D720	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D721	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D722	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D723	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D727	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D740	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D741	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D742	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D743	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D800	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D801	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D802	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D803	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D804	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D805	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D806	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D807	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D808	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D809	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D810	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D811	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D812	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D813	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D816	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D817	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D818	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D819	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D820	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D821	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D824	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D825	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D826	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D827	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D828	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D829	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D830	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D831	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D832	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D833	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D834	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D835	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D836	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D837	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D904S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D914S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D915S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D916S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D917S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D918S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	D919S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D920S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D921S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D922S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D923S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D924S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D925S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D928S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D929S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D501	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A
....4	D814	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D815	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D1100	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D604	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D605	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D608	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	Q1000	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1102	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1106	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q101	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1103	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1104	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1105	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1300L	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1400	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q500	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q602	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000275	FET-SILICON;SI4435DY,P,-30V,+8.0A,0.014	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC306	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC307	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC1001	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	S.A
....4	IC603	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	S.A
....4	IC801	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC	1	S.A
....4	IC106	1001-001440	IC-VIDEO SWITCH;SI9185CTU,QFP,80P,3.3V,	1	S.A
....4	IC800	1006-001266	IC-LINE TRANSCEIVER;SP3232EEY,TSSOP,16P,	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-001385	IC-EEPROM;24C256,256Kbit,32Kx8,SOP,8P,5x	1	S.A
....4	IC113	1105-001780	IC-DRAM;HYB18T512161BF,DDR2,512Mbit,32Mx	1	S.A
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150ML,DUAL,10	1	S.A
....4	T0085	1201-002136	IC-AUDIO AMP;LM4810,MSOP,8P,3x3mm,DUAL,-	1	S.A
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A
....4	T0087	1203-001815	IC-POSIFIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-002074	IC-POSIFIXED REG.;MIC39150,TO-263,3P,-,	1	S.A
....4	T0087	1203-002835	IC-POSIFIXED REG.;KIA7805AF,DPAK,3P,6.6	1	S.A
....4	T0087	1203-002842	IC-POSIFIXED REG.;AP1117D-33A,TO-252,3P	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	T0087	1203-003121	IC-POSIFIXED REG.;FAN1112,SOT-223,3P,6.	1	S.A
....4	IC062	1203-003183	IC-MULTI REG.;SI-3002KWM-TL,DPAK,5P,6.6X	1	S.A
....4	T0087	1203-003696	IC-POSIFIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003703	IC-POSIFIXED REG.;AP1117E-18A,SOT-223,3	1	S.A
....4	IC102	1203-004268	IC-DC/DC CONVERTER;SC4521SETRT,SOIC,8P,4	1	S.N.A
....4	IC600	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC601	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC202	1204-002648	IC-DECODER;215H4AALA11HG,BGA,444P,27x27m	1	S.A
....4	IC1002	1204-002708	IC-AUDIO PROCESSOR;MSP440K-VK-E8-500,PM	1	S.A
....4	IC118	1204-002729	IC-VIDEO PROCESS;S4LF119X01,PBGA,208P,17	1	S.A
....4	IC1201	1205-003149	IC-RECEIVER;MST3388MK-LF-110,PQFP,128P,2	1	S.A
....4	R1244	2007-000042	R-CHIP;499ohm,1%,1/10W,TP,1608	1	S.A
....4	R286	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R295	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A

[illegible]

6 Electrical Parts List

[illegible]

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	R656	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R657	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R658	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R659	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R660	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R662	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R663	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R664	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R666	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R668	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R683	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R790	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R791	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R801	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R819	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R820	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R830	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R831	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R930S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R931S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R941S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R967	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R604	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R803	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R805	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R816	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R817	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R834	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R835	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R943S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R944S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R507	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R1363L	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R738	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R739	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R772	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R773	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R1044	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1052	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1053	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R114	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1200	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1202	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1303L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1370L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R306	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R336	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R383	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R384	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R503	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R629	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R651	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R711	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R731	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	R613	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R614	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R615	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R619	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R621	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R622	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R623	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R624	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R632	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R633	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R634	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R635	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R636	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R682	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R700	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R701	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R709	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R710	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R720	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R727	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R737	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R740	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R741	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R752	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R906S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R907S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R919S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R109	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R764	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R765	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1047	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1050	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R508	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1038	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1039	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R832	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R833	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R100	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1000	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1001	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1002	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1003	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1004	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1005	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1006	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1007	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1024	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1025	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1026	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1027	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1028	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1029	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1030	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1031	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1045	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1056	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R510	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1051	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	1	S.A
....4	R305	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	1	S.A
....4	R1204	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1207	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1209	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1213	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1216	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1218	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1220	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1223	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1225	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R270	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R285	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R288	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	R290	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R292	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R294	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R628	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1206	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1215	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1222	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R511	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1401	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1402	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1403	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1105	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1106	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1201	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R601	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1307L	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	S.A
....4	R509	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R512	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R1227	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1228	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1229	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1230	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1232	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1233	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1235	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R655	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R704	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R724	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R725	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R728	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R729	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R732	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R733	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R735	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R736	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R742	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R753	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R754	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R755	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R756	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R759	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R760	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R761	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R766	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R774	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R775	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R776	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R777	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R778	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R779	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R780	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R781	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R782	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R783	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R784	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R785	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R786	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R787	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R788	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R789	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R804	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R806	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R808	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R824	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R825	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R826	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R921S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R922S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R923S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R924S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R925S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R926S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	R927S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R928S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R959	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R960	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R961	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R962	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R963	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R964	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R965	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R966	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R968	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R757	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R758	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R1300	2007-000669	R-CHIP;2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R104	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1120	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R247	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R250	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R227	2007-000779	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R1212	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R246	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R249	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R1100	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1101	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1102	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1103	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R606	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1107	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1108	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1112	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1113	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1114	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1121	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1125	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1205	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1208	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1211	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1214	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1217	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1219	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1221	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1224	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1226	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R807	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R809	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R810	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R811	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R821	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R822	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R827	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R828	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R829	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R933S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R934S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R945S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R206	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R208	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R232	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R713	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R714	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R726	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R730	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R105	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R505	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R506	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R272	2007-007797	R-CHIP;44.2ohm,1%,1/10W,TP,1608	1	S.A
....4	RA200	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA201	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA202	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	RA203	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA204	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA205	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA308	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA309	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA311	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA312	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA313	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA314	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA315	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA300	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA301	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA316	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA317	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA318	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA319	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA1201	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1202	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1203	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1204	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1205	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1206	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1200	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA302	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA303	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA304	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA305	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA306	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA307	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA310	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	R1320	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA900S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA901S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA902S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	C1032	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1045	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1064	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1065	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1052	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1063	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1112	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1113	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1116	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1126	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1129	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1130	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1133	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1145	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1260	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1261	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1262	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1263	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1267	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1268	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1272	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1273	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1274	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1275	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1276	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1277	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1278	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1281	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1282	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1302	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1304	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1306	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1308	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1319	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1320	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1321	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1331	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1333	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

6 Electrical Parts List

[illegible]

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	C707	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C800	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C814	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C902S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C904S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C100	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C101	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C112	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C116	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C130	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1303	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1305	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1307	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1309	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1312	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1313	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1314	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1315	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1323	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1325	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1326	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1327	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1330	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1332	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1334	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1342L	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1343L	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1400	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1405	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1408	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C308	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C507	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C510	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C515	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C518	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C522	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C602	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C135	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C1066	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1067	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1102	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1103	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1105	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1108	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1109	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1115	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1122	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1123	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1125	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1127	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1135	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1136	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1138	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1142	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1212	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1230	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1242	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1316	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1317	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1318	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1328	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1329	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1340L	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C306	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C508	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C608	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C535	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A
....4	C1251	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C1252	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	C527	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C533	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C606	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C607	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C300	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C301	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C1069	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C136	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C708	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C709	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C717	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C718	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C801	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C802	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C812	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C813	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C815	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C819	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C820	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C821	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C822	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C903S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C905	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C906S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C907S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C908S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C1200	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C525	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C531	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C805	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C806	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C807	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C816	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C817	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C818	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C1049	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C1051	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C536	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C1043	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C519	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C1210	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1211	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1213	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1217	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1218	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1220	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1223	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1228	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1232	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1235	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1236	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1239	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1240	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1241	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1247	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1248	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1249	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1250	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1404	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C211	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C1300	2203-001034	C-CER,CHIP;5.6nF,10%,50V,X7R,1608	1	S.A
....4	C128	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1310	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1035	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1039	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1047	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C526	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C529	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C530	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C532	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1038	2203-001155	C-CER,CHIP;0.068nF,5%,50V,NP0,TP,1608	1	S.A
....4	C1201	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	C521	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C1031	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C1046	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C126	2203-002392	C-CER,CHIP;220nF,+80-20%,50V,Y5V,2012	1	S.A
....4	C1111	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1114	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1124	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1141	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1005	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C102	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1034	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C104	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C106	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1068	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C108	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C111	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C114	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C115	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1203	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1204	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1205	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1207	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1208	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1209	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1215	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1216	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1219	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C122	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1222	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1224	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1227	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1229	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1233	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1234	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1238	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1244	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1245	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1246	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1254	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1255	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1256	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1257	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1259	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C127	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1271	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C132	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1336L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C134	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1345L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C138	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	C600	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C124	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,1608	1	S.A
....4	C1106	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1107	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1110	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1128	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1134	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1140	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1146	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1147	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1148	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1149	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C500	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C504	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C509	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C520	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C523	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1007	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1009	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1011	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1012	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1016	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1017	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1018	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1020	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1023	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1025	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1027	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1028	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1057	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1061	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C118	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C503	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C1019	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1021	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1036	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1040	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1048	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1050	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1202	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1206	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1214	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1226	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1237	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1243	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1253	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1258	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1264	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1265	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1269	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1279	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1280	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1283	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1301	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1346L	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C222	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C228	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C239	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C505	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C514	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C603	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C700	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C702	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C710	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C804	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C824	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C900S	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1030	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1053	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1062	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1100	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1131	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	C1132	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C825	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1029	2402-001006	C-AL,SMD;4.7uF,20%,25V,GP,TP,3.6x6.3x3.	1	S.A
....4	C1033	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1054	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1055	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1058	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C110	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C113	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1225	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1231	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1266	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1270	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C129	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C230	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C232	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C254	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C315	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C450	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C487	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C489	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C490	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C501	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C517	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C537	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C123	2402-001100	C-AL,SMD;0.1uF,20%,50V,GP,TP,4.3x4.3x5.2	1	S.A
....4	C1101	2402-001128	C-AL,SMD;100#IF,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1042	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1311	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1322	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C140	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1402	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C141	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C144	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C524	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C1006	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1044	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C105	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C107	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C516	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1059	2402-001185	C-AL,SMD;2.2UF,20%,50V,WT,TP,4.3X4.3X6MM	1	S.A
....4	C146	2402-001260	C-AL,SMD;100uF,20%,10V,WT,REEL,6.3X5.7	1	S.A
....4	C103	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C109	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C117	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C119	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C121	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C133	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C1104	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10		

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	L100	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	L101	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	T0077	BN41-00817D	PCB MAIN;FR-4,4,192*240	1	S.N.A
....4	M0018	BN97-01387K	ASSY MICOM;T-SC37AUSM-1002,N36A,2007.03.	1	S.N.A
....5	IC520	0903-001485	IC-MICROCONTROLLER;44P,12x12mm,24MHz,TR,	1	S.N.A
....4	M0018	BN97-01587B	ASSY MICOM;T-SC37AUSC-1019,N36A,2007.05.	1	S.N.A
....5	IC115	1107-001666	IC-FLASH MEMORY;KFG5616U1A,256Mbit,16Mx1	1	S.N.A
0.1		BN91-01647D	ASSY SHIELD-SHE;LNT325HAX/XAA	1	S.N.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	4	S.A
..2	M0081	6003-000337	SCREW-TAPTITE;BH,+,S,M4,L10,ZPC(BLK),SWR	4	S.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	4	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	1	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	8	S.N.A
..2	M0081	6003-001439	SCREW-TAPTITE;BH,+,S,M4,L8,ZPC(WHT),SW	1	S.N.A
..2	M2893	BH39-00362G	LEAD CONNECTOR;SONOMA,UL1007#26,5PIN,100	1	S.A
..2	M2893	BN39-00603M	LEAD CONNECTOR;LE40R73BDX,UL1007#26,UL/C	1	S.A
..2	T0076	BN39-00615D	CBF HARNESS;BORDEAUX,1617#22,3P,1P,RING,	1	S.A
..2	M2893	BN39-00802A	LEAD CONNECTOR;LE32R86BDX,UL1007#26,UL/C	1	S.A
..2	M2893	BN39-00875A	LEAD CONNECTOR;LE32R86BDX,UL1571#30,30P,	1	S.A
..2	T0764	BN44-00156A	SMPS-LCDTV;MK32P,SEM,AC/DC,180W,AC100 ~	1	S.A
..2	M0146	BN61-02419A	BRACKET-PANEL SIDE;SONOMA 32,SECC,T1.2,A	4	S.N.A
..2	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	2	S.N.A
..2		BN61-02952J	HOLDER-SIDE AV;32R81,UO,CLUB,PC+ABS,V0,-	1	S.N.A
..2	M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.N.A
..2	T0447	BN96-04681A	ASSY BRACKET P-PANEL;32R81,-,-,-,AM,CM	1	S.N.A
...3	M0131	AA63-01437A	GASKET;Bordeaux,Conductive Fabric,20mm,9	1	S.N.A
...3		BN61-02200A	BRACKET-GUIDE POWER;Bordeaux 32,SECC,T1.	1	S.N.A
...3	M0146	BN61-02970A	BRACKET-PANEL TOP;32 BORDEAUX PLUS,SECC,	1	S.N.A
...3		BN61-02974A	BRACKET-PANEL BOTTOM;32 BORDEAUX PLUS,SE	1	S.N.A
...3		BN61-02978A	BRACKET-GUIDE MAIN;32 BORDEAUX PLUS,SECC	1	S.N.A
...3	M0131	AA63-01438A	GASKET;Bordeaux,Conductive Fabric,7mm,8m	1	S.N.A
...3		BN61-02199B	BRACKET-GUIDE POWER;Bordeaux 32,SECC,T1.	1	S.N.A
...3	M0131	BN63-03327A	GASKET;BORDEAUX PLUS,Conductive Fabric,2	1	S.N.A
0.1		BN91-01702A	ASSY LCD-AMLCD;LNT3232HX/*	1	S.N.A
..2	M0215	BN07-00453A	LCD-PANEL;LTA320WT-L06,8bit,32inch,16.7M	1	S.A
0.1	M0045	BN92-02624C	ASSY ACCESSORY;LNT325HAX/XAA	1	S.N.A
..2	M0045	BN96-05376C	ASSY ACCESSORY;LNT325HAX/XAA	1	S.A
...3	T0268	3903-000144	CBF-POWER CORD;DT,US,BP3/Y,U(IEC C13-RA)	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	T0074	BN59-00598A	REMOCON;JASMINE, TM87C, SAMSUNG28P+EEPROM,	1	S.A
...3	ACCESSORY	BN63-01798A	CLOTH-CLEAN;RE40**,CLOTH,180,200,RHCM	1	S.N.A
...3	T0531	BN63-03103B	COVER-BOTTOM;32R81,HIPS,-,-,-,V0,-,BK500	1	S.A
...3	M0045	BN96-01800A	ASSY ACCESSORY;ROME32,SCREW	1	S.A
....4	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	4	S.A
....4	ACCESSORY	6902-000128	BAG ZIPPER;LDPE,T0.05,W200,L150,TRP,8,2-	1	S.N.A
..2	M0045	BN96-05377A	ASSY ACCESSORY;LNT325HX/XAA	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	ACCESSORY	AA68-00371C	MARK RECYCLE-CARD WARRANTY,06,-,SEA,W/P10	1	S.N.A
...3	ACCESSORY	AA68-03242F	MANUAL FLYER-02;SAFETY GUIDE;All Model,S	1	S.N.A
...3	T0511	BN68-00998P	MANUAL USERS;COMM,SAMSUNG,Eng/Spa,N,Amer	1	S.N.A
...3	ACCESSORY	BN68-01002F	MANUAL FLYER-QSG;COMM,SAMSUNG,English,N.	1	S.N.A
...3	T0238	AA68-03870C	MANUAL FLYER-REGISTRATION CARD;comm,Sams	1	S.N.A
...3	T0238	AA68-03870D	MANUAL FLYER-REGISTRATION CARD;comm,Sams	1	S.N.A
0.1	M0019	BN92-02640E	ASSY LABEL;LNT325HX/XAA	1	S.N.A
0.1	M0113	BN92-02750A	ASSY P/MATERIAL;32R81,CLUB	1	S.N.A
..2	T0376	6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	0.017	S.N.A
..2	T0376	6902-000379	BAG AIR;LDPE,T0.2,W1000,L1800,TRP,-,-	0.006	S.N.A
..2	T0003	6902-000604	BAG WRAPPING;LDPE,T0.02,W500,L10000,TRP,	5.7	S.N.A
..2	T0524	6902-000738	BAG PE;HDPE/HDPE/NITRON (DOUBLE),T0.015/	1	S.N.A
0.1	M0003	BN92-02753A	ASSY BOX;32R83,UO,CLUB,-,-,-	1	S.N.A
..2	T0130	BN69-01963A	BOX-00,SET;32R83,CB,A1,DY-01,W899,D728,H	1.02	S.N.A

6-2 LNT375HAX Parts list

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
		LNT375HAX/XAA	LN-T375HA,N36A/37R83-GBR,37,LCD-TV,UNITE		
0.1	M0216	BN90-01148A	ASSY STAND;37,40R81,SWIVEL,-,-,-	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
..2	M0027	BN96-04661A	ASSY STAND P-BASE;37,40R81,SWIVEL,-,ABS+	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
...3	M0081	6003-001239	SCREW-TAPTITE;FH,+,-,B,M4,L10,ZPC(WHT),S	8	S.A
...3		BN61-02248A	HOLDER-SWIVEL RING;40R71,ACETAL NATUAL,T	1	S.N.A
...3		BN61-02883A	BRACKET-STAND BOTTOM;BORDEAUX PLUS,40,SE	1	S.N.A
...3		BN61-02885A	HOLDER-SWIVEL RING;MURANO40,ACETAL NATUR	1	S.N.A
...3		BN61-02886A	BRACKET-HINGE SWIVEL;BORDEAUX PLUS,40,SE	1	S.N.A
...3	T0920	BN61-02984A	GUIDE-STAND;40R81,ABS,V0,-,-,-,BK500,-	1	S.N.A
....4		BN61-02981A	BRACKET-SUPPORT STAND;40 BORDEAUX PLUS,S	1	S.N.A
....4		BN61-03045A	BRACKET-SUPPORT STAND;40 BORDEAUX PLUS,S	1	S.N.A
...3	CCM1	BN63-02183E	COVER-SHEET;Rhcm,PE Vinyl,T0.05,750mm,20	0.5	S.N.A
...3	T0004	BN63-03030A	COVER-STAND BASE;40R81,ABS+PMMA,-,-,-,HB	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,SILICON,DIA 17 * T1.	4	S.N.A
0.1	M0002	BN90-01152H	ASSY COVER REAR;37R81,UO(CLUB),PC+ABS,V0	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	2	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	1	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	12	S.A
..2	M0013	BN96-04665F	ASSY COVER P-REAR;37R81,UO(CLUB),PC+ABS,	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	T0101	BN61-03348A	BRACKET-WALL;LCD TV 32",SECC T1.6	2	S.N.A
...3	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	0.99	S.N.A
...3	M0006	BN63-03118B	COVER-REAR;37R81,UO,PC+ABS,V0,BK25,H/GLO	1	S.N.A
...3	T0071	BN64-00554A	INLAY-TERMINAL;07,COMMON,UO,PS SHEET,T0.	1	S.N.A
...3	T0064	BN65-00002A	CLAMPER CORE;BORDEAUX,PP,V0,BLK	1	S.N.A
...3	T0069	AA60-00091F	SPACER-FELT;-FELT,150X10,-,-,BLK,T0.5,-	2	S.N.A
...3	T0067	BP60-00099A	SPACER-SCREEN;Club-Bordeaux,EVA SPONGE,L	2	S.N.A
0.1	M0001	BN90-01316A	ASSY COVER FRONT;37R83,UO(CLUB),-,-,PC+ABS	1	S.N.A
..2	T0175	BN96-04768A	ASSY SPEAKER P;8ohm,4pin,10W,Bordeaux PI	1	S.A
..2	T0003	BN96-05629A	ASSY COVER P-FRONT;37R83,UO(CLUB),-,-,PC+A	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A
...3	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	1.983	S.N.A
...3	M0112	BN63-03607A	COVER-FRONT;37R83,UO,CLUB,PC+ABS,-,-,-,V	1	S.N.A
...3	T0059	BN64-00366A	INDICATOR LED;ROME-I,PC,CLEAR,ALL MODEL	1	S.N.A
...3	T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,-,V	1	S.N.A
...3	T0054	BN64-00640A	KNOB-DECORATION;37 BORDEAUX PLUS,ABS,-,-	1	S.N.A
...3	T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A
...3	M0146	BN96-04884C	ASSY BOARD P-POWER & IR;LNT4042HX/XAA,CT	1	S.A
...3		BN96-05666A	ASSY HOLDER P-BOSS;37R81,CLUB,PC+ABS,V0,	1	S.N.A
....4		BN61-03261A	BOSS-TAPE;Tulip,ACRYL,T1.1,W12mm,GRAY,TA	1.45	S.N.A
....4		BN61-03301A	HOLDER-BOSS BOTTOM;37R81,CLUB,PC+ABS,V0,	1	S.N.A
....4	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	0.3	S.N.A
...3	M0279	BN63-00867A	FELT;AS17UO,FELT,0.5,10,68	2	S.N.A
...3	M0145	BN96-05677B	ASSY BOARD P-FUNCTION;LNT375HAX,CT5000-5	1	S.N.A
0.1		BN91-01180L	ASSY LCD-CPT;LE37S71BX*	1	S.N.A
..2	M0215	BN07-00366A	LCD-PANEL;CLAA370WA03,8bit,37inch,16.7M,	1	S.A
0.1	M0017	BN91-01550C	ASSY CHASSIS;LNT375HAX/XAA	1	S.N.A
..2	M0014	BN94-01293D	ASSY PCB MAIN;LNT375HAX/XAA	1	S.A
...3	T0245	0202-001492	SOLDER-WIRE FLUX;HSE-02 LFM48 SR-34 S,-,	0.25	S.N.A
...3	JA900S	3701-001388	CONNECTOR-HDMI;20P,Phosphor Bronze,ANGLE	1	S.A
...3	JA700	3701-001400	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,Ni	1	S.A
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A
...3	CN330	3711-000058	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5MM,AN	1	S.A
...3	CN330	3711-004484	HEADER-BOARD TO CABLE;BOX,5P,1R,2mm,STRA	1	S.A
...3	CN330	3711-004531	HEADER-BOARD TO CABLE;BOX,10P,1R,2mm,ANG	1	S.A
...3	CN330	3711-005606	HEADER-BOARD TO CABLE;BOX,30P,2R,2mm,STR	1	S.A
...3	CN330	3711-005842	HEADER-BOARD TO CABLE;BOX,24P,2R,2MM,STR	1	S.A
...3	JA330	3722-000143	JACK-PHONE;1P(VER),AG,BLK,ANGLE	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
...3	JA332	3722-001163	JACK-VHS;4P,AU,BLK,ANGLE	1	S.A
...3	JA332	3722-001734	JACK-VHS;4P,SN,BLK,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002363	JACK-PIN;3P,Sn,YEL/WHT/RED,STRAIGHT	1	S.A
...3	CN700	3722-002516	JACK-USB;4P/1C,AU30U,BLK,STRAIGHT,A TYPE	1	S.A
...3	JA333	3722-002543	JACK-PIN;3P,Sn,RED/WHT/YEL,ANGLE	1	S.A
...3	CIS3	BN40-00097A	TUNER;DVS227CH281A,DVS227CH281A,ATSC/N	1	S.A
...3	T0603	BN63-03210A	SHIELD-PCB MAIN;BORDEAUX PLUS,SPTT,TO.3,	1	S.N.A
...3	CCMM1	BN73-00024D	SILICON/RUBBER;BORDEAUX,SILICON,28x28XT6	1	S.N.A
...3	T0174	BN97-01586D	ASSY SMD;LNT375HAX/XAA	1	S.N.A
...4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-,D20-45\$, .96.5Sn/	3.861	S.N.A
...4	D728	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D729	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D100	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1000	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D101	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1102	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1103	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1400	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D300	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1401	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1402	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1403	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1405	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1406	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D500	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D700	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D701	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D702	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D703	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D704	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D711	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D712	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D713	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D714	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D715	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D716	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D717	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D718	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D724	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D725	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D730	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D731	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D732	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D733	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D734	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D735	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D736	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D737	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D902S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D903S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D905S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D906S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D907S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D908S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D909S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D910S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D911S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D912S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1101	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1104	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1105	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1106	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1107	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D600D	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D602D	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D603	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D746	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D747	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D930	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D102	0402-001098	DIODE-RECTIFIER;SK34,40V,3A,SMC,TP	1	S.A
....4	D601	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D609	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D719	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D739	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D913S	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D705	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D726	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D744	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D745	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D900S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D901S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D706	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D707	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D708	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D709	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D710	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D720	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D721	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D722	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D723	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D727	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D740	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D741	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D742	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D743	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D800	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D801	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D802	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D803	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D804	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D805	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D806	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D807	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D808	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D809	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D810	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D811	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D812	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D813	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D816	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D817	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D818	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D819	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D820	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D821	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D824	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D825	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D826	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D827	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D828	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D829	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D830	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D831	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D832	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D833	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D834	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D835	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D836	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D837	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D904S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D914S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D915S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D916S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D917S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D918S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D919S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D920S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D921S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D922S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D923S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D924S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D925S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D928S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D929S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D501	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A
....4	D814	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D815	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D1100	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D604	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D605	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D608	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	Q1000	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1102	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1106	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q101	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1103	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1104	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1105	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1300L	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1400	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q500	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q602	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000275	FET-SILICON;SI4435DY,P,-30V,+8.0A,0.014	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC306	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC307	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC1001	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	S.A
....4	IC603	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	S.A
....4	IC801	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC	1	S.A
....4	IC106	1001-001440	IC-VIDEO SWITCH;SiI9185CTU,QFP,80P,3.3V,	1	S.A
....4	IC800	1006-001266	IC-LINE TRANSCEIVER;SP3232EEY,TSSOP,16P,	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-001385	IC-EEPROM;24C256,256Kbit,32Kx8,SOP,8P,5x	1	S.A
....4	IC113	1105-001780	IC-DRAM;HYB18T512161BF,DDR2,512Mbit,32Mx	1	S.A
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	S.A
....4	T0085	1201-002136	IC-AUDIO AMP;LM4810,MSOP,8P,3x3mm,DUAL,-	1	S.A
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A
....4	T0087	1203-001815	IC-POSIFIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-002074	IC-POSIFIXED REG.;MIC39150,TO-263,3P,-,	1	S.A
....4	T0087	1203-002835	IC-POSIFIXED REG.;KIA7805AF,DPAK,3P,6.6	1	S.A
....4	T0087	1203-002842	IC-POSIFIXED REG.;AP1117D-33A,TO-252,3P	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	T0087	1203-003121	IC-POSIFIXED REG.;FAN1112,SOT-223,3P,6.	1	S.A
....4	IC062	1203-003183	IC-MULTI REG.;SI-3002KWM-TL,DPAK,5P,6.6X	1	S.A
....4	T0087	1203-003696	IC-POSIFIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003703	IC-POSIFIXED REG.;AP1117E-18A,SOT-223,3	1	S.A
....4	IC102	1203-004268	IC-DC/DC CONVERTER;SC4521SETRT,SOIC,8P,4	1	S.N.A
....4	IC600	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC601	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	IC202	1204-002648	IC-DECODER;215H4AALA11HG,BGA,444P,27x27m	1	S.A
....4	IC1002	1204-002708	IC-AUDIO PROCESSOR;MSP4450K-VK-E8-500,PM	1	S.A
....4	IC118	1204-002729	IC-VIDEO PROCESS;S4LF119X01,PBGA,208P,17	1	S.A
....4	IC1201	1205-003149	IC-RECEIVER;MST3388MK-LF-110,PQFP,128P,2	1	S.A
....4	R1244	2007-000042	R-CHIP;499ohm,1%,1/10W,TP,1608	1	S.A
....4	R286	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R295	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R296	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R297	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R298	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R299	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1236	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1319	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R602	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R500	2007-000060	R-CHIP;100Kohm,1%,1/10W,TP,1608	1	S.A
....4	R504	2007-000060	R-CHIP;100Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1117	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1238	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1240	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1243	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1245	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1250	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1251	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1321	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1322	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1323	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1333	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1334	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1336	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1338	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1340	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1342	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1358L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1366L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1368L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1371	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1372	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1373	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1374	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1375	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1376	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1377	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1378	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R200	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R201	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R210	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R224	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R230	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R231	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R256	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R262	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R266	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R269	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R278	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R281	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R287	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R303	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R319	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R322	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R329	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R349	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R600D	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R603D	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R665	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R667	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R677	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R680	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R681	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R684	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

[illegible]

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R652	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R654	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R656	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R657	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R658	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R659	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R660	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R662	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R663	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R664	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R666	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R668	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R683	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R790	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R791	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R801	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R819	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R820	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R830	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R831	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R930S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R931S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R941S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R967	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R604	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R803	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R805	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R816	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R817	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R834	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R835	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R943S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R944S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R507	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R1363L	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R738	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R739	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R772	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R773	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R1044	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1052	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1053	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R114	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1200	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1202	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1303L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1370L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R306	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R336	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R383	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R384	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R503	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R629	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R651	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R711	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R731	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R746	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R800	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R802	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R818	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R823	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R915	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R929S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R938S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R949S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R106	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1119	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1364L	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1054	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R1109	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1111	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1115	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1118	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1122	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R116L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1239	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1247	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1305	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1306L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1310	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1316	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1317	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1357L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1362L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1404	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R300	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R301	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R302	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R337	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R338	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R339	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R340	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R342	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R343	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R676	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R716	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R749	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R916S	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R102	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R103	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R107	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R108	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1104	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1203	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1210	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1248	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1249	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1361L	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R239	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R315	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R331	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R350	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R351	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R352	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R353	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R354	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R355	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R356	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R361	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R362	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R363	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R365	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R366	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R367	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R368	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R369	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R370	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R372	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R373	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R374	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R375	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R376	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R377	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R378	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R379	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R380	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R381	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R382	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R607	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R608	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R609	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R610	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R611	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R612	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R613	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R614	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R615	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R619	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R620	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R621	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R622	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R623	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R624	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R632	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R633	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R634	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R635	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R636	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R682	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R700	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R701	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R709	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R710	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R720	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R727	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R737	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R740	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R741	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R752	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R906S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R907S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R919S	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R109	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R764	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R765	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1047	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1050	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R508	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1038	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1039	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R117B	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R832	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R833	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R100	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1000	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1001	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1002	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1003	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1004	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1005	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1006	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1007	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1024	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1025	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1026	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1027	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1028	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1029	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1030	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1031	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1045	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1056	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R510	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1051	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	1	S.A
....4	R305	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	1	S.A
....4	R1204	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1207	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R1209	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1213	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1216	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1218	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1220	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1223	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1225	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R270	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R285	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R288	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R290	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R292	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R294	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R628	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1206	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1215	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1222	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R511	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1401	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1402	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1403	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1105	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1106	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1201	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R601	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1307L	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	S.A
....4	R509	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R512	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R1227	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1228	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1229	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1230	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1232	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1233	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1235	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R655	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R704	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R724	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R725	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R728	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R729	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R732	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R733	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R735	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R736	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R742	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R753	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R754	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R755	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R756	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R759	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R760	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R761	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R766	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R774	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R775	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R776	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R777	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R778	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R779	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R780	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R781	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R782	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R783	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R784	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R785	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R786	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R787	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R788	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R789	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R804	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R806	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R808	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R824	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R825	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R826	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R921S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R922S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R923S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R924S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R925S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R926S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R927S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R928S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R959	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R960	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R961	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R962	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R963	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R964	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R965	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R966	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R968	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R757	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R758	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R1300	2007-000669	R-CHIP;2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R104	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1120	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R247	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R250	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R227	2007-000779	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R1212	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R246	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R249	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R1100	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1101	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1102	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1103	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R606	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1107	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1108	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1112	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1113	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1114	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1121	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1125	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1205	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1208	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1211	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1214	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1217	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1219	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1221	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1224	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1226	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R807	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R809	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R810	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R811	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R821	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R822	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R827	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R828	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R829	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R933S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R934S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R945S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R206	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R208	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R232	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R713	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R714	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R726	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R730	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R105	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R505	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R506	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R272	2007-007797	R-CHIP;44.2ohm,1%,1/10W,TP,1608	1	S.A
....4	RA200	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA201	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA202	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA203	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA204	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA205	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA308	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA309	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA311	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA312	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA313	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA314	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA315	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA300	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA301	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA316	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA317	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA318	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA319	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA1201	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1202	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1203	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1204	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1205	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1206	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1200	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA302	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA303	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA304	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA305	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA306	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA307	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA310	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	R1320	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA900S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA901S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA902S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	C1032	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1045	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1064	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1065	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1052	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1063	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1112	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1113	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1116	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1126	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1129	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1130	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1133	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1145	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1260	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1261	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1262	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1263	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1267	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1268	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1272	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1273	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1274	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1275	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1276	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1277	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1278	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1281	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1282	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1302	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1304	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1306	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1308	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1319	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1320	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1321	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1331	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1333	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1335	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1401	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C200	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C201	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C206	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C209	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C210	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C217	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C218	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C219	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C220	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C221	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C227	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C229	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C231	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C234	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C236	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C237	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C238	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C240	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C241	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C242	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C243	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C244	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C245	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C246	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C247	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C248	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C249	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C250	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C252	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C253	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C302	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C303	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C304	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C305	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C307	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C309	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C310	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C311	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C312	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C313	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C401	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C402	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C403	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C404	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C405	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C406	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C407	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C408	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

[illegible]

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C482	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C483	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C484	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C485	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C486	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C512	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C528	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C534	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C605	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C701	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C703	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C711	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C715	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C716	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C808	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C809	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C810	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C811	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C826	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1121	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C1137	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C506	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C704	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C705	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C706	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C707	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C800	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C814	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C902S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C904S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C100	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C101	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C112	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C116	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C130	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1303	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1305	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1307	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1309	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1312	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1313	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1314	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1315	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1323	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1325	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1326	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1327	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1330	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1332	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1334	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1342L	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1103	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1105	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1108	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1109	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1115	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1122	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1123	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1125	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1127	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1135	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1136	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1138	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1142	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1212	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1230	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1242	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1316	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1317	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1318	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1328	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1329	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1340L	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C306	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C508	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C608	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C535	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A
....4	C1251	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C1252	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C527	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C533	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C606	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C607	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C300	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C301	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C1069	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C136	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C708	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C709	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C717	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C718	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C801	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C802	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C812	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C813	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C815	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C819	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C820	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C821	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C822	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C903S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C905	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C906S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C907S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C908S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C1200	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C525	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C531	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C805	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C806	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C807	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C816	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C817	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C818	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C1049	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C1051	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C536	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C1043	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C519	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C1210	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1211	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1213	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1217	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1218	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1220	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1223	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1228	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1232	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1235	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1236	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1239	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1240	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1241	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1247	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1248	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1249	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1250	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1404	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C211	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C1300	2203-001034	C-CER,CHIP;5.6nF,10%,50V,X7R,1608	1	S.A
....4	C128	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1310	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1035	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1039	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1047	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C526	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C529	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C530	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C532	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1038	2203-001155	C-CER,CHIP;0.068nF,5%,50V,NP0,TP,1608	1	S.A
....4	C1201	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C521	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C1031	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C1046	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C126	2203-002392	C-CER,CHIP;220nF,+80-20%,50V,Y5V,2012	1	S.A
....4	C1111	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1114	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1124	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1141	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1005	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C102	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1034	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C104	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C106	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1068	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C108	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C111	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C114	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C115	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1203	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1204	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1205	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1207	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1208	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1209	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1215	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1216	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1219	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C122	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1222	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1224	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1227	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1229	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1233	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1234	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1238	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1244	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1245	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1246	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1254	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1255	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1256	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1257	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1259	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C127	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1271	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C132	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1336L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C134	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1345L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C138	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1403	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C145	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C149	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C314	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C502	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C601	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C604	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C609	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C803	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C823	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C901S	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1117	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1118	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1119	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1139	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1338L	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1339L	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C251	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C400	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C488	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C600	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C124	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,1608	1	S.A
....4	C1106	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1107	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1110	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1128	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1134	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1140	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1146	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1147	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1148	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1149	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C500	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C504	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C509	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C520	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C523	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1007	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1009	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1011	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1012	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1016	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1017	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1018	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1020	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1023	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1025	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1027	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1028	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1057	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1061	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C118	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C503	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C1019	2203-006333	C-CER,CHIP;1000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1021	2203-006333	C-CER,CHIP;1000nF,20%,16V,X5R,TP,3216	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1036	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1040	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1048	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1050	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1202	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1206	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1214	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1226	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1237	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1243	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1253	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1258	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1264	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1265	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1269	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1279	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1280	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1283	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1301	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1346L	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C222	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C228	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C239	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C505	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C514	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C603	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C700	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C702	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C710	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C804	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C824	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C900S	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1030	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1053	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1062	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1100	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1131	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1132	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C825	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1029	2402-001006	C-AL,SMD;4.7uF,20%,25V,GP,TP,3.6x6.3x3.	1	S.A
....4	C1033	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1054	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1055	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1058	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C110	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C113	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1225	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1231	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1266	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1270	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C129	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C230	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C232	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C254	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C315	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C450	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C487	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C489	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C490	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C501	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C517	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C537	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C123	2402-001100	C-AL,SMD;0.1uF,20%,50V,GP,TP,4.3x4.3x5.2	1	S.A
....4	C1101	2402-001128	C-AL,SMD;100uF,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1042	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1311	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1322	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C140	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1402	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C141	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C144	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C524	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C1006	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1044	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C105	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C107	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C516	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1059	2402-001185	C-AL,SMD;2.2UF,20%,50V,WT,TP,4.3X4.3X6MM	1	S.A
....4	C146	2402-001260	C-AL,SMD;100uF,20%,10V,WT,REEL,6.3X5.7	1	S.A
....4	C103	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C109	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C117	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C119	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C121	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C133	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C1104	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C1120	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C125	2409-001029	C-ORGANIC,SMD;120uF,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C131	2409-001029	C-ORGANIC,SMD;120uF,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C1341L	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	T0052	2703-000222	INDUCTOR-SMD;560nH,10%,2012	1	S.A
....4	T0052	2703-000222	INDUCTOR-SMD;560nH,10%,2012	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000417	INDUCTOR-SMD;220uH,5%,3225	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001426	INDUCTOR-SMD;680uH,20%,7070	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-002275	INDUCTOR-SMD;470nH,5%,2012	1	S.A
....4	T0052	2703-002275	INDUCTOR-SMD;470nH,5%,2012	1	S.A
....4	L1101	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	L1104	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	X600	2801-003326	CRYSTAL-SMD;24MHZ,30PPM,28-ABX,20PF,50OH	1	S.A
....4	X1200	2801-003667	CRYSTAL-SMD;14.31818MHz,30ppm,28-AAN,16p	1	S.A
....4	X300	2801-004224	CRYSTAL-SMD;25.14MHz,0ppm,20pF,50ohm,TP	1	S.A
....4	X1000	2801-004300	CRYSTAL-SMD;18.432MHz,30ppm,28-ABX,13pF,	1	S.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A

6 Electrical Parts List

[illegible]

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	4	S.N.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	1	S.N.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	13	S.N.A
.2	M0081	6003-001439	SCREW-TAPTITE;BH,+,-,S,M4,L8,ZPC(WHT),SW	1	S.N.A
.2	M2893	BH39-00362G	LEAD CONNECTOR;SONOMA,UL1007#26,5PIN,100	1	S.A
.2	M2893	BN39-00802A	LEAD CONNECTOR;LE32R86BDX,UL1007#26,UL/C	1	S.A
.2	M2893	BN39-00849A	LEAD CONNECTOR;LE37M86BDX/XEC,UL1007 #26	1	S.A
.2	M2893	BN39-00894A	LEAD CONNECTOR-LVDS;LE37S86BDX,UL1571#30	1	S.A
.2	T0764	BN44-00157A	SMPS-LCDTV;MK37,SEM,AC/DC,280W,AC100 ~ 2	1	S.A
.2	M0146	BN61-02241A	BRACKET-PANEL SIDE;Bordeaux 37,SECC,T1.2	1	S.N.A
.2	M0146	BN61-02242A	BRACKET-PANEL SIDE;Bordeaux 37,SECC,T1.2	1	S.N.A
.2	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	2	S.N.A
.2	M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A
.2		BN61-02952J	HOLDER-SIDE AV;32R81,UO,CLUB,PC+ABS,V0,-	1	S.N.A
.2	T0447	BN96-04680E	ASSY BRACKET P-PANEL;37S86,EO	1	S.N.A
...3	M0081	6003-000115	SCREW-TAPTITE;BH,+,-,B,M3,L6,ZPC(BLK),SWRC	2	S.A
...3	M0131	AA63-01438A	GASKET;Bordeaux,Conductive Fabric,7mm,8m	1	S.N.A
...3	T0101	BN61-02968A	BRACKET-WALL;40 BORDEAUX PLUS,SECC,T1.2,	1	S.N.A
...3	M0146	BN61-02971A	BRACKET-PANEL TOP;37 BORDEAUX PLUS,SECC,	1	S.N.A
...3		BN61-02977A	BRACKET-PANEL BOTTOM;37 BORDEAUX PLUS,SE	1	S.N.A
...3		BN61-02980A	BRACKET-GUIDE MAIN;37 BORDEAUX PLUS,SECC	1	S.N.A
...3		BN61-03033A	BRACKET-GUIDE POWER;37 BORDEAUX PLUS,SEC	1	S.N.A
...3		BN61-03034A	BRACKET-GUIDE POWER;37 BORDEAUX PLUS,SEC	1	S.N.A
...3	M0131	BN63-03503A	GASKET;JASMINE,Conductive Fabric,25,8,24	1	S.N.A
...3	M0131	BN63-03504A	GASKET;JASMINE,Conductive Fabric,25,8,28	1	S.N.A
.2	T0275	BN96-05361A	ASSY MISC P-INLET;LE37M87BDX/XEC,200/150	1	S.N.A
0.1	M0019	BN92-02640L	ASSY LABEL;LNT375HAX/XAA	1	S.N.A
0.1	M0113	BN92-02751A	ASSY P/MATERIAL;37R81,CLUB	1	S.N.A
.2	T0376	6902-000001	BAG AIR;LDPE,T0.2,L1800,W1000,TRP,,,LDPE	0.01	S.N.A
.2	T0376	6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	0.03	S.N.A
.2	T0524	6902-000524	BAG PE;HDPE/NITRON,T0.015/T0.5,W1200,L11	1	S.N.A
.2	T0214	AA61-20285A	HOLDER-BOX;CTV,PP,NTR,HB	2	S.N.A
.2	T0172	AA69-02609A	BAND-PP;-,-,PP,-,-,W18,-,-,CLEA,1G,-,-	4.74	S.N.A
0.1	M0003	BN92-02754A	ASSY BOX;37R83,UO,CLUB,-,-,-	1	S.N.A
.2	M0521	BN69-01731A	BOX-SET,IN;37M8,CB,C-01,DY-01,AB,W1401,D	1.02	S.N.A
.2		BN69-01957A	BOX-SET,OUT;37R83,CB,C3,DY-01,W1010,D370	1.02	S.N.A
0.1	M0045	BN92-02624D	ASSY ACCESSORY;LNT375HAX/XAA	1	S.N.A
.2	M0045	BN96-05376D	ASSY ACCESSORY;LNT375HAX/XAA	1	S.A
...3	T0268	3903-000144	CBF-POWER CORD;DT,US,BP3/Y,U(IEC C13-RA)	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	T0074	BN59-00598A	REMOCON;JASMINE,TM87C,SAMSUNG28P+EEPROM,	1	S.A
...3	ACCESSORY	BN63-01798A	CLOTH-CLEAN;RE40**,CLOTH,180,200,RHCM	1	S.N.A
...3	T0531	BN63-03113B	COVER-BOTTOM;40R81,HIPS,V0,BK500,NON-DEC	1	S.A
.2	M0045	BN96-05377A	ASSY ACCESSORY;LNT325HX/XAA	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	ACCESSORY	AA68-00371C	MARK RECYCLE-CARD WARRANTY,06;SEA,W/P10	1	S.N.A
...3	ACCESSORY	AA68-03242F	MANUAL FLYER-02;SAFETY GUIDE;All Model,S	1	S.N.A
...3	T0238	AA68-03870B	MANUAL FLYER-REGISTRATION CARD;comm,Sams	1	S.N.A
...3	T0511	BN68-00998P	MANUAL USERS;COMM,SAMSUNG,Eng/Spa,N.Amer	1	S.N.A
...3	ACCESSORY	BN68-01002F	MANUAL FLYER-QSG;COMM,SAMSUNG,English,N.	1	S.N.A

6 Electrical Parts List

6-3 LNT405HAX Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
0		LNT405HAX/XAA	LN-T405HA,N36A/40R83-GBR,40,LCD-TV,UNITE	0	
0.1	M0216	BN90-01148A	ASSY STAND;37,40R81,SWIVEL,-,-,-	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	4	S.A
..2	M0027	BN96-04661A	ASSY STAND P-BASE;37,40R81,SWIVEL,-,ABS+	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	4	S.A
...3	M0081	6003-001239	SCREW-TAPTITE;FH,+,B,M4,L10,ZPC(WHT),S	8	S.A
...3		BN61-02248A	HOLDER-SWIVEL RING;40R71,ACETAL NATUAL,T	1	S.N.A
...3		BN61-02883A	BRACKET-STAND BOTTOM;BORDEAUX PLUS,40,SE	1	S.N.A
...3		BN61-02885A	HOLDER-SWIVEL RING;MURANO40,ACETAL NATUR	1	S.N.A
...3		BN61-02886A	BRACKET-HINGE SWIVEL;BORDEAUX PLUS,40,SE	1	S.N.A
...3	T0920	BN61-02984A	GUIDE-STAND;40R81,ABS,V0,-,-,-,BK500,-	1	S.N.A
....4		BN61-02981A	BRACKET-SUPPORT STAND;40 BORDEAUX PLUS,S	1	S.N.A
....4		BN61-03045A	BRACKET-SUPPORT STAND;40 BORDEAUX PLUS,S	1	S.N.A
...3	CCM1	BN63-02183E	COVER-SHEET;Rhcm,PE Vinyl,T0.05,750mm,20	0.5	S.N.A
...3	T0004	BN63-03030A	COVER-STAND BASE;40R81,ABS+PMMA,-,-,-,HB	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,SILICON,DIA 17 * T1.	4	S.N.A
0.1	M0002	BN90-01151T	ASSY COVER REAR;40R81,UO(CLUB),PC+ABS,V0	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	2	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	1	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,M4,L16,ZPC(BLK)	12	S.A
..2	M0013	BN96-04664J	ASSY COVER P-REAR;40R81,UO(CLUB),PC+ABS,	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	T0101	BN61-03348A	BRACKET-WALL;LCD TV 32",SECC T1.6	2	S.N.A
...3	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	0.99	S.N.A
...3	M0006	BN63-03119A	COVER-REAR;40R81,UO,PC+ABS,-,-,-,V0,-,BK	1	S.N.A
...3	T0071	BN64-00554A	INLAY-TERMINAL;07,COMMON,UO,PS SHEET,T0.	1	S.N.A
...3	T0064	BN65-00002A	CLAMPER CORE;BORDEAUX,PP,V0,BLK	1	S.N.A
...3	T0069	AA60-00091F	SPACER-FELT;-FELT,150X10,-,-,BLK,T0.5,-	2	S.N.A
...3	T0069	AA60-00091X	SPACER-FELT;70X4H1,950,0.35,10	1	S.N.A
...3	T0067	BP60-00099A	SPACER-SCREEN;Club-Bordeaux,EVA SPONGE,L	2	S.N.A
0.1	M0001	BN90-01315A	ASSY COVER FRONT;40R83,UO(CLUB)-,PC+ABS	1	S.N.A
..2	T0175	BN96-04768A	ASSY SPEAKER P;8ohm,4pin,10W,Bordeaux Pl	1	S.A
..2	T0003	BN96-05624A	ASSY COVER P-FRONT;40R83,UO(CLUB)-,PC+A	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	2	S.N.A
...3	T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A
...3	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	1.983	S.N.A
...3	M0112	BN63-03651A	COVER-FRONT;40R83,UO,CLUB,PC+ABS,-,-,-,V	1	S.N.A
...3	T0059	BN64-00366A	INDICATOR LED;ROME-I,PC,CLEAR,ALL MODEL	1	S.N.A
...3	T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,V	1	S.N.A
...3	T0054	BN64-00640A	KNOB-DECORATION;37 BORDEAUX PLUS,ABS,-,-	1	S.N.A
...3	T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A
...3	M0146	BN96-04884C	ASSY BOARD P-POWER & IR;LNT4042HX/XAA,CT	1	S.A
...3		BN96-05668A	ASSY HOLDER P-BOSS;40R81,CLUB,PC+ABS,V0,	1	S.N.A
....4		BN61-03323A	HOLDER-BOSS BOTTOM;40 BORDEAUX PLUS,ABS+	1	S.N.A
....4		BN61-03261A	BOSS-TAPE;Tulip,ACRYL,T1.1,W12mm,GRAY,TA	1.6	S.N.A
....4	CCM1	BN63-02183G	COVER-SHEET;Rhcm,PE Vinyl,T0.05,1100mm,2	0.3	S.N.A
...3	T0069	AA60-00091X	SPACER-FELT;70X4H1,950,0.35,10	2	S.N.A
...3	T0069	AA60-00171V	SPACER-FELT;BE46PS,FELT,500,T0.35,10	2	S.N.A
...3	M0279	BN63-00867A	FELT;AS17UO,FELT,0.5,10,68	1	S.N.A
...3	M0145	BN96-05677B	ASSY BOARD P-FUNCTION;LNT375HAX,CT5000-5	1	S.N.A
0.1		BN91-01180N	ASSY LCD-AUO;LNS4041DX/*	1	S.N.A
..2	M0215	BN07-00370A	LCD-PANEL;T400XW02,8bit,40inch,16.7M,16:	1	S.A
0.1	M0017	BN91-01550B	ASSY CHASSIS;LNT405HX/XAA	1	S.N.A
..2	M0014	BN94-01293C	ASSY PCB MAIN-AUO;LNT405HX/XAA	1	S.A
...3	T0245	0202-001492	SOLDER-WIRE FLUX;HSE-02 LFM48 SR-34 S,-	0.25	S.N.A
...3	JA900S	3701-001388	CONNECTOR-HDMI;20P,Phosphor Bronze,ANGLE	1	S.A
...3	JA700	3701-001400	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,Ni	1	S.A
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A
...3	CN330	3711-000058	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5MM,AN	1	S.A
...3	CN330	3711-004484	HEADER-BOARD TO CABLE;BOX,5P,1R,2mm,STRA	1	S.A
...3	CN330	3711-004531	HEADER-BOARD TO CABLE;BOX,10P,1R,2mm,ANG	1	S.A
...3	CN330	3711-005606	HEADER-BOARD TO CABLE;BOX,30P,2R,2mm,STR	1	S.A
...3	CN330	3711-005842	HEADER-BOARD TO CABLE;BOX,24P,2R,2MM,STR	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
...3	JA330	3722-000143	JACK-PHONE;1P(VER),AG,BLK,ANGLE	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA332	3722-001163	JACK-VHS;4P,AU,BLK,ANGLE	1	S.A
...3	JA332	3722-001734	JACK-VHS;4P,SN,BLK,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002363	JACK-PIN;3P,Sn,YEL/WHT/RED,STRAIGHT	1	S.A
...3	CN700	3722-002516	JACK-USB;4P/1C,AU30U,BLK,STRAIGHT,A TYPE	1	S.A
...3	JA333	3722-002543	JACK-PIN;3P,Sn,RED/WHT/YEL,ANGLE	1	S.A
...3	CIS3	BN40-00097A	TUNER;DTV S227CH281A,DTV S227CH281A,ATSC/N	1	S.A
...3	T0603	BN63-03210A	SHIELD-PCB MAIN;BORDEAUX PLUS,SPT6,T0.3,	1	S.N.A
...3	CCMM1	BN73-00024D	SILICON/RUBBER;BORDEAUX,SILICON,28x28XT6	1	S.N.A
...3	T0174	BN97-01586C	ASSY SMD;LNT405HX/XAA	1	S.N.A
...4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-D20-45\$,96.5Sn/	3.861	S.N.A
...4	D728	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D729	0401-000132	DIODE-SWITCHING;BAV99,70V,50mA,SOT-23,TP	1	S.A
...4	D100	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1000	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D101	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1102	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1103	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1400	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D300	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
...4	D1401	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1402	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1403	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1405	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1406	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D500	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D700	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D701	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D702	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D703	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D704	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D711	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D712	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D713	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D714	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D715	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D716	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D717	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D718	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D724	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D725	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D730	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D731	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D732	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D733	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D734	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D735	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D736	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D737	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D902S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D903S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D905S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D906S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D907S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D908S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D909S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D910S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D911S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D912S	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
...4	D1101	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
...4	D1104	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D1105	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D1106	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D1107	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D602D	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D603	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D746	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D747	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D930	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D102	0402-001098	DIODE-RECTIFIER;SK34,40V,3A,SMC,TP	1	S.A
....4	D609	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D719	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D739	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D913S	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D705	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D726	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D744	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D745	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D900S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D901S	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D706	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D707	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D708	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D709	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D710	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D720	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D721	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D722	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D723	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D727	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D740	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D741	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D742	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D743	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D800	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D801	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D802	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D803	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D804	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D805	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D806	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D807	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D808	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D809	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D810	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D811	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D812	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D813	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D816	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D817	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D818	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D819	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D820	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D821	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D824	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D825	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D826	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D827	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D828	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D829	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D830	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D831	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D832	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D833	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D834	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D835	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D836	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D837	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D904S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D914S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D915S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D916S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D917S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D918S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D919S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D920S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D921S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D922S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D923S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D924S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D925S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D928S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D929S	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D501	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A
....4	D814	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D815	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D1100	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D604	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D605	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D608	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	Q1000	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1102	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q1106	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150MW,SOT-23	1	S.A
....4	Q100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q101	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1100	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1103	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1104	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1105	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1300L	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q1400	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q500	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q602	0501-000342	TR-SMALL SIGNAL;KSC1623-Y,NPN,200mW,SOT-	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000275	FET-SILICON;SI4435DY,P,-30V,+8.0A,0.014	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC104	0801-002270	IC-CMOS LOGIC;74LCX16373,LATCH,TSSOP,48P	1	S.A
....4	IC306	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC307	0904-001838	IC-BUS SWITCH;PCA9546APW,TSSOP,16P,5.1x4	1	S.A
....4	IC1001	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	S.A
....4	IC603	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	S.A
....4	IC801	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC	1	S.A
....4	IC106	1001-001440	IC-VIDEO SWITCH;Sil9185CTU,QFP,80P,3.3V,	1	S.A
....4	IC800	1006-001266	IC-LINE TRANSCEIVER;SP3232EEY,TSSOP,16P,	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-001385	IC-EEPROM;24C256,256Kbit,32Kx8,SOP,8P,5x	1	S.A
....4	IC113	1105-001780	IC-DRAM;HYB18T512161BF,DDR2,512Mbit,32Mx	1	S.A
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	S.A
....4	T0085	1201-002136	IC-AUDIO AMP;LM4810,MSOP,8P,3x3mm,DUAL,-	1	S.A
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A
....4	T0087	1203-001815	IC-POSIFIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-002074	IC-POSIFIXED REG.;MIC39150,TO-263,3P,-,	1	S.A
....4	T0087	1203-002835	IC-POSIFIXED REG.;KIA7805AF,DPAK,3P,6.6	1	S.A
....4	T0087	1203-002842	IC-POSIFIXED REG.;AP1117D-33A,TO-252,3P	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	T0087	1203-003121	IC-POSIFIXED REG.;FAN1112,SOT-223,3P,6	1	S.A
....4	IC062	1203-003183	IC-MULTI REG.;SI-3002KWM-TL,DPAK,5P,6.6X	1	S.A
....4	T0087	1203-003696	IC-POSIFIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003703	IC-POSIFIXED REG.;AP1117E-18A,SOT-223,3	1	S.A
....4	IC102	1203-004268	IC-DC/DC CONVERTER;SC4521SETRT,SOIC,8P,4	1	S.N.A
....4	IC600	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	IC601	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC202	1204-002648	IC-DECODER;215H4AALA11HG,BGA,444P,27x27m	1	S.A
....4	IC1002	1204-002708	IC-AUDIO PROCESSOR;MSP4450K-VK-E8-500,PM	1	S.A
....4	IC118	1204-002729	IC-VIDEO PROCESS;S4LF119X01,PBGA,208P,17	1	S.A
....4	IC1201	1205-003149	IC-RECEIVER;MST3388MK-LF-110,PQFP,128P,2	1	S.A
....4	R1244	2007-000042	R-CHIP;499ohm,1%,1/10W,TP,1608	1	S.A
....4	R286	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R295	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R296	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R297	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R298	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R299	2007-000043	R-CHIP;1Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1236	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1319	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R602	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608	1	S.A
....4	R500	2007-000060	R-CHIP;100Kohm,1%,1/10W,TP,1608	1	S.A
....4	R504	2007-000060	R-CHIP;100Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1117	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1238	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1240	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1243	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1245	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1250	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1251	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1321	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1322	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1323	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1325	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1327	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1328	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1329	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1330	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1332	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1333	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1334	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1335	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1336	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1337	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1338	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1339	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1340	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1341	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1342	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1343	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1344	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1345	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1346	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1358L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1366L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1368L	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1371	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1372	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1373	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1374	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1375	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1376	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1377	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R1378	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R200	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R201	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R210	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R224	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R230	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R231	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R256	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R262	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R266	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R269	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R278	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R261	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R263	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R264	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R265	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R267	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R268	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R271	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R717	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R718	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R721	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R734	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R750	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R751	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	SA
....4	R707	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R708	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R719	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R722	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R744	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R745	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R912S	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R913S	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R952S	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R954S	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	SA
....4	R1036	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1037	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1041	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1042	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1043	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1048	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1055	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1057	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1060	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1061	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1116	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1123	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1124	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1231	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R1369L	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R312	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R314	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R316	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R317	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R318	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R320	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R321	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R323	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R324	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R325	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R326	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R328	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R332	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R333	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R334	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA
....4	R335	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	SA

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R637	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R638	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R639	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R640	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R641	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R642	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R643	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R644	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R645	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R646	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R647	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R648	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R649	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R650	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R652	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R654	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R656	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R657	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R658	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R659	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R660	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R662	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R663	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R664	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R666	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R668	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R683	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R790	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R791	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R801	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R819	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R820	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R830	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R831	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R930S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R931S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R941S	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R967	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R803	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R805	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R816	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R817	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R834	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R835	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R943S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R944S	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	1	S.A
....4	R507	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R1363L	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R738	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R739	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R772	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R773	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R1044	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1052	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1053	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R114	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1200	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1202	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1303L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1370L	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R306	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R336	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R383	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R384	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R503	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R629	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R651	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R711	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R731	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R746	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R800	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R802	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R818	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R823	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R915	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R929S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R938S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R949S	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	SA
....4	R106	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1380G	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1119	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	SA
....4	R1364L	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	SA
....4	R1054	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1109	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1111	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1115	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1118	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1122	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R116L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1239	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1247	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1305	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1306L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1310	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1316	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1317	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1357L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1362L	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R1404	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R300	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R301	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R302	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R337	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R338	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R339	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R340	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R342	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R343	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R676	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R716	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R749	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R916S	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	SA
....4	R101G	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R102	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R103	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R107	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R108	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1104	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1203	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1210	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1248	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1249	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R1361L	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R239	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R315	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R331	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R350	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R351	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R352	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R353	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R354	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R355	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R356	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R361	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R362	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R363	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R365	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA
....4	R366	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R1024	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1025	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1026	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1027	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1028	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1029	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1030	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1031	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1045	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1056	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R510	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1051	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	1	S.A
....4	R305	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	1	S.A
....4	R1204	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1207	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1209	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1213	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1216	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1218	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1220	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1223	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1225	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R270	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R285	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R288	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R290	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R292	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R294	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R628	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R1206	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1215	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1222	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R511	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	1	S.A
....4	R1401	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1402	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1403	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1105	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1106	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1201	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R601	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R1307L	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	S.A
....4	R509	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R512	2007-000287	R-CHIP;100OHM,1%,1/10W,TP,1608	1	S.A
....4	R1227	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1228	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1229	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1230	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1232	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1233	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R1235	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R655	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R704	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R724	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R725	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R728	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R729	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R732	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R733	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R735	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R736	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R742	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R753	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R754	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R755	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R756	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R759	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R760	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R761	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R766	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R774	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R775	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R776	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R777	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R778	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R779	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R780	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R781	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R782	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R783	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R784	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R785	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R786	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R787	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R788	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R789	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R804	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R806	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R808	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R824	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R825	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R826	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R921S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R922S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R923S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R924S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R925S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R926S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R927S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R928S	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R959	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R960	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R961	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R962	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R963	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R964	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R965	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R966	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R968	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R757	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R758	2007-000659	R-CHIP;27OHM,5%,1/10W,TP,1608	1	S.A
....4	R1300	2007-000669	R-CHIP;2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R104	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1120	2007-000683	R-CHIP;3.3Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R247	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R250	2007-000763	R-CHIP;330ohm,1%,1/10W,TP,1608	1	S.A
....4	R227	2007-000779	R-CHIP;33ohm,1%,1/10W,TP,1608	1	S.A
....4	R1212	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R246	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R249	2007-000821	R-CHIP;390ohm,1%,1/10W,TP,1608	1	S.A
....4	R1100	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1101	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1102	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1103	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	S.A
....4	R1107	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1108	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1112	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1113	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1114	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1121	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1125	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R1205	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1208	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1211	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1214	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1217	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1219	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R1221	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1224	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R1226	2007-001134	R-CHIP;68ohm,5%,1/10W,TP,1608	1	S.A
....4	R807	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R809	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R810	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R811	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R821	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R822	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R827	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R828	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R829	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R933S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R934S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R945S	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	1	S.A
....4	R206	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R208	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R232	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R712	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R713	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R714	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R726	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R730	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R105	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R505	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R506	2007-002906	R-CHIP;200Kohm,1%,1/10W,TP,1608	1	S.A
....4	R272	2007-007797	R-CHIP;44.2ohm,1%,1/10W,TP,1608	1	S.A
....4	RA200	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA201	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA202	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA203	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA204	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA205	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA308	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA309	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA311	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA312	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA313	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA314	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA315	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA300	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA301	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA316	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA317	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA318	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA319	2011-000515	R-NET;4.7Kohm,5%,1/16W,L,CHIP,8P,TP,3.2x	1	S.A
....4	RA1201	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1202	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1203	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1204	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1205	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1206	2011-000585	R-NET;47ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1200	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA302	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA303	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA304	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA305	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA306	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA307	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA310	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	R1320	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA900S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA901S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA902S	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	C1032	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1045	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1064	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1065	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C1052	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1063	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1112	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1113	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1116	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1126	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1129	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1130	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1133	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1145	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1260	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1261	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1262	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1263	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1267	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1268	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1272	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1273	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1274	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1275	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1276	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1277	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1278	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1281	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1282	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1302	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1304	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1306	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1308	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1319	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1320	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1321	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1331	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1333	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1335	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1401	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C200	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C201	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C206	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C209	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C210	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C217	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C218	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C219	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C220	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C221	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C227	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C229	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C231	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C234	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C236	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C237	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C238	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C240	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C241	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C242	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C243	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C244	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C245	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C246	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C247	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C248	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C249	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C250	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C252	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C253	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C302	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C303	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C304	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C305	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

6 Electrical Parts List

[illegible]

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C465	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C466	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C467	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C468	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C469	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C470	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C472	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C473	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C474	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C477	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C478	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C479	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C480	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C481	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C482	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C483	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C484	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C485	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C486	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C512	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C528	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C534	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C605	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C701	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C703	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C711	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C715	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C716	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C808	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C809	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C810	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C811	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C826	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C1121	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C1137	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C506	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C704	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C705	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C706	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C707	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C800	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C814	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C902S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C904S	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C100	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C101	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C112	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C116	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C130	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1303	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1305	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1307	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1309	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1312	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1313	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1314	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1315	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1323	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1324	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1325	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1326	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1327	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1330	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1332	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1334	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1342L	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1343L	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C139D	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1400	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1405	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C1408	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C308	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C507	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C510	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C511	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C513	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C515	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C518	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C522	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C602	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C135	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C1066	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1067	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1102	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1103	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1105	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1108	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1109	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1115	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1122	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1123	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1125	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1127	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1135	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1136	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1138	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1142	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1212	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1230	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1242	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1316	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1317	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1318	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1328	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1329	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C1340L	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C306	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C508	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C608	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C535	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A
....4	C1251	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C1252	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C527	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C533	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C606	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C607	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C300	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C301	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C1069	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C136	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C708	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C709	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C717	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C718	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C801	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C802	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C812	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C813	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C815	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C819	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C820	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C821	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C822	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C903S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C905	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C906S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C907S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C908S	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1200	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C525	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C531	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C805	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C806	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C807	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C816	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C817	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C818	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C1049	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C1051	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C536	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C1043	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C519	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C1210	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1211	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1213	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1217	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1218	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1220	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1223	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1228	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1232	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1235	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1236	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1239	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1240	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1241	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1247	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1248	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1249	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1250	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	1	S.A
....4	C1404	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C211	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C1300	2203-001034	C-CER,CHIP;5.6nF,10%,50V,X7R,1608	1	S.A
....4	C128	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1310	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C1035	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1039	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1047	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C526	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C529	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C530	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C532	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C1038	2203-001155	C-CER,CHIP;0.068nF,5%,50V,NP0,TP,1608	1	S.A
....4	C1201	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C521	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C1031	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C1046	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C126	2203-002392	C-CER,CHIP;220nF,+80-20%,50V,Y5V,2012	1	S.A
....4	C1111	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1114	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1124	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1141	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C1005	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C102	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1034	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C104	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C106	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1068	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C108	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C111	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C114	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C115	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1203	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1204	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1205	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1207	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1208	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1209	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1215	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1216	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1219	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C122	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1221	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1222	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1224	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1227	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1229	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1233	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1234	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1238	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1244	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1245	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1246	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1254	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1255	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1256	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1257	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1259	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C127	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1271	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C132	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1336L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C134	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1345L	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C138	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1403	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C143D	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C145	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C148D	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C149	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C314	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C502	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C601	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C604	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C609	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C803	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C823	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C901S	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C1117	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1118	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1119	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1139	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1338L	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C1339L	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C251	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C400	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C488	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C600	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C124	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,1608	1	S.A
....4	C1106	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1107	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1110	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1128	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1134	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1140	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1146	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1147	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1148	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1149	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C500	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C504	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C509	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C520	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C523	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C1007	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C1009	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1011	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1012	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1016	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1017	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1018	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1020	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1023	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1025	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1027	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1028	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1057	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C1061	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C118	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C503	2203-006104	C-CER,CHIP;1000nF,10%,50V,X7R,3225	1	S.A
....4	C1019	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1021	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1036	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1040	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1048	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1050	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1202	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1206	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1214	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1226	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1237	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1243	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1253	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1258	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1264	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1265	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1269	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1279	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1280	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1283	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1301	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1346L	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C222	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C228	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C239	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C505	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C514	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C603	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C700	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C702	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C710	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C804	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C824	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C900S	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1030	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1053	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1062	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1100	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1131	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1132	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C825	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.2m	1	S.A
....4	C1029	2402-001006	C-AL,SMD;4.7uF,20%,25V,GP,TP,3.6x6.3x3.	1	S.A
....4	C1033	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1054	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1055	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1058	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C110	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C113	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1225	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1231	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1266	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1270	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C129	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C147D	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A

6 Electrical Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C230	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C232	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C254	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C315	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C450	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C487	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C489	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C490	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C501	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C517	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C537	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C123	2402-001100	C-AL,SMD;0.1uF,20%,50V,GP,TP,4.3x4.3x5.2	1	S.A
....4	C1101	2402-001128	C-AL,SMD;100uF,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1042	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1311	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1322	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C140	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1402	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C141	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C144	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C524	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C1006	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1044	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C105	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C107	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C516	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1059	2402-001185	C-AL,SMD;2.2UF,20%,50V,WT,TP,4.3X4.3X6MM	1	S.A
....4	C146	2402-001260	C-AL,SMD;100uF,20%,10V,WT,REEL,6.3X5.7	1	S.A
....4	C103	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C109	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C117	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C119	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C121	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C133	2402-001268	C-AL,SMD;100uF,+20%,25V,WT,REEL,8x6.3	1	S.A
....4	C1104	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C1120	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C125	2409-001029	C-ORGANIC,SMD;120uF,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C131	2409-001029	C-ORGANIC,SMD;120uF,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C1341L	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	T0052	2703-000222	INDUCTOR-SMD;560nH,10%,2012	1	S.A
....4	T0052	2703-000222	INDUCTOR-SMD;560nH,10%,2012	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000417	INDUCTOR-SMD;220uH,5%,3225	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001079	INDUCTOR-SMD;220nH,5%,2012	1	S.A
....4	T0052	2703-001426	INDUCTOR-SMD;680uH,20%,7070	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	T0052	2703-002275	INDUCTOR-SMD;470nH,5%,2012	1	S.A
....4	T0052	2703-002275	INDUCTOR-SMD;470nH,5%,2012	1	S.A
....4	L1101	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	L1104	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	X600	2801-003326	CRYSTAL-SMD;24MHZ,30PPM,28-ABX,20PF,50OH	1	S.A
....4	X1200	2801-003667	CRYSTAL-SMD;14.31818MHz,30ppm,28-AAN,16p	1	S.A
....4	X300	2801-004224	CRYSTAL-SMD;25.14MHz,0ppm,20pF,50ohm,TP	1	S.A
....4	X1000	2801-004300	CRYSTAL-SMD;18.432MHz,30ppm,28-ABX,13pF,	1	S.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001148	BEAD-SMD;60ohm,1608,TP,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0313	3404-001207	SWITCH-TACT;12V,50mA,160gf,6.2X6.2,SPST	1	S.A
....4	JA701	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A

6 Electrical Parts List


Level	Loc. No.	Code No.	Description & Specification	Q'ty	S.A/S.N.A
....4	T0087	1203-002699	IC-POSIFIXED REG.;78D05,DPAK,3P,6.6X6.1	1	S.A
0.1		BN91-01648B	ASSY SHIELD-AME;LNT405HAX/XAA	1	S.N.A
.2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	1	S.A
.2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.A
.2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.A
.2	M0081	6003-000337	SCREW-TAPTITE;BH,+,S,M4,L10,ZPC(BLK),SWR	5	S.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	4	S.N.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	1	S.N.A
.2	M0081	6003-001188	SCREW-TAPTITE;BH,+,B,M4,L10,ZPC(WHT),S	13	S.N.A
.2	M0081	6003-001439	SCREW-TAPTITE;BH,+,S,M4,L8,ZPC(WHT),SW	1	S.N.A
.2	M2893	BH39-00362G	LEAD CONNECTOR;SONOMA,UL1007#26,5PIN,100	1	S.A
.2	M2893	BN39-00716F	LEAD CONNECTOR;LNS4696DX,UL3239#24,UL/CS	1	S.A
.2	M2893	BN39-00717A	LEAD CONNECTOR;LE32R71BX/XEC,UL3443#28,5	1	S.A
.2	M2893	BN39-00802E	LEAD CONNECTOR;LE40S81BX,UL1007#26,24PIN	1	S.A
.2	M2893	BN39-00889A	LEAD CONNECTOR;LE40R86BDX,UL1571#30,30P,	1	S.A
.2	M0174	BN44-00134D	IP BOARD;PSIV230601A,40" Neo Mosel,44mA,	1	S.A
.2	M0146	BN61-02256B	BRACKET-PANEL SIDE;Bordeaux 40,SECC,T1.2	1	S.N.A
.2	M0146	BN61-02257B	BRACKET-PANEL SIDE;Bordeaux 40,SECC,T1.2	1	S.N.A
.2	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	2	S.N.A
.2	M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A
.2		BN61-02952J	HOLDER-SIDE AV;32R81,UO,CLUB,PC+ABS,V0,-	1	S.N.A
.2	T0447	BN96-04679C	ASSY BRACKET P-PANEL;40S81,JASMINE	1	S.N.A
...3	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	1	S.A
...3	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	2	S.A
...3	M0131	AA63-01437A	GASKET;Bordeaux,Conductive Fabric,20mm,9	1	S.N.A
...3		BN61-02963A	BRACKET-GUIDE POWER;40 BORDEAUX PLUS,SEC	1	S.N.A
...3	T0101	BN61-02968A	BRACKET-WALL;40 BORDEAUX PLUS,SECC,T1.2,	1	S.N.A
...3	M0146	BN61-02972A	BRACKET-PANEL TOP;40 BORDEAUX PLUS,SECC,	1	S.N.A
...3		BN61-02975A	BRACKET-GUIDE POWER;40 BORDEAUX PLUS,SEC	1	S.N.A
...3		BN61-02979A	BRACKET-PANEL BOTTOM;40 BORDEAUX PLUS,SE	1	S.N.A
...3		BN61-02982A	BRACKET-GUIDE MAIN;40 BORDEAUX PLUS,SECC	1	S.N.A
...3	M0107	BN61-03036A	BRACKET-PCB;40 BORDEAUX PLUS,SECC,T1.2,S	1	S.N.A
...3	M0131	BN63-02958A	GASKET;LE32M71BX,Conductive Fabric,10mm,	1	S.N.A
.2	T0275	BN96-05361A	ASSY MISC P-INLET;LE37M87BDX/XEC,200/150	1	S.N.A
0.1	M0045	BN92-02624D	ASSY ACCESSORY;LNT375HAX/XAA	1	S.N.A
.2	M0045	BN96-05376D	ASSY ACCESSORY;LNT375HAX/XAA	1	S.A
...3	T0268	3903-000144	CBF-POWER CORD;DT,US,BP3/Y,U(IEC C13-RA)	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	T0074	BN59-00598A	REMOCON;JASMINE,TM87C,SAMSUNG28P+EEPROM,	1	S.A
...3	ACCESSORY	BN63-01798A	CLOTH-CLEAN;RE40**,CLOTH,180,200,RHCM	1	S.N.A
...3	T0531	BN63-03113B	COVER-BOTTOM;40R81,HIPS,V0,BK500,NON-DEC	1	S.A
.2	M0045	BN96-05377A	ASSY ACCESSORY;LNT325HX/XAA	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	ACCESSORY	AA68-00371C	MARK RECYCLE-CARD WARRANTY,06;,SEA,W/P10	1	S.N.A
...3	ACCESSORY	AA68-03242F	MANUAL FLYER-02;SAFETY GUIDE;All Model,S	1	S.N.A
...3	T0511	BN68-00998P	MANUAL USERS;COMM,SAMSUNG,Eng/Spa,N.Amer	1	S.N.A
...3	ACCESSORY	BN68-01002F	MANUAL FLYER-QSG;COMM,SAMSUNG,English,N.	1	S.N.A
...3	T0238	AA68-03870C	MANUAL FLYER-REGISTRATION CARD;comm,Sams	1	S.N.A
...3	T0238	AA68-03870D	MANUAL FLYER-REGISTRATION CARD;comm,Sams	1	S.N.A
0.1	M0019	BN92-02640F	ASSY LABEL;LNT405HX/XAA	1	S.N.A
0.1	M0113	BN92-02752A	ASSY P/MATERIAL;40R81,CLUB	1	S.N.A
.2	T0376	6902-000001	BAG AIR;LDPE,T0.2,L1800,W1000,TRP,,,LDPE	0.016	S.N.A
.2	T0524	6902-000524	BAG PE;HDPE/NITRON,T0.015/T0.5,W1200,L11	1	S.N.A
.2	T0214	AA61-20285A	HOLDER-BOX;CTV,PP,NTR,HB	2	S.N.A
.2	T0172	AA69-02609A	BAND-PP,-,PP,-,W18,-,CLEA,1G,-,-	4.94	S.N.A
0.1	M0003	BN92-02755A	ASSY BOX;40R83,UO,CLUB,-,-,-	1	S.N.A
.2		BN69-01964A	BOX-SET, IN;40R83,CB,C-03,W777,L1492	1.02	S.N.A
.2		BN69-01965A	BOX-SET, OUT;40R83,CB,C-03,H790,W370,L10	1.02	S.N.A

5 Exploded View and Parts List

- You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>


5-1 LNT325H Exploded View



5-2 LNT325H Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,V	1	S.N.A	
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0003	BN96-05625A	ASSY COVER P-FRONT;32R83,UO(CLUB),-,PC+A	1	S.A	
T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A	
M0215	BN07-00453A	LCD-PANEL;LTA320WT-L06,8bit,32inch,16.7M	1	S.A	
M0027	BN96-04662A	ASSY STAND P-BASE;32R81,M81,SWIVEL,-,ABS	1	S.A	
T0447	BN96-04681A	ASSY BRACKET P-PANEL;32R81,-,-,-,AM,CM	1	S.N.A	
M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.N.A	
M0013	BN96-04666N	ASSY COVER P-REAR;32R81,UO(CLUB),PC+ABS,	1	S.A	

5-3 LNT375H Exploded View




5 Exploded View & Parts List

5-4 LNT375H Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,V	1	S.N.A	
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0003	BN96-05629A	ASSY COVER P-FRONT;37R81,UO(CLUB),-,PC+A	1	S.A	
T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A	
M0215	BN07-00366A	LCD-PANEL;CLAA370WA03,8bit,37inch,16.7M,	1	S.A	
M0027	BN96-04661A	ASSY STAND P-BASE;37,40R81,SWIVEL,-,ABS+	1	S.A	
T0447	BN96-04680E	ASSY BRACKET P-PANEL;37S86,EO	1	S.N.A	
M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A	
M0013	BN96-04665F	ASSY COVER P-REAR;37R81,UO(CLUB),PC+ABS,	1	S.A	

5-5 LNT405H Exploded View




5 Exploded View & Parts List

5-6 LNT405H Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0023	BN64-00639A	KNOB POWER;37 BORDEAUX PLUS,PC,-,-,-,V	1	S.N.A	
T0060	BN61-01655A	SPRING ETC;STS-304 SUS,D8,L12,T0.5	1	S.N.A	
T0003	BN96-05624A	ASSY COVER P-FRONT;40R81,UO(CLUB),-,PC+A	1	S.A	
T0022	BN64-00645A	KNOB CONTROL;37 BORDEAUX PLUS,PC+ABS,-,-	1	S.N.A	
M0215	BN07-00370A	LCD-PANEL;T400XW02,8bit,40inch,16.7M,16:	1	S.A	
M0027	BN96-04661A	ASSY STAND P-BASE;37,40R81,SWIVEL,-,ABS+	1	S.A	
T0447	BN96-04679C	ASSY BRACKET P-PANEL;40S81,JASMINE	1	S.N.A	
M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A	
M0013	BN96-04664J	ASSY COVER P-REAR;40R81,UO(CLUB),PC+ABS,	1	S.A	

10 Operating Instructions and Installation

10-1 Front



1. (POWER)

Press to turn the TV on and off.

POWER INDICATOR

Blinks and turns off when the power is on and lights up in stand-by mode.

2. REMOTE CONTROL SENSOR

Aim the remote control towards this spot on the TV.

3. SPEAKERS

4. SOURCE

Toggles between all the available input sources (TV, AV1, AV2, S-Video 1, S-Video 2, Component1, Component2, PC, HDMI1, HDMI2, HDMI3)

In the on-screen menu, use this button as you would use the **ENTER** button on the remote control.

5. MENU

Press to see an on-screen menu of your TV's features.

6. - VOL +

Press to decrease or increase the volume.


In the on-screen menu, use the - **VOL** + buttons as you use the ◀ and ▶ buttons on the remote control.

7. ^ CH ^

Press to change channels.

In the on-screen menu, use the ^ **CH** ^ buttons as you use the ▼ and ▲ buttons on the remote control.

10-2 Connection Panel



1. AUDIO OUT

Connects to the audio input jacks on your Amplifier/ Home theater.

2. DIGITAL AUDIO OUT (OPTICAL)

Connect to a Digital Audio component.

3. EX-LINK

Connect this to the jack on the optional wall mount bracket. This will allow you to adjust the TV viewing angle using your remote control.

4. PC IN

Connects to the video and audio output jacks on your PC.

5. HDMI IN 1,2,3 /DVI IN(HDMI1) (AUDIO R/L)

Connects to the HDMI jack of a device with an HDMI output. Use the HDMI 1 IN terminal for a DVI connection to an external device.

You should use the DVI to HDMI cable or DVI-HDMI adapter (DVI to HDMI) for a video connection, and the DVI IN 'R-AUDIO-L' terminal for audio.

- No sound connection is needed for an HDMI to HDMI connection
- When using an HDMI/DVI cable connection, it is only possible from the HDMI IN 1 terminal.

6. ANT 1 IN/ANT 2 IN

Connects to an antenna or cable TV system.

7. AV IN 1, AV IN 2

Video and audio inputs for external devices, such as a camcorder or VCR.

S-VIDEO

Connects an S-Video signal from a camcorder or VCR.

8. HEADPHONE

Connects a set of external headphones for private listening.

9. SERVICE

Connector for service only.

10. POWER INPUT

Connect the supplied power cord.

11. COMPONENT IN 1,2


Connects Component video/audio.

12. KENSINGTON LOCK

The Kensington lock (optional) is a device used to physically fix the system when used in a public place. If you want to use a locking device, contact the dealer where you purchased the TV.

- The place of the Kensington Lock may be different depending on its model.

10-3 Remote Control



- This is a special remote control for the visually impaired, and has Braille points on the Power, Channel and Volume buttons.

1. POWER

Turns the TV on and off.

2. NUMERIC BUTTONS

Press to change the channel.

3. _

Press to select additional channels(digital and analog) being broadcast by the same station. For example, to select channel "54-3", press "54", then press "." and "3".

4. CH LIST

Used to display Channel Lists on the screen.

5. ANTENNA

Press to select "AIR" or "CABLE".

6. VCR/DVD Functions

- Rewind
- Stop
- Play/Pause
- Fast/Forward

7. VOL \oplus / VOL \ominus

Press to increase or decrease the volume.

8. (MUTE)

Press to temporarily cut off the sound.

9. MENU

Displays the main on-screen menu.

10.S.MODE

Sound mode selection.

11.RETURN

Returns to the previous menu.

12.P.MODE

Picture effect selection.

13.SRS

Selects TruSurround XT mode.

14.MTS

Press to choose stereo, mono or Separate Audio Program(SAP broadcast).

15.SLEEP

Press to select a preset time interval for automatic shut off.

16. AUTO PROG.

Press to automatically store selected TV/Cable channels.

17. SET

Adjusts 5 separate devices -
TV, VCR, Cable, DVD, or Set-Top Box

18. TV, DVD, STB, CABLE, VCR

Make the remote control work for TV,
DVD, STB, CABLE, or VCR

19. When pressing this button, a number of buttons on the remote control (e.g. TV, DVD, STB, CABLE, VCR, MUTE, VOL and CH buttons) light up for a few seconds and then turn off to save power. This function is convenient for using the remote at night or when dark.

20.SOURCE

Press to display all of the available video sources.

21. PRE-CH

Turns to the previous channel.

22. FAV.CH

Press to switch to your favorite channels.

23.HDMI

Selects the HDMI mode directly.

24.CH \odot / CH \odot

Press to change channels.

25.EXIT

Press to exit the menu.

26.UP \blacktriangle / DOWN \blacktriangledown / LEFT \blacktriangleleft / RIGHT \blacktriangleright / ENTER \boxplus

Use to select on-screen menu items and change menu values.

27.INFO

Press to display information on the TV screen.

28.CAPTION

Controls the caption decoder.

29.STILL

Press to stop the action during a particular scene. Press again to resume normal video.

30.P.SIZE

Picture size selection.

31.PIP

Picture-in Picture ON/OFF.

32.CH \wedge / \vee

Displays the available channels in sequence. (These buttons change channels in the PIP window only.)

33.ADD/DEL


Use to store and delete channels to/from memory.


34.RESET

When your remote does not work, change the batteries and press the RESET button for 2-3 seconds before use.


12 PCB Diagram

12-1 Main PCB Diagram






12-3 Power PCB Layout 37"



12-4 Power PCB Layout 40"



1 Precautions

Follow these safety, servicing and ESD precautions to prevent damage and to protect against potential hazards such as electrical shock.

1-1 Safety Precautions

1-1-1 Warnings

1. For continued safety, do not attempt to modify the circuit board.
2. Disconnect the AC power and DC power jack before servicing.

1-1-2 Servicing the LCD Monitor

1. When servicing the LCD Monitor, Disconnect the AC line cord from the AC outlet.
2. It is essential that service technicians have an accurate voltage meter available at all times. Check the calibration of this meter periodically.

1-1-3 Fire and Shock Hazard

Before returning the monitor to the user, perform the following safety checks:

1. Inspect each lead dress to make certain that the leads are not pinched or that hardware is not lodged between the chassis and other metal parts in the monitor.
2. Inspect all protective devices such as nonmetallic control knobs, insulating materials, cabinet backs, adjustment and compartment covers or shields, isolation resistor-capacitor networks, mechanical insulators, etc.
3. Leakage Current Hot Check (Figure 1-1):

WARNING : Do not use an isolation transformer during this test.

Use a leakage current tester or a metering system that complies with American National Standards Institute (ANSI C101.1, *Leakage Current for Appliances*), and Underwriters Laboratories (UL Publication ULI410, 59.7).




Figure 1-1. Leakage Current Test Circuit

4. With the unit completely reassembled, plug the AC line cord directly into a 120V AC outlet. With the unit's AC switch first in the ON position and then OFF, measure the current between a known earth ground (metal water pipe, conduit, etc.) and all exposed metal parts, including: metal cabinets, screwheads and control shafts. The current measured should not exceed 0.5 milliamp. Reverse the power-plug prongs in the AC outlet and repeat the test.

1-1-4 Product Safety Notices

Some electrical and mechanical parts have special safety-related characteristics which are often not evident from visual inspection. The protection they give may not be obtained by replacing them with components rated for higher voltage, wattage, etc. Parts that have special safety characteristics are identified by \triangle on schematics and parts lists. A substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire and/or other hazards. Product safety is under review continuously and new instructions are issued whenever appropriate.

1-2 Servicing Precautions

WARNING: An electrolytic capacitor installed with the wrong polarity might explode.

Caution: Before servicing units covered by this service manual, read and follow the Safety Precautions section of this manual.

Note: If unforeseen circumstances create conflict between the following servicing precautions and any of the safety precautions, always follow the safety precautions.

1-2-1 General Servicing Precautions

1. Always unplug the unit's AC power cord from the AC power source and disconnect the DC Power Jack before attempting to:
(a) remove or reinstall any component or assembly, (b) disconnect PCB plugs or connectors, (c) connect a test component in parallel with an electrolytic capacitor.
2. Some components are raised above the printed circuit board for safety. An insulation tube or tape is sometimes used. The internal wiring is sometimes clamped to prevent contact with thermally hot components. Reinstall all such elements to their original position.
3. After servicing, always check that the screws, components and wiring have been correctly reinstalled. Make sure that the area around the serviced part has not been damaged.
4. Check the insulation between the blades of the AC plug and accessible conductive parts (examples: metal panels, input terminals and earphone jacks).
5. **Insulation Checking Procedure:** Disconnect the power cord from the AC source and turn the power switch ON. Connect an insulation resistance meter (500 V) to the blades of the AC plug.

The insulation resistance between each blade of the AC plug and accessible conductive parts (see above) should be greater than 1 megohm.
6. Always connect a test instrument's ground lead to the instrument chassis ground before connecting the positive lead; always remove the instrument's ground lead last.

1-3 Electrostatically Sensitive Devices (ESD) Precautions

Some semiconductor (solid state) devices can be easily damaged by static electricity. Such components are commonly called Electrostatically Sensitive Devices (ESD). Examples of typical ESD are integrated circuits and some field-effect transistors. The following techniques will reduce the incidence of component damage caused by static electricity.

1. Immediately before handling any semiconductor components or assemblies, drain the electrostatic charge from your body by touching a known earth ground. Alternatively, wear a discharging wrist-strap device. To avoid a shock hazard, be sure to remove the wrist strap before applying power to the monitor.
2. After removing an ESD-equipped assembly, place it on a conductive surface such as aluminum foil to prevent accumulation of an electrostatic charge.
3. Do not use freon-propelled chemicals. These can generate electrical charges sufficient to damage ESDs.
4. Use only a grounded-tip soldering iron to solder or desolder ESDs.
5. Use only an anti-static solder removal device. Some solder removal devices not classified as "anti-static" can generate electrical charges sufficient to damage ESDs.
6. Do not remove a replacement ESD from its protective package until you are ready to install it. Most replacement ESDs are packaged with leads that are electrically shorted together by conductive foam, aluminum foil or other conductive materials.
7. Immediately before removing the protective material from the leads of a replacement ESD, touch the protective material to the chassis or circuit assembly into which the device will be installed.

Caution: Be sure no power is applied to the chassis or circuit and observe all other safety precautions.
8. Minimize body motions when handling unpackaged replacement ESDs. Motions such as brushing clothes together, or lifting your foot from a carpeted floor can generate enough static electricity to damage an ESD.

1-4 Installation Precautions

1. For safety reasons, more than two people are required for carrying the product.
2. Keep the power cord away from any heat emitting devices, as a melted covering may cause fire or electric shock.
3. Do not place the product in areas with poor ventilation such as a bookshelf or closet. The increased internal temperature may cause fire.
4. Otherwise, it may cause a fire or electric shock.
5. Make sure to turn the power off and unplug the power cord from the outlet before repositioning the product. Also check the antenna cable or the external connectors if they are fully unplugged. Damage to the cord may cause fire or electric shock.
6. Keep the antenna far away from any high-voltage cables and install it securely. Contact with the highvoltage cable or the antenna falling over may cause fire or electric shock.
7. When installing the product, leave enough space (10cm) between the product and the wall for ventilation purposes.
A rise in temperature within the product may cause fire.

1 Precautions

Memo

2 Product Specifications

2-1 Features

- RF, HDMI(DVI-D), PC(Analog), Component, Video, S-Video
- Brightness : 500cd/m²
- Contrast Ratio : 32"/37"/40" => 8000:1
- Response time : 8ms
- Dynamic contrast
- PIP (on PC only)

2-2 LNT325H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 32-Inch viewable, 0.51075 (H) x 0.51075(V)mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal: 1920 Pixels Vertical: 1080i Pixels (Component/HDMI input)	
Input Video Signal	Analog 0.7 Vp-p $\pm 5\%$ positive at 75 Ω , internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	27.47 inches / 36.7 inches	
AC power voltage & Frequency	AC 110 , 60Hz	
Power Consumption	< 170W (< 1W, stand by)	
Dimensions(W x D x H) Set	31.5 x 3.5 x 21.12 inches _without stand 31.5 x 9.92 x 22.83 inches _with stand	
Weight Set(After installation Stand)	14.8kg(32.63 lbs)	
TV System	Tuning	Frequency Synthesize
	System	ATSC, NTSC
	Sound	MONO, STEREO, SAP
Environmental Considerations	Operating Temperature : 10°C ~ 40°C Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antenna Input	75 Ω	
Sound Characteristic	- MAX Internal speaker Out : Right => 5W, Left => 5W - BASS Control Range : -8 dB ~ +8dB - TREBLE Control Range : -8 dB ~ +8 dB - Headphone Out : 10 mW MAX - Output Frequency : RF : 80 Hz ~ 15 kHz AV : 80 Hz ~ 20 kHz	



2-3 LNT375H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 37-Inch viewable, 0.648 (H) x 0.648(V)mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal: 1920 Pixels Vertical: 1080i Pixels (Component/HDMI input)	
Input Video Signal	Analog 0.7 Vp-p $\pm 5\%$ positive at 75 Ω , internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	32.27inches / 18.14 inches	
AC power voltage & Frequency	AC 110 , 60Hz	
Power Consumption	< 180 W (< 1W, stand by)	
Dimensions(W x D x H) Set	36.08 x 3.43 x 24 inches _without stand 36.08 x 11.81 x 25.99 inches _with stand	
Weight Set(After installation Stand)	19.3kg(42.55 lbs)	
TV System	Tuning	Frequency Synthesize
	System	ATSC, NTSC
	Sound	MONO, STEREO, SAP
Environmental Considerations	Operating Temperature : 10°C ~ 40°C Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antenna Input	75 Ω	
Sound Characteristic	- MAX Internal speaker Out : Right => 7.5 W, Left => 7.5 W - BASS Control Range : -8 dB ~ + 8dB - TREBLE Control Range : -8 dB ~ +8 dB - Headphone Out : 10 mW MAX - Output Frequency : RF : 80 Hz ~ 15 kHz AV : 80 Hz ~ 20 kHz	

2-4 LNT405H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, normally white, 40-Inch viewable, 0.648 (H) x 0.216(V)mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal: 1920 Pixels Vertical: 1080i Pixels (Component/HDMI input)	
Input Video Signal	Analog 0.7 Vp-p \pm 5% positive at 75 Ω , internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	34.85 inches / 19.57 inches	
AC power voltage & Frequency	AC 110 , 60Hz	
Power Consumption	< 195 W (< 1W, stand by)	
Dimensions(W x D x H) Set	39.04 x 3.8 x 25.49 inches _without stand 39.04 x 11.81 x 27.42 inches _with stand	
Weight Set(After installation Stand)	21.4kg(47.18 lbs)	
TV System	Tuning	Frequency Synthesize
	System	ATSC, NTSC
	Sound	MONO, STEREO, SAP
Environmental Considerations	Operating Temperature : 10°C ~ 40°C Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antenna Input	75 Ω	
Sound Characteristic	- MAX Internal speaker Out : Right =>7.5W, Left => 7.5W - BASS Control Range : -8 dB ~ + 8dB - TREBLE Control Range : -8 dB ~ +8 dB - Headphone Out : 10 mW MAX - Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-5 Spec Comparison

Model	LNT325H/LNT375H/LNT405H	LN-S2651D / LN-S3251D / LN-S4051D / LN-S2652D / LN-S3252D / LN-S4052D
Design		
Frequency Horizontal Vertical Display Color	30 ~ 61 kHz 60 ~ 75 Hz 16,777,216 colors	30 ~ 61 kHz 60 ~ 75 Hz 16,777,216 colors
PC Resolution Maximum mode	1360 x 768 / 60 Hz	1360 x 768 / 60 Hz
Input Signal Sync Signal Video Signal	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm
Power Consumption Normal Power Saving	170W/180W/195W <1W	133W / 165W / 218W < 1W
Input source Difference	3HDMI	2HDMI
PIP	PIP(PC Only)	PIP, POP
Sound	10W x 2	3W / 5W / 10W

2-6 Option Specification

Item	Item Name	Code.No	Remark
	Remote Control & Batteries (AAA x 2)	BN59-00598A	
	Power Cord	3903-000144	
	Cover-Bottom	BN63-03093A	
	Stand	BN96-04697A	
	Stand Screw (4 ea)	6002-001294	
	Owner's Instructions	BN68-01250A	
	Cleaning Cloth	BN63-01798A	
	Warranty Card / Registration Card / Safety Guide Manual (Not available in all locations)	BN63-00860A	

14 Reference Information

14-1 Technical Terms

- TFT-LCD

(Thin film Transistor Liquid Crystal Display)

ADC(Analog to Digital Converter)

This is a circuit that converts from analog signal to digital signals.

- PLL(Phase Locked Loop)

During progressing ADC, Device makes clock synchronizing HSYNC with Video clock

- Inverter

Device that supply Power to LCD panel lamp. this device generate about 1,500~2,000V.

- AC Adapter

Device that converts AC(90V~240V) to DC(+12V or 14V)

- SMPS(Switching Mode Power Supply)

Switching Mode Power supply. This design technology is used to step up/down the input power by switching on/off

- FRC(Frame Rate Controller)

Technology that change image frame quantity displayed on screen for one second.

Actually TFT-LCD panel require 60 pcs of frame for one second.

so, this technology is needed to convert input image to 60 pcs regardless input frame quantity.

- Image Scaler

Technology that convert various input resolution to other resolution.(ex. 640* 480 to 1024*768)

- Auto Configuration(Auto adjustment)

This is an algorithm to adjust monitor to optimum condition by pushing one key.

- OSD(On Screen Display)

On screen display. customer can control the screen easily with this.

- Image Lock

This means "Fineness adjustment " in LCD Monitor, the features are "Fine" and "Coarse"

- FINE

"Fine" adjustment is used to adjust visibility by control phase difference.

- COARSE

This is a adjustment by tuning with Video colck and PLL clock.

- DVI (Digital Visual Interface)

This provides a high speed digital connection for visual data types that is display technology independent. this interface is primarily focused at providing a connection between a computer and its display device.

- L.V.D.S.(Low Voltage Differential Signaling)

a kind of transmission method for Digital.It can be used from Main PBA to Panel.

- DVI (Digital Visual Interface)

This provides a high speed digital connection for visual data types that is display technology independent. this interface is primarily focused at providing a connection between a computer and its display device.

- T.M.D.S

(Transition minimized Differential Signaling)

a kind of transmission method for Digital.

It can be used from Video card to Main PBA.

- DDC(Display data channel)

It is a communication method between Host Computer and related equipment.

It can make it Plug and Play between PC and Monitor.

- EDID

Extended Display Identification Data PC can recognize the monitor information as Product data, Product name, Display mode, Serial number and Signal source, etc through DDC Line communicating with PC and Monitor.

- Dot Pitch

The image on a monitor is composed of red, green and blue dots. The closer the dots, the higher the resolution. The distance between two dots of the same color is called the 'Dot Pitch'. Unit: mm

- Vertical Frequency

The screen must be redrawn several times per second in order to create and display an image for the user. The frequency of this repetition per second is called Vertical Frequency or Refresh Rate. Unit: Hz

Example: If the same light repeats itself 60 times per second, this is regarded as 60 Hz.

- Horizontal Frequency

The time to scan one line connecting the right edge to the left edge of the screen horizontally is called Horizontal Cycle. The inverse number of the Horizontal Cycle is called Horizontal Frequency. Unit: kHz

- Interlace and Non-Interlace Methods

Showing the horizontal lines of the screen from the top to the bottom in order is called the Non-Interlace method while showing odd lines and then even lines in turn is called the Interlace method.

The Non-Interlace method is used for the majority of monitors to ensure a clear image. The Interlace method is the same as that used in TVs.

- Plug & Play

This is a function that provides the best quality screen for the user by allowing the computer and the monitor to exchange information automatically.

This monitor follows the international standard VESA DDC for the Plug & Play function.

- Resolution

The number of horizontal and vertical dots used to compose the screen image is called 'resolution'.

This number shows the accuracy of the display.

High resolution is good for performing multiple tasks as more image information can be shown on the screen.

Example: If the resolution is 1280 x 1024, this means the screen is composed of 1280 horizontal dots (horizontal resolution) and 1024 vertical lines (vertical resolution).

- BTSC

Broadcast Television System Committee

The stereo broadcasting system that is used in most of the countries that have adopted the NTSC system, including the United States, Canada, Chile, Venezuela and Taiwan. It also refers to the organization that has been organized to promote its development and management.

- EIAJ

Electronic Industries Association of Japan.

- RF Cable

A round signal cable generally used for TV antennas.

- Satellite Broadcasting

Broadcasting service provided via satellite. Enables high picture quality and clear sound throughout the country regardless of the location of the viewer.

- Sound Balance

Balances the levels of the sound coming from each speaker in televisions with two speakers.

- Cable TV

Whereas the terrestrial broadcasting is delivered via frequency signals through the air, cable broadcasting is transmitted via a cable network. In order to view cable TV, one must purchase a cable receiver and hook it up to the cable network.

- CATV

"CATV" refers to the broadcasting service offered at hotels, schools and other buildings through their own broadcasting system, apart from VHF or UHF broadcasting by terrestrial broadcasters. The CATV programs may include movies, entertainment and educational programs. (Different from cable TV.)

CATV can be viewed only within the area in which the CATV service is offered.

- S-Video

Short for "Super Video." S-Video allows up to 800 lines of horizontal resolution, enabling high-quality video.

- VHF/UHF

VHF indicates TV channels 2 to 13, and UHF indicates channels 14 through 69.

- Channel Fine Tuning

This feature allows the viewer to fine-tune the TV channel to obtain the best viewing conditions. The Samsung LCD TV has both automatic and manual channel fine-tuning features to enable the viewer to adjust their desired settings.

- External Device Input

External device input refers to video input from such external video devices as VCRs, camcorders and DVD players, separate from a TV broadcast.

14-2 Pin Assignments

14-2-1 DVI-D

Pin No.	Sync Type	24P DVI-D			
1		Rx2-	13		NC
2		Rx2+	14		DDC Input power (+5V)
3		GND	15		IDENT-DVI
4		NC	16		Output Signal (HDCP Control)
5		NC	17		Rx0-
6		DDC - SCL	18		Rx0+
7		DDC - SDA	19		GND
8		NC	20		NC
9		Rx1-	21		NC
10		Rx1+	22		GND
11		GND	23		RxC+
12		NC	24		RxC-




Figure 1.

14-2-2 Component 1, 2

RCA Green	Y
	GND
RCA Blue	Pb (Cb)
	GND
RCA Red	Pr (Cr)
	GND
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-2-4 A/V 1,2

RCA Yellow	CVBS
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-2-3 S-Video

Pin	Separate
1	GND
2	Y
3	C
4	GND
5	GND

14-2-5 D-SUB

Pin	Separate
1	Red
2	Green
3	Blue
4	GND
5	GND
6	GND Red
7	GND Green
8	GND Blue
9	DDC Input power(+5V)
10	IDENT PC
11	GND
12	DDC Data(SDA)
13	H SYNC
14	V SYNC
15	DDC Clock(SCL)

14-2-6 PC Display mode

Both screen position and size will vary depending on the type of PC monitor and its resolution.

The resolutions in the table are recommended. (All resolutions between the supported limits are supported)

Mode	Resolution	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Pixel Clock Frequency (MHz)	Sync Polarity (H/V)
IBM	640 x 480	31.469	59.940	25.175	- / -
	720 x 400	31.469	70.087	28.322	- / +
VESA	640 x 480	37.861	72.809	31.500	- / -
	640 x 480	37.500	75.000	31.500	- / -
	800 x 600	37.879	60.317	40.000	+ / +
	800 x 600	48.077	72.188	50.000	+ / +
	800 x 600	46.875	75.000	49.500	+ / +
	1024 x 768	48.364	60.000	65.000	- / -
	1024 x 768	56.476	70.069	75.000	- / -
	1024 x 768	60.023	75.029	78.750	+ / +
	1360 x 768	47.712	60.015	85.800	+ / +


- The interlace mode is not supported.
- The set might operate abnormally if a non-standard video format is selected.
- DVI dose not support PC function.

14-3 Timing Chart

This section of the service manual describes the timing that the computer industry recognizes as standard for computer-generated video signals.

14-3-1 LCD Panel Mode1 mode

Timing No.	LTA400W2
Originator	VESA
Mode Name	1366/60Hz
Resolution (HxV)	1366x768
HORIZONTAL	
Frequency	47.712kHz
Total time	20.959 μ s
Active time	15.906 μ s
Blank time	5.053 μ s
Border(L / R)	0.000 μ s
Data time	15.906 μ s
Front porch	0.749 μ s
Sync. width	1.702 μ s
Back porch	2.994 μ s
Sync. polarity	Positive
VERTICAL	
Frequency	60.015Hz
Total time	16.662 ms
Active time	16.097 ms
Blank time	0.566 ms
Border(T / B)	0.000 ms
Data time	16.097 ms
Front porch	0.063 ms
Sync. width	0.105 ms
Back porch	0.377 ms
Sync polarity	Positive
Dot Clock	85.500MHz
Sync. Type	Separate
Scan Type	N/I



14-3-2 Supported Modes (1)

Timing No. Originator Mode Name Resolution (HxV)	2 IBM VGA2 720x400	3 IBM VGA3 640x480	11 VESA 640/72Hz 640x480	17 VESA 640/75Hz 640x480	32 MAC 640/67Hz 640x480
HORIZONTAL Frequency	31.469kHz	31.469kHz	37.861kHz	37.500kHz	35.000kHz
Total time	31.777μs	31.778μs	26.413μs	26.667μs	28.571μs
Activetime	26.058μs	26.058μs	20.825μs	20.317μs	21.164μs
Blank time	5.720μs	5.720μs	5.588μs	6.350μs	7.407μs
Border(L / R)	0.318μs	0.318μs	0.254μs	0.000μs	0.000μs
Data time	25.422μs	25.422μs	20.317μs	20.317μs	21.164μs
Front porch	0.318μs	0.318μs	0.508μs	0.508μs	2.116μs
Sync. width	3.813μs	3.813μs	1.270μs	2.032μs	2.116μs
Back porch	1.589μs	1.589μs	3.810μs	3.810μs	3.175μs
Sync. polarity	Negative	Negative	Negative	Negative	Negative
VERTICAL Frequency	70.087Hz	59.940Hz	72.809Hz	75.000Hz	66.667Hz
Total time	14.268ms	16.683ms	13.735ms	13.333ms	15.000ms
Active time	13.155ms	15.761ms	13.100ms	12.800ms	13.714ms
Blank time	1.113ms	0.922ms	0.635ms	0.533ms	1.286ms
Border(T / B)	0.222ms	0.254ms	0.211ms	0.000ms	0.000ms
Data time	12.711ms	15.253ms	12.678ms	12.800ms	13.714ms
Front porch	0.191ms	0.064ms	0.026ms	0.027ms	0.086ms
Sync. width	0.064ms	0.064ms	0.079ms	0.080ms	0.086ms
Back porch	0.858ms	0.794ms	0.528ms	0.427ms	1.114ms
Sync polarity	Positive	Negative	Negative	Negative	Negative
Dot Clock	28.322MHz	25.175MHz	31.500MHz	31.500MHz	30.240MHz
Sync. Type	Separate	Separate	Separate	Separate	Separate
Scan Type	N/I	N/I	N/I	N/I	N/I

14-3-3 Supported Modes (2)

Timing No. Originator Mode Name Resolution (HxV)	13 VESA 800/60Hz 800x600	14 VESA 800/72Hz 800x600	18 VESA 800/75Hz 800x600
HORIZONTAL Frequency Total time Active time Blank time Border(L / R) Data time Front porch Sync. width Back porch Sync. polarity	37.879kHz 26.400 μ s 20.000 μ s 6.400 μ s 0.000 μ s 20.000 μ s 1.000 μ s 3.200 μ s 2.200 μ s Positive	48.077kHz 20.800 μ s 16.000 μ s 4.800 μ s 0.000 μ s 16.000 μ s 1.120 μ s 2.400 μ s 1.280 μ s Positive	46.875kHz 21.333 μ s 16.162 μ s 5.171 μ s 0.000 μ s 16.162 μ s 0.323 μ s 1.616 μ s 3.232 μ s Positive
VERTICAL Frequency Total time Active time Blank time Border(T / B) Data time Front porch Sync. width Back porch Sync polarity	60.317Hz 16.579ms 15.840ms 0.739ms 0.000ms 15.840ms 0.026ms 0.106ms 0.607ms Positive	72.188Hz 13.853ms 12.480ms 1.373ms 0.000ms 12.480ms 0.770ms 0.125ms 0.478ms Positive	75.000Hz 13.333ms 12.800ms 0.533ms 0.000ms 12.800ms 0.021ms 0.064ms 0.448ms Positive
Dot Clock	40.000MHz	50.000MHz	49.500MHz
Sync. Type	Separate	Separate	Separate
Scan Type	N/I	N/I	N/I

14-3-4 Supported Modes (3)


Timing No. Originator Mode Name Resolution (HxV)	15 VESA 1024/60Hz 1024x768	16 VESA 1024/70Hz 1024x768	19 VESA 1024/75Hz 1024x768	VESA 1360/60Hz 1360x768
HORIZONTAL				
Frequency	48.363kHz	56.476kHz	60.023kHz	47.712kHz
Total time	20.677 μ s	17.707 μ s	16.660 μ s	20.959 μ s
Activetime	15.754 μ s	13.653 μ s	13.003 μ s	15.906 μ s
Blank time	4.923 μ s	4.053 μ s	3.777 μ s	5.053 μ s
Border(L / R)	0.000 μ s	0.000 μ s	0.000 μ s	0.000 μ s
Data time	15.754 μ s	13.653 μ s	13.003 μ s	15.906 μ s
Front porch	0.369 μ s	0.320 μ s	0.323 μ s	0.749 μ s
Sync. width	2.092 μ s	1.813 μ s	1.219 μ s	1.702 μ s
Back porch	2.462 μ s	1.920 μ s	2.235 μ s	2.994 μ s
Sync. polarity	Negative	Negative	Positive	Positive
VERTICAL				
Frequency	60.004Hz	70.069Hz	75.029Hz	60.015Hz
Total time	16.666ms	14.272ms	13.328ms	16.662ms
Active time	15.880ms	13.599ms	12.795ms	16.097ms
Blank time	0.786ms	0.672ms	0.533ms	0.566ms
Border(T / B)	0.000ms	0.000ms	0.000ms	0.000ms
Data time	15.880ms	13.599ms	12.795ms	16.097ms
Front porch	0.062ms	0.053ms	0.017ms	0.063ms
Sync. width	0.124ms	0.106ms	0.050ms	0.105ms
Back porch	0.600ms	0.513ms	0.466ms	0.377ms
Sync. polarity	Negative	Negative	Positive	Positive
Dot Clock	65.000MHz	75.000MHz	78.750MHz	85.500MHz
Sync. Type	Separate	Separate	Separate	Separate
Scan Type	N/I	N/I	N/I	N/I

Memo

9 Schematic Diagrams







- This Document can not be used without Samsung's authorization.

9-1 MAIN POWER BLOCK Schematic Diagram




- This Document can not be used without Samsung s authorization.

9-2 X242 INOUT MEMORY Schematic Diagram




- This Document can not be used without Samsung's authorization.

9-3 FLEXBUS_PCI_FLASH Schematic Diagram



- This Document can not be used without Samsung's authorization.




9-4




- This Document can not be used without Samsung's authorization.

9-5 TUNER & SPLITTER Schmatic Diagram

ATSC HALF NIM TUNER




9-6






- This Document can not be used without Samsung's authorization.

9-7 PC & HDMI INPUT Schmatic Diagram





DVI SOUND INPUT




- This Document can not be used without Samsung's authorization.

9-8



- This Document can not be used without Samsung's authorization.

9-9 SIDE AV Schmatic Diagram







- This Document can not be used without Samsung s authorization.

9-10 MSP4450K Schmatic Diagram



- This Document can not be used without Samsung's authorization.

9-11 SOUND AMP(NTP3000) Schmetic Diagram




9-12 MST3388 & SIL9185 Schmatic Diagram



- This Document can not be used without Samsung's authorization.


9-13 FBE Schmatic Diagram



- This Document can not be used without Samsung's authorization.


9-14 SUB-FUNCTION Schmatic Diagram

SUB FUNCTION I/F




4 Troubleshooting

4-1 No Power



4-2 No Video (Analog PC Signal)



WAVEFORMS


1 2 3 PC Input (V-Sync, H-Sync)




4 LVDS Out (CLK + / -)




4-3 No Video (HDMI - Digital Signal)




WAVEFORMS

5 6 HDMI Input (CLK + / -)


4-4 No Picture (Tuner_CVBS)



WAVEFORMS


7 Tuner CVBS Out (Pattern: Grey Bar)

4-5 No Picture (Tuner DTV TS)




WAVEFORMS


8 DTV RF +/-



4-6 No Picture(Video CVBS)




4-7 No Picture(S-Video Y/C)



WAVEFORMS**9 S-VIDEO Input (Y/C)**

4-8 No Picture(Component1, 2 : 480i, 480p, 720p, 1080i[Y, Pb, Pr])




WAVEFORMS

10 Component Input (Y/Pb)




4-9 No Sound




WAVEFORMS


11 Audio Input (Sign Wave)



12 12S Input (Clk, Data)




13 Audio Amp Out (Sign Wave)



8 Wiring Diagram

8-1 Wiring Diagram



Memo