

PHILIPS

29" LCD TV chassis PL13.21

Service Manual

Contents

29PFL4508/F4

PHILIPS

(Serial No.: ME1)

© 2013 Funai Electric Co., Ltd.

All rights reserved. No part of this manual may be reproduced, copied, transmitted, disseminated, transcribed, downloaded or stored in any storage medium, in any form or for any purpose without the express prior written consent of Funai. Furthermore, any unauthorized commercial distribution of this manual or any revision hereto is strictly prohibited.

Information in this document is subject to change without notice. Funai reserves the right to change the content herein without the obligation to notify any person or organization of such changes.

FUNAI with the  design is a registered trademark of Funai Electric Co., Ltd and may not be used in any way without the express written consent of Funai. All other trademarks used herein remain the exclusive property of their respective owners. Nothing contained in this manual should be construed as granting, by implication or otherwise, any license or right to use any of the trademarks displayed herein. Misuse of any trademarks or any other content in this manual is strictly prohibited. Funai shall aggressively enforce its intellectual property rights to the fullest extent of the law.

IMPORTANT SAFETY NOTICE

Proper service and repair is important to the safe, reliable operation of all P&F Equipment. The service procedures recommended by P&F and described in this service manual are effective methods of performing service operations. Some of these service special tools should be used when and as recommended.

It is important to note that this service manual contains various CAUTIONS and NOTICES which should be carefully read in order to minimize the risk of personal injury to service personnel. The possibility exists that improper service methods may damage the equipment. It also is important to understand that these CAUTIONS and NOTICES ARE NOT EXHAUSTIVE. P&F could not possibly know, evaluate and advise the service trade of all conceivable ways in which service might be done or of the possible hazardous consequences of each way. Consequently, P&F has not undertaken any such broad evaluation. Accordingly, a servicer who uses a service procedure or tool which is not recommended by P&F must first use all precautions thoroughly so that neither his safety nor the safe operation of the equipment will be jeopardized by the service method selected.

The LCD panel is manufactured to provide many years of useful life. Occasionally a few non active pixels may appear as a tiny spec of color. This is not to be considered a defect in the LCD screen.

TABLE OF CONTENTS

Specifications	1-1
Important Safety Precautions	2-1
Standard Notes for Servicing	3-1
Cabinet Disassembly Instructions	4-1
Electrical Adjustment Instructions	5-1
How to Initialize the LCD TV	6-1
Firmware Renewal Mode	7-1
Troubleshooting	8-1
Block Diagrams	9-1
Schematic Diagrams / CBA and Test Points	10-1
Wiring Diagrams	11-1
Exploded Views	12-1
Parts List	13-1
Revision History	14-1
Comparison List of Model Names	15-1

SPECIFICATIONS

< TUNER/NTSC > (VHF/UHF Input)

ANT. Input ----- 75 Ω Unbal., F type

Description	Condition	Unit	Nominal	Limit
1. AFT Pull-In Range	---	kHz	---	+300
	---	kHz	---	-300
2. Synchronizing Sens.	VHF Lo 67.25MHz (TV.ch.04)	dBu	18	20
	VHF Hi 265.25MHz (CA.ch.31)	dBu	18	20
	UHF 801.25MHz (TV.ch.69)	dBu	18	23
3. BEAT Confirmation	VHF Lo 67.25MHz (TV.ch.04)	dB	---	47

< LCD PANEL >

Description	Condition	Unit	Nominal	Limit
1. Native Pixel Resolution	Horizontal	pixels	1366	---
	Vertical	pixels	768	---
2. Viewing Angle	Horizontal	°	-85 to 85	-75 to 75
	Vertical	°	-80 to 80	-70 to 70

< VIDEO >

Description	Condition	Unit	Nominal	Limit
1. Over Scan	Horizontal	%	5	5±5
	Vertical	%	5	5±5
2. Color Temperature	AT 70% WHITE FIELD	°K	12000	---
	x		0.272	±0.008
	y		0.278	±0.008
3. Resolution (composite video)	Horizontal	line	400	---
	Vertical	line	350	---
4. Brightness	AT 100% WHITE FIELD (AT RETAIL MODE)	cd/m ²	300	---

< AUDIO >

All items are measured across 8 Ω load at speaker output terminal.

Description	Condition	Unit	Nominal	Limit
1. Audio Output Power	500mVrms input Lch/Rch Vol: MAX	W	8/8	7/7
2. Audio Distortion	500mW: Lch/Rch	%	1.5/1.5	3.0/3.0
3. Audio Freq. Response	-6dB: Lch	Hz	70 to 10k	---
	-6dB: Rch	Hz	70 to 10k	---
4. Audio S/N	Lch/Rch	dB	---	≥45/45

Note: Nominal specifications represent the design specifications. All units should be able to approximate these. Some will exceed and some may drop slightly below these specifications. Limit specifications represent the absolute worst condition that still might be considered acceptable. In no case should a unit fail to meet limit specifications.


IMPORTANT SAFETY PRECAUTIONS

Prior to shipment from the factory, our products are strictly inspected for recognized product safety and electrical codes of the countries in which they are to be sold. However, in order to maintain such compliance, it is equally important to implement the following precautions when a set is being serviced.

Safety Precautions for LCD TV Circuit

1. **Before returning an instrument to the customer**, always make a safety check of the entire instrument, including, but not limited to, the following items:
 - a. Be sure that no built-in protective devices are defective and have been defeated during servicing. (1) Protective shields are provided on this chassis to protect both the technician and the customer. Correctly replace all missing protective shields, including any removed for servicing convenience. (2) When reinstalling the chassis and/or other assembly in the cabinet, be sure to put back in place all protective devices, including but not limited to, nonmetallic control knobs, insulating fishpapers, adjustment and compartment covers/shields, and isolation resistor/capacitor networks. **Do not operate this instrument or permit it to be operated without all protective devices correctly installed and functioning. Servicers who defeat safety features or fail to perform safety checks may be liable for any resulting damage.**
 - b. Be sure that there are no cabinet openings through which an adult or child might be able to insert their fingers and contact a hazardous voltage. Such openings include, but are not limited to, (1) spacing between the LCD module and the cabinet mask, (2) excessively wide cabinet ventilation slots, and (3) an improperly fitted and/or incorrectly secured cabinet back cover.
 - c. **Antenna Cold Check** - With the instrument AC plug removed from any AC source, connect an electrical jumper across the two AC plug prongs. Place the instrument AC switch in the on position. Connect one lead of an ohmmeter to the AC plug prongs tied together and touch the other ohmmeter lead in turn to each tuner antenna input exposed terminal screw and, if applicable, to the coaxial connector. If the measured resistance is less than 1.0 megohm or greater than 5.2 megohm, an abnormality exists that must be corrected before the instrument is returned to the customer. Repeat this test with the instrument AC switch in the off position.
 - d. **Leakage Current Hot Check** - With the instrument completely reassembled, plug the AC line cord directly into a 230 V AC outlet. (Do not use an isolation transformer during this test.) Use a leakage current tester or a metering system that complies with American

National Standards Institute (ANSI) C101.1 Leakage Current for Appliances and Underwriters Laboratories (UL) 1410, (50.7). With the instrument AC switch first in the on position and then in the off position, measure from a known earth ground (metal water pipe, conduit, etc.) to all exposed metal parts of the instrument (antennas, handle brackets, metal cabinet, screw heads, metallic overlays, control shafts, etc.), especially any exposed metal parts that offer an electrical return path to the chassis. Any current measured must not exceed 0.5 milli-ampere. Reverse the instrument power cord plug in the outlet and repeat the test.



ANY MEASUREMENTS NOT WITHIN THE LIMITS SPECIFIED HEREIN INDICATE A POTENTIAL SHOCK HAZARD THAT MUST BE ELIMINATED BEFORE RETURNING THE INSTRUMENT TO THE CUSTOMER OR BEFORE CONNECTING THE ANTENNA OR ACCESSORIES.

2. Read and comply with all caution and safety-related notes on or inside the receiver cabinet, on the receiver chassis, or on the LCD module.
3. **Design Alteration Warning** - Do not alter or add to the mechanical or electrical design of this LCD TV receiver. Design alterations and additions, including, but not limited to circuit modifications and the addition of items such as auxiliary audio and/or video output connections, might alter the safety characteristics of this receiver and create a hazard to the user. Any design alterations or additions will void the manufacturer's warranty and may make you, the servicer, responsible for personal injury or property damage resulting therefrom.

4. Hot Chassis Warning -

- a. Some TV receiver chassis are electrically connected directly to one conductor of the AC power cord and maybe safety-serviced without an isolation transformer only if the AC power plug is inserted so that the chassis is connected to the ground side of the AC power source. To confirm that the AC power plug is inserted correctly, with an AC voltmeter, measure between the chassis and a known earth ground. If a voltage reading in excess of 1.0 V is obtained, remove and reinsert the AC power plug in the opposite polarity and again measure the voltage potential between the chassis and a known earth ground.
 - b. Some TV receiver chassis normally have 85V AC(RMS) between chassis and earth ground regardless of the AC plug polarity. This chassis can be safety-serviced only with an isolation transformer inserted in the power line between the receiver and the AC power source, for both personnel and test equipment protection.
 - c. Some TV receiver chassis have a secondary ground system in addition to the main chassis ground. This secondary ground system is not isolated from the AC power line. The two ground systems are electrically separated by insulation material that must not be defeated or altered.
5. Observe original lead dress. Take extra care to assure correct lead dress in the following areas: a. near sharp edges, b. near thermally hot parts-be sure that leads and components do not touch thermally hot parts, c. the AC supply, d. high voltage, and, e. antenna wiring. Always inspect in all areas for pinched, out of place, or frayed wiring. Check AC power cord for damage.
6. Components, parts, and/or wiring that appear to have overheated or are otherwise damaged should be replaced with components, parts, or wiring that meet original specifications. Additionally, determine the cause of overheating and/or damage and, if necessary, take corrective action to remove any potential safety hazard.

7. **Product Safety Notice** - Some electrical and mechanical parts have special safety-related characteristics which are often not evident from visual inspection, nor can the protection they give necessarily be obtained by replacing them with components rated for higher voltage, wattage, etc.. Parts that have special safety characteristics are identified by a  on schematics and in parts lists. Use of a substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire, and/or other hazards. The product's safety is under review continuously and new instructions are issued whenever appropriate. Prior to shipment from the factory, our products are strictly inspected to confirm they comply with the recognized product safety and electrical codes of the countries in which they are to be sold. However, in order to maintain such compliance, it is equally important to implement the following precautions when a set is being serviced.

Precautions during Servicing

- A.** Parts identified by the  symbol are critical for safety.
Replace only with part number specified.
- B.** In addition to safety, other parts and assemblies are specified for conformance with regulations applying to spurious radiation. These must also be replaced only with specified replacements.
Examples: RF converters, RF cables, noise blocking capacitors, and noise blocking filters, etc.
- C.** Use specified internal wiring. Note especially:
 - 1) Wires covered with PVC tubing
 - 2) Double insulated wires
 - 3) High voltage leads
- D.** Use specified insulating materials for hazardous live parts. Note especially:
 - 1) Insulation Tape
 - 2) PVC tubing
 - 3) Spacers
 - 4) Insulators for transistors.
- E.** When replacing AC primary side components (transformers, power cord, etc.), wrap ends of wires securely about the terminals before soldering.
- F.** Observe that the wires do not contact heat producing parts (heat sinks, oxide metal film resistors, fusible resistors, etc.)
- G.** Check that replaced wires do not contact sharp edged or pointed parts.
- H.** When a power cord has been replaced, check that 5~6 kg (11~13 lb) of force in any direction will not loosen it.
- I.** Also check areas surrounding repaired locations.
- J.** Use care that foreign objects (screws, solder droplets, etc.) do not remain inside the set.
- K.** When connecting or disconnecting the internal connectors, first, disconnect the AC plug from the AC supply outlet.
- L.** When installing parts or assembling the cabinet parts, be sure to use the proper screws and tighten certainly.

Safety Check after Servicing

Examine the area surrounding the repaired location for damage or deterioration. Observe that screws, parts and wires have been returned to original positions. Afterwards, perform the following tests and confirm the specified values in order to verify compliance with safety standards.

1. Clearance Distance

When replacing primary circuit components, confirm specified clearance distance (d) and (d') between soldered terminals, and between terminals and surrounding metallic parts. (See Fig. 1)

Table 1 : Ratings for selected area

AC Line Voltage	Clearance Distance (d), (d')
220 to 240 V	$\geq 3\text{mm}(d)$ $\geq 8\text{mm}(d')$

Note: This table is unofficial and for reference only. Be sure to confirm the precise values.

2. Leakage Current Test

Confirm the specified (or lower) leakage current between B (earth ground, power cord plug prongs) and externally exposed accessible parts (RF terminals, antenna terminals, video and audio input and output terminals, microphone jacks, earphone jacks, etc.).

Measuring Method : (Power ON)

Insert load Z between B (earth ground, power cord plug prongs) and exposed accessible parts. Use an AC voltmeter to measure across both terminals of load Z. See Fig. 2 and following table.




Fig. 1




Fig. 2

Table 2: Leakage current ratings for selected areas


AC Line Voltage	Load Z	Leakage Current (i)	One side of power cord plug prongs (B) to:
220 to 240 V	2kΩ RES. Connected in parallel	$i \leq 0.7\text{mA AC Peak}$ $i \leq 2\text{mA DC}$	RF or Antenna terminals
	50kΩ RES. Connected in parallel	$i \leq 0.7\text{mA AC Peak}$ $i \leq 2\text{mA DC}$	A/V Input, Output

Note: This table is unofficial and for reference only. Be sure to confirm the precise values.


STANDARD NOTES FOR SERVICING

Circuit Board Indications


1. The output pin of the 3 pin Regulator ICs is indicated as shown.



2. For other ICs, pin 1 and every fifth pin are indicated as shown.




3. The 1st pin of every male connector is indicated as shown.



Pb (Lead) Free Solder

Pb free mark will be found on PCBs which use Pb free solder. (Refer to figure.) For PCBs with Pb free mark, be sure to use Pb free solder. For PCBs without Pb free mark, use standard solder.



Pb free mark

How to Remove / Install Flat Pack-IC

1. Removal

With Hot-Air Flat Pack-IC Desoldering Machine:

1. Prepare the hot-air flat pack-IC desoldering machine, then apply hot air to the Flat Pack-IC (about 5 to 6 seconds). (Fig. S-1-1)




Fig. S-1-1

2. Remove the flat pack-IC with tweezers while applying the hot air.
3. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
4. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

CAUTION:

1. The Flat Pack-IC shape may differ by models. Use an appropriate hot-air flat pack-IC desoldering machine, whose shape matches that of the Flat Pack-IC.
2. Do not supply hot air to the chip parts around the flat pack-IC for over 6 seconds because damage to the chip parts may occur. Put masking tape around the flat pack-IC to protect other parts from damage. (Fig. S-1-2)
3. The flat pack-IC on the CBA is affixed with glue, so be careful not to break or damage the foil of each pin or the solder lands under the IC when removing it.






Fig. S-1-2

With Soldering Iron:

1. Using desoldering braid, remove the solder from all pins of the flat pack-IC. When you use solder flux which is applied to all pins of the flat pack-IC, you can remove it easily. (Fig. S-1-3)



2. Lift each lead of the flat pack-IC upward one by one, using a sharp pin or wire to which solder will not adhere (iron wire). When heating the pins, use a fine tip soldering iron or a hot air desoldering machine. (Fig. S-1-4)





3. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
4. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

With Iron Wire:



1. Using desoldering braid, remove the solder from all pins of the flat pack-IC. When you use solder flux which is applied to all pins of the flat pack-IC, you can remove it easily. (Fig. S-1-3)
2. Affix the wire to a workbench or solid mounting point, as shown in Fig. S-1-5.
3. While heating the pins using a fine tip soldering iron or hot air blower, pull up the wire as the solder melts so as to lift the IC leads from the CBA contact pads as shown in Fig. S-1-5.
4. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
5. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

Note: When using a soldering iron, care must be taken to ensure that the flat pack-IC is not being held by glue. When the flat pack-IC is removed from the CBA, handle it gently because it may be damaged if force is applied.



2. Installation

1. Using desoldering braid, remove the solder from the foil of each pin of the flat pack-IC on the CBA so you can install a replacement flat pack-IC more easily.
2. The "●" mark on the flat pack-IC indicates pin 1. (See Fig. S-1-7.) Be sure this mark matches the pin 1 on the PCB when positioning for installation. Then presolder the four corners of the flat pack-IC. (See Fig. S-1-8.)
3. Solder all pins of the flat pack-IC. Be sure that none of the pins have solder bridges.



Instructions for Handling Semi-conductors



Electrostatic breakdown of the semi-conductors may occur due to a potential difference caused by electrostatic charge during unpacking or repair work.

1. Ground for Human Body

Be sure to wear a grounding band (1 M Ω) that is properly grounded to remove any static electricity that may be charged on the body.

2. Ground for Workbench

Be sure to place a conductive sheet or copper plate with proper grounding (1 M Ω) on the workbench or other surface, where the semi-conductors are to be placed. Because the static electricity charge on clothing will not escape through the body grounding band, be careful to avoid contacting semi-conductors with your clothing.



CABINET DISASSEMBLY INSTRUCTIONS


Screw Torque Specification

Ref. No.	Part Number	Part Name	Tightening Torque
L7	GBHP3100	SCREW P-TIGHT (M3X10 BIND HEAD+BLK)	6±1 kgf-cm
L23	GBJS3060	SCREW S-TIGHT (M3X6 BIND HEAD+)	6±1 kgf-cm
L27	GBHS3080	SCREW S-TIGHT (M3X8 BIND HEAD+BLK)	6±1 kgf-cm
L45	FPH34100	DOUBLE SEMS SCREW (M4X10 + BLK)	6±1 kgf-cm
SSK1	1ESA34003	SCREW P-TIGHT (M4X14 BIND HEAD+BLK)	(approx. 10±1 kgf-cm)*

* For reference

1. Disassembly Flowchart

This flowchart indicates the disassembly steps for the cabinet parts and the CBA in order to gain access to items to be serviced. When reassembling, follow the steps in reverse order. Bend, route and dress the cables as they were.



2. Disassembly Method

Step/ Loc. No.	Part	Fig. No.	Removal	Note
[1]	Stand Assembly	D1	3(S-1), Stand Neck	---
[2]	Rear Cover	D1	8(S-2), 2(S-3), (S-4)	---
[3]	Power Supply CBA	D2 D5	4(S-5), CN101, CN102, CN103, CN104, CN105	---
[4]	Digital Main CBA Unit	D2 D5	4(S-6), CN9, CN20, CN21, Jack Holder	---
[5]	Speaker	D3	-----	---
[6]	Function CBA Unit	D3	2(S-7), Leading Edge Cover, Shield Plate	1

Step/ Loc. No.	Part	Fig. No.	Removal	Note
[7]	LCD Panel Assembly	D3	-----	---
[8]	X-PCB Cover	D4	2(S-8)	2
[9]	Front Cabinet	D4	2(S-9), Decoration Plate	1

↓ ↓ ↓ ↓ ↓
 (1) (2) (3) (4) (5)

Note:

- (1) Order of steps in procedure. When reassembling, follow the steps in reverse order. These numbers are also used as the Identification (location) No. of parts in figures.
- (2) Parts to be removed or installed.
- (3) Fig. No. showing procedure of part location.
- (4) Identification of parts to be removed, unhooked, unlocked, released, unplugged, unclamped, or desoldered.
N = Nut, L = Locking Tab, S = Screw, H = Hex Screw, CN = Connector
e.g. 2(S-2) = two Screws of (S-2),
2(L-2) = two Locking Tabs of (L-2)
- (5) Refer to the following "Reference Notes in the Table."


Precautions concerning the LCD Panel Assembly:



1. When you disassemble/re-assemble the Front Cabinet or Function CBA Unit

- Be careful not to break the hooks. If you pull with too much force, the hooks may be damaged.
- When disassembling, first detach the hooks on each end on the bottom side, then detach the remaining hooks.
- Make sure the hooks are securely in place when assembling.
- Be careful not to scratch the display panel when assembling.
- Make sure the Function CBA Unit and Shield Plate are securely in place when re-assembling.
- The screw tightening torque must be 5.2lbf-in (6kgf-cm).
- After reassembling the Front Cabinet or Function CBA Unit, check the operational sensitivity of the touch sensor to make sure it functions normally.
- Make sure to replace the Decoration Plate to a new one when replacing the Front Cabinet.

2. When you disassemble/re-assemble the X-PCB Cover

- Be careful not to break the hooks. If you pull with too much force, the hooks may be damaged.
- When disassembling, first hold the top and bottom of the X-PCB Cover on both ends and then moving toward the center, lift up the top side to detach the hooks.
- When assembling be careful not to damage the X-PCB Board or the COF(Chip On Film).
- Make sure the hooks are securely in place when re-assembling.
- The screw tightening torque must be 5.2lbf-in (6kgf-cm).





*1: Make sure to read all the precautions on page 4-1 when you disassemble/re-assemble the Function CBA Unit.




Fig. D4

***1: Make sure to read all the precautions on page 4-1 when you disassemble/re-assemble the Front Cabinet.**

***2: Make sure to read all the precautions on page 4-2 when you disassemble/re-assemble the X-PCB Cover.**

TV Cable Wiring Diagram




Fig. D5

ELECTRICAL ADJUSTMENT INSTRUCTIONS

General Note: “CBA” is abbreviation for “Circuit Board Assembly.”

Note: Electrical adjustments are required after replacing circuit components and certain mechanical parts. It is important to perform these adjustments only after all repairs and replacements have been completed. Also, do not attempt these adjustments unless the proper equipment is available.

Test Equipment Required


1. Remote control unit
2. Color Analyzer, CA-310 (KONICA MINOLTA Luminance meter) or measuring instrument as good as CA-310.

How to set up the service mode:

Service mode:

1. Turn the power on.
2. Press [MENU], [1], [1], [4] and [7] buttons on the remote control unit in this order to enter the service mode. The Factory Setting menu appears in the screen.

Example:




The White Balance Adjustment should be performed when replacing the LCD Module or Digital Main CBA Unit.

White Balance Adjustment


Purpose: To mix red and blue beams correctly for pure white.

Symptom of Misadjustment: White becomes bluish or reddish.

1. Operate the unit for more than 60 minutes.
2. Input the White Raster (70%=70IRE, 40%=40IRE).



3. Enter the service mode.
4. Press [2] button on the remote control unit to display the “GENERAL SETTING” menu.
5. Select “W/B ADJUST” and press [OK] button to display the “W/B ADJUST” menu.
6. Select a color mode (“R-GAIN”, “B-GAIN”, “R-OFFSET” or “B-OFFSET”).
7. Set the color analyzer at the CHROMA mode and zero point calibration. Bring the optical receptor pointing at the center of the LCD-Panel.



Note: The optical receptor must be set perpendicularly to the LCD Panel surface.

8. In each color mode, press [◀] or [▶] button to adjust the color temperature becomes 12000°K ($x=0.272$ / $y=0.278 \pm 0.008$).
9. Select “COPY ALL” and press [OK] button.
10. To cancel or to exit from the White Balance Adjustment, press [EXIT] button.

HOW TO INITIALIZE THE LCD TV

The purpose of initialization is to place the set in a new out of box condition. The customer will be prompted to select a language and program channels after the set has been initialized.

To put the program back at the factory-default, initialize the LCD TV using the following procedure.

1. Turn the power on.
2. Enter the service mode. (Refer to page 5-1.)
 - To cancel the service mode, press [EXIT] button on the remote control unit.
3. Select "Fac Reset" and [OK] button on the remote control unit.
The TV set will go off and turn back on automatically when initialization completes.

FIRMWARE RENEWAL MODE

Equipment Required

- a. USB storage device
- b. Remote Control Unit

Firmware Update Procedure

[Preparation]

1. Prepare USB storage device.
2. Copy F/W-file to USB storage device.
Note: Make sure to use the blank USB Storage.
3. Make sure that the F/W-file's name is "bin_6m182_VG.bin".

[Update procedure]

1. Turn the power on.
2. Insert USB storage device with F/W to TV set.
3. Press the [MENU] button on the remote control unit to display Menu.
4. Select "OPTION".
5. Select "Software Update (USB)" and press [OK] button.
The message "Are you sure?" will appear in the screen.
6. Press [◀] button to select "YES".
7. Updating starts.
Note: Do not turn off the TV set and do not remove the USB storage device while this procedure.
8. The TV set will go off and turn back on automatically when update completes.


[Confirmation of update]

1. Enter the service mode. (Refer to page 5-1.)
2. Shift the cursor down to "SW INFORMATION" and then press the [OK] button.
3. Check the "BUILD TIME" section.


TROUBLESHOOTING

[Power Supply Section]


FLOW CHART NO.1




FLOW CHART NO.2



FLOW CHART NO.3



FLOW CHART NO.4



FLOW CHART NO.5

VLED(+21V) is not output.

Is approximately +21V voltage supplied to the cathode of D501(D502,D510)?

No → Check D501, D502, D504,D510,C502, C503, C504 and their periphery circuit. Repair it if defective.

Yes

Check if there is any leak or short-circuit on the load circuit. Repair it if defective.

FLOW CHART NO.6

AMP+13V is not output.

Is approximately +15V voltage supplied to the cathode of D401(D402,D403)?

No → Check D401, D402, D403, C402, C403,C407 and their periphery circuit. Repair it if defective.

Yes

Check if there is any leak or short-circuit on the load circuit. Repair it if defective.

FLOW CHART NO.7

+5V is not output.

Is approximately +21V voltage supplied to PIN(8) of IC501?

No → See FLOW CHART NO.5 <VLED(+21V) is not output. [Power Supply Section]>

Yes

Check D507,IC501and their periphery circuit. Repair it if defective.

Yes → Check F501 and their periphery circuit. Repair it if defective.

FLOW CHART NO.8

STB+5V is not output.

Is approximately +9V voltage supplied to Drain of Q403?

No → See FLOW CHART NO.6 <AMP+13V is not output. [Power Supply Section]>

Yes

Check IC402,Q403 and their periphery circuit. Repair it if defective.

Yes → Check R410,R416,R417,R430,R431,R432 and their periphery circuit. Repair it if defective.

FLOW CHART NO.9

+12V is not output.

Is approximately +15V voltage supplied to Drain of Q701?

No → See FLOW CHART NO.6 <AMP+13V is not output. [Power Supply Section]>


Yes

Check IC701,Q701,Q702,Q703 and their periphery circuit. Repair it if defective.


Yes → Check R710 and their periphery circuit. Repair it if defective.

[Video Signal Section]


FLOW CHART NO.1



FLOW CHART NO.2




FLOW CHART NO.3




[Audio Signal Section]


FLOW CHART NO.1




Video / Audio Block Diagram



Digital Signal Process Block Diagram



LED Backlight Drive Block Diagram



Power Supply Block Diagram

CAUTION !


For continued protection against fire hazard, replace only with the same type fuse.

CAUTION !

Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit. If Main Fuse (F602) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.

NOTE:

The voltage for parts in hot circuit is measured using hot GND as a common terminal.



SCHEMATIC DIAGRAMS / CBA AND TEST POINTS

Standard Notes

WARNING

Many electrical and mechanical parts in this chassis have special characteristics. These characteristics often pass unnoticed and the protection afforded by them cannot necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts that have these special safety characteristics are identified in this manual and its supplements; electrical components having such features are identified by the mark “▲” in the schematic diagram and the parts list. Before replacing any of these components, read the parts list in this manual carefully. The use of substitute replacement parts that do not have the same safety characteristics as specified in the parts list may create shock, fire, or other hazards.

Notes:

1. Do not use the part number shown on these drawings for ordering. The correct part number is shown in the parts list, and may be slightly different or amended since these drawings were prepared.
2. All resistance values are indicated in ohms ($K = 10^3$, $M = 10^6$).
3. Resistor wattages are 1/4W or 1/6W unless otherwise specified.
4. All capacitance values are indicated in μF ($P = 10^{-6} \mu F$).
5. All voltages are DC voltages unless otherwise specified.
6. This schematic diagrams are masterized version that should cover the entire PL13.21 chassis models. Thus some parts in detail illustrated on this schematic diagrams may vary depend on the model within the PL13.21 chassis.
Please refer to the parts lists for each models.
7. The Circuit Board layout illustrated on this service manual is the latest version for this chassis at the moment of making this service manual.
Depend on the mass production date of each model, the actual layout of each Board may differ slightly from this version.

LIST OF CAUTION, NOTES, AND SYMBOLS USED IN THE SCHEMATIC DIAGRAMS ON THE FOLLOWING PAGES:

1. CAUTION:

FOR CONTINUED PROTECTION AGAINST FIRE HAZARD, REPLACE ONLY WITH THE SAME TYPE FUSE.

2. CAUTION:

Fixed Voltage (or Auto voltage selectable) power supply circuit is used in this unit.


If Main Fuse (F601) is blown, first check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.

3. Note:

1. Do not use the part number shown on the drawings for ordering. The correct part number is shown in the parts list, and may be slightly different or amended since the drawings were prepared.
2. To maintain original function and reliability of repaired units, use only original replacement parts which are listed with their part numbers in the parts list section of the service manual.

4. Voltage indications on the schematics are as shown below:

Plug the TV power cord into a standard AC outlet.:




5. How to read converged lines

1-D3
 ↑ Distinction Area
 ↑ Line Number
 (1 to 3 digits)

Examples:

1. "1-D3" means that line number "1" goes to the line number "1" of the area "D3".
2. "1-B1" means that line number "1" goes to the line number "1" of the area "B1".



6. Test Point Information


- ⊙ : Indicates a test point with a jumper wire across a hole in the PCB.
- : Used to indicate a test point with a component lead on foil side.
- ⊘ : Used to indicate a test point with no test pin.
- : Used to indicate a test point with a test pin.

The reference number of parts on Schematic Diagrams/CBA can be retrieved by application search function.

Power Supply CBA Bottom View

CAUTION !

Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit. If Main Fuse (F602) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.




CAUTION ! : For continued protection against risk of fire, replace only with same type 2.5A, 250V fuse.
ATTENTION : Utiliser un fusible de rechange de même type de 2.5A, 250V.


Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used when repairing. Also, in order to have the ability to increase the input slowly, when troubleshooting this type of power supply circuit, a variable isolation transformer is required.

NOTE:

The voltage for parts in hot circuit is measured using hot GND as a common terminal.




WIRING DIAGRAMS



Packing

Some Ref. Numbers are not in sequence.



PARTS LIST [29PFL4508/F4 (Serial No.: ME1)]

Mechanical Parts

PRODUCT SAFETY NOTE: Products marked with a ▲ have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

NOTE: Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
A3	REAR COVER A30F0PT	1EM128413
A11	STAND NECK A31M2UT	1EM228000A
A13	JACK HOLDER A30F0PT	1EM335081
A15▲	RATING LABEL A30MZZT	-----
A16	LOGO LABEL A30M0PT	-----
A20	LEADING EDGE COVER A31M2UT	1EM228001
AC601▲	AC CORD W/O A GND WIRE TIS/1740/ ANTITRACKIN	WAY172ZHN003
B17	WALL MOUNT BRACKET A11N0UH	1EM434637
B18	WALL MOUNT COVER A2170UT	1EM332137
CL9	SPK WIRE ASSEMBLY 4P/240&50MM/ YL&BK&RD	WX1A30MOC105
CL20	IR_KEY WIRE ASSEMBLY 6P8P/100MM/ RED&BLK	WX1A30MOC104
CL102	+13AMP WIRE ASSEMBLY 4P/95MM/ RED&BLCK	WX1A30MOC103
CL103	BL WIRE ASSEMBLY 6P/95MM/26AWG/BK	WX1A30MOC102
CL104	POWER WIRE ASSEMBLY 10P/95MM/ RED&BLK	WX1A30MOC101
L7	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L23	SCREW S-TIGHT M3X6 BIND HEAD+	GBJS3060
L27	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L45	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
SA1	STAND BASE ASSEMBLY A31M2UT	1ESA34000
SP3801	SPEAKER MAGNETIC 8Ω/8W S0310F14	DS08110XQ002
SP3802	SPEAKER MAGNETIC 8Ω/8W S0310F14	DS08110XQ002
SSK1	STAND SCREW KIT A31M2UT	1ESA34003
PACKING		
S1	CARTON A30MZZT	2EMC00028
S3	STYROFOAM TOP A31M2UT	1EM030032
S4	STYROFOAM BOTTOM A31M2UT	1EM030033
S6	SET BAG A1AF8UT	1EM334734
S7	SERIAL NO. LABEL A01PBUH	-----
S10	PAD(730X150X20) A31M0UT	1EM440257
ACCESSORY		
X1	POLYETHYLENE BAG HDPE 180X340XT0.03	1EM435579
X2▲	OWNERS MANUAL A30MZZT	2EMN00019
X3	REMOTE CONTROL UNIT YKF335-003	URMT41JHG001
X4	BATTERY R03-B500/01S	XB0M451CZB01
X6	QUICK START GUIDE A30MZZT	2EMN00022

LCD PANEL ASSEMBLY

Ref. No.	Description	Part No.
LCD1▲	LCD PANEL ASSEMBLY	U3AM0PA
	Consists of the following	
A1	FRONT CABINET A31M2UT	1EM030005
A4	X PCB COVER A31M0UT	1EM228008
A5	DECORATION PLATE A31M2UT	1EM228002
B12	SHIELD PLATE A31M2UT	1EM334002
CL12	LVDS WIRE 29W CFL2616001	WX1A33M1C106
L7	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
	LCD MODULE 29INCH	-----

Electrical Parts

PRODUCT SAFETY NOTE: Products marked with a ▲ have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25% D.....±0.5% F.....±1%
 G.....±2% J.....±5% K.....±10%
 M.....±20% N.....±30% Z.....+80/-20%

DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	UPBMACVT033

FUNCTION CBA UNIT

Ref. No.	Description	Part No.
	FUNCTION CBA UNIT	UPB000CVT013

POWER SUPPLY CBA

Ref. No.	Description	Part No.
	POWER SUPPLY CBA	A30MAMPW-001
CAPACITORS		
C303	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C402	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C403	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C404	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C405	ELECTROLYTIC CAP. 100µF/10V M(105C)	CE1AMASTH101
C407	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C501	CERAMIC CAP. 2200pF/1kV	CCD3AKA0R222
C502	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C503	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C504	ELECTROLYTIC CAP. 470µF/25V M(105C)	CE1EMASTH471
C506	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C507	CHIP CERAMIC CAP.(1608) F Z 0.22µF/50V	CHD1JZ30F224
C508	CHIP CERAMIC CAP.(1608) B K 0.01µF/50V	CHD1JK30B103
C511	CHIP CERAMIC CAP. B K 10µF/10V	CHE1AK30B106
C512	CAP ELE 105 330µF/10V/M/105	CED3310S6009
C515	CAP CHIP 3216 B K 10µF/25V	CA1E106MR082
C516	CAP CHIP 3216 B K 10µF/25V	CA1E106MR082
C517	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C518	CHIP CERAMIC CAP. CH J 150pF/50V	CHD1JJ3CH151
C601▲	CAP METALLIZED FILM 0.47µF/250V/K/MPX	CTA474EUR001
C605▲	CAP CERAMIC 470pF/250V KX	CA2E471MR100
C606	CAP ELE 82µF/450V/M/105	CV9E820M02W1
C607	CAP ELE 82µF/450V/M/105	CV9E820M02W1
C608	CERAMIC CAP. 2200pF/1kV	CCD3AKA0R222
C609	CERAMIC CAP. 150pF/2kV	CA3D151PAN04
C611	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C612	CHIP CERAMIC CAP. B K 1200pF/50V	CHD1JK30B122
C613	CHIP CERAMIC CAP. CH J 150pF/50V	CHD1JJ3CH151
C614	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032

Ref. No.	Description	Part No.
C615	CAP CERAMIC HV 1000pF/1kV B K	CA3A102TE006
C617	CAP CHIP 3216 B K 10µF/25V	CA1E106MR082
C621▲	CAP CERAMIC 470pF/250V KX	CA2E471MR100
C622	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C703	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C704	CAP CHIP 1608 K/X7R/0.1µF/50V	CHD104EYA032
C1001	CAP ELECTROLYTIC 330µF/25V M/105	CE1EMASTH331
C1002	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C1003	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C1005	ELECTROLYTIC CAP SK100M470YZZP50R	CE2AMASTH470
C1006	ELECTROLYTIC CAP SK100M470YZZP50R	CE2AMASTH470
C1007	CHIP CERAMIC CAP.(3216) X7R K 1.0µF/100V	CA2A105MR080
C1008	CHIP CERAMIC CAP.(3216) X7R K 1.0µF/100V	CA2A105MR080
C1009	CHIP CERAMIC CAP.(3216) X7R K 1.0µF/100V	CA2A105MR080
C1010	CHIP CERAMIC CAP.(1608) B K 1000pF/50V	CHD1JK30B102
C1012	CHIP CERAMIC CAP.(1608) B K 4.7µF/6.3V	CHD0KK30B475
C1013	CHIP CERAMIC CAP.(1608) F Z 0.1µF/50V	CHD1JZ30F104
C1014	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C1017	CHIP CERAMIC CAP.(1608) B K 1000pF/50V	CHD1JK30B102
C1018	CHIP CERAMIC CAP.(1608) C0G/J/220pF/100V	CA2A221MR133
CONNECTORS		
CN101▲	CONNECTOR S2P3-VH (LF)(SN)	JCVHC02JG002
CN102	CONNECTOR PRINT OSU JS-1125-04(K)	J3JT04CHY001
CN103	PH CONNECTOR TOP 6P B6B-PH-K-S (LF)(SN)	J3PHC06JG029
CN104	PH CONNECTOR TOP 10P B10B-PH-K-S(LF)(SN)	J3PHC10JG029
CN105	FPC/FFC CONNECTOR IMSA-9615S-07A-PP-A	JC96J07ER007
DIODES		
D301	DIODE SWITCHING HSC119 TRF -E	QD1Z00HSC119
D401	DIODE SCHOTTKY SB3A0BH	NDWZ000SB3A0
D402	DIODE SCHOTTKY SB3A0BH	NDWZ000SB3A0
D403	DIODE SCHOTTKY SB3A0BH	NDWZ000SB3A0
D501	DIODE SHOTTKY SB3200BR	NDWZ3200D027
D502	DIODE SHOTTKY SB3200BR	NDWZ3200D027
D504	DIODE ZENER 1ZB27BB	NDWZ0001ZB27
D505	DIODE SCHOTTKY SB230BD	NDWZ000SB230
D506	DIODE ZENER 1N4741A B0 11V	NDLZ01N4741A
D507	ZENER DIODE MM5Z18B	ND1B0MM5Z18B
D508	DIODE SCHOTTKY SB230BD	NDWZ000SB230
D510	DIODE SHOTTKY SB3200BR	NDWZ3200D027
D601▲	DIODE RECTIFIEY 1N5408BH	NDL2001N5408
D602▲	DIODE RECTIFIEY 1N5408BH	NDL2001N5408
D603▲	DIODE RECTIFIEY 1N5408BH	NDL2001N5408
D604▲	DIODE RECTIFIEY 1N5408BH	NDL2001N5408
D605	DIODE FAST RECOVERY RS1JTB	ND1Z0RS1JTB
D606	RECTIFIER DIODE 1N4007	NDQZ001N4007
D608	DIODE FAST RECOVERY RS1GJTB	ND1Z0RS1GJTB
D609	ZENER DIODE SMD TFZGTR27B	QD1B000TFZ27
D610	DIODE FAST RECOVERY RS1GJTB	ND1Z0RS1GJTB
D612	DIODE ZENER 1ZB36BB	NDWZ0001ZB36
D613	ZENER DIODE SMD TFZGTR27B	QD1B000TFZ27
D615	DIODE FAST RECOVERY RS1JTB	ND1Z0RS1JTB
D616	RECTIFIER DIODE 1N4007	NDQZ001N4007
D618	ZENER DIODE EDZTE61 20B	QD1B000EDZ20
D622	ZENER DIODE SMD TFZGTR39B	QD1B000TFZ39
D623	ZENER DIODE SMD TFZGTR39B	QD1B000TFZ39
D1001	DIODE SCHOTTKY SB2A0BD	NDWZ000SB2A0
D1002	DIODE SWITCHING HSC119 TRF -E	QD1Z00HSC119

Ref. No.	Description	Part No.
ICS		
IC301	IC SHUNT REGULATOR SN431A-AT	NQSZ00SN431A
IC402	IC SHUNT REGULATOR SN431A-AT	NQSZ00SN431A
IC501	IC DCDC CONVERTER MP2482DN-LF-Z/ SOIC8/	NSCA0T09M005
IC601▲	IC PHOTOCOUPLER TLP781F(D4-FUNBLL F)	QPEL781FBLLF
IC602	IC SWITCHING FA8A00N/SOP-8/8PIN	QSCA0T0FD010
IC701	IC SHUNT REGULATOR SN431A-AT	NQSZ00SN431A
IC1001	IC LED BACKLIGHT CONTROLLER HA7219PB/SOP/14PIN	NSCA0T00H005
COILS		
L501	COIL POWER INDUCTORS DIP RCR1010NP-330M/33UH	LLF3300SF012
L601▲	COIL LINE FILTER JLB20154/18MH	LLEG0Z0XB022
L1001	POWER INDUCTORS CWKBPN-220K	LLF2200KV002
TRANSISTORS		
Q301	CHIP TRANSISTOR KTC3875S-YRTK/P	NQ1YKTC3875S
Q403	FET MOS FDD5612Z	NF2ZFDD56120
Q601	FET MOS TK5A65D(STA4 A Q)	QFEZTK5A65DQ
Q602	FET MOS TK3P50D RQ(S)	QF2Z0TK3P50D
Q603	FET MOS 2SK3471 TE12L F	QF1Z02SK3471
Q701	FET MOS FDD5612Z	NF2ZFDD56120
Q702	CHIP TRANSISTOR KTA1504S-YRTK/P	NQ1YKTA1504S
Q703	CHIP TRANSISTOR KTC3875S-YRTK/P	NQ1YKTC3875S
Q1001	FET MOS SMD AP18T10AGH-HF	NF2Z18T10AGH
RESISTORS		
R301	RES CHIP 3216 1/4W J 330 Ω	RRX4331YF004
R302	RES CHIP 3216 1/4W J 330 Ω	RRX4331YF004
R303	RES CHIP 1608 1/10W F 2.20k Ω	RTW2201HH008
R305	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R306	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R307	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R308	RES CHIP 1608 1/10W F 2.70k Ω	RTW2701HH008
R311	RES CHIP 1608 1/10W F 22.0k Ω	RTW2202HH008
R312	RES CHIP 1608 1/10W F 2.70k Ω	RTW2701HH008
R313	RES CHIP 1608 1/10W F 2.70k Ω	RTW2701HH008
R314	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R404	RES CHIP 1608 1/10W F 1.00k Ω	RTW1001HH008
R407	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R409	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R410	METALOXIDE RES 2W J 56 Ω	RNJ560PAK002
R416	RES CHIP 3216 1/4W J 16 Ω	RRX4160HH034
R417	RES CHIP 3216 1/4W J 16 Ω	RRX4160HH034
R426	RES CHIP 1608 1/10W 0 Ω	RRXA000HH014
R430	RES CHIP 3216 1/4W J 16 Ω	RRX4160HH034
R431	RES CHIP 3216 1/4W J 16 Ω	RRX4160HH034
R432	METALOXIDE RES 2W J 56Ω	RNJ560PAK002
R503	RES CHIP 1608 1/10W J 100k Ω	RRXA104HH013
R504	RES CHIP 3216 1/4W J 100k Ω	RRX4104HH034
R505	RES CHIP 1608 1/10W 0 Ω	RRXA000HH014
R506	RES CHIP 1608 1/10W F 1.50k Ω	RTW1501HH008
R507	CHIP RES. 1/10W F 39k Ω	RRXAFR5H3902
R508	CHIP RES. 1/10W F 3k Ω	RRXAFR5H3001
R509	RES CHIP 1608 1/10W F 4.70k Ω	RTW4701YF002
R510	RES CHIP 1608 1/10W J 10 Ω	RRXA100HH013
R511	RES CHIP 3216 1/4W 0 Ω	RRX4000HH036
R512	RES CHIP 3216 1/4W 0 Ω	RRX4000HH036
R513	RES CHIP 1608 1/10W F 100k Ω	RTW1003HH008
R602	RES CEMENT 5W/J1.2 Ω	RWJ1R2PAK007
R603	METAL OXIDE FILM RES. 2W J 20k Ω	RN02203ZU001
R604	METAL OXIDE FILM RES. 2W J 20k Ω	RN02203ZU001
R605	RES CHIP 3216 1/4W J 270 Ω	RRX4271YF004
R606	RES CHIP 3216 1/4W J 47 Ω	RRX4470YF004
R610	RES CHIP 3216 1/3W J 0.15 Ω	RRJR15RYL008
R611	RES CHIP 3216 1/3W J 0.15 Ω	RRJR15RYL008
R612	RES CHIP 3216 1/3W J 0.15 Ω	RRJR15RYL008
R613	RES CHIP 3216 1/3W J 0.15 Ω	RRJR15RYL008
R615	RES CHIP 3216 1/4W J 6.8k Ω	RRX4682YF004

Ref. No.	Description	Part No.
R617	RES CHIP 1608 1/10W J 3.3k Ω	RRXA332HH013
R621	RES CHIP 3216 1/4W J 10k Ω	RRX4103HH034
R622	RES CHIP 3216 1/4W J 10k Ω	RRX4103HH034
R623	RES CHIP 3216 1/4W J 1.0M Ω	RRX4105HH034
R624	RES CHIP 3216 1/4W J 1.0M Ω	RRX4105HH034
R625	RES CHIP 3216 1/4W J 1.0M Ω	RRX4105HH034
R626	RES CHIP 3216 1/4W J 620k Ω	RRX4624HH034
R627	METALOXIDE RES 2W J 100Ω	RNJ101PAK002
R628	RES CHIP 1608 1/10W J 1.5M Ω	RRXA155HH013
R701	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R702	RES CHIP 1608 1/10W J 1.8k Ω	RRXA182HH013
R703	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R704	RES CHIP 1608 1/10W F 2.70k Ω	RTW2701HH008
R705	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R706	RES CHIP 1608 1/10W 0 Ω	RRXA000HH014
R707	RES CHIP 1608 1/10W F 10.0k Ω	RTW1002HH008
R708	CHIP RES. 1/10W F 39k Ω	RRXAFR5H3902
R709	CHIP RES. 1/10W F 3k Ω	RRXAFR5H3001
R710	METAL OXIDE FILM RES. 2W J 0.47 Ω	RN02R47ZU001
R711	RES CHIP 1608 1/10W F 22.0k Ω	RTW2202HH008
R1001	RES CHIP 1608 1/10W J 240 Ω	RRXA241HH013
R1002	RES CHIP 1608 1/10W J 240 Ω	RRXA241HH013
R1003	RES CHIP 1608 1/10W J 1.0k Ω	RRXA102HH013
R1004	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R1005	RES CHIP 1608 1/10W J 100k Ω	RRXA104HH013
R1006	RES CHIP 1608 1/10W J 10k Ω	RRXA103HH013
R1007	RES CHIP 1608 1/10W J 100k Ω	RRXA104HH013
R1008	RES CHIP 1608 1/10W J 10 Ω	RRXA100HH013
R1009	RES CHIP 1608 1/10W J 200 Ω	RRXA201HH013
R1010	RES CHIP 1608 1/10W F 100 Ω	RTW1000HH008
R1011	RES CHIP 1608 1/10W F 560k Ω	RTW5603HH008
R1012	RES CHIP 1608 1/10W F 510k Ω	RTW5103HH008
R1013	RES CHIP 1608 1/10W F 27.0k Ω	RTW2702HH008
R1014	RES CHIP 1608 1/10W F 100k Ω	RTW1003HH008
R1015	RES CHIP 1608 1/10W F 1.80k Ω	RTW1801HH008
R1016	RES CHIP 1608 1/10W F 6.20k Ω	RTW6201HH008
R1017	RES CHIP 1608 1/10W 0 Ω	RRXA000HH014
R1021	RES CHIP 1608 1/10W 0 Ω	RRXA000HH014
R1022	RES CHIP 3216 1/3W J 0.091 Ω	RRJ91MRYL008
R1023	RES CHIP 3216 1/3W J 0.091 Ω	RRJ91MRYL008
R1025	RES CHIP 1608 1/10W J 47 Ω	RRXA470YF002
R1026	RES CHIP 3216 1/4W J 10 Ω	RRX4100HH034
MISCELLANEOUS		
B19	HEAT SINK PNI A11N5UH	1EM435557A
BC605	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC606	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
F501	CHIP FUSE FHC16252ABTP	PDDAEC0KE252
F602▲	FUSE TIME RAG 2010T2.5A1	PDG21B0W3252
JS603	WIRE CP STP-S-0.50	XZ40F0REN001
JS604	WIRE CP STP-S-0.50	XZ40F0REN001
JS609	WIRE CP STP-S-0.50	XZ40F0REN001
JS1001	WIRE CP STP-S-0.50	XZ40F0REN001
L35	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	VARISTOR 10D 471K SVR	NVQZVR10D471
T601▲	TRANS POWER BCK-28GZ	LTT2PEMEK060

REVISION HISTORY

Chassis PL13.21

- 2013/04/19 29PFL4508/F4 (Serial No.: ME1) added

COMPARISON LIST OF MODEL NAMES

Chassis PL13.21

29PFL4508/F4 (ME1) A30MZZT