LCD-TV

Chassis	Model
GBP23MUS	LNT2353H
	LNT2354H
GBP26MUS	LNT2653H
GBP37MUS	LNT3753H

SERVICE Manual

LCD TV

Fashion Feature

- RF, 2-HDMI, DVI-D, Component, AV, S-Video
- Brightness : 450cd/㎡
- Contrast Ratio : 4000:1
- Response time : 8ms
- Dynamic contrast
- PIP (on PC only)

Copyright

©2007 by Samsung Electronics Co., Ltd.

All rights reserved.

This manual may not, in whole or in part, be copied, photocopied, reproduced, translated, or converted to any electronic or machine readable form without prior written permission of Samsung Electronics Co., Ltd.

LNT2353H / LNT2354H / LNT2653H Service Manual

First edition Oct 2007.

Printed in Korea.

Trademarks

Samsung is the registered trademark of Samsung Electronics Co., Ltd.

LNT2353H / LNT2354H / LNT2653H and MacMaster Cable Adapter are trademarks of Samsung Electronics Co., Ltd.

Macintosh, Power Macintosh are trademarks of Apple Computer, Inc.

All other trademarks are the property of their respective owners.

Contents

1 **Precautions** **1-1**

1-1 Safety Precautions 1-1

1-2 Servicing Precautions 1-2

1-3 Electrostatically Sensitive Devices (ESD) Precautions 1-2

1-4 Installation Precautions 1-3

2 **Product specifications** **2-1**

2-1 Fashion Feature 2-1

2-2 Specifications 2-2

2-3 Option Specification 2-5

3 **Alignments and Adjustments** **3-1**

3-1 General Alignment Instuction 3-1

3-2 Factory Mode Adjustments 3-2

3-3 White Balance - Calibration 3-9

3-4 White Ratio (Balance) Adjustment 3-10

3-5 Servicing Information 3-11

4 **Troubleshooting** **4-1**

4-1 No Power 4-1

4-2 No Video (Analog PC Signal) 4-2

4-3 No Video (HDMI - Digital Signal) 4-4

4-4 No Picture (Tuner_CVBS) 4-6

4-5 No Picture (Tuner DTV TS) 4-8

4-6 No Picture(Video CVBS) 4-10

4-7 No Picture (S-Video Y/C) 4-11

4-8 No Picture(Component1, 2 : 480i, 480p, 720p, 1080i[Y, Pb, Pr]) 4-13

4-9 No Sound 4-15

5 **Exploded View and Parts List** **5-1**

5-1 LNT2353H/LNT2354H Exploded View 5-1

5-2 LNT2353H/LNT2354H Parts list 5-2

5-3 LNT2653H Exploded View 5-3

5-4 LNT2653H Parts list 5-4

6 **Electrical Parts List** **6-1**

6-1 LNT2353HX/LNT2354HX Parts List 6-1

6-2 LNT2653HX Parts List 6-23

7 **Block Diagram** **7-1**

Contents

8 Wiring Diagram 8-1

8-1 Wiring Diagram 8-1

9 Schematic Diagrams 9-1

10 Operating Instructions and Installation 10-1

10-1 Front 10-1

10-2 Connection Panel 10-2

10-3 Remote Control 10-3

11 Disassembly and Reassembly 11-1

11-1 Disassembly 11-1

11-2 Reassembly 11-5

12 Schematic Diagram 12-1

12-1 Main PCB Diagram 12-1

12-2 Power PCB Layout 23" 12-2

12-3 Power PCB Layout 26" 12-3

13 Circuit Descriptions 13-1

13-1 Block description 13-1

14 Reference Infomation 14-1

14-1 Technical Terms 14-1

14-2 Pin Assignments 14-4

14-3 Timing Chart 14-6

14-4 Panel Description 14-10

GSPN(Global Service Partner Network)

Area	Web Site
North America	http://service.samsungportal.com
Latin America	http://latin.samsungportal.com
CIS	http://cis.samsungportal.com
Europe	http://europe.samsungportal.com
China	http://china.samsungportal.com
Asia	http://asia.samsungportal.com
Mideast & Africa	http://mea.samsungportal.com

This Service Manual is a property of Samsung Electronics Co.,Ltd.
Any unauthorized use of Manual can be punished under applicable International and/or domestic law.

©2007 Samsung Electronics Co.,Ltd.
All rights reserved.

Printed in Korea
P/N : BN82-00197A-00

3 Alignments and Adjustments

3-1 General Alignment Instuction

1. Usually, a color LCD-TV needs only slight touch-up adjustment upon installation.
   Check the basic characteristics such as height, horizontal and vertical sync.
2. Use the specified test equipment or its equivalent.
3. Correct impedance matching is essential.
4. Avoid overload. Excessive signal from a sweep generator might overload the front-end
   of the TV. When inserting signal markers, do not allow the marker generator to distort test result.
5. Connect the TV only to an AC power source with voltage and frequency as specified on
   the backcover nameplate.
6. Do not attempt to connect or disconnect any wire while the TV is turned on. Make sure
   that the power cord is disconnected before replacing any parts.
7. To protect aganist shock hazard, use an isolation transformer.

3-2 Factory Mode Adjustments

3-2-1 Entering Factory Mode

To enter 'Service Mode' Press the remote -control keys in this sequence :

- If you do not have Factory remote - control

Power OFF → MUTE → 1 → 8 → 2 → Power On

3-2-2 How to Access Service Mode

¡áUsing the Customer Remote

1.Turn the power off and set to stand-by mode

2.Press the remote buttons in this order; POWER OFF-MUTE-1-8-2-POWER ON to turn the set on.

3.The set turns on and enters service mode.

4.Press the Power button to exit and store data in memory.

¡ØIf you fail to enter service mode, repeat steps 1 and 2 above.

5.Initial SERVICE MODE DISPLAY State

1.Calibration 2.Option Byte 3.White Balance 4.W/B Movie 5.Calibration Target 6.Calibration Value 7.MST3388 8.X242 9.X242 NTSC 10.FBE2 11.Sound 12.Dynamic Contrast 13.Checksum 0x0000 14.Reset	T-JSMNAUS0-1000 T-JSMNAUS5-1000 ACL 28.16.4.1 RFS T-JSMNAUS-061209 2007-02-10 T-LEEUM-0377

6. Buttons operations within Service Mode

KEY	FUNCTION
▲/▼	Item selection by moving the cursor
◀/▶	Data Increase/Decrease for the selected Item
MENU	Save set Data to EEPROM and go upper mode
DIGIT	Change channel
TV/VIDEO	Change AV mode

3-2-3 Factory Data

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

AV Calibration
Comp Calibration
PC Calibration
Hdmi Calibration

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Factory Name	RF	DTV	AV/ SVIDEO	COMP	PC	HDMI
Caption Level	On					
Watchdog enable	On					
Spread Spectrum	1	**1**	0	0	1	0
Panel Option	26AU					
Dimming	EXT_PWM					
RS-232C	Debug					
Gamma	0					
Panel Display Time	XX Hr					
Mute Time[RF]	600mS					
CH Memory	SAMEX					
Shop Mode	OFF					
SUB MICOM DOWN	OFF					
MAIN EEPROM WP	OFF					
DDC WP	OFF					
PC Mode Ident	Auto					
HDMI Mode Ident	Auto					
HPD Ctl Method	1					
HPD Low Duration	900ms					
Download RRT	OFF					
7.5 IRE On/Off	On					
7.5 IRE Offset	60					
HDMI Mute Time	1500					

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Sub Brightness	128
R-Offset	512
G-Offset	512
B-Offset	512
Sub Contrast	128
R-Gain	512
G-Gain	512
B-Gain	512

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

W/B Movie On/Off	on	NOR_RGain	7
Mode	Dynamic	NOR_BGain	-11
Color Tone	Cool1	NOR_ROffset	-2
MSub Brightness	128	NOR_BOffset	2
MSub Contrast	128	C2_RGain	-32
W1_RGain	19	C2_BGain	22
W1_BGain	-26	C2_ROffset	5
W1_ROffset	-1	C2_BOffset	1
W1_BOffset	4	Movie Contrast	70
W2_RGain	49	Movie Bright	50
W2_BGain	-43	Movie Color	25
W2_ROffset	-4	Movie Sharpness	45
W2_BOffset	4		

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

1st_AV_Low	18	2nd_AV_High	235
1st_AV_High	220	2nd_AV_Delta	1
1st_AV_Delta	1	2nd_COMP_Low	1
1st_COMP_Low	16	2nd_COMP_High	235
1st_COMP_High	235	2nd_COMP_Delta	1
1st_COMP_Delta	1	2nd_PC_Low	1
1st_PC_Low	4	2nd_PC_High	235
1st_PC_High	235	2nd_PC_Delta	1
1st_PC_Delta	1	2nd_HDMI_Low	1
2nd_AV_Low	1	2nd_HDMI_High	235
		2nd_HDMI_Delta	1

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

LUMA_OFFSET	501
LUMA_GAIN	582
RED CUTOFF	-
GREEN CUTOFF	-
BLUE OFFSET	-
RED GAIN	-
GREEN GAIN	-
BLUE GAIN	-
2nd_X242_R_L	134
2nd_X242_G_L	134
2nd_X242_B_L	134
2nd_X242_R_H	1150
2nd_X242_G_H	1150
2nd_X242_B_H	1150

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

RED CUTOFF	126	HSOPW	24
GREEN CUTOFF	93	SYNC_CTRL	64
BLUE CUTOFF	125	SOGMID_CTRL	189
PHASE_CC	0	SEP_THR	32
RED GAIN	200	PRECST	4
GREEN GAIN	200	POSTCST	14
BLUE GAIN	200	ADC_BW0	68
PLLDIV	858	ADC_BW1	4
PLL_GAIN	1	RDOFFSC	120
CLPDLY	8	GDOFFSC	0
CLPDUR	8	BDOFFSC	10

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

CH filter	ss_CH01
CV filter	Hardware
NR	ON
UVNR	OFF
LTI-YEE	ON
CTI-UVEE	ON
YH_MAX	128
YH_Edge	4096
YH_MIN	128
UVH_MAX	255
UVH_Edge	300
UVH_MIN	8
Color_Mid_Value	50

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

In Phase Line	24	CR_OFFSET	0
In Phase Frame	26	CB_GAIN	512
Out Phase Line	12	CB_OFFSET	0
Out Phase Frame	22	Y_DELAY_POS	0
CORING	2	Y_DELAY_NEG	12
LUMA_BW	0	CB_DELAY_POS	0
CHROMA_BW	4	CB_DELAY_NEG	13
CKILL_TH1	48	CR_DELAY_POS	0
CKILL_TH2	80	CR_DELAY_NEG	13
LUMA_GAIN	582	AGC_ON/OFF	OFF
LUNA_OFFSET	501	AGC_GAIN	538
CR_GAIN	512		

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Patt-Sel	0	ACR-Th2	100
B-Slope gain	64	Skin-Enable	1
B-Tilt min	70	Skin-Tu	128
B-Tilt max	140	Skin-Tv	128
Lfunc-Basis	75	Sub color	128
Hfunc-Basis	88	M-Skin-Tu	128
Mean-Offset1	75	M-Skin-Tv	128
Mean-Offset2	150	M-Au-Sub color	128
Mean-Slope	41	MW-Skin-Tu	128
Input-offset	128	MW-Skin-Tv	128
ACR-Offset	30	M-Wi-Sub color	128
ACR-Th1	30		

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Carrier Mute	1
Stereo Pilot High	13
Stereo Pilot Low	7
Audio Delay	45
Spdif Delay	OFF
Melody Speak Vol.	5
Melody HP Vol.	5
NTP_Amp Vol.	30
NTP_PWM Mod.	243
NTP_DRC Thresh.	12
NTP_Speaker EQ	Off

1.Calibration	
2.Option Byte	
3.White Balance	
4.W/B Movie	
5.Calibration Target	T-JSMNAUS0-1000
6.Calibration Value	T-JSMNAUS5-1000
7.MST3388	ACL 28.16.4.1
8.X242	RFS T-JSMNAUS-061209
9.X242 NTSC	2007-02-10
10.FBE2	T-LEEUM-0377
11.Sound	
12.Dynamic Contrast	
13.Checksum 0x0000	
14.Reset	

Dynamic CE	Off
Dynamic Dimming	Off
FBE2 Y_MEAN READ	Read Value

3-3 White Balance - Calibration

3-3-1 White Balance -Calibration



3-3-2 White Balance - Adjustment



(W/B adjustment Condition refer next page)

3-3-3 Conditions for Measurement

1. On the basis of toshiba ABL pattern : High Light level (57 IRE)
   - INPUT SIGNAL GENERATOR : MSPG-925LTH
     * Mode NO 1 : 744X484@60 Hz
       NO 6 : 1280X720@60 Hz (Component 720P)
       NO 21 : 1024X768@60 Hz
     * Pattern NO 15 : Color bar
       NO 16 : Toshiba ABL Pattern
       NO 17 : 16 gray
2. Optical measuring device : CA210 (FL)
   Please use the MSPG-925 LTH generator for model LNR2355W,LNR2755W,LNR3255W.

3-4 White Ratio (Balance) Adjustment

1. You can adjust the white ratio in factory mode (1:Calibration, 3:White-Balance).
2. Since the adjustment value and the data value vary depending on the input source, you have to adjust these in CVBS, Component 1 and HDMI 1 modes.
3. The optimal values for each mode are configured by default. (Refer to Table 1, 2.)
   It varies with Panel's size and Specification.

- Equipment : CA-210
- Pattern: Master MIK K7256 #92 "ABL Pattern" as standard
  - Use other equipment only after comparing the result with that of the Master equipment.
- Set Aging time : 60min ↑
- Calibration and Manual setting for WB adjustment.

HDMI: No Calibration Manual adjustment at #16 pattern (720p)

COMP: Calibration at #24 Chessboard Pattern → Manual adjustment at #16 pattern (720p)

CVBS: Calibration at #24 Chessboard Pattern → Manual adjustment at #16 pattern (NTSC)

PC : Calibration at #24 Chessboard Pattern → No Manual adjustment (1024x768@60Hz)

-White Balance Manual Adjustment (ABL Pattern)

	CA-210				
		x	y	Y (cd/m²)	T(K) ± MPCD
CVBS (NTSC) #1, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0
COMP (720P) #6, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0
DVI (720P) #6, #92	H/L	272	278	-	15000K/0
	L/L	272	278	4	15000K/0

-Adjustment Specification

White Balance : High light (± 3), Low light (± 5)

Luminance : High light (¡¾10%)

Low light (2.0fL ¡¾0.1fL, 2.1fL ¡¾0.2fL)

3-5 Servicing Information

3-5-1 USB Download Method

1. Downloading boot code
   (1) Change the boot code's file name into "boot.bin".
   (2) Copy the "boot.bin" into the path "/bordeaux/us" in USB flash driver.
   (3) Turn off LCD TV.
   (4) Insert the USB flash driver into the service 1 jack of LCD TV.
   (5) Turn on LCD TV.
   (6) The banner osd "Updating SW..." is displayed.
   (7) The banner osd "Completed..." is displayed when the updating is completed.
   (8) Turn off and remove the USB flash driver from LCD TV
   (9) Check the program version.

2. Downloading application code
   (1) Change the application code's file name into "appl.rom".
   (2) Copy the "appl.rom" into the path "/bordeaux/us" in USB flash driver.
   (3) Turn off LCD TV.
   (4) Insert the USB flash driver into the service 1 jack of LCD TV.
   (5) Turn on LCD TV.
   (6) The banner osd "Updating SW..." is displayed.
   (7) The banner osd "Completed..." is displayed when the updating is completed.
   (8) Turn off and remove the USB flash driver from LCD TV
   (9) Check the program version.

Memo

7 Block Diagram

- This Document can not be used without Samsung's authorization



Memo

13 Circuit Descriptions

13-1 Block description



NO.	BLOCK	DESCRIPTION	REMARK
1	X242(IC202)	DTV DECODER	215H4AALA11HG
2	FBEX(IC1301)	IMAGE BACKEND ENHANCER	NZ2YFKC
3	SUB_MICOM(IC602)	CONTROL POWER,PANEL, etc.	WT61P6S
4	SOUND AMP(IC1100)	SOUND AMP IC	NTP3000(H12363B)
5	SOUND PROCESSOR(IC1002)	SOUND MAIN PROCESSOR IC	MSP4450K E8
6	TUNER(TU500)	HALF-NIM-TUNER & SPLITTER	DTVS227CH281A
7	DDR MEMORY(IC201)	X242 DDR MEMORY	HYB18T512161BF-25
8	IC-RECEIVER(IC1201)	2ADC+1HDMI	MST3388MK-LF-110
9	HDMI SWITCH(IC1202)	3 TO 1 HDMI SWITCH	SIL9185CTU

Memo

11 Disassembly and Reassembly

This section of the service manual describes the disassembly and reassembly procedures for the TFT-LCD TV.

⚠ **WARNING : This monitor contains electrostatically sensitive devices. Use caution when handling these components.**

11-1 Disassembly

⚠ **Cautions : 1. Disconnect the monitor from the power source before disassembly.**

2. Follow these directions carefully; never use metal instruments to pry apart the cabinet.

Description	Picture Description
1. Place monitor face down on cushioned table. Remove screws from the rear cover and remove screws from the stand.	

Description	Picture Description
2. Lift up the rear cover and remove the stand.	
	
3. Remove Screws from the stand BRKT and lift up the stand BRKT.	

Description	Picture Description
4. Disconnect cable from the boards.	
5. Remove screws from the board and lift up the speakers.	
	

Description	Picture Description
6. Remove screws from the panel BRKT and lift up the BRKT.	
	

11-2 Reassembly

Reassembly procedures are in the reverse order of disassembly procedures.

Memo

6 Electrical Parts List

-You can search for updated part codes through ITSELF web site.
URL : http://itself.sec.samsung.co.kr/

6-1 LNT2353HTX/LNT2354HX Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
		LNT2353HTX/XAA	LN-T2353HT,N34A/23R80-GBP,23,LCD-TV,UNIT		
0.1	M0001	BN90-01147A	ASSY COVER FRONT;23R81,UO,-,PC,V0,BK27,S	1	S.N.A
..2	T0003	BN96-04660A	ASSY COVER P-FRONT;23R81,UO,,PC,V0,,BK27	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	2	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	1	S.N.A
...3	M0112	BN63-03109A	COVER-FRONT;23R81,UO,PC,-,-,-,V0,-,BK27,	1	S.N.A
...3	T0603	BN64-00588A	WINDOW-RMC;32,BORDEAUX PLUS,PC,-,-,-,HB,	1	S.N.A
...3		BN96-04702B	ASSY HOLDER P-BOSS;23,26R81,-,HIPS,V0,-,	1	S.N.A
....4		BN61-02957B	HOLDER-BOSS BOTTOM;23,26R81,HIPS,V0,-,-,	1	S.N.A
....4		BN61-03261A	BOSS-TAPE;Tulip,ACRYL,T1.1,W12mm,GRAY,TA	0.8	S.N.A
...3	M0102	BN96-04848A	ASSY BLU P;Bordeaux Plus,BACK LIGHT UNIT	1	S.A
...3	T0069	AA60-00172L	SPACER-FELT;23R8,FELT,300,T0.8,10	2	S.N.A
...3	T0069	AA60-00172M	SPACER-FELT;23R8,FELT,520,T0.8,10	2	S.N.A
...3	M0145	BN96-04809D	ASSY BOARD P-FUNCTION&IR;LE23R86BDX,CT50	1	S.A
...3	T0056	BN63-03413A	COVER-DECORATION;23 BORDEAUX PLUS,PC,CLE	1	S.N.A
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.47	S.N.A
..2	T0175	BN96-04767A	ASSY SPEAKER P;16ohm,4pin,5W,Bordeaux Pl	1	S.A
0.1	M0216	BN90-01150A	ASSY STAND;23,26R81,NORMAL,-,-,-,-	1	S.N.A
..2	T0524	6902-000561	BAG PE;HDPE+NITRON(DOUBLE),T0.015+T0.5,W	1	S.N.A
..2	M0027	BN96-04663A	ASSY STAND P-BASE;-,23,26R81,NORMAL,-,AB	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
...3	M0081	6003-001239	SCREW-TAPTITE;FH,+,-,B,M4,L10,ZPC(WHT),S	4	S.A
...3		BN61-02954A	BRACKET-STAND BOTTOM;23,26 BORDEAUX PLUS	1	S.N.A
...3	T0920	BN61-02955A	GUIDE-STAND;23,26R81,ABS,-,-,-,BK500,V0	1	S.N.A
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.4	S.N.A
...3	T0004	BN63-03122A	COVER-STAND BASE;23,26R81,ABS+PMMA,-,-,-	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,CR Rubber Gray,T1.5	4	S.N.A
0.1	M0002	BN90-01155H	ASSY COVER REAR;23R81,UO(HOTEL),PC+ABS,V	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	2	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	11	S.A
..2	M0013	BN96-04668D	ASSY COVER P-REAR;23R81,UO(HOTEL),,PC+AB	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	4	S.N.A
...3	T0101	BN61-03346A	BRACKET-WALL;LCD TV,SECC,T1.2	4	S.N.A
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.5	S.N.A
...3	M0006	BN63-03115A	COVER-REAR;23R81,UO,PC+ABS,-,-,-,V0,-,BK	1	S.N.A
...3	T0071	BN64-00554G	INLAY-TERMINAL;07,COMMON,PS SHEET,T0.5,L	1	S.N.A
...3	T0064	BN65-00002A	CLAMPER CORE;BORDEAUX,PP,V0,BLK	1	S.N.A
0.1		BN91-01180J	ASSY LCD-AUO;LE23R32BX/*	1	S.N.A
..2	M0215	BN07-00365A	LCD-PANEL;T230XW01,8bit,23inch,16.7M,16:	1	S.A
0.1	M0017	BN91-01602A	ASSY CHASSIS;LNT2353HTX/XAA	1	S.N.A
..2	M0014	BN94-01334E	ASSY PCB MAIN-AUO TN;LNT2353HTX/*	1	S.A
...3	T0245	0202-001492	SOLDER-WIRE FLUX;HSE-02 LFM48 SR-34 S,-,	0.25	S.N.A
...3	JA701B	3701-001388	CONNECTOR-HDMI;20P,Phosphor Bronze,ANGLE	1	S.A
...3	CN801	3701-001400	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,Ni	1	S.A
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A
...3	CN330	3711-000058	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5MM,AN	1	S.A
...3	CN330	3711-004484	HEADER-BOARD TO CABLE;BOX,5P,1R,2mm,STRA	1	S.A
...3	CN330	3711-004531	HEADER-BOARD TO CABLE;BOX,10P,1R,2mm,ANG	1	S.A
...3	CN330	3711-005606	HEADER-BOARD TO CABLE;BOX,30P,2R,2mm,STR	1	S.A
...3	CN330	3711-005842	HEADER-BOARD TO CABLE;BOX,24P,2R,2MM,STR	1	S.A
...3	JA330	3722-000143	JACK-PHONE;1P(VER),AG,BLK,ANGLE	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA332	3722-001163	JACK-VHS;4P,AU,BLK,ANGLE	1	S.A
...3	JA332	3722-001734	JACK-VHS;4P,SN,BLK,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002363	JACK-PIN;3P,Sn,YEL/WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002543	JACK-PIN;3P,Sn,RED/WHT/YEL,ANGLE	1	S.A
...3	CN704B	3722-002546	JACK-USB;4P/1C,AU,BLK,ANGLE,A type	1	S.N.A
...3	CN601H	3722-002547	JACK-MODULAR;8P/4C,N,STRAIGHT,N,AU,1PORT	1	S.A
...3	CIS3	BN40-00107A	TUNER;DNVS227IH262A,DNVS227IH262A,NTSC/V	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
...3	T0099	BN62-00003A	HEAT SINK-IC;NK,SUN,A6063S,T2.5,W28,L28,	1	S.N.A
...3	T0174	BN97-01622E	ASSY SMD;LNT2353HTX/XAA AUO TN	1	S.N.A
....4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-,D20~45##,96.5Sn/	4.537	S.N.A
....4	D402	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A
....4	D207L	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D208L	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D209	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D213	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D221	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D222	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D223	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D501	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D647H	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D720B	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D721B	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D724	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D725	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D726	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D727	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D728	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D729	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D730	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D731	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D801	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D802	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D804	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D805	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D806	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D808	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D809	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D810	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D811	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D812	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D813	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D814	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D815	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D822	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D823	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D830	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D831	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D832	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D833	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D834	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D835	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D836	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D837	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D215	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D216	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D217	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D220	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D225	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D302	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D401	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D406	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D407	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D408	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D409	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D410	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D411	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D412	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D746	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D842	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D843	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D1101	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1102	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1103	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1104	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1105	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1106	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1107	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1108	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1109	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1110	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1111	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1112	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1113	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D1114	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1115	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1116	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D206	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D214	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D218	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D734	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D820	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D838	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1201	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500mW,LL-	1	S.A
....4	D719	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D722	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D803	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D824	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D648	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D649	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D650	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D651	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D652	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D653	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D654	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D655	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D656	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D657	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D658	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D659	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D660	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D661	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D662	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D663	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D723B	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D747	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D748	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D749	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D750	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D807	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D816	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D817	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D818	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D819	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D821	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D825	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D301	0403-001282	DIODE-ZENER;BZT52-C15,13.8-15.6,410mW,SO	1	S.A
....4	D502	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A
....4	D604	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D609	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D610	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D611	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D617	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D618	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D621	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D622	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D629	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D633	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D634	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D637	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D638	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D642H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D643H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D644H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D702B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D703B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D704B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D711B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D712B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D740B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D741B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D744B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D826	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D827	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D839	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D840	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D841	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D745	0406-001181	DIODE-TVS;NUP4201MR6,6/-/-V,500W,TSOP-6	1	S.A
....4	D201	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D202	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D203	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	Q301	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A
....4	Q401	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	Q405	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A
....4	Q1201	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1305	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1306	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1402	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q201	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q205L	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q206	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q207	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q210	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q502	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q603H	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q901L	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q208	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q402	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q404	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q406	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q101L	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q102L	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q501	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	IC104	0801-002095	IC-CMOS LOGIC;74LCX245,TRANSCEIVER,TSSOP	1	S.A
....4	IC104	0801-002267	IC-CMOS LOGIC;74LCX14,-,SOIC,14P,150MIL,	1	S.A
....4	IC104	0801-002393	IC-CMOS LOGIC;74VHC244,BUS BUFFER,TSSOP,	1	S.A
....4	IC104	0801-002633	IC-CMOS LOGIC;7WBD3125,2bit BUS SWITCH,S	1	S.A
....4	IC104	0801-002780	IC-CMOS LOGIC;74LVC1G17,SCHMITT-TRIGGER	1	S.A
....4	IC301	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	S.A
....4	IC208	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	S.A
....4	IC602	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC	1	S.A
....4	IC106	1001-001440	IC-VIDEO SWITCH;Sil9185CTU,QFP,80P,3.3V,	1	S.A
....4	IC603	1006-001266	IC-LINE TRANSCEIVER;SP3232EEY,TSSOP,16P,	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-001385	IC-EEPROM;24C256,256Kbit,32Kx8,SOP,8P,5x	1	S.A
....4	IC113	1105-001674	IC-DRAM;EM6A9320BI,-,128Mbit,4Mx32Bit,FB	1	S.A
....4	IC113	1105-001712	IC-DRAM;HYB25D256163CE,DDR,256Mbit,16Mx1	1	S.A
....4	IC113	1105-001712	IC-DRAM;HYB25D256163CE,DDR,256Mbit,16Mx1	1	S.A
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	S.A
....4	T0085	1201-002136	IC-AUDIO AMP;LM4810,MSOP,8P,3x3mm,DUAL,-	1	S.A
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A
....4	T0087	1203-001488	IC-POSI.FIXED REG.;7805,T0-252,3P,-,PLAS	1	S.A
....4	T0087	1203-001815	IC-POSI.FIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-001816	IC-POSI.FIXED REG.;78M08,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	S.A
....4	T0087	1203-002974	IC-POSI.FIXED REG.;AP1117D-25A,TO-252,3P	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	IC701	1203-003394	IC-POWER SUPERVISOR;MIC2544-1YM,SOP,8P,4	1	S.A
....4	T0087	1203-003696	IC-POSI.FIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003696	IC-POSI.FIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003697	IC-POSI.FIXED REG.;SC1566I5M-2.5TRT,TO-2	1	S.A
....4	T0087	1203-003697	IC-POSI.FIXED REG.;SC1566I5M-2.5TRT,TO-2	1	S.A
....4	IC205	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC206	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC118	1204-002503	IC-VIDEO PROCESS;SVP-PX56-7256,PQFP,256P	1	S.N.A
....4	IC302	1204-002708	IC-AUDIO PROCESSOR;MSP4450K-VK-E8-500,PM	1	S.A
....4	IC118	1204-002729	IC-VIDEO PROCESS;S4LF119X01,PBGA,208P,17	1	S.A
....4	IC1301	1204-002747	IC-DECODER;S4LF111X01,BGA,416P,27x27mm,P	1	S.A
....4	IC1302	1205-003154	IC-CLOCK GENERATOR;6V10001PGG,TSSOP,24P,	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000067	R-CHIP;15Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000083	R-CHIP;3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000120	R-CHIP;680ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000426	R-CHIP;160ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000669	R-CHIP;2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000729	R-CHIP;300ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001139	R-CHIP;7.5Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	RA1201	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1202	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1203	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1204	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1205	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1206	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1207	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1208	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1401	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1402	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1403	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1404	2011-000002	R-NETWORK;22ohm,5%,1/16W,L,CHIP,8P,TP,32	1	S.A
....4	RA1501	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1502	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1503	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1504	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	RA1505	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1506	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1507	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1508	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1509	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1510	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1511	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1601	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1602	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1603	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1604	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1605	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1606	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1607	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1608	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1609	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1610	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA501	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA502	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	R1630	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	R1631	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	R975	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA701B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA702B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA703B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	C120	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	1	S.A
....4	C120	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000384	C-CER,CHIP;0.015nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000838	C-CER,CHIP;0.39NF,5%,50V,C0G,TP,1608	1	S.A
....4	C120	2203-000851	C-CER,CHIP;0.039nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001034	C-CER,CHIP;5.6nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,1608	1	S.A
....4	C120	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	S.A
....4	C120	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005261	C-CER,CHIP;1000nF,10%,25V,X7R,3216	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1003	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C102	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C103L	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1311	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C133	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1503	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1504	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1780	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C191	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C214	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C323	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C342	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C402	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C506	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C510	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C517	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C712	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C836	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C838	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C105	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1051	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1054	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1055	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C113	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C147	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C165	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C167	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1701	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1732	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C175	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C189	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C343	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C346	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C501	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C330	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C531	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C937	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C953	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1517	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C519	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C524	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C1006	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C106	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C111	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1111	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1322	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1779	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C302	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C332	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C505	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C512	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C527	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C156L	2402-001218	C-AL,SMD;22UF,20%,35V,WT,TP,6.6X6.6X5.8M	1	S.A
....4	C319	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	S.A
....4	C347	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	S.A
....4	C118	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C135	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C161L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C181	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C188	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C922L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C923L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C406	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C422	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C138	2409-001029	C-ORGANIC,SMD;120##F,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C168	2409-001029	C-ORGANIC,SMD;120##F,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C140	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	C171	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000417	INDUCTOR-SMD;220uH,5%,3225	1	S.A
....4	T0052	2703-001426	INDUCTOR-SMD;680uH,20%,7070	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	L401	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	L402	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	X1301	2801-000258	CRYSTAL-SMD;0.032768MHz,20ppm,SMD,12.5pF	1	S.A
....4	X201	2801-003326	CRYSTAL-SMD;24MHZ,30PPM,28-ABX,20PF,50OH	1	S.A
....4	X301	2801-004300	CRYSTAL-SMD;18.432MHz,30ppm,28-ABX,13pF,	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	X1101	2801-004483	CRYSTAL-SMD;28.322MHz,30ppm,HC-49,20pF,5	1	S.A
....4	X1303	2801-004629	CRYSTAL-SMD;27MHz,20ppm,12pF,50ohm,TP	1	S.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-001082	BEAD-SMD;60ohm,3225,TP,43ohm/40MHz,83ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001148	BEAD-SMD;60ohm,1608,TP,-,-	1	S.N.A
....4	T0568	3301-001148	BEAD-SMD;60ohm,1608,TP,-,-	1	S.N.A
....4	T0568	3301-001163	BEAD-SMD;80ohm,2012,TP,-,192ohm/867MHz	1	S.N.A
....4	T0568	3301-001163	BEAD-SMD;80ohm,2012,TP,-,192ohm/867MHz	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001569	BEAD-SMD;600ohm,2012,1000mA,TP,520ohm/90	1	S.N.A
....4	T0313	3404-001207	SWITCH-TACT;12V,50mA,160gf,6.2X6.2,SPST	1	S.A
....4	JA801	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A
....4	JA803	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A
....4	L101	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	L103	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	T0077	BN41-00840C	PCB MAIN;Bordeaux+/Calla,FR-4,4,1.6T,192	1	S.N.A
....4	M0018	BN97-01688C	ASSY MICOM;T-BRDPHUS0-1001,N34A,200709.1	1	S.N.A
.....5	IC115	1107-001666	IC-FLASH MEMORY;KFG5616U1A,256Mbit,16Mx1	1	S.N.A
....4	M0018	BN97-01688D	ASSY MICOM;T-BRDPHUS5-1001,N34A,200709.1	1	S.N.A
.....5	IC520	0903-001485	IC-MICROCONTROLLER;44P,12x12mm,24MHz,TR,	1	S.N.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	Q409	0505-002169	FET-SILICON;Si4435BDY-T1-E3,P,-30V,-9.1A	1	S.N.A
...3	T0603	BN63-03195B	SHIELD-PCB MAIN;TULIP NT,SPTE,T0.3	1	S.N.A
...3	CIS02	BN73-00024B	SILICON/RUBBER-GAP PAD;POSEIDON,SILICON,	1	S.N.A
0.1		BN91-01603A	ASSY SHIELD-SPD;LNT2353HTX/XAA	1	S.N.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	3	S.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	1	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	6	S.N.A
..2	M0081	6003-001439	SCREW-TAPTITE;BH,+,-,S,M4,L8,ZPC(WHT),SW	1	S.N.A
..2	M2893	BN39-00603D	LEAD CONNECTOR;RE26**,UL1007#26,14P,100m	1	S.A
..2	M2893	BN39-00615F	LEAD CONNECTOR;Bordeaux23,1617#22/1015#1	1	S.A
..2	M2893	BN39-00836A	LEAD CONNECTOR;LNT2342HX,UL1571#30,30P,2	1	S.A
..2	T0764	BN44-00158A	SMPS-LCDTV;MK23P,DYREL,AC/DC,120W,AC100	1	S.A
..2	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	1	S.N.A
..2	M0254	BN61-02875A	HOLDER-SIDE AV;07,COMMON,UO,PC+ABS,V0,-,	1	S.N.A
..2	M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.A
..2	M0146	BN61-03060A	BRACKET-PANEL SIDE;BORDEAUX PLUS 23,SECC	2	S.N.A
..2	M2893	BP39-00177B	LEAD CONNECTOR;RE40**,UL1007#26,5P,150mm	1	S.A
..2	M0412	BN96-05137F	ASSY BRACKET P-PCB;-,23R81,UO(HOTEL),-,S	1	S.N.A
...3	M0131	AA63-01438A	GASKET;Bordeaux,Conductive Fabric,7mm,8m	1	S.N.A
...3	M0107	BN61-03037A	BRACKET-PCB;23 BORDEAUX PLUS,SECC,T1.0	1	S.N.A
...3	M0131	BN63-00170A	GASKET;GH17LS,CONDUCTIVE FAB,5MM,10MM,16	2	S.N.A
...3	M0131	BN63-02791A	GASKET;LNS4096D,Conductive Fabric,8mm,10	1	S.N.A
..2	M2893	BN39-00802B	LEAD CONNECTOR;LE40R86BDX,UL1007#26,24PI	1	S.A
0.1	M0003	BN92-02397N	ASSY BOX;23R81,UO(HOTEL)	1	S.N.A
..2	T0130	BN69-01737G	BOX-00,SET;23R8,CB,SY-05,A,YEL,A1,EXPORT	1.02	S.N.A
0.1	M0113	BN92-02398A	ASSY P/MATERIAL;23R81,UO	1	S.N.A
..2	T0214	BN74-00008A	TAPE-OPP MASKING;OPP-2,T0.05,W100,L800M,	1.6	S.N.A
..2	T0376	6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	0.013	S.N.A
..2	T0376	6902-000379	BAG AIR;LDPE,T0.2,W1000,L1800,TRP,-,--	0.004	S.N.A
..2	T0003	6902-000604	BAG WRAPPING;LDPE,T0.02,W500,L10000,TRP,	2.94	S.N.A
..2	T0524	6902-000758	BAG PE;HDPE/HDPE/NITRON(DOUBLE),T0.015/T	1	S.N.A
0.1	M0045	BN92-02776A	ASSY ACCESSORY;LNT2353HTX/XAA	1	S.N.A
..2	M0045	BN96-05698A	ASSY ACCESSORY;LNT2353HTX/XAA,-,-,-,-,-	1	S.A
...3	T0268	3903-000144	CBF-POWER CORD;DT,US,BP3/Y,U(IEC C13-RA)	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	M0521	BN39-00865A	CBF IF-MODULAR/MODULAR;Bordeaux Plus HOT	1	S.A
...3	T0511	BN68-01083C	MANUAL USERS;COMM,SAMSUNG,English,N.Amer	1	S.N.A
...3	M0045	BN96-01800A	ASSY ACCESSORY;ROME32,-,-,-,-,SCREW	1	S.A
....4	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
....4	ACCESSORY	6902-000128	BAG ZIPPER;LDPE,T0.05,W200,L150,TRP,8,2-	1	S.N.A
...3	T0511	AA68-03242L	MANUAL FLYER-SAFETY GUIDE;comm,Samsung,E	1	S.N.A
0.1	M0019	BN92-02789A	ASSY LABEL;LNT2353HTX/XAA	1	S.N.A

6-2 LNT2653HX Parts List

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
		LNT2653HTX/XAA	LN-T2653HT,N34A/26R80-GBP,26,LCD-TV,UNIT		
0.1	M0001	BN90-01146A	ASSY COVER FRONT;26R81,UO,-,PC,V0,BK27,S	1	S.N.A
..2	T0003	BN96-04659A	ASSY COVER P-FRONT;-,26R81,UO,-,PC,V0,-,	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	2	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	1	S.N.A
...3	M0112	BN63-03110A	COVER-FRONT;26R81,UO,PC,-,-,-,V0,-,BK27,	1	S.N.A
...3	T0603	BN64-00588A	WINDOW-RMC;32,BORDEAUX PLUS,PC,-,-,-,HB,	1	S.N.A
...3		BN96-04702B	ASSY HOLDER P-BOSS;23,26R81,-,HIPS,V0,-,	1	S.N.A
....4		BN61-02957B	HOLDER-BOSS BOTTOM;23,26R81,HIPS,V0,-,-,	1	S.N.A
....4		BN61-03261A	BOSS-TAPE;Tulip,ACRYL,T1.1,W12mm,GRAY,TA	0.8	S.N.A
...3	M0102	BN96-04848A	ASSY BLU P;Bordeaux Plus,BACK LIGHT UNIT	1	S.A
...3	M0145	BN96-04809B	ASSY BOARD P-FUNCTION&IR;LE23R81BDX,CT50	1	S.A
...3	T0056	BN63-03414A	COVER-DECORATION;26 BORDEAUX PLUS,PC,CLE	1	S.N.A
...3	CCM1	BN63-02183C	COVER-SHEET;Rhcm,PE Vinyl,T0.05,200mm,20	2.67	S.N.A
..2	T0175	BN96-04767A	ASSY SPEAKER P;16ohm,4pin,5W,Bordeaux Pl	2	S.A
0.1	M0216	BN90-01150A	ASSY STAND;23,26R81,NORMAL,-,-,-,-	1	S.N.A
..2	T0524	6902-000561	BAG PE;HDPE+NITRON(DOUBLE),T0.015+T0.5,W	1	S.N.A
..2	M0027	BN96-04663A	ASSY STAND P-BASE;-,23,26R81,NORMAL,-,AB	1	S.A
...3	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
...3	M0081	6003-001239	SCREW-TAPTITE;FH,+,-,B,M4,L10,ZPC(WHT),S	4	S.A
...3		BN61-02954A	BRACKET-STAND BOTTOM;23,26 BORDEAUX PLUS	1	S.N.A
...3	T0920	BN61-02955A	GUIDE-STAND;23,26R81,ABS,-,-,-,BK500,V0	1	S.N.A
...3	CCM1	BN63-02183D	COVER-SHEET;Rhcm,PE Vinyl,T0.05,680mm,20	0.4	S.N.A
...3	T0004	BN63-03122A	COVER-STAND BASE;23,26R81,ABS+PMMA,-,-,-	1	S.N.A
...3	T0132	BN73-00052A	RUBBER FOOT;ARES 17,CR Rubber Gray,T1.5	4	S.N.A
0.1	M0002	BN90-01154H	ASSY COVER REAR;26R81,UO(HOTEL),PC+ABS,V	1	S.N.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	2	S.A
..2	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	13	S.A
..2	M0013	BN96-04667D	ASSY COVER P-REAR;-,26R81,UO(HOTEL),-,PC	1	S.A
...3	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	4	S.N.A
...3	T0101	BN61-03346A	BRACKET-WALL;LCD TV,SECC,T1.2	4	S.N.A
...3	CCM1	BN63-02183F	COVER-SHEET;Rhcm,PE Vinyl,T0.05,900mm,20	0.6	S.N.A
...3	M0006	BN63-03117A	COVER-REAR;26R81,UO,PC+ABS,-,-,-,V0,-,BK	1	S.N.A
...3	T0071	BN64-00554G	INLAY-TERMINAL;07,COMMON,PS SHEET,T0.5,L	1	S.N.A
...3	T0064	BN65-00002A	CLAMPER CORE;BORDEAUX,PP,V0,BLK	1	S.N.A
0.1	MP1.0	BN91-01017C	ASSY LCD-AMZ;LE26R71BX/*	1	S.N.A
..2	M0215	BN07-00254A	LCD-PANEL;T260XW02,8bit,626.0*373.0*50.0	1	S.A
0.1	M0017	BN91-01602B	ASSY CHASSIS;LNT2653HTX/XAA	1	S.N.A
..2	M0014	BN94-01334F	ASSY PCB MAIN-AUO;LNT2653HTX/*	1	S.A
...3	T0245	0202-001492	SOLDER-WIRE FLUX;HSE-02 LFM48 SR-34 S,-,	0.25	S.N.A
...3	JA701B	3701-001388	CONNECTOR-HDMI;20P,Phosphor Bronze,ANGLE	1	S.A
...3	CN801	3701-001400	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,Ni	1	S.A
...3	CN906	3707-001081	CONNECTOR-OPTICAL;STRAIGHT,SPDIF	1	S.A
...3	CN330	3711-000058	HEADER-BOARD TO CABLE;BOX,4P,1R,2.5MM,AN	1	S.A
...3	CN330	3711-004484	HEADER-BOARD TO CABLE;BOX,5P,1R,2mm,STRA	1	S.A
...3	CN330	3711-004531	HEADER-BOARD TO CABLE;BOX,10P,1R,2mm,ANG	1	S.A
...3	CN330	3711-005606	HEADER-BOARD TO CABLE;BOX,30P,2R,2mm,STR	1	S.A
...3	CN330	3711-005842	HEADER-BOARD TO CABLE;BOX,24P,2R,2MM,STR	1	S.A
...3	JA330	3722-000143	JACK-PHONE;1P(VER),AG,BLK,ANGLE	1	S.A
...3	JA330	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	1	S.A
...3	JA332	3722-001163	JACK-VHS;4P,AU,BLK,ANGLE	1	S.A
...3	JA332	3722-001734	JACK-VHS;4P,SN,BLK,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002360	JACK-PIN;3P,AU,GRN/BLU/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002362	JACK-PIN;2P,Sn,WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002363	JACK-PIN;3P,Sn,YEL/WHT/RED,STRAIGHT	1	S.A
...3	JA333	3722-002543	JACK-PIN;3P,Sn,RED/WHT/YEL,ANGLE	1	S.A
...3	CN704B	3722-002546	JACK-USB;4P/1C,AU,BLK,ANGLE,A type	1	S.N.A
...3	CN601H	3722-002547	JACK-MODULAR;8P/4C,N,STRAIGHT,N,AU,1PORT	1	S.A
...3	CIS3	BN40-00107A	TUNER;DNVS227IH262A,DNVS227IH262A,NTSC/V	1	S.A
...3	T0099	BN62-00003A	HEAT SINK-IC;NK,SUN,A6063S,T2.5,W28,L28,	1	S.N.A
...3	T0174	BN97-01622F	ASSY SMD;LNT2653HTX/XAA AUO	1	S.N.A
....4	SUB05	0202-001477	SOLDER-CREAM;LST309-M,-,D20~45##,96.5Sn/	4.537	S.N.A
....4	D402	0401-000133	DIODE-SWITCHING;RLS4148,75V,150mA,LL-34,	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D207L	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D208L	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D209	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D213	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D221	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D222	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D223	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D501	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D647H	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D720B	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D721B	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D724	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D725	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D726	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D727	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D728	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D729	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D730	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D731	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D801	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D802	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D804	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D805	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D806	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D808	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D809	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D810	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D811	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D812	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D813	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D814	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D815	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D822	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D823	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D830	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D831	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D832	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D833	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D834	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D835	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D836	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D837	0401-001056	DIODE-SWITCHING;MMBD4148SE,100V,200mA,SO	1	S.A
....4	D215	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D216	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D217	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D220	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D225	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D302	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D401	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D406	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D407	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D408	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D409	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D410	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D411	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D412	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D746	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D842	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D843	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,SOD-3	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D0254	0402-000553	DIODE-SCHOTTKY;SS24/B240,40V,2000mA,DO-2	1	S.A
....4	D1101	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1102	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1103	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1104	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1105	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1106	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1107	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1108	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1109	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1110	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D1111	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1112	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1113	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1114	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1115	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1116	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D206	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D214	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D218	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D734	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D820	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D838	0403-000620	DIODE-ZENER;RLZ5.6B,5.45-5.73V,500mW,LL-	1	S.A
....4	D1201	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500mW,LL-	1	S.A
....4	D719	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D722	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D803	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D824	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-	1	S.A
....4	D648	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D649	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D650	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D651	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D652	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D653	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D654	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D655	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D656	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D657	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D658	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D659	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D660	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D661	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D662	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D663	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D723B	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D747	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D748	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D749	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D750	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D807	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D816	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D817	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D818	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D819	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D821	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D825	0403-001052	DIODE-ZENER;RD8.2MB,7.7-8.7V,200mW,SOT-2	1	S.A
....4	D301	0403-001282	DIODE-ZENER;BZT52-C15,13.8-15.6,410mW,SO	1	S.A
....4	D502	0403-001425	DIODE-ZENER;BZX84C33,31-35V,350mW,SOT-23	1	S.A
....4	D604	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D609	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D610	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D611	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D617	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D618	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D621	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D622	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D629	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D633	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D634	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D637	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D638	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D642H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D643H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D644H	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D702B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D703B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D704B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D711B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D712B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D740B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D741B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D744B	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D826	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	D827	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D839	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D840	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D841	0406-001172	DIODE-TVS;CDS3C30GTH,48V,SMD	1	S.A
....4	D745	0406-001181	DIODE-TVS;NUP4201MR6,6/-/-V,500W,TSOP-6	1	S.A
....4	D201	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D202	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	D203	0407-000123	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	1	S.A
....4	Q301	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A
....4	Q401	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A
....4	Q405	0501-000669	TR-SMALL SIGNAL;KTA1505Y,PNP,150mW,SOT-2	1	S.A
....4	Q1201	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1305	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1306	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q1402	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q201	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q205L	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q206	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q207	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q210	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q502	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q603H	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q901L	0501-000445	TR-SMALL SIGNAL;KTC3875S-Y,NPN,150mW,SOT	1	S.A
....4	Q208	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q402	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q404	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q406	0501-000434	TR-SMALL SIGNAL;KTC3875S-GR,NPN,150mW,SO	1	S.A
....4	Q101L	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q102L	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q501	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5ohm,0.	1	S.A
....4	IC104	0801-002095	IC-CMOS LOGIC;74LCX245,TRANSCEIVER,TSSOP	1	S.A
....4	IC104	0801-002267	IC-CMOS LOGIC;74LCX14,-,SOIC,14P,150MIL,	1	S.A
....4	IC104	0801-002393	IC-CMOS LOGIC;74VHC244,BUS BUFFER,TSSOP,	1	S.A
....4	IC104	0801-002633	IC-CMOS LOGIC;7WBD3125,2bit BUS SWITCH,S	1	S.A
....4	IC104	0801-002780	IC-CMOS LOGIC;74LVC1G17,SCHMITT-TRIGGER	1	S.A
....4	IC301	1001-000164	IC-ANALOG MULTIPLEX;74HC4052,CMOS,SOP,16	1	S.A
....4	IC208	1001-001109	IC-ANALOG SWITCH;FST3125M,BUS SWITCH & C	1	S.A
....4	IC602	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC	1	S.A
....4	IC106	1001-001440	IC-VIDEO SWITCH;Sil9185CTU,QFP,80P,3.3V,	1	S.A
....4	IC603	1006-001266	IC-LINE TRANSCEIVER;SP3232EEY,TSSOP,16P,	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-000129	IC-EEPROM;24C02,2Kbit,256x8Bit,SOP,8P,5x	1	S.A
....4	IC112	1103-001385	IC-EEPROM;24C256,256Kbit,32Kx8,SOP,8P,5x	1	S.A
....4	IC113	1105-001674	IC-DRAM;EM6A9320BI,-,128Mbit,4Mx32Bit,FB	1	S.A
....4	IC113	1105-001712	IC-DRAM;HYB25D256163CE,DDR,256Mbit,16Mx1	1	S.A
....4	IC113	1105-001712	IC-DRAM;HYB25D256163CE,DDR,256Mbit,16Mx1	1	S.A
....4	DU410	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DUAL,10	1	S.A
....4	T0085	1201-002136	IC-AUDIO AMP;LM4810,MSOP,8P,3x3mm,DUAL,-	1	S.A
....4	T0124	1201-002430	IC-POWER AMP;NTP-3000,QFN,56P,8x8mm,DUAL	1	S.A
....4	T0087	1203-001488	IC-POSI.FIXED REG.;7805,T0-252,3P,-,PLAS	1	S.A
....4	T0087	1203-001815	IC-POSI.FIXED REG.;78M09,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-001816	IC-POSI.FIXED REG.;78M08,TO-252,3P,-,PLA	1	S.A
....4	T0087	1203-002842	IC-POSI.FIXED REG.;AP1117D-33A,TO-252,3P	1	S.A
....4	T0087	1203-002974	IC-POSI.FIXED REG.;AP1117D-25A,TO-252,3P	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	IC012	1203-002995	IC-POSI.ADJUST REG.;AP1117D-A,TO-252,3P,	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	T0170	1203-003059	IC-SWITCH VOL. REG.;MP1583,SOIC,8P,4.9x3	1	S.A
....4	IC701	1203-003394	IC-POWER SUPERVISOR;MIC2544-1YM,SOP,8P,4	1	S.A
....4	T0087	1203-003696	IC-POSI.FIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A
....4	T0087	1203-003696	IC-POSI.FIXED REG.;NCP1117DT18T5G,DPAK,3	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	T0087	1203-003697	IC-POSI.FIXED REG.;SC1566I5M-2.5TRT,TO-2	1	S.A
....4	T0087	1203-003697	IC-POSI.FIXED REG.;SC1566I5M-2.5TRT,TO-2	1	S.A
....4	IC205	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC206	1203-004364	IC-VOL. DETECTOR;RT9818C-42PV,SOT-23,3P,	1	S.A
....4	IC118	1204-002503	IC-VIDEO PROCESS;SVP-PX56-7256,PQFP,256P	1	S.N.A
....4	IC302	1204-002708	IC-AUDIO PROCESSOR;MSP4450K-VK-E8-500,PM	1	S.A
....4	IC118	1204-002729	IC-VIDEO PROCESS;S4LF119X01,PBGA,208P,17	1	S.A
....4	IC1301	1204-002747	IC-DECODER;S4LF111X01,BGA,416P,27x27mm,P	1	S.A
....4	IC1302	1205-003154	IC-CLOCK GENERATOR;6V10001PGG,TSSOP,24P,	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000040	R-CHIP;150ohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000067	R-CHIP;15Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000071	R-CHIP;22ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000083	R-CHIP;3Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000106	R-CHIP;220Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000120	R-CHIP;680ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000129	R-CHIP;27Kohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000426	R-CHIP;160ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000539	R-CHIP;200ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000669	R-CHIP;2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000701	R-CHIP;3.6Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-000729	R-CHIP;300ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-000882	R-CHIP;4.7ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001139	R-CHIP;7.5Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608	1	S.A
....4	R110	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	R110	2007-002768	R-CHIP;6.2Kohm,1%,1/10W,TP,1608	1	S.A
....4	RA1201	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1202	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1203	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1204	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1205	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1206	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1207	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1208	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1401	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1402	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1403	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1404	2011-000002	R-NET;22ohm,5%,1/16W,L,CHIP,8P,TP,3216	1	S.A
....4	RA1501	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1502	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	RA1503	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1504	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1505	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1506	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1507	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1508	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1509	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1510	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1511	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1601	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1602	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1603	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1604	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1605	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1606	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1607	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1608	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1609	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA1610	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA501	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	RA502	2011-000881	R-NET;33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.	1	S.A
....4	R1630	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	R1631	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	R975	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA701B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA702B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	RA703B	2011-001001	R-NET;0ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6	1	S.A
....4	C120	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	1	S.A
....4	C120	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000189	C-CER,CHIP;100nF,+80-20%,25V,Y5V,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000236	C-CER,CHIP;0.1nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000384	C-CER,CHIP;0.015nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000405	C-CER,CHIP;0.18nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000426	C-CER,CHIP;0.018nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000681	C-CER,CHIP;0.027nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000783	C-CER,CHIP;0.33nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000815	C-CER,CHIP;0.033nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000838	C-CER,CHIP;0.39NF,5%,50V,C0G,TP,1608	1	S.A
....4	C120	2203-000851	C-CER,CHIP;0.039nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000872	C-CER,CHIP;0.0030nF,0.25pF,50V,C0G,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-000998	C-CER,CHIP;0.047nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001034	C-CER,CHIP;5.6nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001071	C-CER,CHIP;0.056nF,5%,50V,C0G,1608	1	S.A
....4	C120	2203-001554	C-CER,CHIP;1.8nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-001630	C-CER,CHIP;330nF,+80-20%,16V,Y5V,1608	1	S.A
....4	C120	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005005	C-CER,CHIP;100nF,10%,16V,X7R,1608	1	S.A
....4	C120	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	S.A
....4	C120	2203-005030	C-CER,CHIP;470nF,+80-20%,50V,Y5V,TP,3216	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,1608	1	S.A
....4	C120	2203-005261	C-CER,CHIP;1000nF,10%,25V,X7R,3216	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-005533	C-CER,CHIP;1000nF,20%,6.3V,X7R,TP,1608	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C120	2203-006333	C-CER,CHIP;10000nF,20%,16V,X5R,TP,3216	1	S.A
....4	C1003	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C102	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C103L	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1311	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C133	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1503	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1504	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C1780	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C191	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C214	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C323	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C342	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C402	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C506	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C510	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C517	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C712	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C836	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C838	2402-001086	C-AL,SMD;100UF,20%,16V,WT,TP,6.6X6.6X5.3	1	S.A
....4	C105	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1051	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1054	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1055	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C113	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C147	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C165	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C167	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1701	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C1732	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C175	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C189	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C343	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C346	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C501	2402-001128	C-AL,SMD;100##F,20%,16V,-,TP,6.3X5.7mm	1	S.A
....4	C330	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C531	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C937	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C953	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	1	S.A
....4	C1517	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C519	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	C524	2402-001147	C-AL,SMD;3.3UF,20%,50V,WT,TP,4X5.8MM	1	S.A
....4	C1006	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C106	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C111	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1111	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1322	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C1779	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C302	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C332	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C505	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C512	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C527	2402-001183	C-AL,SMD;22UF,20%,16V,WT,TP,5.3X5.3X6MM	1	S.A
....4	C156L	2402-001218	C-AL,SMD;22UF,20%,35V,WT,TP,6.6X6.6X5.8M	1	S.A
....4	C319	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	S.A
....4	C347	2402-001226	C-AL,SMD;4.7UF,20%,35V,HR,TP,4.3X4.3X5.8	1	S.A
....4	C118	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C135	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C161L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C181	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C188	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C922L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C923L	2402-001268	C-AL,SMD;100uF,+-20%,25V,WT,REEL,8x6.3	1	S.A
....4	C406	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C422	2402-001273	C-AL,SMD;220uF,20%,35V,WT,REEL,10X10mm	1	S.A
....4	C138	2409-001029	C-ORGANIC,SMD;120##F,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C168	2409-001029	C-ORGANIC,SMD;120##F,20%,6.3V,WT,TP,8.3x	1	S.A
....4	C140	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	C171	2409-001065	C-ORGANIC;82uF,20%,16V,WT,TP,8X6.9mm,-	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000398	INDUCTOR-SMD;10uH,10%,3225	1	S.A
....4	T0052	2703-000417	INDUCTOR-SMD;220uH,5%,3225	1	S.A
....4	T0052	2703-001426	INDUCTOR-SMD;680uH,20%,7070	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	T0052	2703-001778	INDUCTOR-SMD;3.3uH,20%,3225	1	S.A
....4	L401	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	L402	2704-000018	INDUCTOR-SMD-ARRAY;15uH,2000mA,2,0.124oh	1	S.N.A
....4	X1301	2801-000258	CRYSTAL-SMD;0.032768MHz,20ppm,SMD,12.5pF	1	S.A
....4	X201	2801-003326	CRYSTAL-SMD;24MHZ,30PPM,28-ABX,20PF,50OH	1	S.A
....4	X301	2801-004300	CRYSTAL-SMD;18.432MHz,30ppm,28-ABX,13pF,	1	S.A
....4	X1101	2801-004483	CRYSTAL-SMD;28.322MHz,30ppm,HC-49,20pF,5	1	S.A
....4	X1303	2801-004629	CRYSTAL-SMD;27MHz,20ppm,12pF,50ohm,TP	1	S.A
....4	T0568	3301-000314	BEAD-SMD;120ohm,1.6x0.8x0.8mm,-,-,-	1	S.N.A
....4	T0568	3301-001082	BEAD-SMD;60ohm,3225,TP,43ohm/40MHz,83ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001145	BEAD-SMD;60ohm,4516,TP,70ohm/45MHz,82ohm	1	S.N.A
....4	T0568	3301-001148	BEAD-SMD;60ohm,1608,TP,-,-	1	S.N.A
....4	T0568	3301-001148	BEAD-SMD;60ohm,1608,TP,-,-	1	S.N.A
....4	T0568	3301-001163	BEAD-SMD;80ohm,2012,TP,-,192ohm/867MHz	1	S.N.A
....4	T0568	3301-001163	BEAD-SMD;80ohm,2012,TP,-,192ohm/867MHz	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001236	BEAD-SMD;60ohm,1608,-,-,-	1	S.N.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001324	BEAD-SMD;15ohm,2012,600mA,TP,,,0.1ohm	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MHz	1	S.A
....4	T0568	3301-001569	BEAD-SMD;600ohm,2012,1000mA,TP,520ohm/90	1	S.N.A
....4	T0313	3404-001207	SWITCH-TACT;12V,50mA,160gf,6.2X6.2,SPST	1	S.A
....4	JA801	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A
....4	JA803	3701-001367	CONNECTOR-HDMI;19P,2R,FEMALE,SMD,AU	1	S.A
....4	L101	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	L103	BN27-00008A	COIL CHOKE-SMD;SMD12*12*8.5,GH15/17PS,22	1	S.A
....4	T0077	BN41-00840C	PCB MAIN;Bordeaux+/Calla,FR-4,4,1.6T,192	1	S.N.A
....4	M0018	BN97-01688C	ASSY MICOM;T-BRDPHUS0-1001,N34A,200709.1	1	S.N.A
.....5	IC115	1107-001666	IC-FLASH MEMORY;KFG5616U1A,256Mbit,16Mx1	1	S.N.A
....4	M0018	BN97-01688D	ASSY MICOM;T-BRDPHUS5-1001,N34A,200709.1	1	S.N.A
.....5	IC520	0903-001485	IC-MICROCONTROLLER;44P,12x12mm,24MHz,TR,	1	S.N.A
....4	Q409	0505-002169	FET-SILICON;Si4435BDY-T1-E3,P,-30V,-9.1A	1	S.N.A
...3	T0603	BN63-03195B	SHIELD-PCB MAIN;TULIP NT,SPTE,T0.3	1	S.N.A
...3	CIS02	BN73-00024B	SILICON/RUBBER-GAP PAD;POSEIDON,SILICON,	1	S.N.A
0.1		BN91-01660B	ASSY SHIELD-AME;LNT2653HTX/XAA	1	S.N.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	6	S.A
..2	M0081	6003-000115	SCREW-TAPTITE;BH,+,B,M3,L6,ZPC(BLK),SWRC	4	S.A

Level	Loc. No.	Code No.	Description & Specification	Q'ty	SA/SNA
..2	M0081	6003-000337	SCREW-TAPTITE;BH,+,S,M4,L10,ZPC(BLK),SWR	4	S.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	2	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	1	S.N.A
..2	M0081	6003-001188	SCREW-TAPTITE;BH,+,-,B,M4,L10,ZPC(WHT),S	6	S.N.A
..2	M0081	6003-001439	SCREW-TAPTITE;BH,+,-,S,M4,L8,ZPC(WHT),SW	1	S.N.A
..2	M2893	BH39-00362G	LEAD CONNECTOR;SONOMA,UL1007#26,5PIN,100	1	S.A
..2	M2893	BN39-00603E	LEAD CONNECTOR;RE26**AU,UL1007#26,14P,15	1	S.A
..2	T0076	BN39-00615D	CBF HARNESS;BORDEAUX,1617#22,3P,1P,RING,	1	S.A
..2	M2893	BN39-00836A	LEAD CONNECTOR;LNT2342HX,UL1571#30,30P,2	1	S.A
..2	T0764	BN44-00156A	SMPS-LCDTV;MK32P,SEM,AC/DC,180W,AC100 ~	1	S.A
..2	M0146	BN61-02207A	BRACKET-PANEL SIDE;Bordeaux 26,SECC,T1.2	4	S.N.A
..2	M0114	BN61-02500A	HOLDER-WIRE;NYLON6.6,NATURAL	2	S.N.A
..2	M0254	BN61-02875A	HOLDER-SIDE AV;07,COMMON,UO,PC+ABS,V0,-,	1	S.N.A
..2	M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.A
..2	T0447	BN96-04682E	ASSY BRACKET P-PANEL;-,26R81,UO(HOTEL),-	1	S.N.A
...3	M0146	BN61-02205B	BRACKET-PANEL TOP;Bordeaux 26,SECC,T1.2	1	S.N.A
...3		BN61-02210A	BRACKET-GUIDE POWER;Bordeaux 26,SECC,T1.	1	S.N.A
...3		BN61-02966A	BRACKET-GUIDE POWER;23 BORDEAUX PLUS,SEC	1	S.N.A
...3		BN61-02973B	BRACKET-PANEL BOTTOM;26R81,SECC,T1.2,AUO	1	S.N.A
...3		BN61-02976A	BRACKET-GUIDE MAIN;26 BORDEAUX PLUS,SECC	1	S.N.A
...3	M0131	BN63-02549A	GASKET;LE37R72B,Conductive Fabric,26mm,1	1	S.N.A
...3	M0131	BN63-02712A	GASKET;LE40M71BX,Conductive Fabric,8mm,1	2	S.N.A
..2	M2893	BN39-00802B	LEAD CONNECTOR;LE40R86BDX,UL1007#26,24PI	1	S.A
0.1	M0003	BN92-02379P	ASSY BOX;26R81,UO(HOTEL)	1	S.N.A
..2	T0130	BN69-01730G	BOX-00,SET;26R8,CB,SY-05,A,YEL,A1,EXPORT	1.02	S.N.A
0.1	M0113	BN92-02380B	ASSY P/MATERIAL;26R71,UO	1	S.N.A
..2	T0214	BN74-00008A	TAPE-OPP MASKING;OPP-2,T0.05,W100,L800M,	1.8	S.N.A
..2	T0376	6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	0.016	S.N.A
..2	T0376	6902-000379	BAG AIR;LDPE,T0.2,W1000,L1800,TRP,-,--	0.004	S.N.A
..2	T0003	6902-000604	BAG WRAPPING;LDPE,T0.02,W500,L10000,TRP,	3.2	S.N.A
..2	T0524	6902-000737	BAG PE;HDPE/HDPE/NITRON (DOUBLE),T0.015/	1	S.N.A
0.1	M0045	BN92-02776A	ASSY ACCESSORY;LNT2353HTX/XAA	1	S.N.A
..2	M0045	BN96-05698A	ASSY ACCESSORY;LNT2353HTX/XAA,-,-,-,-,-	1	S.A
...3	T0268	3903-000144	CBF-POWER CORD;DT,US,BP3/Y,U(IEC C13-RA)	1	S.A
...3	T0524	6902-000110	BAG PE;LDPE,T0.05,W250,L400,TRP,28,2	1	S.N.A
...3	M0521	BN39-00865A	CBF IF-MODULAR/MODULAR;Bordeaux Plus HOT	1	S.A
...3	T0511	BN68-01083C	MANUAL USERS;COMM,SAMSUNG,English,N.Amer	1	S.N.A
...3	M0045	BN96-01800A	ASSY ACCESSORY;ROME32,-,-,-,-,SCREW	1	S.A
....4	T0081	6002-001294	SCREW-TAPPING;BH,+,,M4,L16,ZPC(BLK)	4	S.A
....4	ACCESSORY	6902-000128	BAG ZIPPER;LDPE,T0.05,W200,L150,TRP,8,2-	1	S.N.A
...3	T0511	AA68-03242L	MANUAL FLYER-SAFETY GUIDE;comm,Samsung,E	1	S.N.A
0.1	M0019	BN92-02789B	ASSY LABEL;LNT2653HTX/XAA	1	S.N.A

5 Exploded View and Parts List

- You can search for updated part codes through ITSELF web site.
  URL : http://itself.sec.samsung.co.kr/

5-1 LNT2353HT/LNT2354H Exploded View



5-2 LNT2353HT/LNT2354H Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04660A	ASSY COVER P-FRONT;23R81,UO,,PC,V0,,BK27	1	S.A	
M0215	BN07-00365A	LCD-PANEL;T230XW01,8bit,23inch,16.7M,16:	1	S.A	
M0107	BN61-03037A	BRACKET-PCB;23 BORDEAUX PLUS,SECC,T1.0	1	S.N.A	
M0146	BN61-03060A	BRACKET-PANEL SIDE;BORDEAUX PLUS 23,SECC	2	S.N.A	
M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.N.A	
M0014	BN94-01334E	ASSY PCB MAIN-AUO TN;LNT2353HTX/*	1	S.A	
M0027	BN96-04663A	ASSY STAND P-BASE;23,26R81,NORMAL,-,ABS+	1	S.A	
M0013	BN96-04668D	ASSY COVER P-REAR;23R81,UO(HOTEL),,PC+AB	1	S.A	

5-3 LNT2653H Exploded View



5-4 LNT2653H Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04659A	ASSY COVER P-FRONT;26R81,UO,-,PC,V0,BK27	1	S.A	
T0175	BN96-04767A	ASSY SPEAKER P;16ohm,4pin,5W,Bordeaux Pl	2	S.A	
M0215	BN07-00254A	LCD-PANEL;T260XW02,8bit,626.0*373.0*50.0	1	S.A	
T0447	BN96-04682B	ASSY BRACKET P-PANEL;26R81,AUO	1	S.N.A	
M0115	BN61-02965A	BRACKET-STAND LINK;32 BORDEAUX PLUS,SECC	1	S.N.A	
M0146	BN61-02207A	BRACKET-PANEL SIDE;Bordeaux 26,SECC,T1.2	4	S.N.A	
M0014	BN94-01183B	ASSY PCB MAIN;LNT2653HX/*	1	S.A	
M0027	BN96-04663A	ASSY STAND P-BASE;23,26R81,NORMAL,-,ABS+	1	S.A	
M0013	BN96-04667A	ASSY COVER P-REAR;26R81,UO,-,PC+ABS,V0,B	1	S.A	

10 Operating Instructions and Installation

10-1 Front



Front Panel buttons
Touch the right side of each button to operate.

- The product color and shape may vary depending on the model.

1. SOURCE

Toggles between all the available input sources (TV, AV1, AV2, S-Video 1, S-Video 2, Component1, Component2, PC, HDMI1, HDMI2, HDMI3).
In the on-screen menu, use this button as you use the **ENTER** button on the remote control.

2. MENU

Press to see an on-screen menu of your TV's features.

3. + VOL −

Press to decrease or increase the volume.
In the on-screen menu, use the + VOL − buttons as you use the ◄ and ► buttons on the remote control.

4. ∧ CH ∨

Press to change channels.
In the on-screen menu, use the ∧ CH ∨ buttons as you use the ▼ and ▲ buttons on the remote control.

5. ⏻ (POWER)

Press to turn the TV on and off.
POWER INDICATOR
Blinks and turns off when the power is on and lights up in stand-by mode.

6. Remote Control Sensor

Aim the remote control towards this spot on the TV.

7. SPEAKERS

10-2 Connection Panel



1. AUDIO OUT
Connect to the audio input jacks on your Amplifier/ Home theater.

2. DIGITAL AUDIO OUT (OPTICAL)
Connect to a Digital Audio component.

3. PC IN
Connect to the video and audio output jacks on your PC.

4. HDMI IN 1,2,3 /DVI IN(HDMI1) (AUDIO R/L)
Connect to the HDMI jack of a device with an HDMI output.
Use the HDMI/DVI terminal for DVI connection to an external device. You should use the DVI to HDMI cable or DVI-HDMI adapter (DVI to HDMI) for the connection, and the DVI IN 'R -AUDIO -L' terminal for audio.
- The HDMI IN 1 terminal does not support PC connection
- No sound connection is needed for an HDMI to HDMI connection.
- When using an HDMI/DVI cable connection, you must use the HDMI IN 1 terminal.
- 23,26 inch model supports HDMI1 and HDMI2 only.

5. ANT 1 IN/ANT 2 IN
Connect to an antenna or cable TV system.

6. EX LINK
Connector for Wall Mount Adjustment only.

7. COMPONENT IN
Connect Component video/audio.

8. Service (LN-T2353H, LN-T2354H, LN-T2653H)
Connector for SERVICE only

9. AV IN 1 / AV IN 2
Video and audio inputs for external devices, such as a camcorder or VCR.
S-VIDEO
Connect an S-Video signal from a camcorder or VCR.

10. POWER INPUT
Connect the supplied power cord.

11. KENSINGTON LOCK
The Kensington lock (optional) is a device used to physically fix the system when used in a public place. If you want to use a locking device, contact the dealer where you purchased the TV.

12. HEADPHONE
Connects a set of external headphones for private listening.

10-3 Remote Control



- This is a special remote control for the visually impaired, and has Braille points on the Power, Channel and Volume buttons.

1. POWER
Turns the TV on and off.

2. NUMERIC BUTTONS
Press to change the channel.

3. _
Press to select additional channels (digital and analog) being broadcast by the same station.
For example, to select channel "54-3", press "54", then press "_" and "3".

4. CH LIST
Used to display Channel Lists on the screen.

5. ANTENNA
Press to select "AIR" or "CABLE".

6. VCR/DVD Functions
- Rewind
- Stop
- Play/Pause
- Fast/Forward

7. VOL ⊕ / VOL ⊖
Press to increase or decrease the volume.

8. (MUTE)
Press to temporarily cut off the sound.

9. MENU
Displays the main on-screen menu.

10. S.MODE
Sound mode selection.

11. RETURN
Returns to the previous menu.

12. P.MODE
Press to select the picture mode.

13. SRS
Selects SRS TruSurround XT mode.

14. MTS
Press to choose stereo, mono or Separate Audio Program (SAP broadcast).

15. SLEEP
Press to select a preset time interval for automatic ahut off.

16. AUTO PROG.
Press to automatically store selected TV/Cable channels.

17. SET
Sets the remote to control your TV, VCR, Cable, DVD, or Set-Top Box

18. TV, DVD, STB, CABLE, VCR
Press to operate your TV,DVD, STB, CABLE (box), or VCR

19. When pressing this button, a number of buttons on the remote control (e.g. TV, DVD, STB, CABLE, VCR, MUTE, VOL and CH buttons) light up for a few seconds and then turn off to save power.
This function is convenient for using the remote at night or when dark.

20. SOURCE
Press to display all of the available video sources.

21. PRE-CH
Tunes to the previous channel.

22. FAV.CH
Press to switch to your favorite channels.

23. HDMI
Selects the HDMI mode directly.

24. CH ⊙ / CH ⊙
Press to change channels.

25. EXIT
Press to exit the menu.

26. UP ▲ / DOWN ▼ / LEFT ◄ / RIGHT ► / ENTER ↵
Use to select on-screen menu items and change menu values.

27. INFO
Press to display information on the TV screen.

28. CAPTION
Controls the caption decoder.

29. STILL
Press to stop the action during a particular scene.
Press again to resume normal video.

30. P.SIZE
Picture size selection.

31. PIP
Picture-in Picture ON/OFF.

32. CH ∧ / ∨
Displays the available channels in sequence.
(These buttons change channels in the PIP window only.)

33. ADD/DEL
Use to store and delete channels to/from memory.

34. RESET
When your remote does not work, change the batteries and press the RESET button for 2-3 seconds before use.

12 PCB Diagram

12-1 Main PCB Diagram for LNT2353H, LNT2653H



12-2 Main PCB Diagram for LNT3753H



12-3 Power PCB Layout 23"



12-4 Power PCB Layout 26"



12-5 Power PCB Layout 37"



Memo

1 Precautions

Follow these safety, servicing and ESD precautions to prevent damage and to protect against potential hazards such as electrical shock.

1-1 Safety Precautions

1-1-1 Warnings

1. For continued safety, do not attempt to modify the circuit board.
2. Disconnect the AC power and DC power jack before servicing.

1-1-2 Servicing the LCD Monitor

1. When servicing the LCD Monitor, Disconnect the AC line cord from the AC outlet.
2. It is essential that service technicians have an accurate voltage meter available at all times. Check the calibration of this meter periodically.

1-1-3 Fire and Shock Hazard

Before returning the monitor to the user, perform the following safety checks:

1. Inspect each lead dress to make certain that the leads are not pinched or that hardware is not lodged between the chassis and other metal parts in the monitor.
2. Inspect all protective devices such as nonmetallic control knobs, insulating materials, cabinet backs, adjustment and compartment covers or shields, isolation resistor-capacitor networks, mechanical insulators, etc.
3. Leakage Current Hot Check (Figure 1-1):

   WARNING : Do not use an isolation transformer during this test.

   Use a leakage current tester or a metering system that complies with American National Standards Institute (*ANSI C101.1, Leakage Current for Appliances*), and Underwriters Laboratories (*UL Publication UL1410, 59.7*).



Figure 1-1. Leakage Current Test Circuit

4. With the unit completely reassembled, plug the AC line cord directly into a 120V AC outlet. With the unit's AC switch first in the ON position and then OFF, measure the current between a known earth ground (metal water pipe, conduit, etc.) and all exposed metal parts, including: metal cabinets, screwheads and control shafts. The current measured should not exceed 0.5 milliamp. Reverse the power-plug prongs in the AC outlet and repeat the test.

1-1-4 Product Safety Notices

Some electrical and mechanical parts have special safety-related characteristics which are often not evident from visual inspection. The protection they give may not be obtained by replacing them with components rated for higher voltage, wattage, etc. Parts that have special safety characteristics are identified by ⚠ on schematics and parts lists. A substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire and/or other hazards. Product safety is under review continuously and new instructions are issued whenever appropriate.

1-2 Servicing Precautions

WARNING: An electrolytic capacitor installed with the wrong polarity might explode.

Caution: Before servicing units covered by this service manual, read and follow the Safety Precautions section of this manual.

Note: If unforeseen circumstances create conflict between the following servicing precautions and any of the safety precautions, always follow the safety precautions.

1-2-1 General Servicing Precautions

1. Always unplug the unit's AC power cord from the AC power source and disconnect the DC Power Jack before attempting to:
   (a) remove or reinstall any component or assembly, (b) disconnect PCB plugs or connectors, (c) connect a test component in parallel with an electrolytic capacitor.
2. Some components are raised above the printed circuit board for safety. An insulation tube or tape is sometimes used. The internal wiring is sometimes clamped to prevent contact with thermally hot components. Reinstall all such elements to their original position.
3. After servicing, always check that the screws, components and wiring have been correctly reinstalled. Make sure that the area around the serviced part has not been damaged.
4. Check the insulation between the blades of the AC plug and accessible conductive parts (examples: metal panels, input terminals and earphone jacks).
5. Insulation Checking Procedure: Disconnect the power cord from the AC source. Connect an insulation resistance meter (500 V) to the blades of the AC plug.

   The insulation resistance between each blade of the AC plug and accessible conductive parts (see above) should be greater than 1 megohm.
6. Always connect a test instrument's ground lead to the instrument chassis ground before connecting the positive lead; always remove the instrument's ground lead last.

1-3 Electrostatically Sensitive Devices (ESD) Precautions

Some semiconductor (solid state) devices can be easily damaged by static electricity. Such components are commonly called Electrostatically Sensitive Devices (ESD). Examples of typical ESD are integrated circuits and some field-effect transistors. The following techniques will reduce the incidence of component damage caused by static electricity.

1. Immediately before handling any semiconductor components or assemblies, drain the electrostatic charge from your body by touching a known earth ground. Alternatively, wear a discharging wrist-strap device. To avoid a shock hazard, be sure to remove the wrist strap before applying power to the monitor.
2. After removing an ESD-equipped assembly, place it on a conductive surface such as aluminum foil to prevent accumulation of an electrostatic charge.
3. Do not use freon-propelled chemicals. These can generate electrical charges sufficient to damage ESDs.
4. Use only a grounded-tip soldering iron to solder or desolder ESDs.
5. Use only an anti-static solder removal device. Some solder removal devices not classified as "anti-static" can generate electrical charges sufficient to damage ESDs.
6. Do not remove a replacement ESD from its protective package until you are ready to install it. Most replacement ESDs are packaged with leads that are electrically shorted together by conductive foam, aluminum foil or other conductive materials.
7. Immediately before removing the protective material from the leads of a replacement ESD, touch the protective material to the chassis or circuit assembly into which the device will be installed.

   Caution: Be sure no power is applied to the chassis or circuit and observe all other safety precautions.
8. Minimize body motions when handling unpackaged replacement ESDs. Motions such as brushing clothes together, or lifting your foot from a carpeted floor can generate enough static electricity to damage an ESD.

1-4 Installation Precautions

1. For safety reasons, more than two people are required for carrying the product.

2. Keep the power cord away from any heat emitting devices, as a melted covering may cause fire or electric shock.

3. Do not place the product in areas with poor ventilation such as a bookshelf or closet. The increased internal temperature may cause fire.

4. Otherwise, it may cause a fire or electric shock.

5. Make sure to turn the power off and unplug the power cord from the outlet before repositioning the product. Also check the antenna cable or the external connectors if they are fully unplugged. Damage to the cord may cause fire or electric shock.

6. Keep the antenna far away from any high-voltage cables and install it securely. Contact with the highvoltage cable or the antenna falling over may cause fire or electric shock.

7. When installing the product, leave enough space (10cm) between the product and the wall for ventilation purposes.
   A rise in temperature within the product may cause fire.

Memo

2 Product Specifications

2-1 Features

- RF, 2-HDMI(3-HDMI only for LNT3753H), DVI-D, Component, AV, S-Video
- Brightness : 450cd/㎡
- Contrast Ratio : 4000:1
- Response time : 8ms
- Dynamic contrast
- PIP (on PC only)

2-2 Specifications

2-2-1 LNT2353H/LNT2354H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, SPVA mode, normaly black, 23-Inch viewable, 0.51075 (H) x 0.1705 (W)*3 mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal : 1366 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75Ω, internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	697.6845 (H) mm / 392.256 (V) mm	
AC power voltage & Frequencya	AC 110 , 60Hz	
Power Consumption	< 100W (< 1W, stand by)	
Dimensions(W x D x H) Set	586 x 79 x 406 mm_with stand	
Weight Set(After installation Stand)	8.1 kg	
TV System	Tunning	Frequency Synthesize
	System	ATSC, NTSC3.58
	Sound	NTSC-M, AC-3 Digital
Environmental Considerations	Operating Temperature : 10℃ ~ 40℃ Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antena Input	75Ω	
Sound Characteristic	- MAX Internal speaker Out : Right => 5W, Left => 5W -BASS Control Range : -8 dB ~ + 8dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-2-2 LNT2653H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, SPVA mode, normaly black, 26-Inch viewable, 0.648(H) x 0.216(W)*3 mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal : 1366 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75Ω, internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	80 MHz	
Active Display Horizontal/Vertical	885.168(H) mm / 497.664(V) mm	
AC power voltage & Frequencya	AC 110 , 60Hz	
Power Consumption	< 140W (< 1W, stand by)	
Dimensions(W x D x H) Set	666 x 75 x 461 mm_with stand	
Weight Set(After installation Stand)	9.8 kg	
TV System	Tunning	Frequency Synthesize
	System	ATSC, NTSC3.58
	Sound	NTSC-M, AC-3 Digital
Environmental Considerations	Operating Temperature : 10°C ~ 40°C Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antena Input	75Ω	
Sound Characteristic	- MAX Internal speaker Out : Right => 5W, Left => 5W -BASS Control Range : -8 dB ~ + 8dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-2-3 LNT3753H Specifications

Item	Description	
LCD Panel	TFT-LCD panel, RGB vertical stripe, SPVA mode, normaly black, 37-Inch viewable, 0.600(H) x 0.600(V)*3 mm pixel pitch	
Scanning Frequency	Horizontal : 30 kHz ~ 61 kHz (Automatic) / Vertical : 60 Hz ~ 75 Hz (Automatic)	
Display Colors	16.7 Million colors	
Maximum Resolution	Horizontal : 1366 Pixels Vertical : 768 Pixels	
Input Video Signal	Analog 0.7 Vp-p ± 5% positive at 75Ω , internally terminated	
Input Sync Signal	Type : Seperate H/V Level : TTL level	
Maximum Pixel Clock rate	85.8MHz	
Active Display Horizontal/Vertical	819.6(H)mm / 460.8(V)mm	
AC power voltage & Frequencya	AC 110 , 60Hz	
Power Consumption	< 180W (< 1W, stand by)	
Dimensions(W x D x H) Set	916.5 x 300.0 x 660.1 mm_with stand	
Weight Set(After installation Stand)	20.1kg	
TV System	Tunning	Frequency Synthesize
	System	ATSC, NTSC3.58
	Sound	NTSC-M, AC-3 Digital
Environmental Considerations	Operating Temperature : 10℃ ~ 40℃ Operating Humidity : 10 % ~ 80 %, non-condensing Storage Temperature : -20°C ~ 45°C Storage Humidity : 5 % ~ 95 %, non-condensing	
Antena Input	75Ω	
Sound Characteristic	- MAX Internal speaker Out : Right => 10W, Left => 10W -BASS Control Range : -8 dB ~ + 8dB -TREBLE Control Range : -8 dB ~ +8 dB -Headphone Out : 10 mW MAX -Output Frequency : RF : 80 Hz ~ 15 kHz A/V : 80 Hz ~ 20 kHz	

2-2-4 Spec Comparison

Model	LNT2353H/LNT2354H/ LNT2653H/LNT3753H	LN-S2651D / LN-S3251D / LN-S4051D / LN-S2652D / LN-S3252D / LN-S4052D /
Design		
Frequency Horizontal Vertical Display Color	30 ~ 61 kHz 60 ~ 75 Hz 16,777,216 colors	30 ~ 61 kHz 60 ~ 75 Hz 16,777,216 colors
PC Resolution Maximum mode	1366 x 768 / 60 Hz	1360 x 768 / 60 Hz
Input Signal Sync Signal Video Signal	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm	H/V Separate, TTL, P. or N. 0.7 Vp-p @ 75ohm
Power Consumption Normal Power Saving	100W/140W/180W < 1W	133W / 165W / 218W < 1W
Input source Difference	2HDMI/3HDMI	2HDMI
PIP	PIP	PIP, POP
Sound	5W / 10W	3W / 5W / 10W

2-3 Option Specification

Item	Item Name	Code.No	Remark
	Remote Control & Batteries (AAA x 2)	LN-T2353H, LN-T2653H, LNT3753H (BN59-00598A) LN-T2354H (BN59-00615A)	
	Power Cord	3903-000144	
	Cover-Bottom	LN-T2353H, LN-T2653H (BN63-03221B) LN-T2354H (BN63-03221C) LNT3753H (BN63-03113B)	
	Stand	LN-T2353H (BN96-04663A) LN-T2354H (BN96-04663B) LN-T2653H (BN96-04663A) LNT3753H (BN96-04661A)	
	Stand Screw (4 ea)	LN-T2353H, LN-T2653H, LNT3753H (6002-001294) LN-T2354H (6003-001324) LNT3753H (BN96-04661A)	
	Owner's Instructions	LNT2353H, LNT2353H (BN68-01156B) LNT2353H (BN68-01156M)	
	Cleaning Cloth	BN63-01798A	
	Warranty Card / Registration Card /Safety Guide Manual (Not available in all locations)	AA68-00371C/ AA68-03870C, AA68-03870D/ AA68-03242L	

14 Reference Infomation

14-1 Technical Terms

- TFT-LCD
(Thin film Transistor Liquid Crystal Display)
ADC(Analog to Digital Converter)
This is a circuit that converts from analog signal to digital signals.

- PLL(Phase Locked Loop)
During progressing ADC, Device makes clock synchronizing HSYNC with Video clock

- Inverter
Device that supply Power to LCD panel lamp. this device gernerate about 1,500~2,000V.

- AC Adapter
Device that converts AC(90V~240V) to DC(+12V or 14V)

- SMPS(Switching Mode Power Supply)
Switching Mode Power supply. This design technology is used to step up/down the input power by switching on/off

- FRC(Frame Rate Controller)
Technology that change image frame quantity displayed on screen for one second.
Actually TFT-LCD panel require 60 pcs of frame for one second.
so,this technology is needed to convert input image to 60 pcs regardless input frame quantity.

- Image Scaler
Technology that convert various input resolution to other resolution.(ex. 640* 480 to 1024*768)

- Auto Configuration(Auto adjustment)
This is an algorithm to adjust monitor to optimum condition by pushing one key.

- OSD(On Screen Display)
On screen display. customer can control the screen easily with this.

- Image Lock
This means "Fineness adjustment " in LCD Monitor, the features are "Fine" and "Coarse"

- FINE
"Fine" adjustment is used to adjust visibility by control phase difference.

- COARSE
This is a adjustment by tuning with Video colck and PLL clock.

- DVI (Digital Visual Interface)
This provides a high speed digital connection for visual data types that is display technology independent. this interface is primarily forcused at providing a connection between a computer and its display device.

- L.V.D.S.(Low Voltage Differential Signaling)
a kind of transmission method for Digital.It can be used from Main PBA to Panel.

- DVI (Digital Visual Interface)
This provides a high speed digital connection for visual data types that is display technology independent. this interface is primarily forcused at providing a connection between a computer and its display device.

- T.M.D.S
(Transition minimized Differential Signaling)
a kind of transmission method for Digital.
It can be used from Video card to Main PBA.

- DDC(Display data channel)
It is a communication method between Host Computer and related equipment.
It can make it Plug and Play between PC and Monitor.

- EDID
Extended Display Identification Data PC can recognize the monitor information as Product data, Product name,Display mode,Serial number and Signal source,etc through DDC Line communicating with PC and Monitor.

- Dot Pitch
The image on a monitor is composed of red, green and blue dots. The closer the dots, the higher the resolution. The distance between two dots of the same color is called the 'Dot Pitch'. Unit: mm

- Vertical Frequency
The screen must be redrawn several times per second in order to create and display an image for the user. The frequency of this repetition per second is called Vertical Frequency or Refresh Rate. Unit: Hz
Example: If the same light repeats itself 60 times per second, this is regarded as 60 Hz.

- Horizontal Frequency
The time to scan one line connecting the right edge to the left edge of the screen horizontally is called Horizontal Cycle. The inverse number of the Horizontal Cycle is called Horizontal Frequency. Unit: kHz

- Interlace and Non-Interlace Methods
Showing the horizontal lines of the screen from the top to the bottom in order is called the Non-Interlace method while showing odd lines and then even lines in turn is called the Interlace method. The Non-Interlace method is used for the majority of monitors to ensure a clear image. The Interlace method is the same as that used in TVs.

- **Plug & Play**
This is a function that provides the best quality screen for the user by allowing the computer and the monitor to exchange information automatically. This monitor follows the international standard VESA DDC for the Plug & Play function.

- Resolution
The number of horizontal and vertical dots used to compose the screen image is called 'resolution'. This number shows the accuracy of the display. High resolution is good for performing multiple tasks as more image information can be shown on the screen.
Example: If the resolution is 1280 x 1024 , this means the screen is composed of 1280 horizontal dots (horizontal resolution) and 1024 vertical lines (vertical resolution).

- BTSC
Broadcast Television System Committee
The stereo broadcasting system that is used in most of the countries that have adopted the NTSC system, including the United States, Canada, Chile, Venezuela and Taiwan. It also refers to the organization that has been organized to promote its development and management.

- EIAJ
Electronic Industries Association of Japan.

- RF Cable
A round signal cable generally used for TV antennas.

- Satellite Broadcasting
Broadcasting service provided via satellite. Enables high picture quality and clear sound throughout the country regardless of the location of the viewer.

- Sound Balance
Balances the levels of the sound coming from each speaker in televisions with two speakers.

- Cable TV
Whereas the terrestrial broadcasting is delivered via frequency signals through the air, cable broadcasting is transmitted via a cable network. In order to view cable TV, one must purchase a cable receiver and hook it up to the cable network.

- CATV
"CATV" refers to the broadcasting service offered at hotels, schools and other buildings through their own broadcasting system, apart from VHF or UHF broadcasting by terrestrial broadcasters. The CATV programs may include movies, entertainment and educational programs. (Different from cable TV.)

CATV can be viewed only within the area in which the CATV service is offered.

- S-Video
Short for "Super Video." S-Video allows up to 800 lines of horizontal resolution, enabling high-quality video.

- VHF/UHF
VHF indicates TV channels 2 to 13, and UHF indicates channels 14 through 69.

- Channel Fine Tuning
This feature allows the viewer to fine-tune the TV channel to obtain the best viewing conditions. The Samsung LCD TV has both automatic and manual channel fine-tuning features to enable the viewer to adjust their desired settings.

- External Device Input
External device input refers to video input from such external video devices as VCRs, camcorders and DVD players, separate from a TV broadcast.

14-2 Pin Assignments

14-2-1 DVI-D

Sync Type / Pin No.	24P DVI-D		
1	Rx2-	13	NC
2	Rx2+	14	DDC Input power (+5V)
3	GND	15	IDENT-DVI
4	NC	16	Output Signal (HDCP Control)
5	NC	17	Rx0-
6	DDC - SCL	18	Rx0+
7	DDC - SDA	19	GND
8	NC	20	NC
9	Rx1-	21	NC
10	Rx1+	22	GND
11	GND	23	RxC+
12	NC	24	RxC-



Figure 1.

14-2-2 Component 1, 2

RCA Green	Y
	GND
RCA Blue	Pb (Cb)
	GND
RCA Red	Pr (Cr)
	GND
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-2-3 S-Video

Pin	Separate
1	GND
2	Y
3	C
4	GND
5	GND

14-2-4 A/V 1,2

RCA Yellow	CVBS
RCA White	Audio L
	GND
RCA Red	Audio R
	GND

14-2-5 D-SUB

Pin	Separate
1	Red
2	Green
3	Blue
4	GND
5	GND
6	GND Red
7	GND Green
8	GND Blue
9	DDC Input power(+5V)
10	IDENT PC
11	GND
12	DDC Data(SDA)
13	H SYNC
14	V SYNC
15	DDC Clock(SCL)

14-2-6 PC Display mode

Both screen position and size will vary depending on the type of PC monitor and its resolution.

The resolutions in the table are recommended. (All resolutions between the supported limits are supported)

Mode	Resolution	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Pixel Clock Frequency (MHz)	Sync Polarity (H/V)
IBM	640 x 480	31.469	59.940	25.175	- / -
	720 x 400	31.469	70.087	28.322	- / +
VESA	640 x 480	37.861	72.809	31.500	- / -
	640 x 480	37.500	75.000	31.500	- / -
	800 x 600	37.879	60.317	40.000	+ /+
	800 x 600	48.077	72.188	50.000	+ /+
	800 x 600	46.875	75.000	49.500	+ /+
	1024 x 768	48.364	60.000	65.000	- / -
	1024 x 768	56.476	70.069	75.000	- / -
	1024 x 768	60.023	75.029	78.750	+ /+
	1360 x 768	47.712	60.015	85.800	+ /+

- The interlace mode is not supported.

- The set might operate abnormally if a non-standard video format is selected.

- DVI dose not support PC function.

14-3 Timing Chart

This section of the service manual describes the timing that the computer industry recognizes as standard for computer-generated video signals.

14-3-1 LCD Panel Mode1 mode

Timing No.	LTA400W2
Originator	VESA
Mode Name	1366/60Hz
Resolution (HxV)	1366x768
HORIZONTAL	
Frequency	47.712kHz
Total time	20.959μs
Activetime	15.906μs
Blank time	5.053μs
Border(L / R)	0.000μs
Data time	15.906μs
Front porch	0.749μs
Sync. width	1.702μs
Back porch	2.994μs
Sync. polarity	Positive
VERTICAL	
Frequency	60.015Hz
Total time	16.662 ms
Active time	16.097ms
Blank time	0.566 ms
Border(T/B)	0.000 ms
Data time	16.097ms
Front porch	0.063 ms
Sync. width	0.105 ms
Back porch	0.377ms
Sync polarity	Positive
Dot Clock	85.500MHz
Sync. Type	Separate
Scan Type	N/I



14-3-2 Supported Modes (1)

Timing No.	2	3	11	17	32
Originator	IBM	IBM	VESA	VESA	MAC
Mode Name	VGA2	VGA3	640/72Hz	640/75Hz	640/67Hz
Resolution (HxV)	720x400	640x480	640x480	640x480	640x480
HORIZONTAL					
Frequency	31.469kHz	31.469kHz	37.861kHz	37.500kHz	35.000kHz
Total time	31.777μs	31.778μs	26.413μs	26.667μs	28.571μs
Activetime	26.058μs	26.058μs	20.825μs	20.317μs	21.164μs
Blank time	5.720μs	5.720μs	5.588μs	6.350μs	7.407μs
Border(L / R)	0.318μs	0.318μs	0.254μs	0.000μs	0.000μs
Data time	25.422μs	25.422μs	20.317μs	20.317μs	21.164μs
Front porch	0.318μs	0.318μs	0.508μs	0.508μs	2.116μs
Sync. width	3.813μs	3.813μs	1.270μs	2.032μs	2.116μs
Back porch	1.589μs	1.589μs	3.810μs	3.810μs	3.175μs
Sync. polarity	Negative	Negative	Negative	Negative	Negative
VERTICAL					
Frequency	70.087Hz	59.940Hz	72.809Hz	75.000Hz	66.667Hz
Total time	14.268ms	16.683ms	13.735ms	13.333ms	15.000ms
Active time	13.155ms	15.761ms	13.100ms	12.800ms	13.714ms
Blank time	1.113ms	0.922ms	0.635ms	0.533ms	1.286ms
Border(T/B)	0.222ms	0.254ms	0.211ms	0.000ms	0.000ms
Data time	12.711ms	15.253ms	12.678ms	12.800ms	13.714ms
Front porch	0.191ms	0.064ms	0.026ms	0.027ms	0.086ms
Sync. width	0.064ms	0.064ms	0.079ms	0.080ms	0.086ms
Back porch	0.858ms	0.794ms	0.528ms	0.427ms	1.114ms
Sync polarity	Positive	Negative	Negative	Negative	Negative
Dot Clock	28.322MHz	25.175MHz	31.500MHz	31.500MHz	30.240MHz
Sync. Type	Separate	Separate	Separate	Separate	Separate
Scan Type*	N/I	N/I	N/I	N/I	N/I

14-3-3 Supported Modes (2)

Timing No.	13	14	18
Originator	VESA	VESA	VESA
Mode Name	800/60Hz	800/72Hz	800/75Hz
Resolution (HxV)	800x600	800x600	800x600
HORIZONTAL			
Frequency	37.879kHz	48.077kHz	46.875kHz
Total time	26.400μs	20.800μs	21.333 μs
Activetime	20.000μs	16.000μs	16.162 μs
Blank time	6.400 μs	4.800 μs	5.171 μs
Border(L / R)	0.000 μs	0.000 μs	0.000 μs
Data time	20.000μs	16.000μs	16.162 μs
Front porch	1.000 μs	1.120 μs	0.323 μs
Sync. width	3.200 μs	2.400 μs	1.616 μs
Back porch	2.200 μs	1.280 μs	3.232 μs
Sync. polarity	Positive	Positive	Positive
VERTICAL			
Frequency	60.317Hz	72.188Hz	75.000Hz
Total time	16.579ms	13.853ms	13.333ms
Active time	15.840ms	12.480ms	12.800ms
Blank time	0.739ms	1.373ms	0.533ms
Border(T/B)	0.000ms	0.000ms	0.000ms
Data time	15.840ms	12.480ms	12.800ms
Front porch	0.026ms	0.770ms	0.021ms
Sync. width	0.106ms	0.125ms	0.064ms
Back porch	0.607ms	0.478ms	0.448ms
Sync polarity	Positive	Positive	Positive
Dot Clock	40.000MHz	50.000MHz	49.500MHz
Sync. Type	Separate	Separate	Separate
Scan Type*	N/I	N/I	N/I

14-3-4 Supported Modes (3)

Timing No.	15	16	19	
Originator	VESA	VESA	VESA	VESA
Mode Name	1024/60Hz	1024/70Hz	1024/75Hz	1360/60Hz
Resolution (HxV)	1024x768	1024x768	1024x768	1360x768
HORIZONTAL				
Frequency	48.363kHz	56.476kHz	60.023kHz	47.712kHz
Total time	20.677μs	17.707μs	16.660μs	20.959μs
Activetime	15.754μs	13.653μs	13.003μs	15.906μs
Blank time	4.923μs	4.053 μs	3.777 μs	5.053μs
Border(L / R)	0.000μs	0.000μs	0.000μs	0.000μs
Data time	15.754μs	13.653μs	13.003μs	15.906μs
Front porch	0.369μs	0.320μs	0.323μs	0.749μs
Sync. width	2.092μs	1.813μs	1.219μs	1.702μs
Back porch	2.462μs	1.920μs	2.235μs	2.994μs
Sync. polarity	Negative	Negative	Positive	Positive
VERTICAL				
Frequency	60.004Hz	70.069Hz	75.029Hz	60.015Hz
Total time	16.666ms	14.272ms	13.328ms	16.662ms
Active time	15.880ms	13.599ms	12.795ms	16.097ms
Blank time	0.786ms	0.672ms	0.533ms	0.566ms
Border(T/B)	0.000ms	0.000ms	0.000ms	0.000ms
Data time	15.880ms	13.599ms	12.795ms	16.097ms
Front porch	0.062ms	0.053ms	0.017ms	0.063ms
Sync. width	0.124ms	0.106ms	0.050ms	0.105ms
Back porch	0.600ms	0.513ms	0.466ms	0.377ms
Sync polarity	Negative	Negative	Positive	Positive
Dot Clock	65.000MHz	75.000MHz	78.750MHz	85.500MHz
Sync. Type	Separate	Separate	Separate	Separate
Scan Type*	N/I	N/I	N/I	N/I

14-4 Panel Description

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LT140X1-002	BN07-00004A	SA	BN68-00239H	-
SEC	LT150XS-L01	BN07-00009A	SB		-
SEC	LT150XS-L01-B	BN07-00022A	SC		-
SEC	LTM150XS-L02	BN07-00005A	SD		-
SEC	LT181E2-132	BN07-00001A	SE		-
SEC	LT150XS-T01	BN07-00010A	SF		-
SEC	LTM181E3-132	BN07-00019A	SG		-
SEC	LT170E2-131	BN07-10001D	SH		-
SEC	LT181E2-131	BN07-10001E	SJ		-
SEC	LTM170E4-L01	BN07-00018A	SK		-
SEC	LTM240W1-L01	BN07-00015A	SL		-
SEC	LTM213U3-L01	BN07-00016A	SM		-
SEC	LTM150XH-L01	BN07-00026A	SN		
SEC	LTM150XH-L03	BN07-00027A	SP		-
SEC	LTM150XS-L01	BN07-00032A	SQ		DELL(ZPD)
SEC	LTM181E4-L01	BN07-00034A	SR		PVA
SEC	LTM170EH-L01	BN07-00036A	SS		TN
SEC	LTM170E5-L01	BN07-00037A	SU		PVA
SEC	LTM150XH-L11	BN07-00041A	SV		-
SEC	LTM213U4-L01	BN07-00039A	SW		PVA
SEC	LTM150XH-L01(ZPD)	BN07-00045A	SX		ZPD
SEC	LTM150XH-L04	BN07-00046A	SY		New panel with high brightness
SEC	LTM170W1-L01	BN07-00047A	SZ		Panel for TV
SEC	LTM150XH-L06	BN07-00053A	EA		Panel for TV/ High luminance for 450cd _ SONY&EOS Team Panel for TV
SEC	LTM153W1-L01	BN07-00054A	EB		Use NIKE MODEL
SEC	LTM170EH-L05	BN07-00055A	EC		Panel EOS proj. for high brightness of 17" EH-L05
SEC	LTM170E5-L03	BN07-00056A	ED		Dell 1702FP pro. E4. EH mechanical Compatible
SEC	LTM190E1-L01	BN07-00057A	EE		DELL 1900 FP
SEC	LTM181E5-L01	BN07-00061A	EF		18" narrow bezel GH18PS
SEC	LTM150XP-L01	BN07-00065A	EG		AMLCD PVA PANEL
SEC	LTM240W1-L02	BN07-00062A	EH		Panel for 15" Wide TV
SEC	LTM170EU-L01	BN07-00071A	EJ		Slim design, TN
SEC	LTM170E5-L04	BN07-00072A	EK		E5-L04 6 bits FRC... for IBM
SEC	LTA220W1-L01	BN07-00074A	EL		Panel for 22" TV
SEC	LTM170E6-L02	BN07-00075A	EM		AMLCD Narrow & slim design 17" PVA mode
SEC	LTM170W1-L01	BN07-00082A	EN		LTM170W1-L01 ZPD panel
SEC	LTM170EH-L01	BN07-00080A	EP		LTM170EH-L01 ZPD panel
SEC	LTM170E5-L01	BN07-00081A	EQ		LTM170E5-L01 ZPD panel
SEC	LTM170EH-L05	BN07-00083A	ER		LTM170EH-L05 ZPD panel
SEC	LTM170E5-L03	BN07-00084A	ES		LTM170E5-L03 ZPD panel
SEC	LTM170EU-L01	BN07-00085A	ET		LTM170EU-L01 ZPD panel
SEC	LTM170E5-L04	BN07-00086A	EU		LTM170E5-L04 ZPD panel
SEC	LTM170E6-L02	BN07-00087A	EV		LTM170E6-L02 ZPD panel
SEC	LTM150XH-L06	BN07-00091A	EW		Color coordinates change for LCD TV
SEC	LTM153W1-L01	BN07-00092A	EX		AMLCD WIDE 15",9/10
SEC	LTM170W1-L01	BN07-00100A	EY		Color Coordinates change code management
SEC	LTM170EH-L05	BN07-00097A	EZ		LTM170E5-L05 Color Coordinates Change Panel Code

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LTA400W1-L01	BN07-00109A	S1		PANEL of AMLCD 40" TV
SEC	LTM153W1-L01	BN07-00110A	S2		Color coordinates change 0.280/0.290, 10000k & ZPD Panel
SEC	LTM150XH-L06	BN07-00111A	S3		Color coordinates change 0.280/0.290, 10000k & ZPD Panel
SEC	LTM170W1-L01	BN07-00112A	S4		Color coordinates change 0.280/0.290, 10000k & ZPD Panel
SEC	LTM170EH-L05	BN07-00113A	S5		Color coordinates change 0.280/0.290, 10000k & ZPD Panel
SEC	LTM220W1-L01	BN07-00114A	S6		ZPD Panel for AMLCD 22" TV
SEC	LTM150XH-L06	BN07-00117A	S7		ZPD Panel code
SEC	LTM153W1-L01	BN07-00118A	S8		ZPD Panel code
SEC	LTM170WP-L01	BN07-00119A	S9		PVA Panel for NIKE
SEC	LTM213U4-L01	BN07-00039A	E1		21.3" NARROW
SEC	LTA260W1-L01	BN07-00121A	E2		VENUS
SEC	LTA220W1-L01	BN07-00074B	E3		"Panel B-level panel code for 22"" TV Panel "
SEC	LTA320W1-L01	BN07-00108A	E4		"Panel for AMLCD 32"" TV"
SEC	LTM213U4-L01	BN07-00124A	E5		NARROW BEZEL 21 " PANEL
SEC	LTM170E6-L04	BN07-00129A	E6		"HIGHLAND 17"" LOW PANEL (Panel only for TCO03)"
SEC	LTM190E1-L01	BN07-00088A	E7		LTM190E1-L01 ZPD panel
SEC	M150X4-L06	BN07-00137A	E8		15" Narrow & Slim panel
SEC	LTA170V1	BN07-00139A	E9		"17"" Panel for Muse 4:3 VGA TV"
SEC	LTM190E1-L02	BN07-00128A	E10		"New Panel from AMLCDl, Specification : 6bit Driver IC"
SEC	LTM170EX-L01	BN07-00143A	E11		"Development new Panel from AMLCD"
SEC	LTM170E8-L01	BN07-00144A	E12		"Development new Panel from AMLCD"
SEC	LTM170E6-L04	BN07-00129B	E13		"ZPD panel for AMLCD (Panel only for TCO03)"
SEC	LTA320W1-L02	BN07-00108B	E14		"Creat B-level Panel code for AMLCD 32"" TV"
SEC	LTM190E1-L03	BN07-00151A	E15		"Development new 19"" Panel form AMLCD (Panel only for TCO03)"
SEC	LTM240W1-L03	BN07-00134A	E16		"AMLCD 24"" panel development"
SEC	LTM190E1-L02	BN07-00128B	E17		"New Panel from AMLCD, Specification : 6bit Driver IC(ZPD)"
SEC	LTM190E4-L01	BN07-00145A	E18		"AMLCD 24"" new panel development"
SEC	LTM170E8-L01	BN07-00158A	E19		"ZPD code derivation"
SEC	LTM170EX-L01	BN07-00159A	E20		"ZPD code derivation"
SEC	LTM190E1-L03	BN07-00151B	E21		"Creat new panel code for AMLCD 19"" (Panel only for TCO03)"
SEC	LTA460H1-L01	BN07-00157A	E22		"creat panel code for AMLCD 46"" TV "
SEC	LTM170EU-L11	BN07-00160A	E23		"creat new panel code for AMLCD 17"" (Panel only for TCO03)"
SEC	LTM240W1-L03	BN07-00134B	E24		"24"" panel ZPD code derivation"
SEC	LTM190E4-L01	BN07-00145B	E25		"AMLCD 19"" ZPD Panel code derivation"
SEC	LTM240W1-L03	BN07-00134B	E26		"24"" panel ZPD code derivation"
SEC	LTM150XO-L01	BN07-00164A	E27		"AMLCD 15"" XO-L01 new panel development"
SEC	LTM150XO-L01	BN07-00164B	E28		"AMLCD 15"" XO-L01 ZPD code derivation"
SEC	LTM170EU-L11	BN07-00160B	E29		"AMLCD 17"" NEW panel code derivation"
SEC	LTA320W2-L01	BN07-00172A	SPZ		AMLCD 32" NEW panel
SEC	LTM213U4-L01	BN07-00124B	SPZ		21.3" Narrow PANEL ZPD Panel derivation
SEC	LTM170EU-L11	BN07-00189A	STH		AMLCD EU-L11 Pb free panel code derivation
SEC	LTM170EU-L11	BN07-00189B	STZ		AMLCD EU-L11 Pb free panel ZPD code derivation
SEC	LTM240W1-L04	BN07-00188A	SPH		24" A-DCC new panel development
SEC	LTM240W1-L04	BN07-00188B	SPZ		24" A-DCC panel ZPD code derivation
SEC	LTM190EX-L01	BN07-00191A	STH		AMLCD 19" TN new Panel
SEC	LTM190EX-L02	BN07-00191B	STZ		AMLCD 19" TN new Panel ZPD derivation
SEC	LTA230W1-L02	BN07-00184A	SPZ		AMLCD 23" 16:9 new Panel

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
SEC	LTA260W2-L01	BN07-00185A	SPZ		AMLCD 26" 16:9 new Panel
SEC	LTM240M1-L01	BN07-00195A	SPH		24" panel with high brightness deveiopment
SEC	LTA400W2-L01	BN07-00186A	SPZ		AMLCD 40" 16:9 new Panel
SEC	LTM150XO-L01	BN07-00197A	STH		AMLCD 15" XO-L01 Pb free panel code
SEC	LTM150XO-L01	BN07-00197B	STZ		AMLCD 15" XO-L01 Pb free panel ZPD code
SEC	LTM170EU-L21	BN07-00202A	STZ		AMLCD EU-L21 ZPD new code derivation
SEC	LTA460W2-L03	BN07-00187A	SPZ		BEETOVEN 46"ZPD new panel
SEC	LTM240M1-L01	BN07-00195B	SPZ		24" igh brightness panel ZPD code derivation
SEC	M170EX-L21	BN07-00206A	STZ		AMLCD LTM170EX-L21 ZPD new code derivation
SEC	LTA460H3-L01	BN07-00200A	SPZ		AMLCD 46" LED BLU panel
SEC	LTM170EU-L15	BN07-00214A	STZ		AMLCD EU-L15 TV high brightness ZPD new code derivation
SEC	LTM170E8-L21	BN07-00218A	SPZ		AMLCD LTM170E8-L21 PVA ZPD new code derivation
SEC	LTM190EX-L21	BN07-00222A	STZ		DISPLAY LCD
SEC	LTM201U1-L01	BN07-00190B	SPZ		AMLCD 20.1" Normal panel ZPD code derivation
SEC	LTM190E4-L21	BN07-00223A	SPZ		HAYDN 17" PZD code PANEL derivation
SEC	LTA570H1-L01	BN07-00196A	SPZ		AMLCD 57" new panel development
SEC	LTM150XO-L21	BN07-00229A	STZ		AMLCD 15" XO-L21 8ms panel code
SEC	LTA260W2-L11	BN07-00239A	SPZ		AMLCD 26" 16:9 7Line new Panel
SEC	LTA400WS-LH1	BN07-00245A	SPZ		AMLCD 40" 16:9 SPVA 90% new Panel
SEC	LTM213U6-L01	BN07-00231A	SPZ		AMLCD 21.3" PVA new Panel Code
SEC	LTA320WS-LH2	BN07-00244A	SPZ		AMLCD 32" 16:9 SPVA 90% new Panel
SEC	LTA400WS-LH1	BN07-00245A	SPZ		AMLCD 40" 16:9 SPVA 90% new Panel
CPT	CLAA150XG09	BN07-00141A	PA		"CPT 15"" Monitor new panel development"
CPT	CLAA170EA02	BN07-00148A	PB		"17"" CPT NEW development panel"
CPT	CLAA170EA02	BN07-00148B	PC		"17"" CPT ZPD panel code derivation"
CPT	CLAA150XG09	BN07-00141B	PTZ		"CPT 15"" panel ZPD code derivation (GOYA-PJT)"
CPT	CLAA150XP01	BN07-00173A	PTH		CPT 15" PSWG code derivation
CPT	CLAA150XP01	BN07-00173B	PTZ		CPT 15" PSWG panel ZPD code
CPT	CLAA170EA07	BN07-00174A	PTH		"CPT 17"" PSWG panel code derivation
CPT	CLAA170EA07	BN07-00174B	PTZ		CPT 17""""" PSWG type new Panel code"""
CPT	CLAA170EA07	BN07-00174B	PTZ		CPT 17" PSWG type new Panel code
CPT	CLAA170EA07Q	BN07-00220A	PTZ		CPT 17" PSWG R/T 8msec code derivation
CPT	CLAA170EA07Q	BN07-00220B	PTH		CPT 17" PSWG R/T 8msec HPD code derivation
CPT	CLAA150XP01F	BN07-00236A	PTZ		CPT 15" PSWG panel ZPD & Lead free code derivation
TOSHIBA	LTM15C419(A)	BN07-00002A	TA		-
TOSHIBA	LTM15C423(B)	BN07-00006A	TB		-
TOSHIBA	LTM18C161	BN07-00008A	TC		-
TOSHIBA	LTM15C443	BN07-00031A	TD		-
TOSHIBA	LTM15C458	BN07-00043A	TE		-
TOSHIBA	LTM15C458S	BN07-00077A	TF		"TSB 15"" high brightness Panel"
TOSHIBA	LTM15C458	BN07-00078A	TG		Toshiba ZPD panel
TOSHIBA	LTM15C458S	BN07-00099A	TH		TSB LTM15C458S (ZPD)
HANNSTAR	HSD150MX41A(A)	BN07-00020A	NA		"TTL type"
HANNSTAR	HSD150MX12	BN07-00030A	NB		"TTL type"
HANNSTAR	HSD170ME13	BN07-00180A	NTH		Hannstar 17" TN new panel development
HANNSTAR	HSD170ME13	BN07-00180B	NTZ		Hannstar 17" TN new panel development ZPD code derivation
HANNSTAR	HSD190ME12	BN07-00210A	NTZ		Hannstar 19" TN new panel development

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
HANNSTAR	HSD150MX17-A	BN07-00226A	NTZ		Hannstar 15" slim panel ZPD code derivation
TORISAN	TM150XG-22L03(A)	BN07-00021A	RA		-
TORISAN	TM150XG-26L06	BN07-00042A	RB		-
TORISAN	TM181SX-76N01	BN07-00048A	RC		-
TORISAN	TM150XG-26L06	BN07-00059A	RD		15" XGA TN MODE(ZPD)
TORISAN	TM290WX-71N31	BN07-00063A	RE		"RS24NS (TORISAN 29"" NEW PANEL)"
TORISAN	TM396WX-71N31	BN07-00064A	RF		"RS24NS (TORISAN 40"" NEW PANEL)"
TORISAN	TM150XG-26L09	BN07-00073A	RG		"Panel for 15"" TV"
TORISAN	TM150XG-26L10	BN07-00089A	RH		"L10(change except D/IC) ZPD"
TORISAN	TM150XG-26L10	BN07-00090A	RJ		L10 NORMAL
TORISAN	TM190SX-70N01	BN07-00098A	RK		Torisan 19" Panel
TORISAN	TM181SX-76N01	BN07-00106A	RL		ZPD Panel code
TORISAN	TM190SX-70N01	BN07-00107A	RM		ZPD Panel code
TORISAN	TM290WX-71N31	BN07-00115A	RN		"Color Coordinates change panel for TORISAN 29"" TV"
TORISAN	TM396WX-71N31	BN07-00116A	RP,Q		"Color Coordinates change panel for TORISAN 40"" TV"
TORISAN	TM22OWX-71N31	BN07-00125A	RR		"Development TORISAN 22"" TV PANEL (ZPD)"
TORISAN	TM22OWX-71N31	BN07-00127A	RS		"Development TORISAN 22"" TV PANEL (HPD)"
TORISAN	TM396WX-71N32A	BN07-00150A	RT		120V inverter Exclusive panel
TORISAN	TM190SX-70N02	BN07-00154A	RMH		Torisan 6bit panel code Derivation
TORISAN	TM190SX-70N02	BN07-00154B	RMZ		Torisan 6bit panel code Derivation
TORISAN	TM150XG-A01	BN07-00162A	RTH		Torisan 15" Narrow & Slim panel development
TORISAN	TM150XG-A01	BN07-00162B	RTZ		Torisan 15" N&S panel ZPD code Derivation
SHARP	LQ181E1DG11(A)	BN07-10001C	PA		-
SHARP	LQ150X1LW71	BN07-00067A	PB		SHARP 15" PVA PANEL
SHARP	LQ370T3LZ41	BN07-00216A	FAZ		Rome2
HITACHI	TX38D12VC0CAA(A)	BN07-00003A	HA		-
HITACHI	TX43DVCOCAB	BN07-00060A	HB		17" SXGA PVA MODE
HITACHI	TX43D15VC0CAB	BN07-00101A	HC		ZPD Panel
HITACHI	TX51D11VC0CAB	BN07-00122A	HD		20.1" NARROW
HITACHI	TX54D11VC0CAB	BN07-00123A	HE		21.3" NARROW
HITACHI	TX80D12VC0CAB	BN07-00169A	HIZ		"Development new panel for Hitachi 32"" TV (ZPD)"
HITACHI	TX54D11VC0CAB	BN07-00123B	HIZ		Hitachi 21.3"ZPD panel
IBM	ITSX94S	BN07-00017A	IA		-
UNIPAC	UM170E0	BN07-00028A	UA		Loaded by cisdba
HYUNDAI	HT15X13	BN07-00035A	DA		-
HYUNDAI	HT17E11-200	BN07-00049A	DB		TN MODE
HYUNDAI	HT17E11-300	BN07-00093A	DC		HT17E11-300 ZPD panel
HYUNDAI	HT17E11-400	BN07-00094A	DD		HT17E11-400 normal panel
HYUNDAI	HT17E11-400	BN07-00095A	DE		HT17E11-400 ZPD panel code
HYUNDAI	HT17E12	BN07-00096A	DF		HT17E12 (Narow & slim Design)
HYUNDAI	HT17E12	BN07-00105A	DG		ZPD Panel code
HYUNDAI	HT15X15-D00	BN07-00146A	DH		"Development for Ares 15"" Hydis TV"
HYUNDAI	HT15X15-D01	BN07-00146B	DJ		"Derivation panel HPD for Ares 15"" Hydis TV "
HYUNDAI	HT17E13-100	BN07-00167A	DTH		"PINEHURST-2(IBM) PJT 17"" HYDIS PANEL Derivation"
HYUNDAI	HT17E13-100	BN07-00167B	DTZ		"PINEHURST-2(IBM) Hydis 17"" ZPD code Derivation"
ACER	L170E3	BN07-00044A	AA		TN(ADT)
ACER	M170EN05	BN07-00076A	AB		AU 17" Panel (Narrow & slim design)

Maker	VENDOR P/N	PANEL_CODE	PANEL_ABB	STICKER_CODE	Remarks
ACER	M170EN05	BN07-00102A	AC		ZPD Panel code
ACER	M190EN02	BN07-00170A	AMH		"AU Monitor 19"" new panel development (P19-1S)"
ACER	M190EN02	BN07-00170B	AMZ		"AU 19"" ZPD code derivation (ZPD)"
ACER	M170EN06	BN07-00171A	ATH		"AU Monitor 17"" New panel development "
ACER	T260XW01	BN07-00163A	AMZ		"AU 26"" new panel development (NF26EO)"
ACER	A201SN01	BN07-00177A	ATZ		"AU TV panel 20.1"" TN SVGA new panel development"
ACER	M170EN06	BN07-00171B	ATZ		AU Monitor 17" ZPD code derivation
ACER	T315XW01	BN07-00194A	AMZ		AU 32" new
ACER	M170EG01	BN07-00192A	ATH		AU TN PSWG type new Panel code
ACER	M170EG01	BN07-00192B	ATZ		AU TN PSWG type NEW panel code derivation
ACER	M190EN04	BN07-00203A	ATH		AU Monitor 19" ZPD new Panel code
ACER	T260XW02	BN07-00208A	AMZ		AUO 26" ZPD panel
ACER	M170EG01 V8	BN07-00221A	ATZ		AU TN PSWG type new Panel (8msec) ZPD code derivation
ACER	T260XW02	BN07-00233A	AMZ		AUO 26" Panel new (Cosmetic spec down grade)
ACER	T315XW01	BN07-00234A	AMZ		AUO 32" Grade new (Cosmetic spec down grade)
ACER	M190EN03	BN07-00224A	AMZ		AU Monitor 19" MVA new code derivation
ACER	T315XW01	BN07-00237A	AMZ		LCD TV VE project new
ACER	T315XW01	BN07-00238A	AMZ		LCD TV VE project new
ACER	M201UN02 V3	BN07-00168A	AMZ		
CHIMEI	M170E3-LO1	BN07-00050A	CA		TN PANEL
CHIMEI	M150X3-L01	BN07-00051A	CB		COMPATIBLE
CHIMEI	M170E4-L01	BN07-00052A	CC		MVA PANEL
CHIMEI	M150X2-L01	BN07-00066A	CD		CHIME 15"I PVA PANEL
CHIMEI	M150X3-L01	BN07-00079A	CE		Chimei ZPD panel
CHIMEI	M170E3-L01	BN07-00103A	CF		ZPD Panel code
CHIMEI	M170E4-L01	BN07-00104A	CG		ZPD Panel code
CHIMEI	V296W1-L01	BN07-00120A	CH		MVA
CHIMEI	M170E6-L02	BN07-00126A	CJ		HIGHLAND 17" LOW PANEL
CHIMEI	M190E2-L01	BN07-00131A	CK		GH19AS,BS CHIMEI PANEL
CHIMEI	M150X4-L06	BN07-00137A	CL		15" Narrow & Slim panel
CHIMEI	M170E6-L01	BN07-00133A	CM		"2003-03-11 vendor change"
CHIMEI	M170E6-L01	BN07-00133B	CN		ZPD derivation panel
CHIMEI	V201V1-T01	BN07-00135A	CP		CHIMEI 20.1" panel development
CHIMEI	M170E6-L02	BN07-00126B	CQ		"HIGHLAND 17"" LOW PANEL ZPD derivation panel"
CHIMEI	M170E6-L05	BN07-00152A	CR		"CMO 17"" new panel development code"
CHIMEI	M170E6-L05	BN07-00152B	CS		"CMO 17"" ZPD panel code derivation"
CHIMEI	M150X4-L06	BN07-00137B	CT		Chimei 15" Narrow & Slim panel ZPD derivation
CHIMEI	M170E5-L05	BN07-00165A	CTH		CMO 17" new panel development code (GOYA2-PJT)
CHIMEI	M170E5-L05	BN07-00165B	CTZ		CMO 17" ZPD panel(GOYA2-PJT)
CHIMEI	V230W1-L02	BN07-00209A	CMZ		CMO 23" development
CHIMEI	V320B1-L01	BN07-00207A	CMZ		CMO 32" development
CHIMEI	V270W1-L01	BN07-00136A	CMZ		CHI MEI 27" panel development
NEC	SVA150XG04TB	BN07-00225A	BTZ		SVA NEC 15" panel ZPD code

9 Schematic Diagrams

- This Document can not be used without Samsung's authorization.

9-1 MAIN POWER BLOCK Schematic Diagram



- This Document can not be used without Samsung's authorization.

9-2 X242 INOUT MEMORY Schematic Diagram



- This Document can not be used without Samsung's authorization.

9-3 FLEXBUS_PCI_FLASH Schematic Diagram



- This Document can not be used without Samsung's authorization.

9-4 X242 POWER Schematic Diagram



- This Document can not be used without Samsung's authorization.

9-5 TUNER & SPLITTER Schmetic Diagram

ATSC HALF NIM TUNER









- This Document can not be used without Samsung's authorization.

9-6 STANDBY MICOM (WT61P6S) Schmetic Diagram



- This Document can not be used without Samsung's authorization.

9-7 PC & HDMI INPUT Schmetic Diagram









- This Document can not be used without Samsung's authorization.

9-8 AV INPUT / OUTPUT Schmetic Diagram









- This Document can not be used without Samsung's authorization.

9-9 SIDE AV Schmetic Diagram









- This Document can not be used without Samsung's authorization.

9-10 MSP4450K Schmetic Diagram



- This Document can not be used without Samsung's authorization.

9-11 SOUND AMP(NTP3000) Schmetic Diagram









- This Document can not be used without Samsung's authorization.

9-12 MST3388 & SIL9185 Schmetic Diagram



- This Document can not be used without Samsung's authorization.

9-13 FBE Schmetic Diagram



- This Document can not be used without Samsung's authorization.

9-14 SUB-FUNCTION Schmetic Diagram

SUB FUNCTION I/F



4 Troubleshooting

4-1 No Power



4-2 No Video (Analog PC Signal)



WAVEFORMS

1 2 3 PC Input (V-Sync, H-Sync)



4 LVDS Out (CLK + / -)



4-3 No Video (HDMI - Digital Signal)



WAVEFORMS

5 **6** HDMI Input (CLK + / -)

4-4 No Picture (Tuner_CVBS)



WAVEFORMS

7 Tuner CVBS Out (Pattern: Grey Bar)



4-5 No Picture (Tuner DTV TS)



WAVEFORMS

8 DTV RF +/-



4-6 No Picture(Video CVBS)



4-7 No Picture(S-Video Y/C)



WAVEFORMS

9 S-VIDEO Input (Y/C)

4-8 No Picture(Component1, 2 : 480i, 480p, 720p, 1080i[Y, Pb, Pr])



WAVEFORMS

10 Component Input (Y/Pb)

4-9 No Sound


Picture is display, no sound.
Yes
Check the sound source and check the connection of sound cable ?
No
Input a sound signal. Check the connected cable.
Yes
Does the signal appear at C1007,C1016,C1012,C1020, C1009,C1017,C1011,C1018?
No
Check JA800,JA803,JA808 & SIDE AV Change the main PCB ASS`Y
Yes
11
Does the signal appear at #50~55 for IC1002?
No
Check IC1001,JA704,JA702 or SIDE AV Change the main PCB ass'y
Yes
12
Does the digital data appear at #4~6 of IC1002?
No
Check IC1002 Change the main PCB ass'y
Yes
13
Does the digital data appear at L1101,L1104?
No
Check IC1100 Change the main PCB ass'y
Yes
Replace the speaker ass'y?
No
Please, call to Samsung Co. LTD.

WAVEFORMS

11 Audio Input (Sign Wave)



12 12S Input (Clk, Data)



13 Audio Amp Out (Sign Wave)



8 Wiring Diagram

8-1 Wiring Diagram



24V	1
24V	2
24V	3
24V	4
24V	5
GND	6
GND	7
GND	8
GND	9
A_D	10
B/L	11
B/L	12
P_D	13
GND	14

24V	1
24V	2
24V	3
24V	4
24V	5
GND	6
GND	7
GND	8
GND	9
GND	10
A_D	11
B/L	12
P_D	13
GND	14

GND	1
ANA_dimming	2
PWM_dimming	3
SW_inverter	4
STB_5V	5

ON/OFF	1	N.C.	2
GND	3	GND	4
GND	5	GND	6
12V	7	12V	8
GND	9	GND	10
GND	11	GND	12
5.3V	13	5.3V	14
5.3V	15	5.3V	16
GND	17	GND	18
13V	19	GND	20
13V	21	13V	22
N.C.	23	N.C.	24

100~120V	L
GND	N

GND	1
ANA_dimming	2
PWM_dimming	3
SW_inverter	4
STB_5V	5

N.C.	1	POWER_ ON/OFF	2
GND_ST6V	3	ST6V	4
GND_Vamp (sound)	5	GND_Vamp (sound)	6
Vamp (sound)	7	Vamp (sound)	8
GND_5V	9	GND_5V	10
GND_5V	11	GND_5V	12
5V	13	5V	14
5V	15	5V	16
GND_12V	17	GND_12V	18
GND_12V	19	12V	20
12V	21	12V	22
NC(FAN_DET)	23	NC(FAN_DET)	24

1	TX0-	16	N.C.
2	TX0+	17	GND
3	TX1-	18	GND
4	TX1+	19	SCL_LOGIC
5	TX2-	20	SDL_LOGIC
6	TX2+	21	TxD_LOGIC
7	TXCLK-	22	RxD_LOGIC
8	TXCLK+	23	GND
9	TX3-	24	GND
10	TX3+	25	GND
11	TX4-	26	
12	TX4+	27	
13	TX5-	28	
14	TX5+	29	
15	N.C.	30	

IR	1
GND	2
A5V	3
LED_STB	4
BUZZER	5
KEY1	6
KEY2	7
GND	8
	9
LED_CTRL	10

R+_OUT	1
R-_OUT	2
L+_OUT	3
L-_OUT	4

Memo